NASA TN D-132

TECHNICAL NOTE

D-132

A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF

EQUILIBRIUM COMPOSITIONS AND THEORETICAL

ROCKET PERFORMANCE OF PROPELLANTS

By Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff

Lewis Research Center
Cleveland, Ohio

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

WASHINGTON October 1959

ERRATA

NASA TECHNICAL NOTE D-132

By Sanford Gordon, Frank J. Zeleznik
and Vearl N. Huff

October 1959

E-417

Figure 2, page 138: The second term of $\Delta \ln T$ for "Enthalpy" should be $\sum (H_T^0)_i q_i p_i$.

Figure 3, page 139: The terms in the column headings should be (a change in mathematical sign)

$$-\left(\frac{\partial \ln p_Z}{\partial \ln T}\right)_P, \; -\left(\frac{\partial \ln p_Y}{\partial \ln T}\right)_P, \; -\left(\frac{\partial \ln p_X}{\partial \ln T}\right)_P, \; -\left(\frac{\partial n_M}{\partial \ln T}\right)_P, \; -\left(\frac{\partial n_N}{\partial \ln T}\right)_P, \text{ and } +\left(\frac{\partial \ln A}{\partial \ln T}\right)_P.$$

Page 71, cards 464, 470, 471, and 474: TEMPO and 9059 should be TEM 1 and 9049, respectively.

NASA - Langley Field, Va

Issued 3-14-60

TABLE OF CONTENTS

L-417

E-417

CA-1

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

TECHNICAL NOTE D-132

A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF EQUILIBRIUM COMPOSITIONS AND THEORETICAL ROCKET PERFORMANCE OF PROPELLANTS

By Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff

SUMMARY

A general computer program for chemical equilibrium and rocket performance calculations was written for the IBM 650 computer with 2000 words of drum storage, 60 words of high-speed core storage, indexing registers, and floating point attachments. The program is capable of carrying out combustion and isentropic expansion calculations on a chemical system that may include as many as 10 different chemical elements, 30 reaction products, and 25 pressure ratios. In addition to the equilibrium composition, temperature, and pressure, the program calculates specific impulse, specific impulse in vacuum, characteristic velocity, thrust coefficient, area ratio, molecular weight, Mach number, specific heat, isentropic exponent, enthalpy, entropy, and several thermodynamic first derivatives.

INTRODUCTION

Almost the entire work involved in the calculation of theoretical performance of propellants is in the determination of the equilibrium composition and temperature of the reaction products. The difficulty in determining equilibrium compositions, especially where many reaction products are involved, is due to the fact that the necessary equations for their solution are not simultaneously linear; and hence, in general, a direct solution is not feasible.

In recent years, a number of articles have appeared in the literature dealing with equilibrium calculations for complex mixtures that describe various systematic iterative techniques for obtaining equilibrium compositions (e.g., refs. 1 to 22). With the increasing availability of high-speed digital computers, a number of programs have been prepared to solve for equilibrium compositions automatically (e.g., refs. 13, 16, and 19 to 22).

The present report presents a completely general method programmed for the IBM 650 data processing system with 2000 words of drum storage, 60 words of high-speed core storage, index registers, floating decimal-point attachment, and alphabetic device. This program can handle any chemical system within certain limitations set by the storage capacity of the IBM 650. The program is based essentially on the method described in reference 9; however, some modifications have been made. The program was prepared during 1957 and has been in operation since January 1958.

EQUATIONS DEFINING ADIABATIC COMBUSTION AND ISENTROPIC EXPANSION

The computer program described in this report is primarily concerned with the calculation of theoretical rocket performance of chemical propellants. This calculation is simple and straightforward once the temperature and composition of the reaction products are known at combustion and exit points in the nozzle. The temperature and composition following a process such as adiabatic combustion at constant pressure or isentropic expansion to an assigned pressure can be determined from an appropriate combination of equations describing the conservation of atomic species, chemical equilibrium, Dalton's law of partial pressures, and the conservation of enthalpy or entropy. Since these equations do not constitute a set of linear equations, they must usually be solved by some iterative technique.

Combustion at Constant Pressure

For given initial conditions, the temperature and composition following a combustion process are to be found. The substances entering into the reaction may be represented by an equivalent formula

$$Z_{a_0}Y_{b_0}X_{c_0}\ \ldots$$

where $a_0, b_0, c_0, \ldots$ are proportional to the total number of gram atoms of the elements $Z, Y, X, \ldots$ in the reaction mixture. (A complete list of symbols is given in appendix A.) For example,

$$N_2H_4 + \frac{3}{2}\,H_2O_2 \rightarrow H_7N_2O_3 \tag{1}$$

The reaction at equilibrium may be written as

$$A(Z_{a_0}Y_{b_0}X_{c_0}\ \ldots) \rightarrow \sum_i n_i(Z_{a_i}Y_{b_i}X_{c_i}\ \ldots) \tag{2}$$

or

$$Z_{a_0}Y_{b_0}X_{c_0} \; . \; . \; . \rightarrow \frac{1}{A}\sum_i n_i(Z_{a_i}Y_{b_i}X_{c_i} \; . \; . \; .) \tag{3}$$

where A is the number of formula weights of the equivalent reactant, and n_i is the number of moles of the i^{th} molecule or atom.

With this representation of the reaction, the equations involving mass conservation, chemical equilibria, pressure, and enthalpy may be written as follows.

Conservation of mass. - Equations defining the relative amounts of each element in the reaction products may be written as follows:

$$\left.\begin{aligned} a &= \frac{1}{A}\sum_i a_i n_i \\ b &= \frac{1}{A}\sum_i b_i n_i \\ c &= \frac{1}{A}\sum_i c_i n_i \\ . &= . \; . \; . \; . \; . \end{aligned}\right\} \tag{4}$$

where $a, b, c, \ldots$ are the number of gram atoms of substance $Z, Y, X, \ldots$ per equivalent formula required to form the reaction products. For the reaction of equation (3), conservation of mass is defined by the following relations:

$$\left.\begin{aligned} a &= a_0 \\ b &= b_0 \\ c &= c_0 \\ \ldots &= \ldots \end{aligned}\right\} \tag{5}$$

Chemical-equilibrium equations. - For convenience in handling the equations, each reaction product can be considered as being formed from the gaseous atoms as follows:

$$a_i Z + b_i Y + c_i X + \; . \; . \; . = Z_{a_i}Y_{b_i}X_{c_i} \; . \; . \; . \tag{6}$$

The change in free energy across reaction (6), $(\Delta F)_i$, in terms of activities α is given by the relation

$$(\Delta F)_i = (\Delta F^o)_i + RT(\ln \alpha_i - a_i \ln \alpha_Z - b_i \ln \alpha_Y - c_i \ln \alpha_X - \ldots) \quad (7)$$

where $(\Delta F^o)_i$ is the standard-state free-energy change across the reaction.

E-417

For gaseous reaction products, the standard state, or the state of unit activity, is usually taken to be the ideal gas at 1-atmosphere pressure. This choice of standard state makes the activity and the fugacity numerically equal. If, furthermore, all the gaseous reaction products are assumed to behave ideally, then the fugacity and partial pressure are identical. In this case, dividing by RT and using the symbol δ for $\Delta F/RT$, equation (7) may be written as

$$\delta_i = \left(\frac{\Delta F^o}{RT}\right)_i + \ln p_i - (a_i \ln p_Z + b_i \ln p_Y + c_i \ln p_X + \ldots) \quad (8)$$

The criterion for equilibrium for a reaction at constant temperature and pressure is that ΔF (or δ_i) be equal to zero; that is,

$$\left(\frac{\Delta F^o}{RT}\right)_i + \ln p_i - (a_i \ln p_Z + b_i \ln p_Y + c_i \ln p_X + \ldots) = 0 \quad (9)$$

In this report, a condensed phase is assumed to be a pure solid or liquid, excluding the possibility of solid or liquid solutions. The activity for a condensed phase is conventionally taken to be unity for the pure solid or liquid at 1-atmosphere pressure. At moderate pressures the activity of the condensed phase is essentially the same as in the standard state, and hence the equilibrium relation for the formation of the condensed product $Z_{a_N}Y_{b_N}X_{c_N} \ldots$ from the gaseous atoms may be written as

$$\delta_N = \left(\frac{\Delta F^o}{RT}\right)_N - (a_N \ln p_Z + b_N \ln p_Y + c_N \ln p_X + \ldots) \quad (10)$$

Similar expressions may be written for other condensed products, $Z_{a_M}Y_{b_M}X_{c_M} \ldots$, and so forth. At equilibrium conditions $\delta_N, \delta_M, \ldots$ are equal to zero; that is,

$$\left.\begin{aligned} \left(\frac{\Delta F^o}{RT}\right)_N - (a_N \ln p_Z + b_N \ln p_Y + c_N \ln p_X + \ldots) &= 0 \\ \ldots\ldots\ldots\ldots\ldots\ldots\ldots\ldots\ldots\ldots &= 0 \end{aligned}\right\} \quad (11)$$

E-417

Dalton's law of partial pressures. - The static pressure of the system is the sum of the partial pressures of the gaseous products:

$$P = \sum_i p_i \tag{12}$$

If a process has an assigned pressure P_0, then

$$P = P_0 \tag{13}$$

In this report, it is assumed that the gases at combustion conditions have zero velocity; and hence, in the combustion chamber, static pressure is equal to the total pressure.

Conservation of enthalpy. - Adiabatic combustion is a constant-enthalpy process; and hence, if chemical energy is included in the enthalpy of each substance, the enthalpy of the products of reactions must equal the enthalpy of the reactants.

Since only differences in enthalpy are involved, an arbitrary base may be adopted for assigning absolute values to the enthalpy of various substances. The molar enthalpy of a substance is defined as

$$(H_T^o)_i = \int_0^T (C_P^o)_i \, dT + (H_0^o)_i \tag{14}$$

where $(C_P^o)_i$ is the molar specific heat at constant pressure, and $(H_0^o)_i$ is the assigned reference enthalpy at 0^o K of the i^{th} substance.

If the enthalpy of the reactants per formula weight of the equivalent formula $Z_{a_0}Y_{b_0}X_{c_0} \ldots$ is H_0, then

$$H_0 = \sum_i n_{f_i}(H_T^o)_{f_i} + \sum_i n_{x_i}(H_T^o)_{x_i} \tag{15}$$

where n_{f_i} and n_{x_i} are the moles of the i^{th} fuel and i^{th} oxidant corresponding to equivalent formula $Z_{a_0}Y_{b_0}X_{c_0} \ldots$, and $(H_T^o)_{f_i}$ and $(H_T^o)_{x_i}$ are the molar enthalpies of the i^{th} fuel and i^{th} oxidant, respectively.

The enthalpy of the combustion products per equivalent formula of reactants may be written as

$$H = \frac{1}{A} \sum_i (H_T^\circ)_i \, n_i \tag{16}$$

If the H_0° values for all substances are consistently assigned (taking into account heats of reaction and transition), then for adiabatic combustion,

$$H = H_0 \tag{17}$$

Isentropic Expansion to Assigned Pressure

The temperature and composition following an isentropic expansion of the combustion gases to an assigned pressure may be determined by equations for (1) conservation of atomic species, (2) chemical equilibrium, (3) the law of partial pressures, and (4) the conservation of entropy. The first three types of equations ((5), (9), (11), and (13)) have been discussed in the previous section and again apply. The fourth type is discussed herein.

The entropy of the reaction products per formula weight of the equivalent reactant is given by

$$S = \frac{1}{A} \sum_i (S_T)_i \, n_i \tag{18}$$

where

$$(S_T)_i = \begin{cases} (S_T^\circ)_i - R \ln p_i & \text{for gases} \\ (S_T^\circ)_i & \text{for condensed phases} \end{cases} \tag{19}$$

and $(S_T^\circ)_i$ is the absolute molar entropy of the i^{th} product at temperature T in the standard state.

For an isentropic expansion following a combustion process, the entropy at any point in the expansion S_e must be equal to the value of entropy at combustion conditions S_c. If S_c is considered to be an assigned value S_0, then

$$S_e = S_c = S_0 \tag{20}$$

Summary of Equations for Adiabatic Combustion and Isentropic Expansion

Equations (5), (9), (11), and (13), together with equation (17) for adiabatic combustion or equation (20) for isentropic expansion, are sufficient to solve the problem of equilibrium calculations completely. However, these equations involve both the moles n_i and the partial pressures p_i. The equations can be expressed in the same variables by letting A be that number of formula weights of equivalent reactant such that, for ideal gases,

$$p_i = n_i \tag{21}$$

This is the same as saying that the reaction takes place in a volume V numerically equal to RT. Each condensed phase is considered to occupy a negligible volume with respect to the volume occupied by the gases, even when finely divided and suspended in the gas. Condensed phases are further discussed in the subsequent section on "Condensation phenomena."

ITERATION TECHNIQUE

The two sets of equations ((5), (9), (11), (13), and (17), and (5), (9), (11), (13), and (20)) are sets of nonlinear equations, and therefore it is usually not feasible to find a direct solution. The Newton-Raphson method for solving nonlinear equations (ref. 23) is well suited to this type of calculation. In this method the finite-difference approximation to the total differential serves as a basis for the iteration procedure. This method will be illustrated by a simple example.

Let Q_1 and Q_2 be two nonlinear functions of x and y:

$$\left.\begin{aligned} Q_1 = Q_1(x,y) = 0 \\ Q_2 = Q_2(x,y) = 0 \end{aligned}\right\} \tag{22}$$

and let their simultaneous solution be $\overline{x},\overline{y}$. For any other values of x and y, say x_i,y_i,

$$\left.\begin{aligned} Q_1(x_i,y_i) \neq Q_1(\overline{x},\overline{y}) \\ Q_2(x_i,y_i) \neq Q_2(\overline{x},\overline{y}) \end{aligned}\right\} \tag{23}$$

or

$$\left.\begin{aligned} \Delta Q_1 = Q_1(\overline{x},\overline{y}) - Q_1(x_i,y_i) \\ \Delta Q_2 = Q_2(\overline{x},\overline{y}) - Q_2(x_i,y_i) \end{aligned}\right\} \tag{24}$$

The total differentials of (22) are

$$\left.\begin{aligned} dQ_1 &= \frac{\partial Q_1}{\partial x}\,dx + \frac{\partial Q_1}{\partial y}\,dy \\ dQ_2 &= \frac{\partial Q_2}{\partial x}\,dx + \frac{\partial Q_2}{\partial y}\,dy \end{aligned}\right\} \quad (25)$$

In finite-difference form, these become

$$\left.\begin{aligned} \Delta Q_1 &= \left(\frac{\partial Q_1}{\partial x}\right)\Delta x + \left(\frac{\partial Q_1}{\partial y}\right)\Delta y \\ \Delta Q_2 &= \left(\frac{\partial Q_2}{\partial x}\right)\Delta x + \left(\frac{\partial Q_2}{\partial y}\right)\Delta y \end{aligned}\right\} \quad (26)$$

If the difference terms ΔQ_1 and ΔQ_2 and the analytic expressions for the partial derivatives are evaluated numerically at the point x_i, y_i, the correction variables Δx and Δy can be solved for simply, since equation (26) is a simultaneous linear set of equations in the correction variables.

Because equation (26) is not exact,

$$\left.\begin{aligned} x_{i+1} &= x_i + \Delta x \neq \bar{x} \\ y_{i+1} &= y_i + \Delta y \neq \bar{y} \end{aligned}\right\} \quad (27)$$

but rather x_{i+1} and y_{i+1} will in general be a closer approximation to $\bar{x}$ and $\bar{y}$ than are x_i and y_i. The process of solving for corrections Δx and Δy is repeated until Δx and Δy (or ΔQ_1 and ΔQ_2) are sufficiently small.

Linear Correction Equations

Equations. - The finite-difference form of the total differential of equations (5), (9), (11), (13), (17), and (20) in terms of logarithmic correction variables is

$$\left.\begin{aligned}
A\,\Delta a &= A(a_0 - a) = \sum_i a_i n_i \,\Delta \ln n_i - \sum_i a_i n_i \,\Delta \ln A \\
A\,\Delta b &= A(b_0 - b) = \sum_i b_i n_i \,\Delta \ln n_i - \sum_i b_i n_i \,\Delta \ln A \\
A\,\Delta c &= A(c_0 - c) = \sum_i c_i n_i \,\Delta \ln n_i - \sum_i c_i n_i \,\Delta \ln A \\
\cdots &= \cdots\cdots = \cdots\cdots\cdots\cdots\cdots
\end{aligned}\right\} \quad (28)$$

E-417

$$-\delta_i = \Delta \ln p_i - (a_i \,\Delta \ln p_Z + b_i \,\Delta \ln p_Y + c_i \,\Delta \ln p_X + \ldots) - q_i \,\Delta \ln T \quad (29)$$

CA-2

$$\left.\begin{aligned}
-\delta_N &= -(a_N \,\Delta \ln p_Z + b_N \,\Delta \ln p_Y + c_N \,\Delta \ln p_X + \ldots) - q_N \,\Delta \ln T \\
\cdots &= \cdots
\end{aligned}\right\} \quad (30)$$

where $q = \dfrac{\Delta H_T^{\circ}}{RT} = \dfrac{\partial\left(-\dfrac{\Delta F_T^{\circ}}{RT}\right)}{\partial \ln T}$;

$$\Delta P = (P_0 - P) = \sum_i p_i \,\Delta \ln p_i \quad (31)$$

$$A\,\Delta H = A(H_0 - H) = \sum_i (H_T^{\circ})_i n_i \,\Delta \ln n_i - \sum_i (H_T^{\circ})_i n_i \,\Delta \ln A + T \sum_i (C_P^{\circ})_i n_i \,\Delta \ln T \quad (32)$$

$$A\,\Delta S = A(S_0 - S) = \sum_i (S_T)_i n_i \,\Delta \ln n_i - \sum_i (S_T)_i n_i \,\Delta \ln A + \sum_i (C_P^{\circ})_i n_i \,\Delta \ln T \quad (33)$$

where

$$(S_T)'_i \begin{cases} = (S_T^o)_i - R(1 + \ln p_i) = (S_T)_i - R & \text{for gases} \\ = (S_T^o)_i & \text{for condensed phases} \end{cases} \qquad (34)$$

The values for Δa, Δb, Δc, . . ., $(-\delta_i)$, $(-\delta_N)$, . . ., ΔP, ΔH, and ΔS serve to indicate the error still left in the system of equations with the estimates n_i, A, and T.

E-417

Relation between δ_i and q_i. - For purposes of machine computation, it was found more convenient to write equations (8) and (10) in a different form. The relation

$$\left(\frac{\Delta F_T^o}{RT}\right)_i = \left(\frac{\Delta H_T^o}{RT}\right)_i - \left(\frac{\Delta S_T^o}{R}\right)_i = q_i - \left(\frac{\Delta S_T^o}{R}\right)_i \qquad (35)$$

is used to eliminate $(\Delta F_T^o/RT)_i$ in equations (8) and (10), which become

$$\delta_i = q_i - \left[\left(\frac{S_T^o}{R}\right)_i - \ln p_i\right] + a_i\left[\left(\frac{S_T^o}{R}\right)_Z - \ln p_Z\right] + b_i\left[\left(\frac{S_T^o}{R}\right)_Y - \ln p_Y\right] + c_i\left[\left(\frac{S_T^o}{R}\right)_X - \ln p_X\right] + \ldots \qquad (36)$$

$$\delta_N = q_N - \left[\left(\frac{S_T^o}{R}\right)_N\right] + a_N\left[\left(\frac{S_T^o}{R}\right)_Z - \ln p_Z\right] + b_N\left[\left(\frac{S_T^o}{R}\right)_Y - \ln p_Y\right] + c_N\left[\left(\frac{S_T^o}{R}\right)_X - \ln p_X\right] + \ldots \qquad (37)$$

Matrix Representation of Correction Equations

Matrix. - The augmented matrix for the combustion problem (eqs. (28) to (32)) is given in figure 1. The augmented matrix for the expansion problem is identical to that for combustion, except that equation (32) is replaced by equation (33), as indicated in the footnote in figure 1. A direct elimination of the correction variables pertaining to the gaseous molecules gives a new matrix whose order is equal to the sum of the different chemical elements and condensed phases plus 2. This reduced matrix is presented as figure 2, where the correction variables for the condensed phases are linear rather than logarithmic to permit a greater symmetry in the coefficient matrix.

In figure 2 and elsewhere in this report, the symbol p_i is used in summations that include only gaseous reaction products, whereas the symbol n_i is used in summations that include condensed as well as gaseous reaction products.

Condensation phenomena. - In this report, a molecular species which appears in a condensed phase is considered to be independent of the same species in the gaseous phase. The vapor pressure is assigned completely to the gas phase, and a zero vapor pressure is assigned to the condensed phase. Two separate equilibrium equations (eqs. (8) and (10)) are written for this species, one for the gaseous phase and one for the condensed. The vapor-condensed-phase equilibrium is implicit in these two equations.

The present program is capable of considering several situations when the chemical system is such that condensed reaction products are possible. In the first situation, a condensed product is assumed to be present. After the equilibrium compositions have been determined, the assumption is checked. If correct, the program continues; if incorrect (a negative value for the amount of the condensed product), the program automatically restarts the calculations with this condensed phase excluded. In a second situation, a condensed phase is assumed to be not present. After equilibrium compositions have been determined, if the assumption is correct the program continues. If the assumption is incorrect (the partial pressure of the condensable gas exceeds the vapor pressure), the program automatically restarts the calculations with the condensed phase included.

The criterion for condensation is easily obtained from the equilibrium constant. Thus, for the reaction

$$(Z_{a_i} Y_{b_i} X_{c_i} \ . \ . \ .)_g = (Z_{a_N} Y_{b_N} X_{c_N} \ . \ . \ .)_c \tag{38}$$

where $a_i = a_N$, $b_i = b_N$, $c_i = c_N$ . . ., the equilibrium constant is

$$K = \frac{K_N}{K_i} = \frac{1}{p_{vap}} = e^{-\left[\frac{(F_T^o)_c - (F_T^o)_g}{RT}\right]} \tag{39}$$

Condensation occurs when

$$p_i \geq p_{vap} = \frac{1}{K}$$

E-417

CA-2 back

or

$$p_i K \geq 1$$

which can be written as

$$\frac{(F_T^o)_c - (F_T^o)_g}{RT} - \ln p_i \leq 0 \tag{40}$$

E-417

THERMODYNAMIC FIRST PARTIAL DERIVATIVES

From the many thermodynamic first partial derivatives, it is possible arbitrarily to select three independent derivatives and then to express all the other possible thermodynamic first partial derivatives in terms of these three. The three thermodynamic derivatives selected for calculation in this report are $(\partial H/\partial T)_P$, $(\partial \ln \mathcal{M}/\partial \ln T)_P$, and $(\partial \ln \mathcal{M}/\partial \ln P)_T$, where $\mathcal{M}$ is the molecular weight of the reaction products as defined in equation (45).

Heat Capacity at Constant Pressure

The enthalpy of the products of reaction per equivalent formula of reactant is given by (16). Since the heat capacity per equivalent formula of reactant is $(\partial H/\partial T)_P$, then the heat capacity of the reaction products per mole of reaction product is

$$\frac{A}{n}\left(\frac{\partial H}{\partial T}\right)_P = C_P^o \tag{41}$$

where

$$n = \sum_i n_i$$

Differentiation of equation (16) gives an expression for $(\partial H/\partial T)_P$ that may be used to obtain C_P^o in equation (41):

$$\left(\frac{\partial H}{\partial T}\right)_P = \frac{1}{AT}\left[\sum_i (H_T^o)_i p_i \left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P + (H_T^o)_N \left(\frac{\partial n_N}{\partial \ln T}\right)_P + (H_T^o)_M \left(\frac{\partial n_N}{\partial \ln T}\right)_P + \right.$$

$$\left. \ldots + T\sum_i (C_P^o)_i n_i - \sum_i (H_T^o)_i n_i \left(\frac{\partial \ln A}{\partial \ln T}\right)_P\right] \tag{42}$$

Equation (42) may be written in another form that was found more convenient with the calculation method of this report. Differentiation of (9) gives the identity

$$\left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P = a_i\left(\frac{\partial \ln p_Z}{\partial \ln T}\right)_P + b_i\left(\frac{\partial \ln p_Y}{\partial \ln T}\right)_P + \cdot \cdot \cdot + q_i \tag{43}$$

Combining equations (41), (42), and (43) gives the following expression for C_P^o:

$$C_P^o = \frac{1}{nT}\left[\sum_i (H_T^o)_i a_i p_i\left(\frac{\partial \ln p_Z}{\partial \ln T}\right)_P + \sum_i (H_T^o)_i b_i p_i\left(\frac{\partial \ln p_Y}{\partial \ln T}\right)_P + \cdot \cdot \cdot \right.$$
$$+ (H_T^o)_N\left(\frac{\partial n_N}{\partial \ln T}\right)_P + (H_T^o)_M\left(\frac{\partial n_M}{\partial \ln T}\right)_P + \cdot \cdot \cdot - \sum_i (H_T^o)_i n_i\left(\frac{\partial \ln A}{\partial \ln T}\right)_P$$
$$\left. + T\sum_i (C_P^o)_i n_i + (H_T^o)_i q_i p_i\right] \tag{44}$$

A comparison of equation (44) with the last row in figure 2 shows that the coefficients of the derivatives are the elements of the enthalpy row. The solution of the partials $(\partial \ln p_Z/\partial \ln T)_P$, $(\partial \ln p_Y/\partial \ln T)_P$, . . ., is discussed in the section on "Derivative Matrices."

Molecular-Weight Derivatives

Each condensed phase is considered to occupy a negligible volume with respect to the volume occupied by the gases, even when finely divided and suspended in the gas. An average molecular weight is then defined to be the weight of the reaction products divided by the number of moles of gaseous products:

$$\mathcal{M} = \frac{\sum_i n_i \mathcal{M}_i}{\sum_i p_i} = \frac{A\,\mathcal{M}_r}{P} \tag{45}$$

where $\mathcal{M}_r$ is the formula weight of the equivalent formula of equation (3). When only gaseous products are formed in the reaction, this definition is identical to the usual definition of an average molecular weight. With the definition of equation (45), the molecular weight is suitable for use in the ideal gas law even when solids are present:

$$\left.\begin{aligned} P &= \frac{\rho RT}{\mathcal{M}} \\ &\text{or} \\ Pv &= \frac{RT}{\mathcal{M}} \end{aligned}\right\} \tag{46}$$

The density ρ or specific volume v in equation (46) is the average value of the mixture of gases and condensed phases. Taking logarithms of equation (45),

$$\ln \mathcal{M} = \ln A + \ln \mathcal{M}_r - \ln P \tag{47}$$

Differentiation of equation (47) with respect to $\ln T$ at constant P gives

$$\left(\frac{\partial \ln \mathcal{M}}{\partial \ln T}\right)_P = \left(\frac{\partial \ln A}{\partial \ln T}\right)_P \tag{48}$$

Differentiation of equation (47) with respect to $\ln P$ at constant T gives

$$\left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T = \left(\frac{\partial \ln A}{\partial \ln P}\right)_T - 1 \tag{49}$$

Differentiation of equation (12) with respect to $\ln A$ at constant T gives

$$\left(\frac{\partial \ln P}{\partial \ln A}\right)_T = \frac{1}{\left(\frac{\partial \ln A}{\partial \ln P}\right)_T} = \frac{1}{P}\sum_i p_i\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T \tag{50}$$

which may be used in equation (49) to give

$$\left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T = \left[\frac{P}{\sum_i p_i\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T} - 1\right] \tag{51}$$

Differentiation of equation (9) gives

$$\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T = a_i\left(\frac{\partial \ln p_Z}{\partial \ln A}\right)_T = b_i\left(\frac{\partial \ln p_Y}{\partial \ln A}\right)_T + \cdots \tag{52}$$

Equations (51) and (52) may be combined to give

$$\left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T = \left[\frac{P}{\sum_i a_i p_i\left(\frac{\partial \ln p_Z}{\partial \ln A}\right)_T + \sum_i b_i p_i\left(\frac{\partial \ln p_Y}{\partial \ln A}\right)_T + \cdots} - 1\right] \tag{53}$$

Comparison of equation (53) and the pressure row in figure 2 shows that the coefficients of the derivatives in equation (53) are the elements of the pressure row.

E-417

Other First Partial Derivatives (γ and C_V^O)

Bridgman (ref. 24) presents a convenient scheme for expressing all first partial derivatives in terms of three first partial derivatives, one of which is the same as selected in this report, $(\partial H/\partial T)_P = C_P^O$, and two of which are different, $(\partial v/\partial T)_P$ and $(\partial v/\partial P)_T$. In order to make use of the tables of reference 24, $(\partial v/\partial T)_P$ and $(\partial v/\partial P)_T$ can be obtained from the derivatives given in this report by means of the following equations, which have been derived from the equation of state for ideal gases with variable molecular weight (eq. (46)):

$$\left(\frac{\partial v}{\partial T}\right)_P = \frac{v}{T}\left[1 - \left(\frac{\partial \ln \mathcal{M}}{\partial \ln T}\right)_P\right] \tag{54}$$

$$\left(\frac{\partial v}{\partial P}\right)_T = -\frac{v}{P}\left[1 + \left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T\right] \tag{55}$$

With the aid of the tables in reference 24 and equations (46), (54), and (55), other first partial derivatives can be expressed in terms of C_P^O, $(\partial \ln \mathcal{M}/\partial \ln T)_P$, and $(\partial \ln \mathcal{M}/\partial \ln P)_T$. As examples, expressions are derived for the isentropic exponent γ, which is used to calculate velocity of sound, and specific heat at constant volume C_V^O.

By definition,

$$\gamma = \left(\frac{\partial \ln P}{\partial \ln \rho}\right)_s = -\left(\frac{\partial \ln P}{\partial \ln v}\right)_s = -\frac{v}{P}\left(\frac{\partial P}{\partial v}\right)_s \tag{56}$$

From Bridgman's tables (ref. 24),

$$\left(\frac{\partial P}{\partial v}\right)_s = \frac{C_P^O/\mathcal{M}}{\left(\frac{C_P^O}{\mathcal{M}}\right)\left(\frac{\partial v}{\partial P}\right)_T + T\left(\frac{\partial v}{\partial T}\right)_P^2} \tag{57}$$

Substituting equations (46), (54), (55), and (57) into equation (56) yields

$$\gamma = \frac{C_P^O/R}{\frac{C_P^O}{R}\left[1 + \left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T\right] - \left[1 - \left(\frac{\partial \ln \mathcal{M}}{\partial \ln T}\right)_P\right]^2} \tag{58}$$

For nonreacting gases ("frozen" composition), $\mathscr{M}$ is a constant, and equation (58) reduces to

$$\gamma = \frac{C_P^o/R}{\dfrac{C_P^o}{R} - 1} \tag{59}$$

By definition and from Bridgman's tables (ref. 24),

$$\frac{C_V^o}{\mathscr{M}} = \frac{1}{\mathscr{M}}\left(\frac{\partial E}{\partial T}\right)_V = \frac{\left(\dfrac{C_P^o}{\mathscr{M}}\right)\left(\dfrac{\partial v}{\partial P}\right)_T + T\left(\dfrac{\partial v}{\partial T}\right)_P^2}{\left(\dfrac{\partial v}{\partial P}\right)_T} \tag{60}$$

Substituting equations (46), (54), and (55) into equation (60) gives

$$C_V^o = C_P^o - R\,\frac{\left[1 - \left(\dfrac{\partial \ln \mathscr{M}}{\partial \ln T}\right)_P\right]^2}{\left[1 + \left(\dfrac{\partial \ln \mathscr{M}}{\partial \ln P}\right)_T\right]} \tag{61}$$

For nonreacting gases, $\mathscr{M}$ is constant, and equation (61) reduces to

$$C_V^o = C_P^o - R \tag{62}$$

Derivative Matrices

The evaluation of the three independent thermodynamic first partial derivatives is possible if the quantities $(\partial \ln p_Z/\partial \ln T)_P$, $(\partial \ln p_Y/\partial \ln T)_P$ . . . $(\partial n_N/\partial \ln T)_P$ . . . $(\partial \ln A/\partial \ln T)_P$ and $(\partial \ln p_Z/\partial \ln A)_T$, $(\partial \ln p_Y/\partial \ln A)_T$, . . . are known. These quantities may be calculated for equilibrium conditions by the solution of a set of simultaneous equations involving the preceding derivatives. The necessary equations for the temperature derivatives may be obtained from equations (5), (9), (11), and (13). Differentiation of these equations with respect to $\ln T$ at constant P gives

$$\left.\begin{aligned}
\sum_i a_i p_i \left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P + a_N\left(\frac{\partial n_N}{\partial \ln T}\right)_P + \cdots - \sum_i a_i n_i\left(\frac{\partial \ln A}{\partial \ln T}\right)_P &= 0\\
\sum_i b_i p_i \left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P + b_N\left(\frac{\partial n_N}{\partial \ln T}\right)_P + \cdots - \sum_i b_i n_i\left(\frac{\partial \ln A}{\partial \ln T}\right)_P &= 0\\
\cdots\cdots\cdots\cdots\cdots\cdots\cdots\cdots\cdots\cdots &= 0
\end{aligned}\right\} \tag{63}$$

$$\left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P - \left[a_i\left(\frac{\partial \ln p_Z}{\partial \ln T}\right)_P + b_i\left(\frac{\partial \ln p_Y}{\partial \ln T}\right)_P + \cdot\cdot\cdot\right] - q_i = 0 \qquad (64)$$

$$\left.\begin{array}{r} a_N\left(\dfrac{\partial \ln p_Z}{\partial \ln T}\right)_P + b_N\left(\dfrac{\partial \ln p_Y}{\partial \ln T}\right)_P + \cdot\cdot\cdot + q_N = 0 \\ \cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot = 0 \end{array}\right\} \qquad (65)$$

$$\sum_i p_i\left(\frac{\partial \ln p_i}{\partial \ln T}\right)_P = 0 \qquad (66)$$

If equation (64) is used to eliminate $(\partial \ln p_i/\partial \ln T)_P$ from equations (63) and (66), then the resulting augmented matrix is identical to the matrix of figure 2 with the last row and column deleted, as shown in figure 3.

CA-3

The derivatives with respect to $\ln A$ at constant T are obtained in a similar fashion. Differentiation of equations (5), (9), and (11) yields:

$$\left.\begin{array}{r} \displaystyle\sum_i a_i p_i\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T + a_N\left(\frac{\partial n_N}{\partial \ln A}\right)_T + \cdot\cdot\cdot - \sum_i a_i n_i = 0 \\ \displaystyle\sum_i b_i p_i\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T + b_N\left(\frac{\partial n_N}{\partial \ln A}\right)_T + \cdot\cdot\cdot - \sum_i b_i n_i = 0 \\ \cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot = 0 \end{array}\right\} \qquad (67)$$

$$\left(\frac{\partial \ln p_i}{\partial \ln A}\right)_T - \left[a_i\left(\frac{\partial \ln p_Z}{\partial \ln A}\right)_T + b_i\left(\frac{\partial \ln p_Y}{\partial \ln A}\right)_T + \cdot\cdot\cdot\right] = 0 \qquad (68)$$

$$\left.\begin{array}{r} a_N\left(\dfrac{\partial \ln p_Z}{\partial \ln A}\right)_T + b_N\left(\dfrac{\partial \ln p_Y}{\partial \ln A}\right)_T + \cdot\cdot\cdot = 0 \\ \cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot\cdot = 0 \end{array}\right\} \qquad (69)$$

If equation (68) is used to eliminate $(\partial \ln p_i/\partial \ln A)_T$ from equation (67), then the resulting augmented matrix is identical to the matrix of figure 2 with the last two rows and columns deleted, as shown in figure 4.

ROCKET PERFORMANCE PARAMETERS

Calculation

The evaluation of rocket performance parameters for a propellant is simple once the temperature and composition are known at combustion and exit points of a nozzle. The following formulas used in computing the various performance parameters were derived from the one-dimensional forms of continuity, energy, and momentum equations and the following assumptions: zero velocity in the combustion chamber, perfect gas law, complete combustion, homogeneous mixing, adiabatic combustion, and isentropic expansion. (The units used were h = cal/g, T = $^{\circ}$K, P = lb force/sq in., A = sq in., w = lb mass/sec, and g_c = 32.174 (lb mass/lb force)(ft/sec^2).)

Specific impulse with ambient and exit pressures equal, (lb force)(sec)/lb mass:

$$I = 294.98\sqrt{\frac{h_c - h}{1000}} \tag{70}$$

Specific impulse in vacuum (ambient pressure zero), (lb force)(sec)/lb mass:

$$I_{vac} = I + P\left(\frac{A}{w}\right) \tag{71}$$

Nozzle area per unit mass-flow rate, (sq in.)(sec)/lb:

$$\frac{A}{w} = \frac{86.4554\ T}{PM\!I} \tag{72}$$

Characteristic velocity, ft/sec:

$$c^* = g_c P_c \frac{A_t}{w} = 32.174\ P_c \frac{A_t}{w} \tag{73}$$

Coefficient of thrust:

$$C_F = \frac{g_c I}{c^*} = 32.174 \frac{I}{c^*} \tag{74}$$

Mach number:

$$M = \frac{U}{a} = \frac{I}{\sqrt{\dfrac{86.4554\ \gamma T}{\mathscr{M}}}} \tag{75}$$

E-417

CA-3 back

Effect of Chamber Pressure on Performance Parameters

For a given pressure ratio P_c/P, the logarithms of the performance parameters given in equations (70) to (74) are very nearly linear in the logarithm of the combustion-chamber pressure P_c. Thus, if any one of the performance parameters is denoted by λ, then, to a good approximation,

$$\left(\frac{\partial \ln \lambda}{\partial \ln P_c}\right)_{P_c/P} = \pi_\lambda \cong \frac{\ln \lambda_2 - \ln \lambda_1}{\ln(P_c)_2 - \ln (P_c)_1} \tag{76}$$

or

$$\frac{\lambda_2}{\lambda_1} \cong \left[\frac{(P_c)_2}{(P_c)_1}\right]^{\pi_\lambda} \tag{77}$$

Analytical expressions are readily obtained for the partial derivatives π_λ by the method indicated in reference 25. Using this technique it is possible to derive the following identities:

$$\pi_I = \frac{RT}{I^2}\left[\frac{1}{\mathscr{M}_c} - \frac{1}{\mathscr{M}}\right] \tag{78}$$

$$\pi_{A/w} = -\left\{\frac{R}{C_P^o \dfrac{\mathscr{M}_c}{\mathscr{M}}}\left[1 - \left(\frac{\partial \ln \mathscr{M}}{\partial \ln T}\right)_P\right] + \frac{1}{\gamma} + \pi_I\right\} \tag{79}$$

$$\pi_\epsilon = \pi_{A/w} - (\pi_{A/w})_t \tag{80}$$

$$\pi_{c*} = 1 + (\pi_{A/w})_t \tag{81}$$

$$\pi_T = \frac{R}{C_P^o}\left[1 - \left(\frac{\partial \ln \mathscr{M}}{\partial \ln T}\right)_P\right] - \frac{R}{C_P^o\left(\dfrac{\mathscr{M}_c}{\mathscr{M}}\right)} \tag{82}$$

$$\pi_{C_F} = \pi_I - \pi_{c*} \tag{83}$$

$$\pi_{I_{vac}} = \frac{I(\pi_I) + (I_{vac} - I)(\pi_\epsilon + \pi_{c*})}{I_{vac}} \tag{84}$$

ITERATION TO AN ASSIGNED MACH NUMBER

It may sometimes be desired to calculate conditions following an isentropic expansion to an assigned Mach number rather than to an assigned pressure. For example, one might wish to find the conditions at the throat of a nozzle where the Mach number is 1. The procedure used in this report for calculating conditions at an assigned Mach number is as follows:

(1) An estimate of pressure corresponding to the assigned Mach number is made.

(2) After equilibrium composition and temperature have been obtained in a manner identical to isentropic expansion to assigned pressure, the Mach number is then calculated.

(3) The error between the desired Mach number and the calculated Mach number is used to obtain a new estimate for pressure.

(4) Steps (2) and (3) are repeated until the desired degree of accuracy is obtained.

The correction to the assumed pressure ratio can be obtained by using a parameter h^*, defined as

$$h^* = h + \frac{M_0^2}{2} \frac{\gamma RT}{\mathscr{M}} \tag{85}$$

where h, γ, T, and $\mathscr{M}$ are values corresponding to the assumed pressure, and M_0 is the assigned Mach number. When the correct pressure (or pressure ratio) is used, h^* will equal the initial enthalpy of the propellants h_c. The estimate for the pressure ratio is corrected on the basis of the difference between h^* and h_c. Since h^* is a function of P,

$$\Delta h^* = \left(\frac{\partial h^*}{\partial \ln P}\right)_s \Delta \ln P \tag{86}$$

where

$$\Delta h^* = h_c - h_k^*$$

and

$$\Delta \ln P = \frac{P_{k+1} - P_k}{P_k}$$

E-417

with the subscript k referring to the k^{th} estimate. Equation (86) then gives

$$\frac{P_c}{P_{k+1}} = \frac{P_c/P_k}{\left[1 + \frac{h_c - h_k^*}{\left(\frac{\partial h^*}{\partial \ln P}\right)_s}\right]} \tag{87}$$

The $(k+1)^{th}$ estimate can be obtained from the k^{th} estimate for the pressure ratio by means of equation (87), provided that $(\partial h^*/\partial \ln P)_s$ can be evaluated. Since γ is essentially constant for a small change in pressure ratio, then from equation (85),

$$\left(\frac{\partial h^*}{\partial \ln P}\right)_s \cong P\left\{\left(\frac{\partial h}{\partial P}\right)_s + \frac{\gamma R M_0^2}{2}\left[\frac{\partial(T/\mathcal{M})}{\partial P}\right]_s\right\} \tag{88}$$

From equation (46) for an ideal gas,

$$\left[\frac{\partial(T/\mathcal{M})}{\partial P}\right]_s = \frac{1}{R\rho}\left[1 - \left(\frac{\partial \ln \rho}{\partial \ln P}\right)_s\right] = \frac{1}{R\rho}\left(\frac{\gamma - 1}{\gamma}\right) \tag{89}$$

Using the thermodynamic relation $(\partial h/\partial P)_s = 1/\rho$ and equation (89) in equation (88) yields

$$\left(\frac{\partial h^*}{\partial \ln P}\right)_s \cong \frac{RT}{\mathcal{M}}\left[1 + \frac{M_0^2}{2}(\gamma - 1)\right] \tag{90}$$

In particular, at the throat $M_0 = 1$ and equation (90) becomes

$$\left(\frac{\partial h^*}{\partial \ln P}\right)_s \cong \frac{RT}{2\mathcal{M}}(\gamma + 1) \tag{91}$$

COMPUTER PROGRAM

A computer program for performing the calculations previously discussed has been made for an IBM 650 Magnetic Drum Data-Processing Machine with 2000 words of drum storage, 60 words of high-speed core storage, indexing registers, floating point attachments, and an alphabetic device. When additional attachments such as tapes and RAMAC are available, the program may be modified to make use of these attachments. A wiring diagram for the IBM type 533 Read-Punch Unit is given in appendix I. In the description of the program, a familiarity with the symbolic coding for the IBM 650 computer (SOAP II) is assumed, as described in IBM Form 32-7646-1, "Soap Programmer's Reference Manual." References to storage

locations will be made with symbolic addresses given in upper case and enclosed by quotes. For the absolute equivalents of the symbolic addresses, the program listing given in appendixes F, G, and H can be consulted.

Because of computer storage limitations, it was necessary to divide the program into two sections, (1) The "Vector and Propellant Program," which prepares most of the input data and requires an alphabetic device on the IBM 650, and (2) The "Main Calculating Program," which solves for the equilibrium compositions and temperatures and the performance parameters. The Main Calculating Program may be used without using the Vector and Propellant Program if the necessary input data are prepared manually. The primary use of the Vector and Propellant Program is to simplify the preparation of input data and to minimize the possibility of errors. However, since the use of the Vector and Propellant Program is optional, the Main Calculating Program will be described first.

MAIN CALCULATING PROGRAM

General Description

Figure 5 gives a schematic outline of the Main Calculating Program. Individual portions of the program will be discussed in more detail in later sections. A SOAP listing of the Main Program is given in appendix F, and operating instructions are given in appendix C.

The program as written is capable of performing thermodynamic equilibrium calculations for both combustion and isentropic expansion conditions for a chemical system that may include as many as 10 different chemical elements (if no condensed phases appear as reaction products). When condensed phases are present as reaction products, then the sum of the different chemical elements and different condensed phases must not exceed 10. This restriction implies that the size of the reduced augmented matrix (fig. 2) is limited to 12×13. It should be emphasized that this restriction is imposed solely by machine storage limitations.

The program will handle as many as 30 reaction products and 25 pressure ratios including the combustion chamber and the throat. The restriction on the number of products and pressure ratios is also the result of storage limitations. The program calculates the equilibrium composition, temperature, pressure, enthalpy, and entropy of the reaction products, and the following performance parameters: specific impulse, specific impulse in vacuum, thrust coefficient, characteristic velocity, area ratio, specific heat, isentropic exponent γ, and Mach number. The program also calculates the derivatives $\left(\frac{\partial \ln \mathcal{M}}{\partial \ln T}\right)_P$, $\left(\frac{\partial \ln \mathcal{M}}{\partial \ln P}\right)_T$, and the chamber-pressure derivatives π_I, π_ϵ, π_T, and π_{c^*}.

Normally the program calculates combustion conditions ($P_c/P = 1$), then throat conditions, and finally other exit conditions corresponding to assigned pressure ratios. The program is easily modified to operate for assigned temperatures and pressures or to work a series of constant-enthalpy calculations at various pressures. The necessary changes in the program are given in the section "Program Modifications."

The following input data are required by the Main Calculating Program for the solution of equilibrium compositions and temperature following an adiabatic combustion process:

(1) The reaction products to be considered

(2) Gram atoms of elements in 1 gram of fuel and 1 gram of oxidant

(3) Enthalpies of fuel and oxidant per gram of fuel and oxidant

(4) Oxidant to fuel weight ratio O/F (or percent fuel or equivalence ratio r)

(5) Thermodynamic data for products considered

(6) Chamber pressure

(7) Initial estimate of temperature, composition, and number of formula weights A. (A set of estimates is already provided by the program and therefore need not be supplied unless a better set is desired.)

Reaction products (the composition vector). - The composition of any product of reaction in terms of the elements may be represented as a chemical vector whose components are determined by the chemical formula for the reaction product. Thus, the molecule $Z_{a_i}Y_{b_i}X_{c_i}$ . . . may be associated with the vector

$$C = \left\{a_i,\ b_i,\ c_i\ .\ .\ .\right\}$$

The number of components associated with each composition vector is known once it is decided how many chemical elements are to be considered in any particular problem. For example, if hydrogen and oxygen were the only two elements appearing, then any reaction product could be specified with two components. If hydrogen, oxygen, and nitrogen were the elements under consideration, then each reaction product would have three components. This is illustrated in the following table for four possible products of reaction involving hydrogen, oxygen, and nitrogen:

Product	Component		
	H	N	O
N	0	1	0
OH	1	0	1
H_2O	2	0	1
NO	0	1	1

A considerable portion of the matrix of figure 2 may be constructed in a reasonably systematic manner with the aid of the composition vector. This is described in the section "Vector multiplication routine."

E-417

Packed chemical vector. - The total number of components of all the chemical vectors is directly related to the size of the chemical system and to the number of possible reaction products. Thus, for a 10-element system in which 30 different products of reaction are to be considered, a total of 300 components requiring 300 storage locations would have to be specified. Since these numbers would be placed in the storage area of a computer with limited storage capacity, the storage area available for programming would be seriously reduced. It has been found that with a few suitable restrictions all the components of a vector may be packed into one 10-digit word, and thus only 30 storages would be required for 30 products. The following restrictions have been set forth:

(1) All the chemical vector components that are not specified are assumed to be zero.

(2) No reaction product may be formed from more than five different chemical elements; that is, the chemical vector may have no more than five nonzero components.

(3) Each subscript in the chemical formula for the reaction product must be less than 10; that is, no vector component may be greater than 9.

The packed chemical vector may now be generated from the chemical formula of a reaction product in the following manner:

(1) Each element in the chemical system is assigned a number equal to one less than its column assignment in the reduced augmented matrix (fig. 2). This number is used to specify the component.

(2) The magnitude of any component is equal to the subscript associated with the chemical element in the chemical formula for the reaction product under consideration.

(3) The packed vector consists of five pairs of numbers. In each pair of numbers (where both numbers are not zero) the number designating the component precedes the number that gives the magnitude of the component.

(4) The nonzero vector components and their associated magnitudes are arranged in the packed vector in the order of their appearance in the chemical formula of the reaction product, the entire packed vector being shifted as far to the right as possible.

(5) The sign of the packed composition vector is positive for a gaseous reaction product and negative for a condensed-phase reaction product.

An example of how components might be designated in an H-N-O system is as follows:

Element	H	N	O
Column of matrix in fig. 2	1	2	3
Number designating component (column number - 1)	0	1	2

The assignment of numbers designating the elements is completely arbitrary. However, once an assignment has been made for some problem, then all product vectors must be consistent with this assignment.

Examples of packed vectors for four reaction products using the numbers designating components given in the previous table are as follows:

Reaction product	Packed vector
N	00 00 00 00 11+
OH	00 00 00 21 01+
H_2O	00 00 00 02 21+
NO	00 00 00 11 21+

To read the preceding packed vectors, proceed as follows:

(1) Pair the digits into groups of two.

(2) The first digit of a pair designates the atom.

(3) The second digit of the pair tells how many of these atoms there are.

E-417

CA-4

(4) The sign is + for gas and - for condensed phases.

For example, the H_2O packed vector may be interpreted as follows:

00 00 00 02 21 +

Ignored because both digits of each pair are zero
Number designating element hydrogen
Magnitude (number of hydrogen atoms)
Number designating element oxygen
Magnitude (number of oxygen atoms)
Gaseous product

Calculation of gram atoms of elements in fuel and oxidant or in reactant. - To specify a reactant, the relative proportion of the elements in the reactant is all that is required. That is, the absolute magnitude of the elements $a_0, b_0, c_0, \ldots$ in the equivalent reactant $Z_{a_0}Y_{b_0}X_{c_0} \ldots$ is immaterial if their ratios remain constant. In the IBM 650 program the number of gram atoms of each element in a reactant is calculated to be that number which gives an equivalent formula with a formula weight $\mathcal{M}_r$ of 1.

For example, the equivalent formula in equation (1) ($H_7N_2O_3$) has a molecular weight of 83.072. In the IBM 650 program the equivalent formula would be $H_{(7/83.072)}\,N_{(2/83.072)}\,O_{(3/83.072)}$ or $H_{0.08426}\,N_{0.02408}\,O_{0.03611}$ ($\mathcal{M}_r = 1$).

The method selected in this report for the calculation of the gram atoms of element per gram of reactant was based on the assumption that performance data for a particular reactant would be desired for a number of oxidant-fuel ratios. For this reason, the input to the Main Calculating Program consists of the number of gram atoms of each element per gram of fuel and the number of gram atoms of each element per gram of oxidant. The number of gram atoms of each element per gram of reactant can then be calculated from these quantities as soon as the oxidant-fuel ratio (or % fuel or equivalence ratio r) is specified as shown in the following discussion.

The fuels are considered to be those materials undergoing oxidation primarily and the oxidants those materials undergoing reduction primarily. Let 1 gram of equivalent fuel be $Z_{a_f}Y_{b_f}X_{c_f} \ldots$ and 1 gram of equivalent oxidant be $Z_{a_x}Y_{b_x}X_{c_x} \ldots$ where $a_f, b_f, c_f \ldots$ and $a_x, b_x, c_x \ldots$ are the number of gram atoms of elements $Z, Y, X \ldots$ in 1 gram of equivalent fuel and 1 gram of equivalent oxidant, respectively. If W_x is the weight of the oxidant and W_f the weight of

the fuel ($O/F = W_x/W_f$), then the number of gram atoms of each element in 1 gram of equivalent reactant $Z_{a_0}Y_{b_0}X_{c_0}$ . . . is

$$\left.\begin{aligned} a_0 &= \frac{W_x a_x + W_f a_f}{W_x + W_f} = \frac{(O/F)a_x + a_f}{(O/F) + 1} \\ b_0 &= \frac{W_x b_x + W_f b_f}{W_x + W_f} = \frac{(O/F)b_x + b_f}{(O/F) + 1} \\ \cdot\ \cdot &= \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot = \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot\ \cdot \end{aligned}\right\} \tag{92}$$

Equation (92) may be illustrated by considering the example of equation (1):

$$N_2H_4 + \frac{3}{2} H_2O_2 \tag{1}$$

The formulas per gram of equivalent fuel and oxidant are

$$\left.\begin{aligned} N_{(2/32.048)}\ H_{(4/32.048)} &= N_{0.062406390}\ H_{0.12481278} \\ H_{(2/34.016)}\ O_{(2/34.016)} &= H_{0.058795860}\ O_{0.058795860} \end{aligned}\right\} \tag{93}$$

(Eight significant figures are kept in this example, since the IBM 650 floating point attachment keeps eight significant figures.) For equation (1),

$$O/F = \frac{1.5(34.016)}{32.048} = 1.5921118 \tag{94}$$

and therefore

$$\left.\begin{aligned} (H)\ a_0 &= \frac{1.5921118(0.058795860) + 0.12481278}{1.5921118 + 1} = 0.084264252 \\ (N)\ b_0 &= \frac{1.5921118(0) + 0.062406390}{1.5921118 + 1} = 0.024075501 \\ (O)\ c_0 &= \frac{1.5921118(0.058795860) + 0}{1.5921118 + 1} = 0.036113250 \end{aligned}\right\} \tag{95}$$

Calculation of enthalpy of fuel and oxidant or of propellant. - Let h_f and h_x be the enthalpy per gram of equivalent fuel and per gram of equivalent oxidant, respectively. Then the enthalpy per gram of equivalent reactant $Z_{a_0}Y_{b_0}X_{c_0}$ . . . is

$$H_0 = h_0 = \frac{(O/F)h_x + h_f}{(O/F) + 1} \tag{96}$$

Equation (96) may be illustrated by again considering the reaction of equation (1). Using values similar to those on page 19 of reference 9 and the O/F value from equation (94),

$$\left.\begin{aligned} h_{N_2H_4} &= h_f = \frac{154{,}702.97}{32.048} = 4827.2269 \text{ cal/g} \\ h_{H_2O_2} &= h_x = \frac{28{,}681.626}{34.016} = 843.18043 \text{ cal/g} \end{aligned}\right\} \tag{97}$$

$$h_0 = \frac{1.5921118\ (843.18043) + 4827.2269}{1.5921118 + 1} = 2380.1691 \text{ cal/g} \tag{98}$$

Optional specification of O/F. - In addition to the oxidant to fuel weight ratio O/F, two other quantities may be used to give the relative amounts of oxidant and fuel. One of these is the weight percent of fuel in the propellant %F and the other is the equivalence ratio r.

(1) %F: The relation between O/F and %F is given by

$$\%F = \frac{100}{(O/F) + 1} \tag{99}$$

(2) Equivalence ratio r: The equivalence ratio is defined in terms of arbitrary, permanently assigned oxidation states for each element in a compound. This practice produces no difficulty so long as all the elements have the assigned oxidation state in all their compounds (e.g., H = +1, Na = +1, F = -1). Some elements have various oxidation states; for example, sulfur, which has the oxidation numbers -2, +4, +6 in the compounds H_2S, SO_2, and H_2SO_4, respectively. In cases such as this the assigned oxidation states are taken to be those considered as occurring commonly in products. For this reason it is possible that some components of the propellant combination may show a net positive or negative oxidation state, contrary to the usual practice of having the sum of the oxidation numbers of a compound add up to zero.

Let V_Z^+, V_Y^+, V_X^+ . . . be the positive oxidation states and V_Z^-, V_Y^-, V_X^- . . . be the negative oxidation states of the elements Z, Y, X . . in the reactant. Let V_x^+ and V_x^- be the total positive oxidation state and total negative oxidation state, respectively, per gram of equivalent oxidant, and let V_f^+ and V_f^- be the total positive and negative oxidation states, respectively, per gram of equivalent fuel. Then,

$$\left.\begin{aligned}
V_x^+ &= \left[a_x V_Z^+ + b_x V_Y^+ + c_x V_X^+ + \ldots\right] \\
V_x^- &= \left[a_x V_Z^- + b_x V_Y^- + c_x V_X^- + \ldots\right] \\
V_f^+ &= \left[a_f V_Z^+ + b_f V_Y^+ + c_f V_X^+ + \ldots\right] \\
V_f^- &= \left[a_f V_Z^- + b_f V_Y^- + c_f V_X^- + \ldots\right]
\end{aligned}\right\} \tag{100}$$

The total positive oxidation state V^+ and total negative oxidation state V^- per gram of propellant are

$$\left.\begin{aligned}
V^+ &= \frac{(O/F)V_x^+ + V_f^+}{(O/F) + 1} \\
V^- &= \frac{(O/F)V_x^- + V_f^-}{(O/F) + 1}
\end{aligned}\right\} \tag{101}$$

The equivalence ratio may now be defined as

$$r \equiv \left|\frac{V^-}{V^+}\right| = \left|\frac{V_f^- + (O/F)V_x^-}{V_f^+ + (O/F)V_x^+}\right| \tag{102}$$

This definition of r gives $r = 1$ for stoichiometric conditions, $r > 1$ for oxidant-rich conditions, and $r < 1$ for fuel-rich conditions. For those who prefer to consider $r > 1$ for fuel-rich conditions and $r < 1$ for oxidant-rich conditions, the reciprocal of r in equation (102) may be taken as the definition of equivalence ratio, provided that the computing program be correspondingly modified.

The reaction of equation (1) may be again taken to illustrate equations (100) and (102). Let a, b, c refer to H, N, O, respectively. Then, from equation (100),

$$\left.\begin{aligned}
H_2O_2 &\begin{cases} V_x^+ = [2(1) + (0)(0) + 2(0)]/34.016 = 0.058795860 \\ V_x^- = [2(0) + (0)(0) + 2(-2)]/34.016 = -0.11759172 \end{cases} \\
N_2H_4 &\begin{cases} V_f^+ = [4(1) + 2(0) + 0(0)]/32.048 = 0.12481278 \\ V_f^- = [4(0) + 2(0) + 0(0)]/32.048 = 0 \end{cases}
\end{aligned}\right\} \tag{103}$$

From equation (102), and using the $O/F = 1.5921118$ of equation (94),

$$r = \left| \frac{(1.5921118)(-0.11759172) + 0}{(1.5921118)(0.058795860) + 0.12481278} \right| = 0.85714286 \qquad (104)$$

For any problem it is sufficient to specify any one of the three quantities O/F, %F, or r, since any two may be expressed in terms of the third. (See eqs. (99) and (102), e.g.)

E-417

Thermodynamic data. - Since the computer program solves for temperature simultaneously with composition, it was found convenient to represent the thermodynamic data for each product as a function of temperature as follows:

$$C_P^o/R = A + BT + CT^2 + DT^3 \qquad (105)$$

$$H_T^o/RT = A + \frac{BT}{2} + \frac{CT^2}{3} + \frac{DT^3}{4} + \frac{E}{T} \qquad (106)$$

$$S_T^o/R = A \ln T + BT + \frac{CT^2}{2} + \frac{DT^3}{3} + F \qquad (107)$$

where T is in degrees Kelvin. The function H_T^o/RT must include H_0^o/RT, where H_0^o is the reference enthalpy at 0^o K (see eq. (14)).

In order to minimize the errors resulting from a functional representation of the thermodynamic data, the six coefficients A, B, C, D, E, and F for each product were obtained from a simultaneous least-squares fit of the thermodynamic functions C_P^o/R, H_T^o/RT, and S_T^o/R for several selected temperature intervals with continuity from one interval to the next. Coefficients for several substances in the C, H, O, N, F, and Cl chemical system are given in table I.

Calculating Routines

The Main Calculating Program consists of ten major routines and several auxiliary routines with suitable connecting links. These routines are described in the following sections.

Packed vector loading routine. - The flow chart for the packed vector loading routine is given in figure 6. This short program permits direct loading of the packed vectors from the Vector and Propellant Program. The packed vectors are in the form of load hub cards on which the second word gives the permanent code number associated with the reaction product, and the fourth word gives the packed vector for the same product. The permanent code and the packed vector are loaded into sequential locations in

the P region; that is, the code and packed vector from the first card are placed into "P0001" and "P0002," respectively; the code and vector from the next card are placed into "P0003" and "P0004," and so forth.

When the program encounters a condensed phase, it examines the contents of the word "OASIS" to determine whether or not this product is to be considered in the first iteration. Thereafter, the decision to use or not to use a condensed phase is made internally. All positions of "OASIS" must be either zero or one, a zero indicating use and one indicating nonuse of a condensed phase. Each position of "OASIS" corresponds to a different condensed phase; thus position 1 (right-most position) is associated with the first condensed phase encountered, position 2 with the second, and so forth. For example, if "OASIS" contained

00 0000 1101 +

the program would not initially consider the first, third, and fourth condensed phases encountered. Should only two condensed-phase packed vectors be present, the program will ignore all positions beyond the first two. If the operator does not specify the contents of "OASIS," the program puts ones in all positions, thus initially considering only the gas phase.

The packed vector loading routine requires a transfer card to precede the first packed vector. The transfer card is a load hub card on which the first word is

NOP 0000 V0001 + (or numerical equivalent, 000000 1599+)

The last packed vector must be followed by another load hub card on which the first word is

00 0000 0000+

The packed vectors themselves must be arranged so that all the gaseous atoms enter storage before any gaseous molecules or condensed phases. If this condition is not met, a programmed stop will halt the loading. (The vectors for gaseous atoms may be loaded in any order followed by the remainder of the vectors in any order. However, the thermal data coefficients must be loaded in the same order as the vectors.) As each gaseous atom and each condensed-phase vector considered by "OASIS" is placed into storage, it is counted so that the two constants "ATOM1" and "SYS," used to specify the size of the reduced augmented matrix, may be obtained. Both of these are fixed point numbers in the low-order positions. "ATOM1" gives the number of different elements in the chemical system, and "SYS" gives the number of elements plus the condensed phases currently being considered. During the course of loading packed vectors, any load card with word 2 blank or zero will be bypassed.

Input data routine. - The flow chart for the input data routine is given in figure 7. The routine converts the input data as specified by the operator into suitable form for use in the computer. Thus, using equations (99) and (102), it calculates any two of the quantities O/F, r, and %F from the one which is supplied by the operator. The numbers a_O, b_O, c_O, . . . h_O are calculated from a_f, a_x, b_f, b_x, . . . h_x, h_f using equations (92) and (96). Also, the combustion-chamber pressure in pounds per square inch absolute is converted to atmospheres.

The input data for this routine and, hence, for the general program consist of the following:

(1) A 4-digit identification number for the problem (case no.) is loaded into "F0039" as

0000 Case no. 00+

(2) The chamber pressure P_c in pounds per square inch absolute is loaded into "F0000."

(3) The numbers a_x, b_x, . . . j_x; h_x, V_x^+, and V_x^- are loaded into locations 0537, 0538, . . .; 0547, 0548, and 0549, respectively, and the numbers a_f, b_f, . . . j_f; h_f, V_f^+, and V_f^- are loaded into locations 0587, 0588, . . .; 0597, 0598, and 0599, respectively. If the Vector and Propellant Program is used, these numbers will be prepared automatically.

(4) Any one of the three quantities O/F, r, and %F is loaded into "O/F," "EQRAT," or "PCT F," respectively, while the other two are loaded as zero.

(5) A schedule of up to 25 pressure ratios is loaded into the region R(1075-1099).

A set of estimates for $\ln p_i$, n_N, $\ln T$, and $\ln A$ is already provided by the program and need not be supplied unless one wishes to use a better set of estimates. Convergence usually occurs without good estimates.

The output from this routine is seven Bell format cards (see discussion in section on "Auxiliary routines" and also appendix B). The first Bell card contains the following six words: r, O/F, %F, P_c (atm), h_O (cal/g), and the identification number for the problem. The identification number is a composite of the equivalence ratio, the case number, and the chamber pressure in pounds per square inch absolute. The input data a_f, b_f, . . . j_f; h_f, V_f^+, V_f^-, a_x, b_x, . . . j_x; h_x, V_x^+, and V_x^- are punched out on the next six Bell cards. A console-controlled punch can be used to obtain the calculated numbers a_O, b_O . . . (h_O/R).

Load thermal data routine. - The thermodynamic data for each reaction product are represented by six coefficients A, B, C, D, E, and F, which were discussed in the section on "Thermodynamic data." The routine requires the coefficients to be on a load hub card in columns 21 through 80 (the last six words). The first word on the card is actually the first instruction in the routine following the read command for a basic load card and is

RAL 9051 RDB

The second word is the identification for the card, being a composite of the permanent code for the molecule and the low temperature (divided by 10) and high temperature (divided by 10) of the interval for which the coefficients were obtained. Thus, if the code for the molecule is 0121 and the temperature range is from 2600° to 3200° K, word 2 would be

Code	T_{low}	T_{high}
0121	260	320

With this scheme no molecule may have a code greater than four digits in length or a temperature interval higher than 9990° K.

The information from a thermodynamic coefficient card appears on the drum in a block of ten consecutive storages in the T region. The first word of the block contains the permanent code for the molecule in the instruction address position. For the previous example this would be

00 0000 0121

The following six storage positions contain the thermal coefficients. The eighth word is reserved for the composition estimate $\ln p_i$ or n_N, while the last two words of the block are reserved for q_i and $-\delta_i$. Since the sequential blocks of ten storages are assigned to reaction products on the basis of their order of appearance, within any temperature interval the order of the thermal data cards must match the order of the packed vectors. If this is not so, a programmed stop will halt the loading of the thermal coefficients.

Each set of basic load cards corresponding to some temperature interval must be followed by a Bell format card that is filled with zeros except for words 1 (columns 11 to 21) and 2 (columns 22 to 32). Word 1 is the floating point number for the low temperature, and word 2 is the floating point number for the high temperature of the interval covered by the preceding cards.

The flow chart for the load thermal data routine is given in figure 8.

Unpacking routine and thermal routine. - The purpose of the unpacking and thermal routines is to construct a "row vector." This row vector is a set of consecutive core storage locations representing a convenient arrangement of quantities that will eventually be used to construct the elements of the reduced augmented matrix. The row vector and its contents are as follows:

Symbolic location	Absolute location	Contents
RV000	9004	$(H_T^\circ/R)_i$ During expansion, zero during combustion
RV001	9005	a_i
RV002	9006	b_i
RV003	9007	c_i
RV004	9008	d_i
RV005	9009	e_i Composition vector components as floating point numbers
RV006	9010	f_i
RV007	9011	g_i
RV008	9012	h_i
RV009	9013	i_i
RV010	9014	j_i
RV011	9015	1 For gas, 0 for condensed
RV012	9016	q_i
RV013	9017	δ_i
RV014	9018	$(H_T^\circ/R)_i$ For combustion, $(S'/R)_i$ for expansion

Storage space has been provided for ten subscripts or ten components of the composition vector. If the chemical system being used does not require ten components, then the first component appears in the location "RV011" minus "SYS" and is followed by the remaining components. The locations from "RV001" to "RV010" minus "SYS" inclusive remain zero. The unpacking routine fills in the locations "RV001" through "RV011" inclusive, the thermal routine completing the remaining quantities. The flow chart for the unpacking routine is given in figure 9, while the thermal routine is given in figure 10.

Vector multiplication routine. - The vector multiplication routine calculates the elements of the reduced augmented matrix by multiplication of vectors. The gaseous-product contributions to the matrix elements of the mass-balance equations in figure 2 are generated by the following operation:

$$\begin{bmatrix} a_i p_i \\ b_i p_i \\ \cdot\ \cdot\ \cdot \\ \cdot\ \cdot\ \cdot \\ \cdot\ \cdot\ \cdot \\ j_i p_i \end{bmatrix} \qquad \begin{bmatrix} a_i, b_i, \ . \ . \ . \ j_i, 1, q_i, \delta_i \end{bmatrix} \tag{108}$$

Only those terms that are on or to the right of the principal diagonal are filled in. The gaseous-product contributions to the pressure-row elements are obtained from

$$p_i \begin{bmatrix} a_i, b_i, \ . \ . \ . \ j_i, 0, q_i, \delta_i \end{bmatrix} \tag{109}$$

The gaseous-product contributions to the enthalpy-row elements are obtained from

$$\frac{p_i (H_T^O)_i}{R} \begin{bmatrix} a_i, b_i, \ . \ . \ . \ j_i, 1, q_i, \delta_i \end{bmatrix} \tag{110}$$

An entropy row is used in place of the enthalpy row during expansion, and the gaseous-product contributions to the entropy-row elements are given by

$$\frac{p_i S_i'}{R} \begin{bmatrix} a_i, b_i, \ . \ . \ . \ j_i, 1, q_i, \delta_i \end{bmatrix} \tag{111}$$

The condensed products each contribute a row to the reduced augmented matrix, which, for $Z_{a_N} Y_{b_N} X_{c_N} \ . \ . \ .$, is

$$\begin{bmatrix} a_N, b_N, \ . \ . \ . \ j_N, 0, q_N, \delta_N \end{bmatrix} \tag{112}$$

and, in addition, the contribution of this condensed product to the column $(-\Delta \ln A)$ is

$$\begin{bmatrix} a_N n_N \\ b_N n_N \\ \cdot\ \cdot\ \cdot \\ \cdot\ \cdot\ \cdot \\ \cdot\ \cdot\ \cdot \\ j_N n_N \\ 0 \\ (H_T^O)_N n_N \end{bmatrix} \tag{113}$$

E-417

The flow chart for this routine is given in figure 11.

Matrix completion routine. - This routine completes the matrix by calculating and adding to the appropriate matrix elements the quantities $A\,\Delta a$, $A\,\Delta b$, . . . ΔP, $A\,\Delta h$, $\sum_i (C_P^o)_i n_i / R$ or $T \sum_i (C_P^o)_i n_i / R$, and reflecting the symmetric portions of the matrix about the diagonal. During expansion, $\sum_i (S_T)_i n_i / R$ replaces the term in the entropy row and $-\Delta \ln A$ column. When this has been completed, the routine examines all the error terms, requiring them to be smaller than some preassigned value before the iteration process is halted. After convergence is complete, the program checks to make sure that the thermal data for the correct temperature interval were used and examines the partial pressures of the condensable materials to ascertain whether or not condensed-phase products should have been considered. The flow chart for this routine is given in figure 12.

E-417

Matrix solution routine. - The correction variables for the gaseous atoms and condensed phases are obtained from the reduced augmented matrix (fig. 2) by the matrix solution routine presented in figure 13. The corrections to the gaseous molecules are obtained from the correction equations for the gaseous atoms using equation (29). When the iteration process has converged to the equilibrium values, this same routine is used to solve the two sets of equations discussed in the section on "Derivative Matrices."

The solution routine carries out a Gauss reduction on the linear set; that is, it eliminates the first variable from all equations following the first equation, the second variable from all equations following the second equation, and so on. The solution routine assumes that the equations appear in consecutive bands of storage, the n^{th} equation in band one, the $(n - 1)^{th}$ equation in band two, and so forth. Thus, the energy equation appears in band one and the pressure equation in band two. Within each band the coefficients of the variables are placed in consecutive storage locations with the constant term appearing in the last storage location of the band.

The number of equations to be solved must appear as an integer in the low-order positions of the upper accumulator when entering the routine. For the correction equations, this is specified by the constant "SYS + 2." The results of the solution appear in the first band with the first variable appearing in location 0049-"(SYS + 1)" as shown in the following table:

E-417

Storage location	Variable
0049 - "(SYS + 1)"	$\Delta \ln n_Z$
0049 - "(SYS)"	$\Delta \ln n_Y$
0049 - "(SYS - 1)"	$\Delta \ln n_X$
----------------	-------
----------------	-------
0046	Δn_M
0047	Δn_N
0048	$-\Delta \ln A$
0049	$\Delta \ln T$

Two entries to the routine are provided. The first is at location "SOLVE," and the second is at location "BACK." The first entry is used when the Gauss reduction must be performed, while the second is used when the reduction has already been accomplished and only the back solution is needed.

The solution routine can run into difficulty in several situations while carrying out the Gauss reduction. The first happens when the machine attempts to perform a floating multiplication of two numbers that are so small that the resulting product would be less than 10^{-51}, and an underflow occurs. This has been taken care of for several operations by using branch on overflow commands and replacing the result of the multiplication by a zero if underflow occurs.

A second difficulty occurs when the coefficient matrix of figure 2 is singular or nearly singular; that is, its determinant is zero or very nearly so. In this case, because of the way in which the reduction is performed, the machine attempts division by zero. This problem arises when the system is such that within the precision of the calculations only one reaction product exists, as may occur for stoichiometric conditions at low temperatures. For example, in the chemical system hydrogen and oxygen at low temperatures and stoichiometric conditions, gaseous water is the only reaction product of any significance. This type of difficulty may be handled by changing the relative amounts of oxidant and fuel slightly from stoichiometric conditions (perhaps 1 to 10 parts per million) and repeating the calculation.

A third, and perhaps the most difficult, situation occurs when the coefficient matrix is poorly conditioned. For example, if the coefficient of the k^{th} variable in the k^{th} equation is small relative to the coefficients of the $(k + 1)^{th}$, $(k + 2)^{th}$, . . . variables in the same equation, and if the k^{th} equation is then used to eliminate the k^{th}

variable from the $(k + 1)^{th}$, $(k + 2)^{th}$, . . . equations at an early stage of the calculations, then large rounding errors may occur. This situation occurs more often when condensed phases are present in the calculation than when only gaseous products are considered. In particular, if one chemical element appears almost exclusively in the condensed phase, the matrix element for this chemical element, which appears on the diagonal, will be very small. Should the row containing this small element be used to eliminate its variable at an early stage of the solution, then large rounding errors may occur, causing the solution vector obtained to bear little resemblance to the true solution vector.

To take care of this situation, a modified pivot method has been incorporated into the solution routine. This feature may be used at the operator's discretion, since it is console-controlled. An 8 in position one of the console (right-most position) causes pivoting. Prior to each elimination, the program examines the remaining equations and selects the best one for eliminating the next variable. The program selects the best equation to be that equation in which the coefficients differ by the smallest amount after division by the coefficient of the variable to be eliminated.

For the usual problems involving only gaseous products and those for which graphite is the only condensed phase, adequate solutions can be obtained without use of the modified pivoting routine. If no difficulty is expected, it is recommended that the pivot feature not be used, since each iteration will require more time.

Correction routine and performance-parameter routine. - The correction routine (fig. 14) applies the corrections to the estimates during the course of iteration. Once the iteration procedure has converged to a solution, the performance-parameter routine (fig. 15) calculates the performance parameters.

Auxiliary routines. - During the course of calculations it is necessary to use subroutines for exponentiation, taking square roots, and for punching the results of the calculations on Bell format cards. The subroutines that have been incorporated into the program for this purpose were taken from a collection of closed subroutines in reference 26. The three subroutines have been assembled in the locations 1833 to 1999, and a listing is given in appendix F. The arrangement of the words in the punch band by the punching subroutine, just prior to punching, and the corresponding card columns in which they are to appear are given in appendix B.

Because of the iterative nature of the calculation, it is at times desirable to have information on the progress of the calculations. This has been provided in the form of four console-controlled punches that

may be used individually or in any combination to give intermediate answers during the iterative process. However, because of storage limitations it was necessary to consider these intermediate answer-punching routines as expendable. For this reason they were assembled in the lower portions of the P and T regions and hence can only be used at the expense of a number of reaction products. The output of the punches is on Bell format cards. The punches are as follows:

(1) Console position 2: To be used only when there are 28 or less reaction products. An 8 in position 2 of the console causes punching, in order, of $(1 - P/P_0)$, $(1 - h/h_0)$, or $(1 - s/s_0)$ depending upon whether it is a combustion or expansion process, $(1 - a/a_0)$, $(1 - b/b_0)$, ... These are followed by the code and $-\delta_i$ for each reaction product.

(2) Console position 3: To be used only when there are 26 or less reaction products. An 8 in position 3 of the console causes punching of P, T, and A, followed by the code and n_i for each reaction product.

(3) Console position 4: To be used only when there are 26 or less reaction products. An 8 in position 4 of the console causes punching of the entire reduced matrix, one equation at a time.

(4) Console sign: To be used only when there are 28 or less reaction products. A minus sign on the console causes punching of the solution to the reduced augmented matrix.

Convergence

Because of the complexity and variability of the problem, no exact analysis can be made of the rate of convergence of the iteration. It is possible, however, to obtain useful information on the rate of convergence by studying a few representative chemical systems. A function E is defined that will be used to indicate the error left in the system by the current estimates:

$$E = \left(1 - \frac{P}{P_0}\right)^2 + \left(1 - \frac{h}{h_0}\right)^2 + \left(1 - \frac{a}{a_0}\right)^2 + \ . \ . \ . + \sum \delta_i^2 \qquad (114)$$

where the summation includes all reaction products. The first group of terms will be called the mass balance errors, and the last group will be referred to as the equilibrium errors. Using identical initial estimates in all cases - namely, $p_i = 1$ atm, $n_N = 1\times10^{-11}$ mole, $T = 3800^\circ$ K, and $A = 148.4$ formula weights - it was possible to construct the curves given in figures 16 to 18.

From figure 16 it is seen that $\ln\sqrt{E}$ decreases linearly in the initial stages of the calculation, the slope increasing quite rapidly once E has been reduced to approximately 1. In other words, as convergence is approached, the rate of convergence increases. The erratic behavior of the curves for small E is due to loss of significance when convergence is essentially complete. Although the total error of the system is exponentially reduced in a rather systematic fashion, no such trend has been observed in the mass balance or equilibrium errors taken separately.

For the three cases shown in figure 16, 10 to 18 iterations were required to reduce the error to an acceptable limit when starting with poor estimates. The number of iterations may be even higher in some cases, in particular, if the temperature interval for the thermodynamic data that was selected on the basis of the initial estimate for the temperature is not the correct interval, or if there are any additions to or subtractions from the list of reaction products when the program checks for condensation of condensable materials.

The number of iterations can usually be significantly reduced if the correct assumption on the existence or nonexistence of condensed phases is made and if a good estimate for the reaction temperature and composition is available. A large number of iterations is unusual for pressure ratios other than the first, because the program uses the answers from the preceding calculation as estimates for the following point. These are generally good estimates, and therefore fewer iterations are required. This is illustrated in figure 17, where $\ln\sqrt{E}$ is plotted as a function of the iteration number. The data in figure 17 were obtained for the reaction of equation (1) using the same initial estimates as for figure 16. As shown by figure 17, convergence to combustion and throat conditions each required 11 iterations, while the following three exit points needed only 8, 6, and 5 iterations, respectively. The performance results of this example are given in table IV.

For the problem shown in figure 17, it was assumed that the iteration procedure had converged to a solution when each of the mass balance errors, such as $(1 - a/a_0)$, had a magnitude less than 5×10^{-7} and each of the equilibrium errors δ_i had a magnitude less than 5×10^{-6}:

$$\left.\begin{matrix} \left|1 - \dfrac{P}{P_0}\right| \\ \left|1 - \dfrac{h}{h_0}\right| \\ \left|1 - \dfrac{a}{a_0}\right| \\ \left|\ldots\ldots\right| \end{matrix}\right\} < 5\times10^{-7}; \quad \left|\delta_i\right| < 5\times10^{-6}$$

These convergence criteria result in more accuracy than may be desired in some cases. For the example in figure 17, relaxing the convergence criteria by a factor of 10 permitted the total number of iterations to be reduced from 41 to 34 while still retaining five or more figures of accuracy in the final result.

When a poor set of estimates is made for the variables, the first iteration usually overcorrects the estimates and results in an increase in the value of E, as may be seen from figure 16. A solution to this problem is to restrict the size of the applied corrections. This technique is often used in iterative calculations; however, an increased number of iterations is generally required to converge. One procedure is to multiply each correction by some constant factor less than 1 (see ref. 19, e.g.). With such a technique it is often possible to induce convergence in what would normally be a divergent case, although an increased number of iterations is required. An alternative procedure has been developed that not only prevents overcorrection and produces convergence in all divergent cases that have occurred so far in this laboratory, but also often decreases the number of iterations required to reach convergence. In this procedure, the magnitude of each component of the solution vector of figure 2 must be less than a specified maximum value. If one or more components are larger than this specified maximum, the largest component is reduced to the specified maximum, and all the other components, including all $\Delta \ln p_i$, are reduced proportionally. Figure 18 shows the effect of various maximum magnitudes imposed on the solution vector. Restricting the magnitudes of the components to 5 results in the fewest number of iterations for this case. In other cases a maximum component magnitude of 3 appeared to be best, particularly in systems with fewer chemical elements and reaction products.

The restriction of magnitude of the solution vector is given as an optional program and is discussed in the next section.

Program Modifications

The standard program is considered to be the program that first calculates combustion conditions for assigned enthalpy and pressure and then throat and other exit conditions assuming equilibrium composition of the reaction products during isentropic expansion. However, several modifications to the standard program are available.

The limitations to be discussed apply only to the particular assembly given in appendix F. If the program were assembled in some other fashion, then these limitations would no longer apply.

E-417

CA-6

Assigned enthalpy for series of pressures. - The first modification permits the calculation of an assigned enthalpy problem for a series of pressures. This is accomplished by changing one instruction of the program and can be done at no sacrifice in the number of permitted reaction products.

Restriction on magnitude of solution vector. - A second modification places a size restriction on the maximum magnitude of the solution vector of the matrix of figure 2. If any component is larger than this maximum value, then all the corrections, including $\Delta \ln p_i$, are multiplied a number less than 1 so that the maximum component of the solution vector of figure 2 becomes equal to the maximum permitted value. This program modification may be used only if no more than 26 reaction products are being considered. In addition, only the intermediate punches controlled by console position 2 and sign may be used.

Assigned temperature and pressure. - The third program modification permits calculations for an assigned temperature and pressure. This is done at a sacrifice of five reaction products; however, the intermediate punches controlled by console position 2 and sign may be used in addition to the program change that controls the size of the solution vector. The modified program for calculations at assigned temperature and pressure is not very efficient, since the program performs many unnecessary calculations. However, a more efficient program for this type of calculation can be made with more extensive modifications. The modified pivoting routine may not be used for assigned temperature and pressure calculations. To perform calculations at an assigned temperature for a series of pressures, the program modifications for an assigned enthalpy and a series of pressures must also be included.

Calculations for Assumption of Frozen Composition During Expansion

Rocket performance parameters are generally calculated either with the assumption of complete chemical equilibrium among the combustion products during the expansion process (equilibrium expansion) or with composition remaining fixed at combustion-chamber composition during the expansion process (frozen composition). The method for calculating performance for the first assumption has been described in the previous sections. Performance calculations for the second assumption are the same with respect to determining combustion conditions; however, determination of exit conditions, which is described in the next section, is far simpler, since the composition of reaction products is already known.

Equations for frozen-composition isentropic expansion to assigned pressure. - Since composition during expansion is fixed as the combustion-chamber composition, the following relations are obtained:

$$\frac{(p_i)_c}{(p_i)_e} = \frac{(n_i)_c}{(n_i)_e} = \frac{A_c}{A_e} = \frac{P_c}{P_e} \tag{115}$$

Substituting equation (115) into equations (18), (19), and (20) and rearranging terms give, as the condition for frozen isentropic expansion,

$$\sum_i (n_i)_c (S_T^o)_{i_e} + RP_c \ln \frac{P_c}{P_e} = \left[\sum_i n_i (S_T^o)_i\right]_c \tag{116}$$

E-417

Equation (116) can be written in a form analogous to equation (20) if the following definitions are used:

$$S_e^f = \sum_i (n_i)_c (S_T^o)_{i_e} + RP_c \ln \frac{P_c}{P_e} \tag{117}$$

$$S_c^f = \left[\sum_i n_i (S_T^o)_i\right]_c \tag{118}$$

CA-6 back

for then,

$$S_e^f = S_c^f \tag{119}$$

For an assigned exit pressure, equation (117) is a function of temperature only. For any guess of exit temperature T, equation (119) will not be satisfied identically, and hence an iteration scheme again is employed to converge to correct temperature. The total differential of equation (119) in finite-difference form is

$$\Delta S^f = (S_c^f - S_e^f) = \sum_i (n_i)_c (C_P^o)_i \, \Delta \ln T \tag{120}$$

or

$$\Delta \ln T = \frac{\Delta S^f}{\sum_i (n_i)_c (C_P^o)_i} \tag{121}$$

Equation (121) may be used to obtain new values of T until the value of ΔS^f is less than some assigned small value.

After convergence has been reached, the calculation of the rocket performance parameters is similar to that described for equilibrium composition during expansion.

Description of program. - Because of storage limitations, the program for the calculation of rocket performance assuming frozen composition during expansion could not be incorporated as part of the standard program for equilibrium-composition calculations. Equilibrium composition in the combustion chamber is first calculated with the standard deck. The program for frozen-composition calculations is then read into storage and calculations for frozen composition are begun. Operating instructions for this program are given in appendix D, a flow diagram in figure 19, and a SOAP listing in appendix G.

VECTOR AND PROPELLANT PROGRAM

The Vector and Propellant Program was prepared in order to have a simple and almost automatic method of preparing the packed vectors and the quantities (henceforth referred to as packed propellants) a_f, b_f, c_f, . . ., a_x, b_x, c_x, . . ., V_f^+, V_f^-, V_x^+, V_x^-, h_f, and h_x. The output of this program serves as part of the input data for the Main Calculating Program (see input data routine). The storage locations for the packed propellants are a_x, b_x, c_x, . . ., 537 to 546; h_x, V_x^+, V_x^-, 547, 548, 549; a_f, b_f, c_f, . . ., 587 to 596; h_f, V_f^+, V_f^-, 597, 598, 599.

The flow diagrams for this program are given in figures 20 to 25 and are discussed in the section on "Calculating Routines." Operating instructions are given in appendix E, and a SOAP listing is given in appendix H. Included in the SOAP listing are two punch subroutines taken from reference 26. The format of the output of these two routines (Bell and Random) is given in appendix B. Also given in appendix B is the output format of the packed vectors.

There are ten types of input cards to the Vector and Propellant Program. The type of card is indicated by a symbol of two or three alphabetic or numerical characters appearing in columns 48, 49, and 50 of the IBM card. The data (if any) corresponding to the type of card follow in columns 51 through 72 of the card. The ten types and their functions are listed in the following table and will be discussed more fully in the following sections:

Symbol for type of input	Function	Comment
ATM	Specifies an alphabetic chemical vector for the gaseous atom; e.g., H, AL, or CL	No subscripts permitted for chemical symbol
BOP	Begins program by clearing and initializing	
END	Begins calculations (end of input data)	Begins calculation of a_f, a_x, b_f, b_x, etc.
EFn	Specifies enthalpy of n^{th} fuel in cal/g-mol	$0 \leq n \leq 9$*
EXn	Specifies enthalpy of n^{th} oxidant in cal/g-mol	$0 \leq n \leq 9$*
Fn	Specifies n^{th} fuel	$0 \leq n \leq 9$*
MOL	Specifies all reaction products that are not atoms; e.g., H1F1, N1H3, H1CL1	All subscripts must be given explicitly
PFn	Gives the weight percent or weight fraction of n^{th} fuel in combined fuel	Weight percent or weight fraction in floating point $0 \leq n \leq 9$*
PXn	Gives weight percent or weight fraction of n^{th} oxidant in combined oxidant	Weight percent or weight fraction in floating point $0 \leq n \leq 9$*
Xn	Specifies n^{th} oxidant	$0 \leq n \leq 9$*

*n = 1 through 9 specifies fuel or oxidant 1 through 9, but n = 0 specifies the tenth fuel or oxidant.

Only two types of cards in the preceding table are general for every problem. These are BOP and END.

Transfer Cards

BOP - Initialize card. - The BOP card serves to initialize the program, preparing it to process a new collection of vector and propellant cards. BOP precedes all other input cards:

Input		Output
Card column		
3	+ Sign (12 punch)	
48-50	BOP	No output

END - Start calculations. - The END card follows at the end of all other input cards and serves as a transfer card to begin calculation of the packed propellants:

Input		Output
Card column		
3	+ Sign (12 punch)	
48-50	END	No output

Input for Packed Vectors

The preparation of the packed vectors requires only two types of input cards, ATM and MOL. These two types specify the products of reaction to be considered. For bookkeeping purposes each product of reaction is given a permanent 4-digit numerical code. This permanent code also appears on the thermodynamic data cards for the same product and serves as a check during calculations in the Main Calculating Program.

ATM - Atom cards. - The ATM cards are used to specify which chemical elements will be considered in the equilibrium calculations. They are to be used only for the gaseous atoms. The reduced matrix column assignments are based on the order of appearance of the ATM cards. ATM cards must precede all the other type cards with the exception of BOP cards. The output of an ATM card is a packed vector for the gaseous atom:

Input		Output	
Card column		Card column	
3	+ Sign (12 punch)	17-20	4-Digit code for gaseous element (same as 44-47 of input)
44-47	4-Digit permanent code for gaseous element	31-40	Packed chemical vector
48-50	ATM	41-80	Input reproduced
51-52	Chemical symbol for element, e.g., AL, CL, H (no numerical subscripts)		
53-80	Blank		

MOL - Molecule cards. - The MOL cards are used for the composition vectors of all reaction products that are not gaseous atoms. Thus, condensed elements such as graphite would be on MOL cards. The output of a MOL card is a packed vector for the corresponding product:

Input		Output	
Card column		Card column	
3	+ Sign (12 punch)	17-20	4-Digit code for reaction product
42	Sign (- for condensed phase, + or blank for gaseous phase)	31-40	Packed chemical vector
44-47	4-Digit permanent code for reaction product	41-80	Input reproduced
48-50	MOL		
51-65	Chemical symbol for reaction product. All subscripts must be explicitly given; e.g., CH_4 is C1H4 H_2O is H2Ō1 Al_2O_3 is AL2Ō3 (Ō is an alphabetic character)		
66-80	Blank		

Input for Packed Propellants

A number of propellants consist of more than one fuel or one oxidant. The Vector and Propellant Program can accommodate a propellant consisting of a mixture of up to 10 fuels and up to 10 oxidants. Each fuel and each oxidant in the propellant is characterized by three cards. For the fuel, the three cards are Fn, PFn, and EFn; and for the oxidant, Xn, PXn, and EXn.

Fn - Fuel cards. - The Fn cards are used to specify the chemical formula of the n^{th} fuel, where n is any one of the integers 1, 2, 3, 4, 5, 6, 7, 8, 9, 0 (0 is used for the tenth fuel). The subscripts for elements on the fuel cards may either be integers less than 9 digits in length or floating point numbers. Either one or both forms may be used in the same Fn card. Should the chemical formula for the n^{th} fuel be too long to fit on one card (more than 22 columns) it may be continued on the next card providing that (1) the same Fn symbol is used, and (2) the complete numerical subscript for an element is on the same card as the alphabetic symbol for the element:

Input		Output	
Card column		Card column	
3	+ Sign (12 punch)	0-80	Input reproduced
43-47	Anything - never used in program		
48-49	Fn where n = 1,2,3,4,5,6,7,8,9,0		
50	Blank		
51-72	Chemical formula for the fuel		

Three examples are given to illustrate Fn cards:

Fuel	Columns 48-49	Columns 51-72
N_2H_4	F1	N2H4
C_8H_{18}	F1	C8H18 (or C8H1800000052)
Mixture of NH_3 and H_2	F1 F2	N1H3 H2

Xn - Oxidant cards. - The Xn cards are identical to the fuel cards except that these cards are used for the n^{th} oxidant, and Fn in card columns 48 and 49 is replaced by Xn. Two examples are given to illustrate Xn cards:

Oxidant	Columns 48-49	*Columns 51-72
H_2O_2	X1	H2$\bar{0}$2
$HN_{1.0529061}\,O_{3.0344255}$ (Red fuming nitric acid)	X1 X1	H1N1052906151 $\bar{0}$3034425551

*$\bar{0}$ is an alphabetic character.

PFn - Percent fuel cards. - The percent fuel card PFn gives the weight percent of the n^{th} fuel in the fuel mixture. The percent or weight fractions must be expressed as floating point numbers. There must be a PFn card corresponding to each Fn card:

Input		Output	
Card column		Card column	
3	+ Sign (12 punch)	0-80	Input reproduced
48-50	PFn (n = 1,2,3,4,5,6,7,8,9,0)		
51-60	Weight percent of n^{th} fuel in fuel mixture (a floating point number)		

Two examples are given to illustrate PFn cards:

	Columns 48-50	Columns 51-60
One fuel only	PF1	1000000053
Mixture of fuels (20 percent fuel 1, 80 percent fuel 2 by weight)	PF1 PF2	2000000052 8000000052

PXn - Percent oxidant cards. - The PXn cards are identical to the PFn cards except that they refer to the n^{th} oxidant.

EFn - Fuel enthalpy cards. - The EFn card format is identical to that of PFn and PXn, except that instead of weight percentages this type of card gives the enthalpy of the n^{th} fuel in calories per formula weight as a floating point number. An example is given to illustrate an EFn card:

	Columns 48-50	Columns 51-72
Enthalpy of N_2H_4 (l) at 298.16° K (see eq. (97))	EF1	1547029756

EXn - Oxidant enthalpy cards. - The EXn cards are the same as the EFn card except that they refer to oxidant rather than fuel.

Calculating Routines

Flow charts and tables. - Figure 20 gives a general flow chart for the Vector and Propellant Program and includes the BOP routine. Flow charts for the other routines are given in figures 21 to 25.

For the calculation of the packed propellants, the program requires a table of atomic weights and assigned oxidation states. The atomic weight table for 101 elements is located in the M region, while the corresponding table for the oxidation states is in the V region. The atomic weight table is complete, while oxidation-state assignments have been made only for several elements. Additions or alterations to the tables of atomic weights and oxidations states may be made as needed.

Formulas for propellants containing several fuels or several oxidants. - The program can prepare "packed propellant cards" for propellants containing as many as 10 fuels and 10 oxidants. The combination of all fuels is referred to as the equivalent fuel, while the combination of all oxidants is referred to as the equivalent oxidant. The necessary equations are given as follows:

According to the definitions given in previous sections, $Z_{a_f}Y_{b_f}X_{c_f}$ . . . and $Z_{a_x}Y_{b_x}X_{c_x}$ . . . refer to 1 gram of equivalent fuel and 1 gram of equivalent oxidant having enthalpies h_f and h_x, respectively, where a_f, b_f, c_f . . . and a_x, b_x, c_x . . . are the number of gram atoms of elements Z, Y, X, . . . in the gram of equivalent fuel and the gram of equivalent oxidant, respectively. Let the i^{th} oxidant have the formula $Z_{a_{x_i}}Y_{b_{x_i}}X_{c_{x_i}}$ . . ., its mass W_{x_i}, and its

enthalpy $(H_T^\circ)_{x_i}$, while the i^{th} fuel has the formula $Z_{a_{f_i}} Y_{b_{f_i}} X_{c_{f_i}} \ldots$, its mass W_{f_i}, and its enthalpy $(H_T^\circ)_{f_i}$. The total weight of oxidant is W_x and the total weight of fuel is W_f:

$$\left.\begin{aligned} W_f &= \sum_i W_{f_i} \\ W_x &= \sum_i W_{x_i} \end{aligned}\right\} \tag{122}$$

Therefore, the oxidant-to-fuel weight ratio is

$$\frac{O}{F} = \frac{W_x}{W_f} \tag{123}$$

The gram atoms of elements per gram of equivalent oxidant or fuel are

$$\left.\begin{aligned} a_x &= \frac{1}{W_x}\sum \frac{a_{x_i} W_{x_i}}{\mathscr{M}_{x_i}},\quad b_x = \frac{1}{W_x}\sum \frac{b_{x_i} W_{x_i}}{\mathscr{M}_{x_i}},\quad \ldots \\ a_f &= \frac{1}{W_f}\sum \frac{a_{f_i} W_{f_i}}{\mathscr{M}_{f_i}},\quad b_f = \frac{1}{W_f}\sum \frac{b_{f_i} W_{f_i}}{\mathscr{M}_{f_i}},\quad \ldots \end{aligned}\right\} \tag{124}$$

and the enthalpies are

$$\left.\begin{aligned} h_x &= \frac{1}{W_x}\sum \frac{(H_T^\circ)_{x_i} W_{x_i}}{\mathscr{M}_{x_i}} \\ h_f &= \frac{1}{W_f}\sum \frac{(H_T^\circ)_{f_i} W_{f_i}}{\mathscr{M}_{f_i}} \end{aligned}\right\} \tag{125}$$

Equation (124) may be used in equations (92) and (100) to obtain a_O, b_O, c_O, . . . and V_x^+, V_x^-, V_f^+, and V_f^-, while equation (125) may be used in equation (96) to obtain h_O.

Example

The propellant $N_2H_4 + \frac{3}{2} H_2O_2$ has been used in this report for purposes of illustration (see eqs. (1), (93), (94), (95), (97), and (98)). This same problem will be used to illustrate the input and output of the Vector and Propellant Program and the Main Calculating Program.

The products considered, which are all gaseous, are H, N, O, H_2, H_2O, N_2, NO, O_2, and OH. The values of enthalpy for the propellants are similar to those on page 19 of reference 9:

$$(H^O_{298.16})_{N_2H_4(l)} = 154,702.97 \text{ cal/mol}$$

$$(H^O_{298.16})_{H_2O_2(l)} = 28,681.626 \text{ cal/mol}$$

The input and output of the Vector and Propellant Deck and the Main Operating Deck are given in tables II to V.

Lewis Research Center
National Aeronautics and Space Administration
Cleveland, Ohio, July 2, 1959

E-417

APPENDIX A

SYMBOLS

A	number of formula weights of equivalent reactant; also, cross-sectional area of a nozzle, sq in.
a	velocity of sound, $\sqrt{\left(\frac{\partial P}{\partial \rho}\right)_S}$, ft/sec
$a,b,c, \ldots$	number of gram atoms of the elements $Z,Y,X, \ldots$
C_F	thrust coefficient
C_P^o	molar heat capacity at constant pressure, cal/(mole)(^{o}K)
C_V^o	heat capacity at constant volume, cal/(mole)(^{o}K)
c^*	characteristic velocity, ft/sec
E	internal energy per unit mass, cal/mole; also error function defined by eq. (114)
F	free energy per mole of formula weight of material, cal/mole
$\%F$	weight or mass percent fuel
g_c	gravitational conversion factor, 32.174 (lb mass/lb force)(ft/sec^2)
H	sum of sensible enthalpy and chemical energy per mole or formula weight of material, cal/mole
h	sum of sensible enthalpy and chemical energy per unit mass of material, cal/g
h^*	iteration parameter defined by eq. (85)
I	specific impulse with ambient and exit pressures equal, (lb force)(sec)/(lb mass)
I_{vac}	specific impulse in vacuum (ambient pressure equal to zero), (lb force)(sec)/(lb mass)

K	thermodynamic equilibrium constant
M	Mach number
$\mathcal{M}$	molecular weight, formula weight or atomic weight
N	number
n	number of moles or formula weights of material
O/F	oxidant-to-fuel weight or mass ratio
P	static pressure (sum of partial pressures), consistent units
p	partial pressure, consistent units
p_{vap}	equilibrium vapor pressure of gas
Q	any function
q	symbol for $\partial(-\Delta F_T^O/RT)/\partial \ln T = \Delta H_T^O/RT$
R	universal gas constant, consistent units
r	equivalence ratio defined by eq. (102)
S	entropy per mole or formula weight of material
s	entropy per unit mass of material, cal/(g)($^{\circ}$K)
T	temperature, $^{\circ}$K
U	velocity
V	oxidation state or volume
v	volume per unit mass
W	mass
w	mass-flow rate, (lb mass)/sec; also, weight or mass fraction
x,y	independent variables
Z,Y,X, . . .	symbols for the chemical elements

E-471

α	activity of a material
γ	isentropic exponent, $(\partial \ln P/\partial \ln \rho)_s$
δ	error in equilibrium equation, $\Delta F/RT$
ϵ	area ratio
π	with a subscript, a chamber-pressure exponent defined by eq. (76)
ρ	mass density, consistent units

Subscripts:

c	combustion chamber or condensed phase
e	exit points of a nozzle
f_i	i^{th} fuel
g	gaseous phase
i	i^{th} product of reaction, i^{th} function, i^{th} variable
M,N	M^{th}, N^{th}, . . . condensed reaction products
P	constant pressure
r	equivalent reactant
s	constant entropy
T	at temperature T; also, constant temperature
t	throat of a nozzle
V	constant volume
x_i	i^{th} oxidant
Z,Y,X, . . .	refers to chemical elements
O	an assigned value, equivalent reactant, or absolute zero of temperature

Superscripts:

f	frozen composition during expansion
o	thermodynamic standard state
+	positive oxidation state
-	negative oxidation state

E-417

E-417

CA-8

APPENDIX B

CARD FORMATS

Following are word arrangements for Bell, Random, and SOAP II output cards:

Word arrangement for Bell card:

Punch band	Card column
Word 1	11-21 (sign in 11)
Word 2	22-32 (sign in 22)
Word 3	33-43 (sign in 33)
Word 4	44-54 (sign in 44)
Word 5	55-65 (sign in 55)
Word 6	66-76 (sign in 66)
Word 7 (positions 8-5)	6-9 (location of word 1)
Word 8 (positions 8-5)	5, 77-79 (prob. no.)
Word 9 (position 5)	10 (word count)
Word 10 (positions 9-5)	80 (tab. space control)
	1-4 (card number)

Word arrangement for Random card:

Punch band	Card column
Word 1	5-15 (sign in 15)
Word 2	20-30 (sign in 30)
Word 3	35-45 (sign in 45)
Word 4	50-60 (sign in 60)
Word 5	65-75 (sign in 75)
Word 6 (positions 8-5)	1-4 (location of word 1)
Word 7 (positions 8-5)	16-19 (location of word 2)
Word 8 (positions 8-5)	31-34 (location of word 3)
Word 9 (positions 8-5)	46-49 (location of word 4)
Word 10 (positions 8-5)	61-64 (location of word 5)
	76-80 (not used)

E-417

E-417

CA-8 back

Word arrangement for SOAP II output (packed vectors):

Punch band	Card column	Comments
	1-10 (sign in 10), emitted	Not used in program
Word 9	11-20 (sign in 20)	Columns 17-20 are product code
	21-30 (sign in 30), emitted	Not used in program
Word 7	31-40 (sign in 40)	Packed vectors
Word 8 (position 1)	41	Reproduce input
Sign of word 7	42	
Word 1 (positions 5 to 1)	43-47	
Word 4 (positions 5 to 3)	48-50	
Word 1 (positions 5 to 1)	51-55	
Word 4 (position 2)	56	
Word 3 (positions 5 to 1)	57-61	
Word 4 (position 1)	62	
Word 5 (positions 5 to 1)	63-67	
Word 6 (positions 5 to 1)	68-72	

APPENDIX C

OPERATING INSTRUCTIONS FOR MAIN CALCULATING PROGRAM

Normally the computer program will not be loaded as one instruction per card, SOAP cards, but will be subjected to some shrinking procedure that will permit loading of five or six instructions per card. (See appendix B for formats of Bell and Random cards.) Assuming this to be the case and also assuming that all input data which must be loaded are in the same card format, the following operating instructions apply for the Main Calculating Program:

(1) Set console:

(a) Storage entry switches (70 1951 9/8 9/8 9/8 9/8±):
An 8 in position 1 - pivoting during solution
An 8 in position 2 - punching of current errors
An 8 in position 3 - punching of current values for variables
An 8 in position 4 - punching of reduced augmented matrix
Minus sign - punching of solution vector for reduced augmented matrix

When the program has been loaded, the 9 in the position 7 of the console may be changed to an 8 if the operator does not wish the program to check for condensation.

(b) Set programmed switch to STOP.

(c) Set half-cycle switch to RUN.

(d) Set control switch to RUN.

(e) Set display switch to PROGRAM REGISTER.

(f) Set overflow switch to SENSE.

(g) Set error switch to STOP.

(2) Place cards in the read feed so that they will be read in the following order:

(a) Loading routine for program

(b) Computer program
Equilibrium program
Rocket package excerpt

E-417

(c) Input data to be loaded:

Case card
r card: O/F, %F, or r (any one of the three may be used)
Chamber-pressure card in lb/sq in. abs
Pressure-ratio schedule, as many as 25 pressure ratios
Atoms cards ($a_f, b_f, c_f, \ldots j_f;$ $h_f, V_f^+, V_f^-, a_x, b_x, c_x, \ldots j_x;$ h_x, V_x^+, V_x^-)

(d) Packed vectors

(e) Thermodynamic data as coefficients

Items (a), (b), and (c) are loaded by a loading routine, while (d) and (e) are read into storage by program read commands.

(3) Ready the punch feed with blank cards.

(4) Press computer reset key.

(5) Press program start key.

To aid in detecting errors, programmed stops have been incorporated into the program. The following list gives the card number of the instruction, in the SOAP listing, which produced the stop; the contents of the program register at the time of the stop; and the significance of the stop:

Card number	Instruction	Significance
198	HLT 0000 7766	Thermal data out of order
229	HLT 0000 7777	Elements plus condensed phases greater than 10
325	HLT 0000 8855	Trying to process a molecule or condensed phase before all atoms done
378	HLT 0000 8866	Picked up wrong thermal data for the product
635	NZU XXXX 8877	Trying to process too many condensed phases
1702	HLT 0000 9955	Overflow occurred during construction of matrix
1740	HLT 0000 9966	Overflow occurred in back solution
1827	HLT 0000 9988	Some molecules ahead of some atoms
1570	NZU XXXX 9999	End of program

E-417

APPENDIX D

OPERATING INSTRUCTIONS FOR FROZEN COMPOSITION

To carry out frozen-composition calculations it is necessary first to perform an equilibrium-combustion calculation. Thus, the initial operating instructions are identical to those of the Main Calculating Program (appendix C), with the exception that an additional instruction is included (with the input data (2)(c)) that causes the program to stop when combustion calculations are complete. The instruction loads into storage location "FROZ" (1362) and is HLT 9999 9999 (01 9999 9999).

The following instructions apply after combustion calculations are complete:

(1) Run out any cards remaining in the read hopper.

(2) Place cards in the read feed hopper so that they will be read in the following order:

(a) Loading routine for program

(b) Frozen-composition program

(c) A transfer card to start program at "START"

(d) Thermodynamic data as coefficients

(3) Press computer reset key.

(4) Press program start key.

APPENDIX E

OPERATING INSTRUCTIONS FOR VECTOR AND PROPELLANT PROGRAM

The following operating instructions are for the Vector and Propellant Program, which may be used to prepare input data for the Main Calculating Program:

(1) Prepare the appropriate alphabetic ATM and MOL cards. There must be one ATM card for each chemical element and one MOL card for each other product of reaction.

(2) Prepare Fn, PFn, and EFn cards for each fuel, and Xn, Pxn, and EXn cards for each oxidant in the equivalent reactant.

(3) Set console:

(a) Storage entry switches (70 1951 19 9/8 8±); an 8 in position 2 - punching of fuels, oxidants, and percents and enthalpies of fuels and oxidants.

(b) Set programmed switch to STOP.

(c) Set half-cycle switch to RUN.

(d) Set control switch to RUN.

(e) Set display switch to PROGRAM REGISTER.

(f) Set overflow switch to STOP.

(g) Set error switch to STOP.

(4) Place cards in read feed so that they will be read in the following order:

(a) Loading routine for program

(b) Vector and Propellant Program

(c) Input data to be read:
BOP card (if desired)
ATM cards
MOL cards
Fn, PFn, EFn, Xn, PXn, EXn in any order
END card

(5) Ready punch feed with blank cards.

(6) Press computer reset key.

(7) Press program start key.

As an aid in the detection of errors, the following programmed stops have been included in the program:

Card number	Instruction	Significance
337	HLT 9999 1111	Wrong symbol in ATM program
342	HLT 9999 2222	Wrong symbol in BOP program
351	HLT 9999 3333	Wrong symbol in EFn program
364	HLT 9999 4444	Wrong symbol in END program
378	HLT 9999 5555	Wrong symbol in EXn program
388	HLT 9999 6666	Wrong symbol in Fn program
395	HLT 9999 7777	Wrong symbol in MOL program
404	HLT 9999 8888	Wrong symbol in PFn program
414	HLT 9999 9999	Wrong symbol in PXn program
424	HLT 9999 0000	Wrong symbol in Xn program
460	HLT 2222 8888	Trying to process ATM card after MOL, Fn, or Xn cards
466	HLT 3333 7777	Symbol for atom has more than two letters
491	HLT 4444 6666	More than 10 atoms processed
500	HLT 5555 5555	Trying to process more condensed phases than are permitted
506	HLT 6666 4444	Formula for reaction product has more than 15 letters and digits
509	HLT 7777 3333	No chemical formula on MOL card
551	HLT 8888 2222	An element on a MOL card that did not appear on an ATM card
616	HLT 9988 9988	More than 10 ATM cards
665	HLT 4321 4321	Column equivalent for element not in table
680	HLT 2233 4455	Subscript for element greater than 10 digits
684	HLT 5544 3322	Subscript for element is 9 digits
713	HLT 8888 1111	Enthalpy or percent greater than 10 digits
784	HLT 1111 1111	Sum of percents not close enough to 100

E-417

APPENDIX F

MAIN OPERATING PROGRAM (CHEMICAL EQUILIBRIUM)

```
                 CHEMICAL EQUILIBRIUM PROGRAM


                 PROTECT ROCKET PACKAGE EXCERPT
                 BY LOADING AVAILABILITY TABLE


               SYN FROZ       1362
               SYN CHEK       0499
               SYN PROB       1904
               SYN EXP E      1850
               SYN SQRT       1900
               SYN PUNCH      1950
               SYN CARDN      1852
               SYN LINK       1855
               SYN TEMP1      1048          LOW TEMP
               SYN TEMP2      1049          HIGH TEMP
               REG A0961      0980          ATOM DATA
               REG B1247      1249          TWO 3 FOU
               REG C9050      9050
               REG D0001      0001
               BLA   0001     0001
               BLR   0037     0049
               BLR   0087     0099
               BLR   0137     0149
               BLR   0187     0199
               BLR   0237     0249
               BLR   0287     0299
               BLR   0337     0349
               BLR   0387     0399
               BLR   0437     0449
               BLR   0487     0499
               BLR   0537     0549
               BLR   0587     0599
               REG F1110      1149
               REG G0001      0015
               REG H0987      0999          EXTRA H E
               REG I1001      1005
               REG J1006      1012
               REG K1013      1019
               REG M9000      9000
               REG N9015      9015
               REG P1599      1659          PROD DAT
               REG Q1020      1027
               REG R1075      1099          PRES RATIO
               REG T0660      0959          HEAT DAT
               REG U0050      0058
               REG Y0059      0065
               REG Z1340      1349          PRESS RO
               EQU PCP       F0001
               EQU TEE       F0002
               EQU P         F0003
               EQU H         F0004
               EQU I         F0005
               EQU M         F0006
               EQU CF        F0007
               EQU EPSIL     F0008
               EQU MACH      F0009
               EQU I VAC     F0010
               EQU CP        F0011
               EQU GAMMA     F0012
               EQU LMPT      F0013
               EQU LMTP      F0014
               EQU S         F0015
               EQU NI        F0016
               EQU NT        F0017
               EQU NEPS      F0018
               EQU NCSTR     F0019
               EQU CSTAR     F0020
               EQU AW        F0021
               EQU NAW       F0022
               EQU HSTR      F0023
               EQU AAY       F0024
               EQU HC        F0025
               EQU RECMC     F0026
               EQU NAWT      F0027
               EQU AWT       F0028
               EQU HSTR2     F0029
               EQU P1        F0030
               EQU CONS1     F0031
               EQU CONS2     F0032
               EQU CONS3     F0033
               EQU CONS4     F0034
               EQU CONS5     F0035
               EQU S2        F0036
               EQU R         F0037
               EQU GC        F0038
               EQU IDENT     F0039
```

E-417

CA-9 back

```
          EQU ONE        F0040
          EQU LNAAY      G0001
          EQU LNT        G0002
          EQU SO/R       G0003
          EQU HO/R       G0004
          EQU AOMOL      G0005
          EQU BOMOL      G0006
          EQU COMOL      G0007
          EQU DOMOL      G0008
          EQU EOMOL      G0009
          EQU FOMOL      G0010
          EQU GOMOL      G0011
          EQU HOMOL      G0012
          EQU IOMOL      G0013
          EQU JOMOL      G0014
          EQU PO         G0015
          EQU CODE        9000
          EQU SIR         9001
          EQU ATOM2       9002
          EQU T           9003
          EQU RV000       9004
          EQU RV001       9005
          EQU RV002       9006
          EQU RV003       9007     ROW VECTOR
          EQU RV004       9008     EXTENDS
          EQU RV005       9009     FROM 9005
          EQU RV006       9010     TO 9018
          EQU RV007       9011
          EQU RV008       9012
          EQU RV009       9013
          EQU RV010       9014
          EQU RV011       9015
          EQU RV012       9016
          EQU RV013       9017
          EQU RV014       9018
          EQU NI          9019
          EQU A           9021
          EQU B           9022
          EQU C           9023
          EQU D           9024
          EQU E           9025
          EQU F           9026
          EQU LN NI       9027
          EQU 1A          9011
          EQU 1B          9012
          EQU 1C          9013
          EQU 1D          9014
          EQU 1E          9015
          EQU 1F          9016
          EQU LNNI        9017
          EQU TWO         9028
          EQU THREE       9029
          EQU FOUR        9030
          EQU CPR         9031
          EQU S CPR       9032
          EQU HRT         9033
          EQU S HRT       9034
          EQU SR          9035
          EQU S  SR       9036
          EQU MINEX       9045
          EQU MINCO       9046
          EQU MAXCO       9047
          EQU VARBL       9048
          EQU TEM 1       9049
          EQU TEMPO       9059
          EQU MOVE1       9058
          EQU MOVE2       9059
          EQU BASIC       9050
          EQU INDXA      THREE
          EQU INDXC      FOUR
          EQU S1         C0001
          EQU ELMIN      C0001
          EQU NOROW      C0000
          SYN RDB         1193
          SYN PC         F0000


 BEGIN    RAU LNT                  SET TO          0000  60 0002 0107
          STL COMEX                COMBUSTION      0107  20 0111 0114
          STD PCPCT                FIRST PC        0114  24 0017 0020
          LDD            EXP E     OVER P          0020  69 0023 1850
          STU T                    T FROM LNT      0023  21 9003 0031
          LDD TDATA      PCP 1                     0031  69 0034 0637

            IF COMEX IS ZERO WE ARE DOING
            COMBUSTION OTHERWISE EXPANSION
            COMEX EQUALS MINUS UNITY FOR
            THROAT AND PLUS UNITY FOR
            EXPANSION


```

```
                       READ THERMAL DATA ROUTINE FOR
                       GENERAL ROCKET PERFORMANCE
                                 CALCULATION
TDATA   RAA  0000                                   0034  80 0000 0640
        RAC  0000     TD001                         0640  88 0000 0646
TD001   RCD BASIC     BELL       READ CARD          0646  70 9050 1046
BASIC   RAL  9051     RDB        ARE WE             9050  65 9051 1193
RDB     SLT  0004                GOING TO           1193  35 0004 0103
        STU  9051                STORE IN           0103  21 9051 0161
        RAU P0001 A              COPRECT            0161  60 3599 0153
        SLT  0001                PLACE              0153  35 0001 0109
        SRT  0001                                   0109  30 0001 0115
        SUP  9051                                   0115  11 9051 0073
        NZU TD005                                   0073  44 0027 0028
        LDD T0008 C              YES STORE          0028  69 6667 0070
        STD  9058                THERMAL            0070  24 9058 0026
        SET  9051                DATA               0026  27 9051 0081
        SBB T0001 C                                 0081  28 6660 0113
        AXA  0002                                   0113  50 0002 0019
        AXC  0010     TD001                         0019  58 0010 0646
TD005   HLT  0000      7766                         0027  01 0000 7766
BELL    RAU  9051                WAS THE            1046  60 9051 0203
        FSB T                    DATA JUST          0203  33 9003 0033
        BMI TDATA                READ IN            0033  46 0034 1037
        RAU T                    FOR THE            1037  60 9003 0645
        FSB  9050                CORRECT            0645  33 9050 0025
        BMI TDATA                INTERVAL           0025  46 0034 0029
        SET  9050                                   0029  27 9050 0084
        SBB TEMP1     UNPAK                         0084  28 1048 0101


                       UNPACKING ROUTINE FOR GENERAL
                       ROCKET PERFORMANCE CALCULATION

                       ATOM1 IS THE NUMBER OF THE
                       ELEMENTS IN THE SYSTEM AND IS
                       IN THE I ADDRESS POSITION

                       SYS IS THE SUM OF ELEMENTS
                       AND CONDENSED PHASES IN THE
                       I ADDRESS POSITION AND MUST
                       BE LESS THAN OR EQUAL TO TEN

                       SYSTM IS GENERATED FROM SYS
                       BY SHIFTING TO THE D ADDRESS
                       POSITION

UNPAK   RAU UNITY                IS  SYS            0101  60 0104 0159
        SLT  0001                GREATER            0159  35 0001 0165
        SUP SYS                  THAN TEN           0165  11 0018 0123
        BMI           UP000                         0123  46 0076 0077
        HLT  0000      7777                         0076  01 0000 7777
UP000   RAU SYS                  GENERATE           0077  60 0018 0173
        SLT  0004                I ADDRESS          0173  35 0004 0083
                                 CONSTANTS
        STU SYSTM                SYS+1 AND          0083  21 0638 0641
        RAL SYS                  SYS+2 AND          0641  65 0018 0223
        ALO UNITY                ATM-1 ALSO         0223  15 0104 0209
        AUP  8001                D ADDRESS          0209  10 8001 0067
        AUP  8002                CONSTANT           0067  10 8002 0075
        STL SYS+1                SYSTM FROM         0075  20 0079 0032
        STU SYS+2                SYS AND            0032  21 0036 0639
        RAU ATOM1                ATOM1              0639  60 0642 0647
        SUP UNITY                                   0647  11 0104 0259
        STU ATM-1                                   0259  21 0164 0117
        STL S CPR                CLEAR THE          0117  20 9032 0024
        STD S HRT                SUMMATION          0024  24 9034 0030
        STD S  SR                STORAGES           0030  24 9036 0086
        STD P                                       0086  24 1112 0215
        RAL STORE                SET STORE          0215  65 0068 0273
        SLO SYSTM                ORDER FOR          0273  16 0638 0643
        LDD UP033                SUBSCRIPT          0643  69 1196 0649
        SDA UP033                                   0649  22 1196 1199
        LDD TH024                SET DATA           1199  69 0102 0105
        SDA TH024                ADDRESS OF         0105  22 0102 0155
        LDD TH035                TH024 AND          0155  69 0108 0211
        SDA TH035                TH035              0211  22 0108 0261
        RAU SYS                  SET SOLIDS         0261  60 0018 0323
        SUP ATOM1                COUNTER            0323  11 0642 1047
        STU COUNT                                   1047  21 0152 0205
        STD SOLID                                   0205  24 0158 0311
        SLT  0004                SET                0311  35 0004 0021
        RSL  8003                DATA               0021  66 8003 0129
        ALO STORE                ADDRESS OF         0129  15 0068 0373
        LDD VM007                VM007 AND          0373  69 0126 0179
        SDA VM007                VM048 TO           0179  22 0126 0229
        LDD VM048                RV011B             0229  69 0082 0035
        SDA VM048                LESS SOLID         0035  22 0082 0085
        RAU LNT                  GET T FROM         0085  60 0002 0157
        LDD UP001     EXP E      LNT                0157  69 0110 1850
```

E-417

E-417

```
UP001   STU T                           0110  21 9003 0167
        LDD ATOM1          SET ATOM     0167  39 0642 1045
        STD ATOM2           COUNTER     1045  24 9002 0151

            INDEX ACCUMULATOR C WILL BE
            USED FOR PICKING UP THE
            THERMAL DATA IN THE FUTURE

        RAC  0000                       0151  88 0000 0207
        RAA  0012                       0207  80 0012 0163
        RAU WIPE1     8003              0163  60 0016 8003
 8003   STL  9007 A UP003  CLEAR THE    8003  20 9207 0078
UP003   NZA UP005   UP007  LAST 13      0078  40 0131 0132
UP005   SXA  0001     8003 POSITIONS    0131  51 0001 8003
UP007   RAB  0011   UP009  OF FIRST     0132  82 0011 1038
UP009   SET  9007          12 BANDS     1038  27 9007 1043
        STB  0037 A        FOR MATRIX   1043  29 2037 1040
        NZB         UP012               1040  42 1243 0644
        SXB  0001                       1243  53 0001 1299
        AXA  0050   UP009               1299  50 0050 1038
UP012   SET  9007          CLEAR THE    0644  27 9007 1399
        STB H0001          H REGION     1399  29 0987 1190
        RAA  0000   UP013               1190  80 0000 1246
UP013   RAB  0013          CLEAR 14     1246  82 0013 0202
        RAU WIPE2     8003 CORE LOCA    0202  60 0255 8003
 8003   STL RV001 B UP015  FOR ROW      8003  20 9405 0066
UP015   NZB UP017   UP019  VECTOR       0066  42 0069 0120
UP017   SXB  0001     8003              0069  53 0001 8003

            INDEX ACCUMULATOR A WILL BE
            USED FOR PICKING UP THE
            CURRENT PRODUCT CODE IN FUTURE

            DATA ADDRESS OF UP033 HAS BEEN
            SET TO RV011B MINUS SYSTM AT
            START OF UNPAK ROUTINE

UP019   RAL P0001 A        STORE PROD   0120  65 3599 0253
        NZE         MATRX  CODE IF      0253  45 0106 0257
        SLT  0001          HERE IF NO   0106  35 0001 0213
        NZU UP021          GO CLEAN     0213  44 0217 0118
        SRT  0001          UP MATRIX    0118  30 0001 0125
        STL CODE    UP024               0125  20 9000 0182
UP021   SRT  0001          PASS UP      0217  30 0001 0423
        STU T0008 C        SOLID AND    0423  21 6667 0170
        STD T0010 C        SET NI AND   0170  24 6669 0022
        AXA  0002          DELTAI TO    0022  50 0002 0128
        AXC  0010   UP019  ZERO         0128  58 0010 0120
UP024   RAU P0002 A        GAS OR       0182  60 3600 0305
        STL CHECK          CONDENSED    0305  20 0309 0112
        BMI         UP037  SET ONE OR   0112  46 0265 0116
        RSU  8003   UP029  LEAVE ZERO   0265  61 8003 0473
UP029   SRT  0002   UP030  IN RV011     0473  30 0002 0279
UP030   SUP  8003                       0279  11 8003 1187
        STD TEMPO                       1187  24 9059 1293
        AUP ATOM2          CHECK ATOM   1293  10 9002 0201
        NZU         UP031               0201  44 0355 0156
        HLT  0000     8855              0355  01 0000 8855
UP031   SLT  0001                       0156  35 0001 0263
        ALO 51             FLOAT AND    0263  15 0166 0071
        RAB  8003   UP033  STORE THE    0071  82 8003 1196
UP033   STL RV011 B        SUBSCRIPT    1196  20 9415 0154
        RAU TEMPO          GET NEXT     0154  60 9059 0361
        NZU UP029          SUBSCRIPT    0361  44 0473 0216
        AXA  0002   THERM               0216  50 0002 0072

            PREPARE FOR NEXT PRODUCT THEN
            GO TO THE THERMAL ROUTINE

UP037   LDD ONE            SET ONE IN   0116  69 1149 0252
        STD RV011          RV011        0252  24 9015 0208
        SRT  0002          IS IT ONE    0208  30 0002 0315
        NZU UP030          ELEMENT      0315  44 0279 0220
        STL TEMPO          YES IT WAS   0220  20 9059 0178
        SLT  0001          IS IT AN     0178  35 0001 0135
        RAU  8002          ATOM         0135  60 8002 1393
        SUP UNE                         1393  11 1296 0251
        NZU         UP038  IT WAS A     0251  44 0405 0206
        RAL TEMPO   UP030  MOLECULE     0405  65 9059 0279
UP038   RAU ATOM2          IT WAS AN    0206  60 9002 0313
        SUP UNITY          ATOM         0313  11 0104 0359
        STD CHECK                       0359  24 0309 0162
        STU ATOM2                       0162  21 9002 0119
        RAL TEMPO                       0119  65 9059 0127
        STU TEMPO   UP031               0127  21 9059 0156

            CONSTANTS FOR UNPACKING
STORE    00 RV011 B  0000               0068  00 9415 0000
WIPE1   STL  9007 A UP003               0016  20 9207 0078
WIPE2   STL RV001 B UP015               0255  20 9405 0066
ONE      10  0000     0051              1149  10 0000 0051
```

```
     UNITY    00  0000     0001                       0104  00 0000 0001
     51       00  0000     0051                       0166  00 0000 0051
     UNF      10  0000     0000                       1296  10 0000 0000
 1
 1
                 THERMAL ROUTINE FOR GENERAL
 1               ROCKET PERFORMANCE CALCULATION
 1
 1               THE DATA ADDRESSES OF TH024
 1               AND TH035 SHOULD BE SET TO
 1               RV011B MINUS SYSTM AT START OF
 1                    UNPACKING ROUTINE
 1
     THERM    SET  9020                  PICK UP      0072  27 9020 0177
              LBB T0001 C                THERMAL      0177  08 6660 0363
 1                                        DATA
              RAU  9020                  IS THIS      0363  60 9020 0121
              SUP CODE                   THE RIGHT    0121  11 9000 0329
              NZU            TH003       DATA         0329  44 0133 0134
              HLT  0000       8866                    0133  01 0000 8866
     TH003    RAU P0000 A                             0134  60 3598 0303
              BMI            TH007                    0303  46 0256 0307
 1
 1               IF DEALING WITH CONDENSED
 1               PRODUCT SET LN NI TO ZERO
 1
              RAU LN NI                  LN NI IS     0256  60 9027 0413
              STL LN NI                  REALLY NI    0413  20 9027 0270
              STU NI         TH009                    0270  21 9019 0227
     TH007    RAU LN NI                  GET NI       0307  60 9027 0365
              LDD            EXP E       FROM LN NI   0365  69 0168 1850
              STU NI         TH009                    0168  21 9019 0227
     TH009    SET TWO                    TWO 3 FOUR   0227  27 9028 0232
              LDB B0001                  ON CORE      0232  09 1247 0100
              RAU D                      CALCULATE    0100  60 9024 0357
              FMP T                      CPR          0357  39 9003 0160
              FAD C                                   0160  32 9023 1039
              FMP T                                   1039  39 9003 1042
              FAD B                                   1042  32 9022 0171
              FMP T                                   0171  39 9003 0074
              FAD A                                   0074  32 9021 0353
 1
 1               S CPR  S HRT  S  SR MUST BE
 1               CLEARED AT MATRIX CLEARING
 1
              STU CPR                                 0353  21 9031 0411
              FMP NI                     SUM CPRXNI   0411  39 9019 0214
              FAD S CPR                  IN CORE      0214  32 9032 1443
              STU S CPR                               1443  21 9032 0301
              RAU D                      CALCULATE    0301  60 9024 0409
              FDV FOUR                   HRT          0409  34 9030 0212
              FMP T                                   0212  39 9003 0415
              STU TEMPO                               0415  21 9059 0523
              RAU C                                   0523  60 9023 0181
              FDV THREE                               0181  34 9029 0184
              FAD TEMPO                               0184  32 9059 0463
              FMP T                                   0463  39 9003 0266
              STU TEMPO                               0266  21 9059 0573
              RAU B                                   0573  60 9022 0231
              FDV TWO                                 0231  34 9028 0234
              FAD TEMPO                               0234  32 9059 0513
              FMP T                                   0513  39 9003 0316
              STU TEMPO                               0316  21 9059 0623
              RAU E                                   0623  60 9025 0281
              FDV T                                   0281  34 9003 0284
              FAD TEMPO                               0284  32 9059 0563
              FAD A                                   0563  32 9021 1493
              STU HRT                                 1493  21 9033 0351
              FMP NI                     SUM HRTXNI   0351  39 9019 0204
              FAD S HRT                  IN CORE      0204  32 9034 0183
              STU S HRT                               0183  21 9034 1041
              RAU D                      CALCULATE    1041  60 9024 1449
              FDV THREE                  SR           1449  34 9029 0302
              FMP T                                   0302  39 9003 0455
              STU TEMPO                               0455  21 9059 0613
              RAU C                                   0613  60 9023 0221
              FDV TWO                                 0221  34 9028 0124
              FAD TEMPO                               0124  32 9059 0403
              FMP T                                   0403  39 9003 0306
              FAD B                                   0306  32 9022 0185
              FMP T                                   0185  39 9003 1188
              STU TEMPO                               1188  21 9059 1195
              RAU A                                   1195  60 9021 0453
              FMP LNT                                 0453  39 0002 0352
              FAD TEMPO                               0352  32 9059 0331
              FAD F                                   0331  32 9026 0461
              FSB LN NI                  SR MINUS     0461  33 9027 1191
              STU SR                     LN PI        1191  21 9035 1499
              FMP NI                     SUM SR       1499  39 9019 0402
              FAD S  SR                  LESS LN PI   0402  32 9036 0381
              STU S  SR                  X NI  CORE   0381  21 9036 1189
              RAU CHECK                  IS IT ATOM   1189  60 0309 1063
```

E-417

E-417

```
              NZU            TH023                         1063  44 0267 0218

                REGION A IS PERMANENT STORAGE
                OF ATOM GAS THERMAL PROPERTIES

              RAU HRT                      PERMANENT       0267  60 9033 0175
              STU A0001 B                  STORAGE OF      0175  21 4961 0264
              RAL SR                       HRT AND SR      0264  65 9035 0271
              STL A0011 B                  LESS LN PI      0271  20 4971 0174
              STU T0009 C                  OF GASEOUS      0174  21 6668 0321
              STD T0010 C TH044            ATOMS           0321  24 6669 0122
      TH023   RAU ATM-1                    SET MULT        0218  60 0164 0169
              RAB   8003                   FREQUENCY       0169  82 8003 0228
              STL TEMPO                    FOR QI          0228  20 9059 0136
              SET   9050                                   0136  27 9050 1241
              LRB A0001      TH024                         1241  08 0961 0102
      TH024   RAU RV011 B                                  0102  60 9415 0459
              NZU            TH027                         0459  44 1163 0314
              FMP   9050 B                                 1163  39 9450 0366
              FAD TEMPO                                    0366  32 9059 1245
              STU TEMPO      TH027                         1245  21 9059 0314
      TH027   NZB            TH031                         0314  42 0317 0266
              SXB   0001     TH024                         0317  53 0001 0102
      TH031   RSU TEMPO                                    0266  61 9059 0225
              FAD HRT                                      0225  32 9033 0505
              STU RV012                    QI IN 9016      0505  21 9016 1213
              STD TEM 1                    AND TEM 1       1213  24 9049 0219
              STD T0009 C                  AND T REGN      0219  24 6669 0371
              RAU ATM-1                    SET MULT        0371  60 0164 0269
              RAB   8003                   FREQUENCY       0269  82 8003 0278
              SET   9050                                   0278  27 9050 0233
              LRB A0011      TH035                         0233  08 0971 0108
      TH035   RAU RV011 B                                  0108  60 9415 0465
              NZU            TH039                         0465  44 0319 0320
              FMP   9050 B                                 0319  39 9450 0172
              FAD TEM 1                                    0172  32 9049 0401
              STU TEM 1      TH039                         0401  21 9049 0320
      TH039   NZB            TH043                         0320  42 1073 0224
              SXB   0001     TH035                         1073  53 0001 0108
      TH043   RAU TEM 1                                    0224  60 9049 0431
              FSB SR                       DELTA I IN      0431  33 9035 0511
              STU RV013                     9017           0511  21 9017 0369
              RSU   8003                   STORE NEG       0369  61 8003 0277
              STU T0010 C TH044            DELTAI IN       0277  21 6669 0122
      TH044   AXC   0010                   T REGION        0122  58 0010 0328
              RAU HRT                      H OVER R        0328  60 9033 0235
              FMP T                        IN HR           0235  39 9003 1238
              STU HR                                       1238  21 1192 1295
              RAU P0000 A                                  1295  60 3598 0503
              BMI TH045                                    0503  46 0356 0407
              RAU SR                       S PRIMED        0407  60 9035 0515
              FSB ONE        TH050         OVER R          0515  33 1149 0275
      TH045   RAU SP         TH050                         0356  60 9035 0275
      TH050   STU S1R        TH051         IN S1R          0275  21 9001 0283
      TH051   RAU COMEX                                    0283  60 0111 0565
              NZU EXPAN      COMB                          0565  44 0419 0370
      COMB    RAU HR                                       0370  60 1192 1197
              STL RV000      TH047                         1197  20 9004 0254
      EXPAN   RAU S1R                                      0419  60 9001 0327
              LDD HR                                       0327  69 1192 1395
              STD RV000      TH047                         1395  24 9004 0254
      TH047   STU RV014      MULT                          0254  21 9018 0561

                CONSTANTS FOR THERMAL ROUTINE
      ONE     10   0000      0051                          1149  10 0000 0051
      UNITY   00   0000      0001                          0104  00 0000 0001
      B0001   20   0000      0051          TWO             1247  20 0000 0051
      B0002   30   0000      0051          THREE           1248  30 0000 0051
      B0003   40   0000      0051          FOUR            1249  40 0000 0051


                VECTOR MULTIPLICATION ROUTINE
                FOR GENERAL ROCKET PERFORMANCE
                         CALCULATION

                WHEN THERE ARE N EQUATIONS THE
                NTH APPEARS IN BAND 1 AND THE
                1ST APPEARS IN BAND N

                IN THIS ROUTINE INDEX A WILL
                TRACK THE CURRENT EQUATION  B
                WILL  TRACK  THE CURRENT
                SUBSCRIPT   C WILL TRACK THE
                NUMBER OF MULTIPLICATIONS

                THE SOLIDS COUNTER SHOULD BE
                SET TO ITS MAXIMUM VALUE PRIOR
                TO CLEARING MATRIX LOCATIONS
```

```
540 1             THE DATA ADDRESSES OF VM007
541 1             AND VM048 SHOULD BE SET TO
542 1             RV011B MINUS SOLID AT THE
543 1             START OF THE UNPACKING ROUTINE
544 1
545 1
546     MULT   LDD  8005     VM001    STORE INDX  0561  69 8005 0367
547     VM001  STD  INDXA             A  AND  C   0367  24 9029 1173
548            LDD  8007              FOP THE     1173  69 8007 0379
549            STD  INDXC             TIME BEING  0379  24 9030 0285
550            RAU  P0000 A           IS PRODUCT  0285  60 3598 0553
551            BMI  VM042             CONDENSED   0553  46 0406 0457
552 1
553 1             GASEOUS PRODUCT PROCESSING
554 1
555            RAU  SYS+1             SET INDXA   0457  60 0079 0333
556            MPY  50                TO SYS+1    0333  19 0186 0456
557            RAA  8002              TIMES 50    0456  80 8002 0615
558            RSU  ATOM1             SET INDEXB  0615  61 0642 1297
559            RAB  8003     VM002    TO ATOM     1297  82 8003 0506
560 1                                 NEGATIVED
561     VM002  RAC  8003              SET INDEXC  0506  88 8003 0364
562            LDD  SOLID             TO INDEXB   0364  69 0158 0611
563            SXC  8001              LESS SOLID  0611  59 8001 0417
564            SXC  0002     VM007    LESS TWO    0417  59 0002 0126
565     VM007  RAU  RV011 B           IS IT ZERO  0126  60 9415 0383
566            NZU           VM023    SUBSCRIPT   0383  44 1237 1288
567            FMP  NI                SUBSCRIPT   1237  39 9019 1240
568            STU  TEMPO             TIMES NI    1240  21 9059 1397
569            SET  9037              BRING IN    1397  27 9037 0452
570            LDB  0037 A   VM013    EQUATION    0452  09 2037 1290
571     VM013  RAU  RV013 C                       1290  60 9617 1447
572            NZU           VM017                1447  44 0451 0502
573            FMP  TEMPO             PERFORM A   0451  39 9059 0304
574            FAD  9049 C            MULTIPLY    0304  32 9649 0433
575            STU  9049 C   VM017    AND ADD     0433  21 9649 0502
576     VM017  NZC           VM021    ANY MORE    0502  48 0555 0556
577            AXC  0001     VM013    TO MULTPLY  0555  58 0001 1290
578     VM021  SET  9037                          0556  27 9037 1061
579            STB  0037 A   VM023                1061  29 2037 1288
580     VM023  AXB  0001              ANY MORE    1288  52 0001 1044
581            NZB           VM027    EQUATIONS   1044  42 1497 0648
582            RAU  8006                          1497  60 8006 0605
583            SXA  0050     VM002                0605  51 0050 0506
584     VM027  RAA  0000              COMPLETE    0648  80 0000 0354
585            RAB  0001              BOTH THE    0354  82 0001 0210
586            RAU  RV014    VM101    ENTROPY     0210  60 9018 0467
587     VM101  NZU           VM104    AND THE     0467  44 0421 0222
588            FMP  NI                ENTHALPY    0421  39 9019 0274
589            STU  TEMPO             DURING THE  0274  21 9059 0481
590            RAU  SYS+2             EXPANSION   0481  60 0036 1291
591            RSC  8003              SET INDXC   1291  89 8003 0150
592            SET  9037                          0150  27 9037 0655
593            LDB  0037 A   VM028                0655  09 2037 1390
594     VM028  RAU  RV013 C           DO THE      1390  60 9617 1547
595            NZU           VM031    LAST        1547  44 0501 0552
596            FMP  TEMPO             EQUATION    0501  39 9059 0404
597            FAD  9049 C            WHICH IS    0404  32 9649 0483
598            STU  9049 C   VM031    ENTHALPY    0483  21 9649 0552
599     VM031  NZC           VM035    OR ENTROPY  0552  48 1055 0606
600            AXC  0001     VM028                1055  58 0001 1390
601     VM035  SET  9037                          0606  27 9037 1161
602            STB  0037 A   VM104                1161  29 2037 0222
603     VM104  NZB           VM036                0222  42 0325 0176
604            SXB  0001              DURING      0325  53 0001 0531
605            RAA  0950              EXPANSION   0531  80 0950 1287
606            RAU  RV000    VM101    ENTHALPY    1287  60 9004 0467
607 1                                 EQUATION
608 1                                 IS IN 0950
609 1                                 BAND
610 1                                 ALSO FILL
611     VM036  RAU  SYS+2             IN THE      0176  60 0036 1391
612            STL  RV011             PRESSURE    1391  20 9015 1198
613            RSC  8003              EQUATION    1198  89 8003 0656
614            SET  9037                          0656  27 9037 1211
615            LDB  0087     VM037                1211  09 0087 1440
616     VM037  RAU  RV013 C                       1440  60 9617 1597
617            NZU           VM039                1597  44 0551 0602
618            FMP  NI                            0551  39 9019 0454
619            FAD  9049 C                        0454  32 9649 0533
620            STU  9049 C   VM039                0533  21 9649 0602
621     VM039  NZC           VM041                0602  48 1105 1056
622            AXC  0001     VM037                1105  58 0001 1440
623     VM041  SET  9037                          1056  27 9037 1261
624            STB  0087                          1261  29 0087 1490
625            RAU  NI                SUM PI      1490  60 9019 1697
626            FAD  P                             1697  32 1112 1239
627            STU  P        VM061                1239  21 1112 1065
628 1
```

E-417

CA-10

```
1            CONDENSED PRODUCT PROCESSING
1
1            COUNT IS NUMBER OF UNPROCESSED
1                 CONDENSED PRODUCTS
1
   VM042   RAU COUNT                                 0406   60 0152 0507
           NZU          8877                         0507   44 1311 8877
1
1            ARE WE TRYING TO PROCESS TOO
1            MANY CONDENSED PHASES
1
           RSB  8003                  SET THE        1311   83 8003 0420
           ALO  8003                  INDICES TO     0420   15 8003 0377
           SUP UNITY                  STORE          0377   11 0104 0509
           ALO  8001                  CONDENSED      0509   15 8001 0517
           STU COUNT                  PHASE          0517   21 0152 1155
           RAU  8002                  EQUATION       1155   60 8002 1263
           MPY 50                     AND ITS        1263   19 0186 1106
           RAA  8002                  ENTHALPY       1106   80 8002 1165
1                                     OR ENTROPY
           SET RV001                  STORE THE      1165   27 9005 0470
           STB  0037 A                EQUATION       0470   29 2037 1540
           RAU RV014                  STORE THE      1540   60 9018 1747
           STU  0047 B                ENTHALPY       1747   21 4047 0200
1                                     OR ENTROPY
           FMP NI                     COMPLETE       0200   39 9019 0603
           FAD  0047                  ENTHALPY       0603   32 0047 1223
           STU  0047                  ROW            1223   21 0047 0250
           RAU COMEX                                 0250   60 0111 1215
           NZU           VM111                       1215   44 0469 0520
           RAU RV000                                 0469   60 9004 0427
           STU H0011 B                               0427   21 4997 0300
           FMP NI                                    0300   39 9019 0653
           FAD H0011                                 0653   32 0997 1273
           STU H0011     VM111                       1273   21 0997 0520
   VM111   RAU SYS+1                  COMPLETE       0520   60 0079 0583
           MPY 50                     THE COLUMN     0583   19 0186 1156
           RAA  8002                  FOR AAY        1156   80 8002 1265
           RAU ATOM1                                 1265   60 0642 1797
           RSB  8003     VM048                       1797   83 8003 0082
   VM048   RAU RV011 B                               0082   60 9415 1289
           NZU           VM051                       1289   44 1543 1194
           FMP NI                                    1543   39 9019 1396
           FAD  0047 A                               1396   32 2047 1323
           STU  0047 A   VM051                       1323   21 2047 1194
   VM051   AXB  0001                                 1194   52 0001 0350
           NZB           VM061                       0350   42 1053 1065
           SXA  0050     VM048                       1053   51 0050 0082
   VM061   RAA INDXA                  GO TO NEXT     1065   80 9029 1373
           RAC INDXC     UP013        PRODUCT        1373   88 9030 1246
1
1            CONSTANTS FOR VECTOR MULTIPLY
1                        ROUTINE
   50      00  0000      0050                        0186   00 0000 0050
1
1
1            MATRIX CLEAN UP ROUTINE FOR
1            GENERAL ROCKET PERFORMANCE
1                      CALCULATION
1
   MATRX   RAU LNAAY                  GET AAY        0257   60 0001 1205
           LDD MC003     EXP E        FROM           1205   69 0258 1850
   MC003   STU AAY                    LNAAY          0258   21 1133 0236
           LDD ATM-1                  SET INDXB      0236   69 0164 0567
           RAB  8001                  TO ATM-1       0567   82 8001 1423
           RAU SOLID                                 1423   60 0158 1313
           AUP UNITY                  SET INDXA      1313   10 0104 0559
           AUP  8001                  TO SOLID       0559   10 8001 0617
           MPY 50                     PLUS TWO       0617   19 0186 1206
           RAA  8002     MC007        TIMES 50       1206   80 8002 1315
1
   MC007   RAU AOMOL B MC009          ADD MASS       1315   60 4005 0609
   MC009   FMP AAY                    BALANCE        0609   39 1133 0653
           STU TEMPO                  AND            0633   21 9059 1441
           FSB  0047 A                ENTHALPY       1441   33 2047 1473
           FAD  0049 A                OR ENTROPY     1473   32 2049 0375
           STU  0049 A                DELTAS TO      0375   21 2049 0652
1                                     MATRIX
           RAU TEMPO                  STORE          0652   60 9059 0659
           FSB  0047 A                ERRORS         0659   33 2047 1523
           FDV TEMPO                                 1523   34 9059 0226
           STU RV002 B                               0226   21 9406 0983
           BMB MC031                                 0983   43 0286 1337
           NZB MC015     MC017                       1337   42 1590 1491
   MC015   SXB  0001                                 1590   53 0001 1446
           AXA  0050     MC007                       1446   50 0050 1315
   MC017   RAA  0000                                 1491   80 0000 1298
           RSB  0001                                 1298   83 0001 0504
           RAU COMEX                                 0504   60 0111 1365
           NZU MC019     MC021                       1365   44 0519 0570
   MC019   LDD S  SR                  PLACE S/R      0519   69 9036 0425
           STD  0047                  IN ENTROPY     0425   24 0047 0400
```

```
               RAU SO/R     MC009    ROW AND       0400  60 0003 0609
      1                              COLUMN A
      MC021    RAU HO/R     MC009                  0570  60 0004 0609
      MC031    RAU PO                ADD           0286  60 0015 0569
               FSB P                 PRESSURE      0569  33 1112 1339
               STU TEMPO             DELTA TO      1339  21 9059 1398
               FAD  0099             MATRIX        1398  32 0099 0475
               STU  0099                           0475  21 0099 1052
               RAU TEMPO             STORE         1052  60 9059 1059
               FDV PO                ERROR         1059  34 0015 1415
               STU RV000    MC103                  1415  21 9004 1573
      MC103    RAU COMEX             COMPLETE      1573  60 0111 1465
               NZU MC109    MC105    ENTROPY       1465  44 0619 0620
      MC105    RAU S CPR             AND THE       1620  60 9032 0477
               FMP T                 ENTHALPY      0477  39 9003 0080
               FAD  0048             EQUATIONS     0080  32 0048 0525
               STU  0048                           0525  21 0048 0601
               SET  9037                           0601  27 9037 1256
               LDB  0037                           1256  09 0037 1690
               SET  9037                           1690  27 9037 1445
               STB H0001    MC115                  1445  29 0987 1740
      MC109    RAU S CPR                           0619  60 9032 0527
               FAD  0048                           0527  32 0048 0575
               STU  0048                           0575  21 0048 0651
               RAU S CPR                           0651  60 9032 1159
               FMP T                               1159  39 9003 0262
               FAD  0998                           0262  32 0998 0625
               STU  0998    MC115                  0625  21 0998 1740
      1             DURING COMPLETION OF SYMMETRIC
      1             PORTIONS OF MATRIX    FOR GAS
      1             PHASE  INDXA WILL TRACK THE
      1             EQUATION BEING USED    INDXB
      1             WILL TRACK THE DIAGONAL
      1             POSITION AND INDXC WILL TRACK
      1             THE CURRENT MOVE OPERATION
      1
      1             THE PHASE TEST WORD CHECK IS
      1             ZERO FOR GAS REFLECTION AND
      1             UNITY FOR SOLID REFLECTION
      1
      MC115    RSU SOLID                           1740  61 0158 1363
               SLT  0004             SET CHECK     1363  35 0004 1673
               STL CHECK             TO GAS        1673  20 0309 0312
               AUP LDD                             0312  10 1515 1069
               STU MOVE1             GENERATE      1069  21 9058 0577
               RSU SYSTM             MOVE1 AND     0577  61 0638 1593
               AUP STD               MOVE2         1593  10 1496 1051
               STU MOVE2             ORDERS        1051  21 9059 1209
               RAU ATM-1             SET INDXB     1209  60 0164 1169
               NZU          MC151    TO ATM-1      1169  44 1723 0324
               RSB  8003    MC117    NEGATIVED     1723  83 8003 0282
      MC117    LDD  8006             SET INDXC     0282  69 8006 1338
               RAC  8001             TO INDXB      1338  88 8001 1244
               RSU  8001             INDXA IS      1244  61 8001 1101
               AUP SOLID             SOLID PLUS    1101  10 0158 1413
               AUP UNITY             TWO MINUS     1413  10 0104 1259
               AUP  8001             INDXB ALL     1259  10 8001 1067
               MPY 50                TIMES 50      1067  19 0186 1306
               RAA  8002                           1306  80 8002 1565
               LDD  8005             GAS           1565  69 8005 0471
               STD INDXA    MC123                  0471  24 9029 0627
      MC121    LDD  8005             CONDENSED     0450  69 8005 1356
               STD INDXA                           1356  24 9029 0362
               RSU  8006                           0362  61 8006 1219
               AUP UNITY                           1219  10 0104 1309
               MPY 50                              1309  19 0186 1406
               RAA  8002    MC123                  1406  80 8002 0627
      MC123    SET  9037                           0627  27 9037 0332
               LDB  0037 A                         0332  09 2037 1790
               RAA INDXA                           1790  80 9029 1448
               RAU MOVE1                           1448  60 9058 1255
               ALO MOVE2    8003     REFLECT       1255  15 9059 8003
      8003     LDD  9046 C  8002     ONE           8003  69 9646 8002
      8002     STD  0047 A  MC133    EQUATION      8002  24 2047 0500
      MC133    NZC MC135    MC139    AT A TIME     0500  48 1103 0554
      MC135    AXC  0001                           1103  58 0001 1359
               SXA  0050    8003                   1359  51 0050 8003
      MC139    AXB  0001                           0554  52 0001 0260
               NZB          MC151                  0260  42 1463 0324
               ALO UNO                             1463  15 0416 0521
               STL MOVE2    MC143                  0521  20 9059 0378
      MC143    RAU CHECK             GAS OR        0378  60 0309 1513
               NZU MC160    MC117                  1513  44 1167 0282
      MC151    RAU SOLID             ANY SOLIDS    0324  60 0158 1563
               NZU MC153    MC041    IN SYSTEM     1563  44 1217 0318
      MC153    RAU CHECK                           1217  60 0309 1663
               NZU MC041    MC159                  1663  44 0318 0368
      MC159    ALO UNITY             SET CHECK     0368  15 0104 1409
               STL CHECK             TO SOLID      1409  20 0309 0412
               RSU SOLID                           0412  61 0158 1713
               SLT  0004             GENERATE      1713  35 0004 1773
```

```
          STU TEMPO              MOVE1 AND    1773  21 9059 0581
          AUP LDD                MOVE2 FOR    0581  10 1515 1269
          STU MOVE1              CONDENSED    1269  21 9058 1177
          RAU TEMPO              PHASE        1177  60 9059 0335
          AUP STD                             0335  10 1496 1151
          STU MOVE2                           1151  21 9059 1459
          RAU SOLID              INDXB IS     1459  60 0158 1763
          RSB  8003     MC160    NEG SOLID    1763  83 8003 1167
 MC160    LDD ATM-1              INDEXC IS    1167  69 0164 1267
          RSC  8001              ATM-1        1267  89 8001 1823
                                 NEGATIVED
          RAU SYS+1              INDXA IS     1823  60 0079 1033
          MPY 50                 SYS+1        1033  19 0186 1456
          RAA  8002     MC121    TIMES 50     1456  30 8002 0450

             AT THIS POINT DECIDE IF
             ITERATION WILL BE NEEDED
             BY TESTING ON EXPONENT EACH
             DELTA MUST BE LESS THAN
             SOME SPECIFIED VALUE

 MC041    RAB  0052     MC042    EXP TEST     0318  82 0052 0374
                                 ITERATION
 MC042    RAU ATOM1              CONTINUED    0374  60 0642 1498
          AUP UNITY              UNTIL THE    1498  10 0104 1509
          RAC  8003     MC043    EXPONENT     1509  88 8003 0418
 MC043    RAU RV000 C            OF DELTAS    0418  60 9604 1175
          FAD  8006              IS EIGHT     1175  32 8006 1305
          NZU MC053              LESS THAN    1305  44 1559 0310
          NZC           MC049    THAT GIVEN   0310  48 1813 0414
          SXC  0001     MC043    BY WORD      1813  59 0001 0418
 MC049    RAB  0054     MC050    IN INDEXB    0414  82 0054 1070
 MC050    RAA  0000                           1070  80 0000 0276
          RAC  0000     MC051                 0276  88 0000 0382
 MC051    RAU P0001 A                         0382  60 3599 1153
          NZU           MC052                 1153  44 0557 0308
          RAU T0010 C            DEL SUB I    0557  60 6669 0424
          AXA  0002                           0424  50 0002 0130
          AXC  0010                           0130  58 0010 0336
          FAD  8006                           0336  32 8006 1665
          NZU MC053     MC051                 1665  44 1559 0382
 MC052    RAU TESTX              CONVERGED    0308  60 1361 1715
          NZU MC054              IF ERROR     1715  44 1319 1170
          LDD UNITY              LESS THAN    1170  69 0104 0607
          STD TESTX              EXPON 45     0607  24 1361 0464
          RAB  0053     MC050    ONCE OR      0464  82 0053 1070
                                 EXPON 46
                                 TWICE

            WHEN CONVERGED GO TO MC054

 MC054    LDD T                  SAVE TEMP    1319  69 9003 1225
          STD TEE                ON DRUM      1225  24 1111 0514
          SET  9050              WAS THE      0514  27 9050 1369
          LBB TEMP1              ITERATION    1369  08 1048 1201
          RAU  9051              DONE WITH    1201  60 9051 1709
          FSB T                  THE RIGHT    1709  33 9003 1389
          BMI MC058              THERMAL      1389  46 1242 1693
          RAU T                  DATA         1693  60 9003 1251
          FSB  9050                           1251  33 9050 0631
          BMI MC058                           0631  46 1242 0385

            ROUTINE TO CHECK ON TRANSITION
            FROM GAS TO CONDENSED PHASE

            IF POSITION 7 ON THE CONSOLE
            IS  AN EIGHT CONDENSING
            PROGRAM IS PASSED BY

            THE PROGRAM ASSUMES THAT BOTH
            GAS AND CONDENSED VECTOR ARE
            IN STORAGE

          LDD  8000                           0385  69 8000 1541
          BD7 DONE                            1541  97 1294 1546
          STL SW1                INITIALIZE   1546  20 1301 0604
          RAA  0000              SWITCH SW1   0604  80 0000 0360
          RAC  0000     MC201                 0360  88 0000 0466
 MC201    RAU P0001 A            ANY MORE     0466  60 3599 1203
          NZU           MC230    PRODUCTS     1203  44 0657 0358
          RAU P0002 A            YES IS IT    0657  60 3600 1355
          BMI           MC227    GASEOUS      1355  46 0408 1759
          RAL P0001 A            NO           0408  65 3599 1253
          SLT  0001              WAS THE      1253  35 0001 1809
          NZU MC205              SOLID USED   1809  44 0564 0614
          RAL T0008 C            YES IS NI    0614  65 6667 0571
          BMI           MC227    NEGATIVE     0571  46 0474 1759
          RAU UNITY              YES IGNORE   0474  60 0104 0410
          SRT  0001              THIS SOLID   0410  30 0001 1317
          ALO P0001 A            NEXT TIME    1317  15 3599 1303
          STL P0001 A                         1303  20 3599 1102
          RSU UNITY     MC219                 1102  61 0104 0460
```

```
MC205   RAB  0000                NO LOCATE    0564  82 0000 1220
        RAU P0002 A MC207        THE GAS      1220  60 3600 1405
MC207   AUP P0002 B              PHASE        1405  10 5600 1455
        NZU            MC211     VECTOR       1455  44 0510 0560
        SUP  8001                             0510  11 8001 1367
        AXB  0002      MC207                  1367  52 0002 1405
MC211   RAU  8006                FOUND IT     0560  60 8006 1417
        MPY FUNF                              1417  19 1270 1591
        RAB  8002                             1591  82 8002 1549
1
1          INDEX C LOCATES SOLID AND
1          INDEX B THE GAS PHASE DATA
1
        LDD  8007                STORE        1549  69 8007 1505
        STD INDXC                INDEX C      1505  24 9030 1411
        LDD TEE                  GET T TWO    1411  69 1111 1064
        STD T                    AND THREE    1064  24 9003 1320
        SET TWO                  FOR CORE     1320  27 9028 1275
        LBB B0001                             1275  08 1247 0550
        LDD MC215      F/RT                   0550  69 1353 1506
F/RT    STD LINK                 CALCULATES   1506  24 1855 0458
        SET  9010                F/RT FOR     0458  27 9010 1164
        LBB T0001 C              SOLID AND    1164  08 6660 1214
        RAU 1E                   GAS          1214  60 9015 0621
        FDV T                                 0621  34 9003 0524
        STU TEM1                              0524  21 0428 0981
        RAU 1D                                0981  60 9014 1439
        FDV TWO                               1439  34 9028 1292
        FMP T                                 1292  39 9003 1495
        FAD 1C                                1495  32 9013 1325
        FDV THREE                             1325  34 9029 0478
        FMP T                                 0478  39 9003 1031
        FAD 1B                                1031  32 9012 1461
        FDV TWO                               1461  34 9028 1264
        FMP T                                 1264  39 9003 1467
        FAD 1F                                1467  32 9016 1548
        FSB TEM1                              1548  33 0428 1555
        STU TEM 1                             1555  21 9049 1314
        RAU ONE                               1314  60 1149 1403
        FSB LNT                               1403  33 0002 0429
        FMP 1A                                0429  39 9011 0432
        FSB TEM 1      LINK                   0432  33 9049 1855
MC215   STU TEMPO                STORE F/RT   1253  21 9059 1511
        LDD  8006                             1511  69 8006 1517
        RAC  8001                             1517  88 8001 0574
        LDD MC217      F/RT                   0574  69 1227 1506
MC217   RSU  8003                CHECK FOR    1227  61 8003 0435
        FAD TEMPO                CONDENSING   0435  32 9059 1765
        FSB LNNI                              1765  33 9017 1545
        BMI            MC225                  1545  46 1598 1699
        RAU P0001 A              IT SHOULD    1598  60 3599 1453
        SLT  0001                HAVE BEEN    1453  35 0001 0610
        SRT  0001                CONDENSED    0610  30 0001 1567
        STU P0001 A              FIX IT       1567  21 3599 1152
        RAU UNITY      MC219                  1152  60 0104 0460
MC219   AUP SYS                  MODIFY       0460  10 0018 0624
        STU SYS                  SYS          0624  21 0018 1071
        LDD UNITY                SET SWITCH   1071  69 0104 1057
        STD SW1        MC225     SW1          1057  24 1301 1699
MC225   RAC INDXC      MC227     ADVANCE TO   1699  88 9030 1759
MC227   AXA  0002                THE NEXT     1759  50 0002 1815
        AXC  0010      MC201     PRODUCT      1815  58 0010 0466
MC230   STL TESTX                             0358  20 1361 1364
        RAU SW1                  ANY WRONG    1364  60 1301 1705
        NZU UNPAK      DONE      PRODUCTS     1705  44 0101 1294
DONE    LDD S  SR                SUMMATIONS   1294  69 9036 0600
        STD S                    OF S/P AND   0600  24 1124 1277
        LDD S HRT                H/RT ON      1277  69 9034 1183
        STD H                    DRUM         1183  24 1113 0516
        LDD ATM-1                INDXC IS     0516  69 0164 1667
        RSC  8001                ATM-1 NEG    1667  89 8001 1074
        LDD SYS+2                INDXA IS     1074  69 0036 1489
        RSA  8001                SYS+2 NEG    1489  81 8001 1595
        SET  9059 C              STORE        1595  27 9659 0650
        LBB  0099 A              PRESSURE     0650  08 2099 1202
        SET  9059 C              ROW IN       1202  27 9659 1107
        SBB Z0010 C MC057        Z REGION     1107  28 7349 1252
MC058   STL TESTX      MC059                  1242  20 1361 1414
1
1          TEST CONSOLE FOR PUNCHING
1          INTERMEDIATE ANSWERS
1
MC053   LDD ITERA      TEST1                  1559  69 0462 0566
MC057   LDD DERIV      TEST1                  1252  69 1755 0566
MC059   LDD MC060      TEST1                  1414  69 1717 0566
MC060   LDD TEE                               1717  69 1111 1464
        STD T          TDATA                  1464  24 9003 0034
TEST1   STD LINK1                             0566  24 1419 0272
        LDD  8000                             0272  69 8000 0528
        RD2 DELS       NEXT1     TEMPORARY    0528  92 1181 1233
NEXT1   LDD  8000                PUNCHES      1233  69 8000 1539
        RD3 VARIA      NEXT2     FOR          1539  93 1392 1394
```

E-417

```
        NEXT2   LDD  8000                  PROGRAM      1394  69 8000 1000
                RD4 MTRIX    LINK1         CHECKING     1000  94 1503 1419
      1
      1           CONSTANTS FOR MATRIX
      1           CLEAN UP ROUTINE
        LDD     LDD  9046 C  8002                       1515  69 9646 8002
        STD     STD  0047 A MC133                       1496  24 2047 0500
        UNO      00  0001     0000                      0416  00 0001 0000
        FUNE     00  0000     0005                      1270  00 0000 0005
      1
      1
      1           ROUTINE FOR CALCULATING THE
      1           CORRECTIONS TO THE CURRENT
      1           COMPOSITIONS  AAY AND THE
      1           TEMPERATURE
      1
        ITERA   RAU SYS+2    NEW00         SOLVE  FOR   0462  60 0036 1691
        NEW00   LDD NEW01    SOLVE         CORECTIONS   1691  69 1444 1698
        NEW01   LDD SYS+2                  LOAD         1444  69 0036 1589
                RSB  8001                  VARIABLES    1589  83 8001 1695
                SET M0001                  IN           1695  27 9000 1050
                LDB D0050 B NEW02          M-REGION     1050  09 4050 1553
      1
      1           INDXA WILL TRACK THE PRODUCT
      1           CODE AND INDXC WILL TRACK
      1           THE LN NI
      1
        NEW02   RSA  0002                               1553  81 0002 0960
                RSC  0010                               0960  89 0010 0616
                LDD SOLID                               0616  69 0158 1561
                STD COUNT    NEW03                      1561  24 0152 1805
      1
        NEW03   LDD ATOM1                               1805  69 0642 1745
                RAB  0010                  CLEAR 11     1745  82 0010 1351
                RAU WIPE9     8003         CORE         1351  60 0654 8003
         8003   STL N0001 B NEW04          LOCATIONS    8003  20 9415 1066
        NEW04   NZB           NEW06        FOR ROW      1066  42 1469 1370
                SXB  0001     8003         VECTOR       1469  53 0001 8003
        WIPE9   STL N0001 B NEW04                       0654  20 9415 1066
      1
        NEW06   AXA  0002                               1370  50 0002 0326
                AXC  0010                               0326  58 0010 0482
                RAL P0001 A                DO WE HAVE   0482  65 3599 1703
                NZE NEW07    NEW18         A PRODUCT    1703  45 1556 1157
        NEW07   SLT  0001                  YES   USE    1556  35 0001 1514
                NZU NEW06    NEW08         OR BYPASS    1514  44 1370 0468
      1
        NEW08   RAU P0002 A                TEST FOR     0468  60 3600 1706
                BMI NEW20    NEW10         CONDENSED    1706  46 1060 1160
      1
        NEW10   SRT  0002                  GET THE      1160  30 0002 1767
                SUP  8003                  MOLECULE     1767  11 8003 1375
                STD TEMPO                  SUBSCRIPTS   1375  24 9059 1231
                SLT  0001                  AND LOCATE   1231  35 0001 1387
                ALO 51                     POSITION     1387  15 0166 1171
                RAB  8003                  TO STORE     1171  82 8003 0180
                STL N0001 B                STORE        0180  20 9415 1388
                RAU TEMPO                  SUBSCRIPTS   1388  60 9059 1795
                NZU NEW10                  IN CORE      1795  44 1160 1100
                LDD SYS+2                  LOAD         1100  69 0036 1689
                RAB  8001                  OI AND       1689  82 8001 1596
                SET N0000 B                DELTAI       1596  27 9414 1401
                LDB T0009 C NEW15          ON CORE      1401  09 6668 1221
      1
        NEW15   SET C0001                  ROUTINE      1221  27 9050 0376
                LBB 00001     C0001        FOR          0376  08 1020 9050
        00001   SXB  0001     C0002        DEL LN PI    1020  53 0001 9051
        00002   RAU M0001 B C0003                       1021  60 9400 9052
        00003   FMP N0001 B C0004                       1022  39 9415 9053
        00004   FAD N0002 B C0005                       1023  32 9416 9054
        00005   STU N0001 B C0006                       1024  21 9415 9055
        00006   NZB C0001     C0007                     1025  42 9050 9056
        00007   FAD T0008 C C0008          NEW LN NI    1026  32 6667 9057
        00008   STU T0008 C NEW03          FOR GAS      1027  21 6667 1805
      1
        NEW20   LDD COUNT                  NEW NI       1060  69 0152 1756
                RSB  8001    NEW21         FOR          1756  83 8001 0512
        NEW21   RAU D0048 B NEW22          CONDENSED    0512  60 4048 1753
        NEW22   FAD T0008 C                             1753  32 6667 1743
                STU T0008 C                             1743  21 6667 1420
                RAU COUNT                  DECREASE     1420  60 0152 1207
                SUP UNITY                  COUNT        1207  11 0104 1210
                STU COUNT    NEW06         FOR SOLIDS   1210  21 0152 1370
      1
        NEW18   RAU D0049    NEW19         NEW LNT      1157  60 0049 1803
        NEW19   FAD LNT                                 1803  32 0002 0479
                STU LNT      NEW60                      0479  21 0002 1806
        NEW60   RSU D0048    NEW61         NEW LNA      1806  61 0048 1104
        NEW61   FAD LNAAY                               1104  32 0001 1327
                STU LNAAY                               1327  21 0001 1154
                RAU  8000                  PUNCH THE    1154  60 8000 1661
                BMI DELX     UNPAK         CORRECTION   1661  46 1564 0101
      1
```

```
               START NEW ITERATION AT UNPAK



               PERFORMANCE PARAMETER ROUTINE

               WHEN ITERATION IS COMPLETED
               ENTER AT DERIV

      DERIV  RAU SYS+2   D1          SOLVE FOR    1755  60 0036 1741
      D1     LDD 1LESS   REDUC       DLNPI/       1741  69 1494 1748
      1LESS  RAU SYS+1               DLNT AT      1494  60 0079 1283
             LDD CP  1   SOLVE       CONSTANT P   1283  69 0386 1698
      CP  1  LDD SYS+1               LOAD         0386  69 0079 0532
             RSA  8001               PARTIALS     0532  81 8001 1438
             RAB  8001                DLNPI/      1438  82 8001 1544
             SET M0001               DLNT AT      1544  27 9000 1749
             LDB D0050 A             CONSTANT P   1749  09 2050 1204
                                     ON CORE

             SET N0001               ENTHALPY     1204  27 9015 1260
             LDB H0012 A CP  2       ROW MOVED    1260  09 2998 1451
                                     TO CORE

      CP  2  SXB  0001               CALCULATE    1451  53 0001 1257
             RSU M0001 B             SPECIFIC     1257  61 9400 1166
             FMP N0001 B             HEAT TIMES   1166  39 9415 1519
             FAD N0002 B             MOLECULAR    1519  32 9416 1799
             STU N0001 B             WEIGHT       1799  21 9415 1307
             NZB CP  2               DIVIDED      1307  42 1451 1711
             FDV P                   BY R         1711  34 1112 0562
             FDV TEE                              0562  34 1111 1761
             STU CPMR                             1761  21 1216 1569
             RAU D0049 -             STORE        1569  60 0049 1254
             STU LMTP                DLNM/DLNT    1254  21 1123 0426
             LDD  8000               AT CONST P   0426  69 8000 0582
             RD1         CP  3       CHANGES      0582  91 0485 1437
             LDD NOOP                MADE         0485  69 1488 1791
             STD MC041   UNPAK       NECESSARY    1791  24 0318 0101
      ONCE   LDD NORM                BY           1150  69 1304 1357
             STD MC041               EQUATION     1357  24 0318 1271
             RAU SYS+2               SHIFTING     1271  60 0036 1442
             LDD         REDUC                    1442  69 1696 1748
             RAU SYS+1                            1696  60 0079 1333
             LDD         REDUC                    1333  69 0436 1748
             RAU SYS                              0436  60 0018 1174
             LDD DLMPT   SOLVE                    1174  69 1377 1698
      NOOP   NOP  0000   ONCE                     1488  00 0000 1150
      NORM   RAB  0052   MC042                    1304  82 0052 0374
      CP  3  RAU SYS+1                            1437  60 0079 1383
             LDD 2LESS   REDUC                    1383  69 0486 1748

      2LESS  RAU SYS                              0486  60 0018 1224
             LDD DLMPT   BACK                     1224  69 1377 0230



               CONSTANTS FOR USE IN PARAMETER
               CALCULATIONS

      CONS1   14  6960    0652       PSI/ATM      1140  14 6960 0652
      CONS2   86  4554    0052                    1141  86 4554 0052
      CONS3   10  0000    0054                    1142  10 0000 0054
      CONS4   29  4980    0053                    1143  29 4980 0053
      CONS5   57  0000    0050                    1144  57 0000 0050
      52      00  0000    0052                    1145  00 0000 0052
      R       19  8718    0051       CAL/MOL K    1146  19 8718 0051
      GC      32  1740    0052       GRAVITY      1147  32 1740 0052
      ONE     10  0000    0051                    1149  10 0000 0051

               SET CORE LOCATIONS EQUIVALENT
               TO PARAMETERS AND CONSTANTS
               OF THE E REGION

             EQU PCP     M0001       9000
             EQU TEE     M0002
             EQU P       M0003
             EQU H       M0004
             EQU I       M0005
             EQU M       M0006
             EQU CF      M0007
             EQU EPSIL   M0008
             EQU MACH    M0009
             EQU I VAC   M0010
             EQU CP      M0011
             EQU GAMMA   M0012
             EQU LMPT    M0013
             EQU LMTP    M0014
             EQU S       M0015
             EQU NI      M0016
             EQU NT      M0017
             EQU NEPS    M0018
             EQU NCSTR   M0019
```

E-417

```
         EQU CSTAR    M0020
         EQU AW       M0021
         EQU NAW      M0022
         EQU HSTR     M0023
         EQU AAY      M0024
         EQU HC       M0025
         EQU RECMC    M0026
         EQU NAWT     M0027
         EQU AWT      M0028
         EQU HSTR2    M0029
         EQU P1       M0030
         EQU CONS1    M0031
         EQU CONS2    M0032
         EQU CONS3    M0033
         EQU CONS4    M0034
         EQU CONS5    M0035
         EQU 52       M0036
         EQU R        M0037
         EQU GC       M0038
         EQU IDENT    M0039
         EQU ONE      M0040        9039

             CALCULATE THE PARTIAL DERIV
             OF THE LOG OF MOLEC WEIGHT
             WITH RESPECT TO THE LOG OF
             PRESSURE AT CONSTANT TEMPERTUR

DLMPT    SET M0001                              1377  27 9000 0632
         LDB F0001                              0632  09 1110 1664
         LDD SYS                   LOAD         1664  69 0018 1321
         RSA  8001                 DLNPT/DLNA   1321  81 8001 1427
         SET M0041                 IN CORE      1427  27 9040 0982
         LDB D0050 A                            0982  09 2050 1354
         LDD ATM-1                              1354  69 0164 1817
         RSA  8001                              1817  81 8001 1274
         RAB  8001                              1274  82 8001 0280
         SET M0051                              0280  27 9050 0535
         LDB Z0010 A LMPT1         BRING AAY    0535  09 3349 1302
LMPT1    RAU M0041 B               COLUMN       1302  60 9440 1310
         FMP M0051 B               TO CORE      1310  39 9450 1714
         FAD LMPT                               1714  32 9012 1793
         STU LMPT                               1793  21 9012 1501
         NZB          LMPT2                     1501  42 1404 1407
         SXB  0001    LMPT1                     1404  53 0001 1302
LMPT2    RAU P                                  1407  60 9002 1266
         FDV LMPT                               1266  34 9012 1669
         FSB ONE                                1669  33 9039 1200
         STU LMPT                               1200  21 9012 1457

             CALCULATE SEVERAL OTHER
             PARAMETERS

         RAU AAY                   CALCULATE    1457  60 9023 1316
         FDV P                     MOLECULAR    1316  34 9002 1719
         STU M                     WEIGHT       1719  21 9005 1477

         RAU CPMR                  SPECIFIC     1477  60 1216 1371
         FMP R                     HEAT         1371  39 9036 1324
         FDV M                     CAL/G        1324  34 9005 1527
         STU CP                                 1527  21 9010 0585

         RAU ONE                   GAMMA        0585  60 9039 1594
         FSB LMTP                  EQUALS       1594  33 9013 1374
         FMP  8003                 PARTIAL OF   1374  39 8003 1577
         STU TEMPO                 LN PRESSUR   1577  21 9059 0635
         RAU ONE                   WITH RESP    0635  60 9039 1694
         FAD LMPT                  TO           1694  32 9012 1424
         FMP CPMR                  LN DENSITY   1424  39 1216 1366
         FSB TEMPO                 AT CONSTNT   1366  33 9059 1746
         STU TEMPO                 ENTROPY      1746  21 9059 1454
         RAU CPMR                               1454  60 1216 1421
         FDV TEMPO                              1421  34 9059 1474
         STU GAMMA                              1474  21 9011 1281

         RAU H                     CALCULATE    1281  60 9003 1739
         FDV AAY                   ENTHALPY     1739  34 9023 1492
         FMP TEE                   CAL/G        1492  39 9001 1796
         FMP R                                  1796  39 9036 1250
         STU H                                  1250  21 9003 1507

         RAU S                     CALCULATE    1507  60 9014 1416
         FDV AAY                   ENTROPY      1416  34 9023 1769
         STU TEMPO                              1769  21 9059 1677
         FMP R                                  1677  39 9036 0330
         STU S                                  0330  21 9014 1487

             TEST IF COMBUSTION  THROAT  OR
             EXIT

         RAU COMEX                              1487  60 0111 1466
         NZU TOREX                              1466  44 1819 1470
```

E-417

```
            RAU ONE                 STORE        470   60 9039 1727
            FDV M                   1/MC         727   34 9005 0380
            STU RECMC                            380   21 9025 1537
 1
            FMP R                   CALCULATE    537   39 9036 1542
            FDV CP                  N SUB T      542   34 9010 1798
            FMP LMTP                             798   39 9013 1551
            RSU  8003                            551   61 8003 1360
            STU NT                               360   21 9016 0518
 1
            LDD H                   SAVE HC      0518  69 9003 1524
            STD HC                               1524  24 9024 0430
            LDD TEMPO                            0430  69 9059 0536
            STD SO/R                SAVE SO/R    0536  24 0003 1557
            RSU UNITY    FIX H      SET COMEX    1557  61 0104 1410
    FIX H   STU COMEX    H FIX      FOR THROAT   1410  21 0111 1764
    H FIX   STL CSTAR    PNCH       CLEAR CSTR   1764  20 9019 0322
 1
 1              TEST IF THROAT OR EXIT IS
 1              BEING PROCESSED
 1
 1
    TOREX   BMI THROT    EXIT                    1819  46 0372 1574
    EXIT    LDD REMAN    SEVRL                   1574  69 1777 0480
 1
 1
            EQU TWO      80001
 1
    THROT   RAU TEE                 CALCULATE    0372  60 9001 0529
            FDV M                   HSTR AS      0529  34 9005 1032
            FMP R                   H PLUS       1032  39 9036 0985
            FDV TWO                 VELOCITY     0985  34 1247 1300
            STU RT/2M               OF SOUND     1300  21 1504 1707
            FMP GAMMA               SQUARED      1707  39 9011 1460
            FAD H                   OVER TWO     1460  32 9003 1789
            STU HSTR                             1789  21 9022 1350
            FDV HC                  THROAT IS    1350  34 9024 1554
            FSB FINS                GOOD WHEN    1554  33 1757 1433
            NZU          CSTR1      HSTR EQUAL   1433  44 1587 1538
                                    HC
 1
            RAU GAMMA               THROAT NOT   1587  60 9011 1400
            FAD ONE                 DONE YET     1400  32 9039 0579
            FMP RT/2M                            0579  39 1504 1704
            STU TEMPO               CALCULATE    1704  21 9059 1811
            RAU HC                  THE NEXT     1811  60 9024 1520
            FSB HSTR                PRESSURE     1520  33 9022 1450
            FDV TEMPO               ESTIMATE     1450  34 9059 1754
            FAD ONE                 FOR THROAT   1754  32 9039 1483
            FMP P                                1483  39 9002 0586
            STU PO                               0586  21 0015 0568
            RAU PC                               0568  60 1109 1814
            STL TESTX                            1814  20 1361 1516
            FDV PO                               1516  34 0015 1566
            STU R0002                            1566  21 1076 0629
            STU F0001    UNPAK      STOR PC/PT   0629  21 1110 0101
 1
 1              START REITERATING WITH THE NEW
 1              THROAT PRESSURE ESTIMATE
 1
 1              CONSTANT FOR TESTING THROAT
 1                      FOR CONVERGENCE
 1
    FINS    00  1000     0053       THROT TEST   1757  00 1000 0053
 1
 1
    CSTR1   LDD CSTR2    SEVRL                   1538  69 1592 0480
 1
    CSTR2   STU NAWT                CALCULATE    1592  21 9026 1500
            FAD ONE                 C STAR       1500  32 9039 1029
            STU NCSTR               EXPONENT     1029  21 9018 1687
 1
            RAU AW                  STORE        1687  60 9020 1550
            STD AWT                 THROAT A/W   1550  24 9027 1807
 1
            FMP PC                               1807  39 1109 1510
            FMP GC                  CALCULATE    1510  39 9037 1666
            FMP CONS1               CSTAR        1666  39 9030 1570
            STU CSTAR                            1570  21 9019 1827
 1
            LDD UNITY               SET COMEX    1827 .69 0104 0508
            STD COMEX    REMAN      FOR EXIT     0508  24 0111 1777
 1
 1
 1              SUBROUTINE TO
 1              CALCULATE SEVERAL PERFORMANCE
 1              PARAMETERS WHICH ARE NEEDED
 1              AFTER BOTH THROAT AND EXIT ARE
 1              CONVERGED BUT ARE ALSO USED TO
 1              OBTAIN SEVERAL SPECIAL THROAT
 1              PARAMETERS AFTER THROAT IS
 1              CONVERGED
 1
```

```
     SEVRL  STD LINK1            CALCULATE   0480  24 1419 0422
            RAU HC               SPECIFIC    0422  60 9024 1179
            FSB H                IMPULSE     1179  33 9003 1560
            FDV CONS3                        1560  34 9032 1716
            LDD IMPUL   SQRT                 1716  69 1670 1900
     IMPUL  FMP CONS4                        1670  39 9033 1674
            STU I                            1674  21 9004 1331
 1
            RSU ONE              CALCULATE   1331  61 9039 1692
            FDV M                SPECIFIC    1692  34 9005 1700
            FAD RECMC            IMPULSE     1700  32 9025 1229
            FMP TEE              EXPONENT    1229  39 9001 1182
            FMP CONS2                        1182  39 9031 1035
            FDV I                            1035  34 9004 1588
            FDV I                            1588  34 9004 1742
            STU NI                           1742  21 9015 1750
 1
            RAU TEE              CALCULATE   1750  60 9001 0558
            FDV AAY              AREA PER    0558  34 9023 0612
            FDV I                UNIT FLOW   0612  34 9004 1766
            FMP CONS2            RATE        1766  39 9031 1720
            FDV CONS1                        1720  34 9030 1724
            STU AW                           1724  21 9020 1381
 1
            RAU R                CALCULATE   1381  60 9036 1792
            FDV CP               R OVER      1792  34 9010 1800
            FMP RECMC            CP TIMES    1800  39 9025 1804
            STU RCPMC            MC          1804  21 0608 1062
 1
            RAU ONE              CALCULATE   1062  60 9039 1770
            FDV GAMMA            AREA PER    1770  34 9011 1774
            STU TEMPO            UNIT FLOW   1774  21 9059 1431
            RAU LMTP             RATE        1431  60 9013 1744
            FSB ONE              EXPONENT    1744  33 9039 1824
            FMP RCPMC                        1824  39 0608 0658
            FSB TEMPO                        0658  33 9059 1737
            FSB NI                           1737  33 9015 0618
            STU NAW     LINK1                0618  21 9021 1419
 1
 1
 1              CALCULATE THOSE PERFORMANCE
 1              PARAMETERS WHICH HAVE NOT YET
 1              BEEN CALCULATED
 1
 1
     REMAN  RAU I                CALCULATE   1777  60 9004 1185
            FMP GC               THRUST      1185  39 9037 1688
            FDV CSTAR            COEFFICIEN  1688  34 9019 1794
            STU CF               C SUB F     1794  21 9006 1701
 1
            RAU AW               CALCULATE   1701  60 9020 1660
            FDV AWT              AREA RATIO  1660  34 9027 1816
            STU EPSIL                        1816  21 9007 1425
 1
            RAU AW               CALCULATE   1425  60 9020 1533
            FMP P                SPEC IMPLS  1533  39 9002 0636
            FMP CONS1            ASSUMING    0636  39 9030 1751
            FAD I                AMBIENT     1751  32 9004 1481
            STU I VAC            PRESS ZERO  1481  21 9009 1801
 1
            RAU GAMMA            CALCULATE   1801  60 9011 1710
            FMP TEE              MACH        1710  39 9001 1068
            FMP CONS2            NUMBER      1068  39 9031 1471
            FDV M                            1471  34 9005 1475
            LDD MACH1   SQRT                 1475  69 0578 1900
     MACH1  STU TEMPO                        0578  21 9059 1235
            RAU I                            1235  60 9004 1352
            FDV TEMPO                        1352  34 9059 1058
            STU MACH                         1058  21 9008 1168
 1
            RAU ONE              CALCULATE   1168  60 9039 1525
            FSB LMTP             TEMPERATUR  1525  33 9013 1108
            FDV CPMR             EXPONENT    1108  34 1216 1218
            FSB RCPMC            N SUB T     1218  33 0608 1285
            STU NT                           1285  21 9016 1402
 1
            RAU NAW              CALCULATE   1402  60 9021 1760
            FSB NAWT             AREA RATIO  1760  33 9026 1452
            STU NEPS    PNCH     EXPONENT    1452  21 9017 0322
 1
 1
 1              ROUTINE FOR PUNCHING ROCKET
 1              PERFORMANCE PARAMETERS AND
 1              COMPOSITION OF COMBUSTION
 1              PRODUCTS
 1
     PNCH   RAU  8003            SET CARD    0322  60 8003 1279
            STL CARDN            NUMBR ZERO  1279  20 1852 1158
            SET M0001                        1158  27 9000 1268
            STB F0001                        1268  29 1110 1318
            RSA  0005            PUNCHES 2   1318  81 0005 1575
            RAB  0004            PERFORMANC  1575  82 0004 1531
```

```
                LDD IDENT              PARAMETERS    531   69 9038 1787
                STD M0011     PNCH1    ON 4 CARDS    787   24 9010 1502

       PNCH1    NZB           COMP1    EACH CARD     502   42 1208 1258
                SXB  0001              HAS 5         208   53 0001 1368
                AXA  0005              PARAMETERS    368   50 0005 1675
                SET M0005              PLUS          675   27 9005 0530
                LBB F0001 A            IDENTIFI-     530   08 3110 1418
                NZA SPEC               CATION AS     418   40 1521 0472
                RAL SPEC1     PNCH2    6TH WORD      472   65 1725 1329
       PNCH2    LDD PNCH1     PUNCH                  329   69 1502 1950

       SPEC     RAL SPEC2     PNCH2                 1521   65 1775 1329
       COMP1    RAA  0000                           1258   80 0000 1468
                RAB  0000     COMP2                 1468   82 0000 1825

       COMP2    RSC  0005              CLEAR        1825   89 0005 1581
                RAU  8003     COMP3    POSITIONS    1581   60 8003 1552
       COMP3    STL M0011 C            FOR          1552   20 9610 1810
                AXC  0001              PRODUCTS     1810   58 0001 1518
                BMC COMP3              AND CODES    1518   49 1552 0522

                RSC  0004     COMP4                 0522   89 0004 0628
       COMP4    RAU P0001 A            DO WE HAVE   0628   60 3599 1308
                NZU           COMP5    A PRODUCT    1308   44 1162 1212

                STU M0010 C            LOAD CODE    1162   21 9609 1820
                AXC  0001                           1820   58 0001 0476

                RAU P0002 A            TEST FOR     0476   60 3600 1358
                BMI COMP6              CONDENSED    1358   46 1262 1312

                RAU T0008 B            CALC PI      1312   60 4667 1571
                LDD COMP7     EXP E    FROM LN PI   1571   69 0526 1850
       COMP7    STU M0010 C            AND LOAD     0526   21 9609 1583
                AXA  0002                           1583   50 0002 1702
                AXB  0010                           1702   52 0010 1408
                AXC  0001                           1408   58 0001 1568
                BMC COMP4     COMP5                 1568   49 0628 1212

       COMP5    NZA           SPACE                 1212   40 1668 1718
                RAL SPEC2     COMP8                 1668   65 1775 1379
       SPACE    RAL SPEC3     COMP8                 1718   65 1671 1379
       COMP8    LDD           PUNCH    PRODUCTS     1379   69 1232 1950
                RAU P0001 A            AND CODES    1232   60 3599 1458
                NZU COMP2     FROZ                  1458   44 1825 1362
       FROZ     LDD UNPAK     PCP 1                 1362   69 0101 0637

       COMP6    RAU T0008 B COMP7      COND IS NI   1262   60 4667 0526


                  CONSTANTS FOR PUNCH ROUTINE

       SPEC1     07 M0006     0006                  1725   07 9005 0006
       SPEC2     00 M0006     0006                  1775   00 9005 0006
       SPEC3     06 M0006     0006                  1671   06 9005 0006


                EQU PCP       F0001
                EQU TEE       F0002
                EQU P         F0003
                EQU H         F0004
                EQU I         F0005
                EQU M         F0006
                EQU CE        F0007
                EQU EPSIL     F0008
                EQU MACH      F0009
                EQU I VAC     F0010
                EQU CP        F0011
                EQU GAMMA     F0012
                EQU LMPT      F0013
                EQU LMTP      F0014
                EQU S         F0015
                EQU NI        F0016
                EQU NT        F0017
                EQU NEPS      F0018
                EQU NCSTR     F0019
                EQU CSTAR     F0020
                EQU AW        F0021
                EQU NAW       F0022
                EQU HSTR      F0023
                EQU AAY       F0024
                EQU HC        F0025
                EQU RECMC     F0026
                EQU NAWT      F0027
                EQU AWT       F0028
                EQU HSTR2     F0029
                EQU P1        F0030
                EQU CONS1     F0031
                EQU CONS2     F0032
                EQU CONS3     F0033
                EQU CONS4     F0034
```

E-417

```
                EQU CONS5    F0035
                EQU 52       F0036
                EQU R        F0037
                EQU GC       F0038
                EQU IDENT    F0039
 1
 1
 1                  SUBROUTINE TO SET ASSIGNED
 1                  PRESSURE
 1
      PCP 1     STD LINK                                0637  24 1855 1508
                RAL PCPCT                 ADVANCE       1508  65 0017 1721
                ALO UNITY                 PRESSURE      1721  15 0104 1412
                STL PCPCT                 RATIO         1412  20 0017 1771
 1                                        COUNTER
                RAA  8001                               1771  80 8001 1028
                SLT  0004                               1028  35 0004 1752
                STL PROB                                1752  20 1904 1558
                RAU R0000 A                             1558  60 3074 1429
                STL TESTX                               1429  20 1361 1768
                STU PCP                   NEW PC/PE     1768  21 1110 1818
                NZU          9999         TEST FOR      1818  44 1821 9999
 1                                        LAST PC/PE
                RAU PC                                  1821  60 1109 0572
                FDV PCP                                 0572  34 1110 1462
                STU PO       CLER1                      1462  21 0015 0622
 1
      CLER1     RAB  0018                 CLEAR 18      0622  82 0018 1178
                RAU WIPE7    8003         PARAMETER     1178  60 1681 8003
       8003     STL F0001 B CL  1         STORAGES      8003  20 5110 1072
      CL  1     SXB  0001                               1072  53 0001 1228
                NZB  8003    LINK                       1228  42 8003 1855
 1
 1                  CONSTANTS FOR ASSIGNED
 1                  PRESSURE SUBROUTINE
 1
      UNITY      00  0000    0001                       0104  00 0000 0001
      WIPE7     STL F0001 B CL  1                       1681  20 5110 1072
 1
 1
 1                  SUBROUTINE FOR SOLUTION OF
 1                  N SIMULTANEOUS EQUATIONS
 1
      SOLVE     STD LINK                                1698  24 1855 1708
                STU EQUAT                               1708  21 1512 1172
                SUP UNITY                               1172  11 0104 1562
                NZU OKEH                                1562  44 1222 1272
                RAU D0049                               1272  60 0049 1758
                FDV D0048                               1758  34 0048 1802
                STU D0049    LINK                       1802  21 0049 1855
      OKEH      AUP UNITY    START                      1222  10 0104 1662
 1
 1
      BACK      STD LINK                  BACK          0230  24 1855 1808
                STU NOROW                 SOLUTION      1808  21 9049 1322
                RAU D0049    BACK1        ONLY          1322  60 0049 1712
      START     STU NOROW                 STORE EQUA    1662  21 9049 1372
                STD MINEX                 NUMBER        1372  24 9045 1278
                STL MINCO                               1278  20 9046 0986
                LDD  8000                 MUST EQUA     0986  69 8000 1762
                BD1 AGAIN    STRT1        BE SHIFTED    1762  91 1422 1472
      AGAIN     STU VARBL                               1422  21 9048 1479
                SUP UNITY                               1479  11 0104 1812
                BMI SHOVE                               1812  46 1522 1572
                MPY 50                    INDXB         1572  19 0186 1672
                RAB  8002                 FOLLOWS       1672  82 8002 1731
                SXB NOROW                 EQUATIONS     1731  53 9049 1722
                RAU NOROW                 INDXA THE     1722  60 9049 1529
                SUP UNITY                 VARIABLES     1529  11 0104 1772
                NZU          BACKS                      1772  44 0576 0626
                RAA  8003                               0576  80 8003 0334
                RAC  8003                               0334  88 8003 1822
                SET M0001                 BRING EQUA    1822  27 9000 1328
                LDB D0049 B               TO CORE       1328  09 4049 1176
                SET C0001                               1176  27 9050 1781
                LDB U0001    C0001                      1781  09 0050 9050
      U0001     RAU M0001    C0002        DIVIDE THE    0050  60 9000 9051
      U0002     NZU C0003    LEAVE        EQUATION      0051  44 9052 1226
      U0003     RAU M0001 A  C0004        BY THE        0052  60 9200 9053
      U0004     FDV M0001    C0005        LEADING       0053  34 9000 9054
      U0005     RAM  8003    C0006        COEFICIENT    0054  67 8003 9055
      U0006     STL M0001 A  C0007                      0055  20 9200 9056
      U0007     SXA  0001    C0008                      0056  51 0001 9057
      U0008     NZA C0003    C0009                      0057  40 9052 9058
      U0009     STU MAXCO                               0058  21 9047 1326
                RAA NOROW                 TO ZERO       1326  30 9049 0384
                SXA  0001                               0384  51 0001 1376
                SET C0001                               1376  27 9050 1831
                LDB Y0001    C0001                      1831  09 0059 9050
      Y0001     RAU MAXCO    C0002        SEARCH FOR    0059  60 9047 9051
      Y0002     FSB M0001 A  C0003        MAXIMUM       0060  33 9200 9052
      Y0003     BMI C0004    C0006        COEFICIENT    0061  46 9053 9055
```

```
1641   Y0004   LDD M0001 A C0005
1642   Y0005   STD MAXCO   C0006
1643   Y0006   SXA  0001   C0007
1644   Y0007   NZA C0001
1645           RSU MINCO
1646           NZU         BOOK
1647           FAD MAXCO
1648           BMI BOOK    LEAVE
1649   BOOK    LDD MAXCO
1650           STD MINCO
1651           LDD VARBL
1652           STD MINEX   LEAVE
1653   LEAVE   RAU VARBL
1654           SUP UNITY   AGAIN
1655   SHOVE   RAU NOROW
1656           SUP MINEX
1657           NZU         STRT0
1658           RAU NOROW
1659           SUP UNITY
1660           MPY 50
1661           RAA  8002
1662           RAU MINEX
1663           SUP UNITY
1664           MPY 50
1665           RAB  8002
1666           SET M0001
1667           LDB D0037 A
1668           LDB D0037 B
1669           SET M0001
1670           STB D0037 B
1671           STB D0037 A STRT0
1672   STRT0   RAU NOROW   STRT1
1673   STRT1   SUP UNITY
1674           NZE         BACKS
1675           MPY 50
1676           RAB  8002
1677           SXB NOROW
1678           SET M0001
1679           LDB D0049 B
1680           RAA NOROW   DIV
1681   DIV     SET C0001
1682           LBB I0001   C0001
1683   I0001   RAU M0001 A C0002
1684   I0002   FDV M0001   C0003
1685   I0003   STU M0001 A C0004
1686   I0004   SXA  0001   C0005
1687   I0005   NZA C0001   NEXTR
1688 1
1689   NEXTR   SET M0002
1690           STB D0050 B
1691           SET C0001
1692           LBB J0001   NEW R
1693 1
1694   NEW R   SXB  0050
1695           AXB NOROW
1696           BOV OFLO1
1697           BMB OUT 1
1698           SXB NOROW
1699           SET N0001
1700           LDB D0049 B
1701           RAA NOROW   ELMIN
1702   OFLO1   HLT  0000   9955
1703   OUT 1   RAU NOROW
1704           SUP UNITY   START
1705   J0001   RSU N0001   C0002
1706   J0002   FMP M0001 A C0003
1707   J0003   BOV ZEROU   C0004
1708   J0004   FAD N0001 A C0005
1709   J0005   STU N0001 A C0006
1710   J0006   SXA  0001   C0007
1711   J0007   NZA ELMIN
1712           SET N0002
1713           STB D0050 B NEW R
1714   ZEROU   RAU  8002   C0004
1715 1
1716   BACKS   RAU N0003   B1
1717   B1      FDV N0002
1718           LDD EQUAT
1719 1
1720           STD NOROW   BACK1
1721   BACK1   RAB  0000
1722           RAC  0001
1723           SET C0001
1724           LBB K0001   S7
1725 1
1726   S7      SXC  0001
1727           STU D0049 C
1728           BOV OFLO2
1729           RSL  8007
1730           RAA  8002
1731           AXA  0001
```

```
                0062  69 9200 9054
                0063  24 9047 9055
                0064  51 0001 9056
                0065  40 9050 1426
PLACE           1426  61 9046 1683
SMALLEST        1683  44 1738 1788
COEFFICIENT     1738  32 9047 1476
IN MINCO        1476  46 1788 1226
AND EQUAT       1788  69 9047 1526
NUMBER IN       1526  24 9046 1282
MINEX           1282  69 9048 1576
                1576  24 9045 1226
GO TO NEXT      1226  60 9048 1733
EQUATION        1733  11 0104 1422
                 522  60 9049 1579
                1579  11 9045 1676
                1676  44 1679 0580
                1679  60 9049 1726
                1726  11 0104 1776
                1776  19 0186 1826
                1826  80 8002 1335
                1335  60 9045 1378
                1378  11 0104 1428
                1428  19 0186 1478
                1478  82 8002 1528
SHIFT THE       1528  27 9000 1783
EQUATIONS       1783  09 2037 1578
                1578  09 4037 1678
                1678  27 9000 0434
                0434  29 4037 1728
                1728  29 2037 0580
                0580  60 9049 1472
                1472  11 0104 1778
                1778  45 1332 0626
                1332  19 0186 1828
                1828  82 8002 1729
                1729  53 9049 1779
TRANSFER        1779  27 9000 0484
EQ TO CORE      0484  09 4049 1829
                1829  80 9049 0630
                0630  27 9050 1385
DIVIDE          1385  08 1001 9050
ELEMENTS        1001  60 9200 9051
OF FIRST        1002  34 9000 9052
EQUATION        1003  21 9200 9053
BY LEADING      1004  51 0001 9054
COEFFIC         1005  40 9050 1030
AND STORE       1030  27 9001 1435
BACK ON         1435  29 4050 1180
DRUM            1180  27 9050 1485
                1485  08 1006 1230
ANY MORE        1230  53 0050 1036
EQUATIONS       1036  52 9049 1280
CHK OVRFLO      1280  47 0534 1535
                1535  43 1330 1380
YES             1380  53 9049 1430
                1430  27 9015 1585
                1585  09 4049 1480
                1480  80 9049 9050
                0534  01 0000 9955
NO              1330  60 9049 1530
                1530  11 0104 1662
ELIMINATE       1006  61 9015 9051
A VARIABLE      1007  39 9200 9052
CHK OVRFLO      1008  47 1580 9053
                1009  32 9215 9054
                1010  21 9215 9055
                1011  51 0001 9056
                1012  40 9050 1680
                1680  27 9016 1685
                1685  29 4050 1230
OVERFLOW        1580  60 8002 9053
LEAVES THE      0626  60 9017 0584
LAST            0584  34 9016 1730
VARIABLE        1730  69 1512 1780
IN UPPER
                1780  24 9049 1712
                1712  82 0000 1830
                1830  88 0001 1186
                1186  27 9050 1382
                1382  08 1013 1432
                1432  59 0001 1482
                1482  21 6049 1532
CHK OVRFLO      1532  47 1735 1582
                1582  66 8007 1682
                1682  80 8002 1732
                1732  50 0001 1782
```

E-417

E-417

```
          AXB  0049                               1782  52 0049 1832
          SXA  NOROW                              1832  51 9049 0634
          BMA           LINK                      0634  41 0984 1855
          AXA  NOROW                              0984  50 9049 1034
          SET  M0001                VARIABLES     1034  27 9000 1184
          LDB  D0049 C              IN M0001      1184  09 6049 1234
          SET  N0001                COEFFICNTS    1234  27 9015 1284
          LDB  D0049 B S1           IN N0001      1284  09 4049 9050
OFLO2     HLT  0000     9966                      1735  01 0000 9966
49        49   0000     0000                      1334  49 0000 0000


             CALCULATE AND LEAVE NEXT
             VARIABLE IN UPPER

K0001     SXA  0001     C0002                     1013  51 0001 9051
K0002     RSU  M0001 A  C0003                     1014  61 9200 9052
K0003     FMP  N0001 A  C0004                     1015  39 9215 9053
K0004     BOV  ZERUP    C0005       CHK OVRFLO    1016  47 1384 9054
K0005     FAD  N0002 A  C0006                     1017  32 9216 9055
K0006     STU  N0001 A  C0007                     1018  21 9215 9056
K0007     NZA  S1       S7                        1019  40 9050 1432
ZERUP     RAU  8002     C0005                     1384  60 8002 9054


             SUBROUTINE TO REDUCE MATRIX BY
             ONE COLUMN AND ONE ROW

REDUC     STD  LINK                 REDUCE        1748  24 1855 1434
          RSB  8003                 MATRIX        1434  83 8003 1484
          RAA  8003                 BY            1484  80 8003 1534
          SXA  0001     SHIFT       ONE           1534  51 0001 1584
SHIFT     AXB  0050                 COLUMN        1584  52 0050 1684
          SET  M0001                AND           1684  27 9000 1734
          LDB  D0049 B              ONE           1734  09 4049 1784
          SET  M0001                ROW           1784  27 9000 1785
          STB  D0000 B                            1785  29 4000 1236
          SXA  0001                               1236  51 0001 1286
          NZA  SHIFT    LINK                      1286  40 1584 1855


             ROUTINE TO LOAD PACKED VECTORS
             AND GENERATE ATOM1 AND SYS THE
             PROGRAM DEFINING CONSTANTS

             PRECEED PACKED VECTORS WITH
             A LOAD HUB TRANSFER CARD WHICH
             IS  NOP GO TO V0001

             FOLLOW PACKED VECTORS WITH A
             LOAD HUB CARD WORD1 EQUAL ZERO

             THE PROGRAM BYPASSES THE
             PROPELLANT IDENTIFICATION CARD

             INDEXB TOTALS GASEOUS ATOMS
             INDEXC TOTALS CONDENSED PHASES

             OASIS SPECIFIES WHICH OF THE
             CONDENSED PHASES ARE USED

          REG  R1951    1960        READ BAND
          REG  V1599    1659        IN PREGION
          REG  C9000    9000
          EQU  PCH10    1986        WRD 10 PCH
          EQU  ODIN     C0048
          EQU  OASIS    C0049
          EQU  RELAY    C0050

8000      RCD  R0001    1998        CONSOLE       8000  70 1951 1998
R0001     00   0000     V0001       TRANSFR CD    1951  00 0000 1599
V0001     SET  C0003    V0002                     1599  27 9002 1600
V0002     LDB  V0003    C0003                     1600  09 1601 9002
V0003     RAA  0000     C0004       CLEAR         1601  80 0000 9003
V0004     RAB  0000     C0005       INDEX A B     1602  82 0000 9004
V0005     RAC  0000     C0006       AND C         1603  88 0000 9005
V0006     SUP  8003     C0007                     1604  11 8003 9006
V0007     STU  RELAY    C0008                     1605  21 9049 9007
V0008     RCD  PCH10    9977                      1606  70 1986 9977
PCH10     NOP  0000     C0009                     1986  00 0000 9008
V0009     RAU  R0001    C0010       ARE ALL       1607  60 1951 9009
V0010     NZU  C0011    C0042       VECTORS IN    1608  44 9010 9041
V0011     RAU  R0002    C0012       NO BYPASS     1609  60 1952 9011
V0012     NZU  C0013    C0008       NONVECTORS    1610  44 9012 9007
V0013     RAU  R0004    C0014                     1611  60 1954 9013
V0014     BMI  C0025    C0015       IS THIS       1612  46 9024 9014
V0015     SRT  0002     C0016       AN ATOM OR    1613  30 0002 9015
V0016     NZU  C0025    C0017       MOLECULE      1614  44 9024 9016
V0017     SLT  0001     C0018                     1615  35 0001 9017
V0018     SLO  ODIN     C0019                     1616  16 9047 9018
V0019     RAL  8002     C0020                     1617  65 8002 9019
```

```
1823   V0020   NZE C0025   C0021                  1618  45 9024 9020
1824   V0021   AXB  0001   C0022    GAS ATOM      1619  52 0001 9021
1825   V0022   RAU RELAY   C0023    ARE ALL       1620  60 9049 9022
1826   V0023   NZU C0024   C0037    ATMS AHEAD    1621  44 9023 9036
1827   V0024   HLT  0000    9988                  1622  01 0000 9988
1828   V0025   LDD ODIN    C0026    IT IS A       1623  69 9047 9025
1829   V0026   STD RELAY   C0027    MOLECULE      1624  24 9049 9026
1830   V0027   RAU R0004   C0028    IS PRODUCT    1625  60 1954 9027
1831   V0028   BMI C0029   C0037    CONDENSED     1626  46 9028 9036
1832   V0029   RAU OASIS   C0030    YES           1627  60 9048 9029
1833   V0030   SRT  0001   C0031                  1628  30 0001 9030
1834   V0031   STU OASIS   C0032                / 1629  21 9048 9031
1835   V0032   RAL  8002   C0033    IS IT TO    / 1630  65 8002 9032
1836   V0033   NZE C0036   C0034    BE USED       1631  45 9035 9033
1837   V0034   RAL R0002   C0035    YES           1632  65 1952 9034
1838   V0035   AXC  0001   C0038                  1633  58 0001 9037
1839   V0036   ALO R0002   C0038    NO            1634  15 1952 9037
1840   V0037   RAL R0002   C0038                  1635  65 1952 9037
1841   V0038   STL P0001 A C0039    STORE CODE    1636  20 3599 9038
1842   V0039   LDD R0004   C0040    AND VECTOR    1637  69 1954 9039
1843   V0040   STD P0002 A C0041                  1638  24 3600 9040
1844   V0041   AXA  0002   C0008                  1639  50 0002 9007
1845   V0042   RAU  8007   C0043                  1640  60 8007 9042
1846   V0043   STL P0001 A C0044                  1641  20 3599 9043
1847   V0044   LDD  8006   C0045                  1642  69 8006 9044
1848   V0045   STD ATOM1   C0046    STORE SYS     1643  24 0642 9045
1849   V0046   AUP  8001   C0047    AND ATOM1     1644  10 8001 9046
1850   V0047   STU SYS     CHEK                   1645  21 0018 0499
1851 1
1852 1             CONSTANTS
1853 1
1854   V0048   10  0000    0000     ODIN          1646  10 0000 0000
1855   V0049   11  1111    1111     OASIS         1647  11 1111 1111
1856 1
1857 1             BUILT IN ESTIMATES FOR
1858 1             ALL THE VARIABLES
1859 1
1860   T0008   10  0000    0040     ESTIMATES     0667  10 0000 0040
1861   T0018   10  0000    0040     FOR LN OF     0677  10 0000 0040
1862   T0028   10  0000    0040     COMPOSITON    0687  10 0000 0040
1863   T0038   10  0000    0040     EQUIVALENT    0697  10 0000 0040
1864   T0048   10  0000    0040     TO PARTIAL    0707  10 0000 0040
1865   T0058   10  0000    0040     PRESSURES     0717  10 0000 0040
1866   T0068   10  0000    0040     OF I          0727  10 0000 0040
1867   T0078   10  0000    0040     ATMOSPHERE    0737  10 0000 0040
1868   T0088   10  0000    0040     FOR ALL       0747  10 0000 0040
1869   T0098   10  0000    0040     GASEOUS       0757  10 0000 0040
1870   T0108   10  0000    0040     PRODUCTS      0767  10 0000 0040
1871   T0118   10  0000    0040                   0777  10 0000 0040
1872   T0128   10  0000    0040                   0787  10 0000 0040
1873   T0138   10  0000    0040                   0797  10 0000 0040
1874   T0148   10  0000    0040                   0807  10 0000 0040
1875   T0158   10  0000    0040                   0817  10 0000 0040
1876   T0168   10  0000    0040                   0827  10 0000 0040
1877   T0178   10  0000    0040                   0837  10 0000 0040
1878   T0188   10  0000    0040                   0847  10 0000 0040
1879   T0198   10  0000    0040                   0857  10 0000 0040
1880   T0208   10  0000    0040                   0867  10 0000 0040
1881   T0218   10  0000    0040                   0877  10 0000 0040
1882   T0228   10  0000    0040                   0887  10 0000 0040
1883   T0238   10  0000    0040                   0897  10 0000 0040
1884   T0248   10  0000    0040                   0907  10 0000 0040
1885   T0258   10  0000    0040                   0917  10 0000 0040
1886   T0268   10  0000    0040                   0927  10 0000 0040
1887   T0278   10  0000    0040                   0937  10 0000 0040
1888   T0288   10  0000    0040                   0947  10 0000 0040
1889   T0298   10  0000    0040                   0957  10 0000 0040
1890   G0001   50  0000    0051     LNA ESTM T    0001  50 0000 0051
1891   G0002   82  4300    0051     LNT ESTM T    0002  82 4300 0051
1892 1
1893 1
1894 1             TO RUN AT CONSTANT ENTHALPY
1895 1             AT VARIOUS PRESSURE RATIOS
1896 1             LOAD THE FOLLOWING CARD
1897 1
1898   FIX H   STL COMEX   H FIX    CONST H       1410  20 0111 1764
1899 1
     1             TO RUN FROZEN COMPOSITION
     1             CALCULATIONS LOAD THE
     1             FOLLOWING CARD
     1
       FROZ    HLT  9999   9999                   1362  01 9999 9999
     1
1900 1
1901           PAT
```

II-41

E-417

```
          PUNCH ROUTINE FOR TESTING
          GENERAL ROCKET PERFORMANCE
                 CALCULATION

          PUNCHING IS CONSOLE CONTROLLED
          BY POSITIONS 2 3 4 AND SIGN
          THESE POSITIONS MUST BE EITHER
          EIGHT OR NINE PUNCHING ON 8

          POSITION 2 PUNCHES ONE MINUS
          P/PO ETC  AND NEGATIVE DELTAI

          POSITION 3 PUNCHES P   T   AAY
          AND THE COMPOSITIONS NI

          POSITION 4 PUNCHES THE
          REDUCED MATRIX

          A MINUS ON CONSOLE PUNCHES
          CORRECTION VARIABLES

          ANY COMBINATION OF THE FOUR
          PUNCHES MAY BE USED TOGETHER

        BLA  1656     1659
        BLA  0940     0959


          PUNCH THE DELS AT THIS TIME

DELS    RAL PCH01                PUNCH ONE     1181   65 1336 0941
        ALO ATOM1                MINUS A       0941   15 0642 0947
        LDD DELS1    PUNCH       OVER A0       0947   69 0950 1950
DELS1   RAA  0000                ETC           0950   80 0000 0956
        RAC  0000    DELS2                     0956   88 0000 1386
DELS2   RAU P0001 A              PUNCH THE     1386   60 3599 0953
        NZU          DELS3       PRODUCT       0953   44 0957 0958
        STU  9000 A              CODES AND     0957   21 9200 1436
        LDD T0010 C              THE DELTAI    1436   69 6669 1486
        STD  9001 A                            1486   24 9201 0942
        AXA  0002                              0942   50 0002 0948
        AXC  0010    DELS2                     0948   58 0010 1386
DELS3   RAL  8005                              0958   65 8005 1536
        ALO PCH02                              1536   15 0940 0945
        LDD NEXT1    PUNCH                     0945   69 1233 1950


          PUNCH THE SOLUTION TO THE
                CURRENT MATRIX

DELX    LDD SYS+1                PUNCH THE     1564   69 0079 1586
        RSA  8001                SOLUTION      1586   81 8001 0943
        SET  9000                TO THE        0943   27 9000 0949
        LDB D0049 A              CORRECTION    0949   09 2049 0952
        RAL PCH02                MATRIX        0952   65 0940 0946
        ALO SYS+2                              0946   15 0036 0944
        LDD UNPAK    PUNCH                     0944   69 0101 1950

          CONSTANTS FOR THE PUNCH
                   ROUTINE
```

```
         PCH01    06 RV000     0002                                  1336  06 9004 0002
         PCH02    06   9000    0000                                  0940  06 9000 0000
       1
                  PAT




                  BLA  1652    1655
                  BLA  0920    0939
       1
       1             PUNCH THE CURRENT VARIABLES
       1
         VARIA    RAU LNT                        PUNCH TEMP          1392  60 0002 1657
                  LDD VAR01        EXP E         PRESSURE            1657  69 0920 1850
         VAR01    STU  9000                      AND AAY             0920  21 9000 0927
                  LDD P                                              0927  69 1112 0921
                  STD  9001                                          0921  24 9001 0928
                  LDD AAY                                            0928  69 1133 0936
                  STD  9002                                          0936  24 9002 0951
                  RAL PCH03                                          0951  65 0954 0959
                  LDD VAR02        PUNCH                             0959  69 0922 1950
         VAR02    RAA  0000                      PUNCH THE           0922  80 0000 0929
                  RAC  0000        VAR03         PRODUCT             0929  88 0000 0935
         VAR03    RAU P0001 A                    CODE AND            0935  60 3599 1653
                  NZU              VAR11         MOLES OF            1653  44 1658 1659
                  STD  9000 A                    EACH                1658  24 9200 0923
                  RAU P0002 A                    COMBUSTION          0923  60 3600 0955
                  BMI VAR07                      PRODUCT             0955  46 0924 0925
                  RAU T0008 C                                        0925  60 6667 0926
                  LDD VAR05        EXP E                             0926  69 0930 1850
         VAR05    STU  9001 A VAR09                                  0930  21 9201 0937
         VAR07    LDD T0008 C                                        0924  69 6667 0931
                  STD  9001 A VAR09                                  0931  24 9201 0937
         VAR09    AXA  0002                                          0937  50 0002 1652
                  AXC  0010        VAR03                             1652  58 0010 0935
         VAR11    RAL PCH02                                          1659  65 0940 1654
                  ALO  8005                                          1654  15 8005 0932
                  LDD NEXT2        PUNCH                             0932  69 1394 1950
       1
       1
       1             PUNCH OUT THE MATRIX
       1
         MTRIX    RAU SYS+1                                          1503  60 0079 0933
                  MPY 50                                             0933  19 0186 1656
                  RAA  8002        MTR01                             1656  80 8002 0934
         MTR01    SET  9000                                          0934  27 9000 0939
                  LDB  0037 A                                        0939  09 2037 1655
                  RAL PCH04                                          1655  65 1686 1736
                  LDD MTR03        PUNCH                             1736  69 1786 1950
         MTR03    NZA              LINK1                             1786  40 0938 1419
                  SXA  0050        MTR01                             0938  51 0050 0934
       1
       1
       1             CONSTANTS FOR THE PUNCH
       1                           ROUTINE
       1
         PCH03    06   9000    0003                                  0954  06 9000 0003
         PCH04    06   9000    0013                                  1686  06 9000 0013
                  PAT
```

E-417

```
1           PROGRAM CHANGE TO CONTROL SIZE
1           OF APPLIED CORRECTION
1
                 BLA  1652     1655
                 BLA  0920     0939
                 REG C9050     9050
1           LOAD AVAILABILITY TABLE GIVEN
1           BY CARD NUMBER 1967
1
        NEW00    LDD MAG00     SOLVE                       1691   69 0951 1698
        MAG00    LDD SYS+1                                 0951   69 0079 0932
                 RSA  8001                                 0932   81 8001 0938
                 RAB  8001                 BRING           0938   82 8001 1652
                 RAC  8001                 SOLUTION        1652   88 8001 1658
                 SET M0001                 VECTOR TO       1658   27 9000 0920
                 LDB D0049 A MAG01         CORE            0920   09 2049 1653
        MAG01    RAM M0001 B               MAKE ALL        1653   67 9400 0921
                 STL N0001 B               COMPONENTS      0921   20 9415 0928
                 NZB           MAG03       POSITIVE        0928   42 0931 0933
                 SXB  0001     MAG01                       0931   53 0001 1653
        MAG03    RAU N0001 C MAG05         FIND THE        0933   60 9615 0954
        MAG05    FSB N0000 C               LARGEST         0954   33 9614 0934
                 BMI           TOP         COMPONENT       0934   46 0937 0939
                 RAU N0000 C MAG07                         0937   60 9614 1654
        TOP      FAD N0000 C MAG07                         0939   32 9614 1654
        MAG07    SXC  0001                 IF THE          1654   59 0001 0922
                 NZC MAG05                 COMPONENT       0922   48 0954 0926
                 FSB MAXMA                 IS LARGER       0926   33 0929 0955
                 BMI           MAG09       THAN MAXMA      0955   46 0959 1659
                 LDD F0040                 STORE THE       0959   69 1149 1655
                 STD RATIO     NEW01       RATIO OF        1655   24 0923 1444
        MAG09    FAD MAXMA                 COMPONENT       1659   32 0929 1656
                 FDV MAXMA                 TO MAXMA        1656   34 0929 0930
                 STU RATIO     NEW01                       0930   21 0923 1444
        MAXMA     50  0000     0051        MAX RATIO       0929   50 0000 0051
        Q0006    NZB C0001                                 1025   42 9050 0935
                 FDV RATIO     Q0007                       0935   34 0923 1026
        NEW21    RAU D0048 B                               0512   60 4048 1657
                 FDV RATIO     NEW22                       1657   34 0923 1753
        NEW18    RAU D0049                                 1157   60 0049 0924
                 FDV RATIO     NEW19                       0924   34 0923 1803
        NEW60    RSU D0048                                 1806   61 0048 0925
·                FDV RATIO     NEW61                       0925   34 0923 1104
1
1
1           PROGRAM MAY BE MODIFIED TO
1           CONVERGE FOR ASSIGNED
1           TEMPERATURE AND PRESSURE BY
1           INCLUDING THE FOLLOWING STEPS
1
                 BLA  0910     0919
                 BLA  1650     1651
1
        MC021    RAU H0/R                                  0570   60 0004 0910
                 STL RV001     MC031                       0910   20 9005 0286
        ITERA    LDD HOLD1                                 0462   69 0915 0918
                 STD BACKS                                 0918   24 0626 0936
                 RAU SYS+2     NEW00                       0936   60 0036 1691
        HOLD1    SUP  8003     B1                          0915   11 8003 0584
        DERIV    LDD HOLD2                                 1755   69 0911 0914
                 STD BACKS•                                0914   24 0626 1686
                 RAU SYS+2     D1                          1686   60 0036 1741
        HOLD2    RAU N0003     B1                          0911   60 9017 0584
                 PAT
```

```
  1           INPUT DATA ROUTINE
  1
              BLR  0000      0036
              BLR  0050      0086
              BLR  0100      0136
              BLR  0150      0186
              BLR  0200      0236
              BLR  0250      0286
              BLR  0300      0336
              BLR  0350      0386
              BLR  0400      0436
              BLR  0450      0486
              BLR  0500      1999
              BLA  0987      0999
              BLA  1340      1349
              REG G0001      0015
              REG I0040      0045
              REG F1110      1110
              REG M9000      9000
              SYN VFPLS      0598      +FUEL VALN
              SYN VFMIN      0599      -FUEL VALN
              SYN VXPLS      0548      +OXID VALN
              SYN VXMIN      0549      -OXID VALN
              SYN O/F        0199
              SYN PCT F      0299
              SYN EQRAT      0399      EQUIVLENCE
  1                                    RATIO
              SYN CHEK       0499
              SYN BEGIN      0000
              SYN PUNCH      1950
              SYN PC         F0000
              SYN IDENT      F0039
              SYN R          F0037
              SYN TEMPO      9011
              SYN CONS1      1140
              SYN PROB       1904
  1
  1            CALCULATE NUMBER OF MOLES OF
  1            OXIDANT PER MOLE OF FUEL
  1
  1
     CHEK     RAU O/F                              0499  60 0199 0037
              NZU OXFUL                            0037  44 0091 0092
              RAU PCT F                            0092  60 0299 0087
              NZU PRCNT                            0087  44 0141 0142
              RAU EQRAT                            0142  60 0399 0137
              NZU EQUIV                            0137  44 0191 0192
              HLT  9999      9999                  0192  01 9999 9999
  1
     OXFUL    RAU O/F                              0091  60 0199 0187
              FAD 10051                            0187  32 0090 0237
              STU TEMPO                            0237  21 9011 0095
              RAU 10053                            0095  60 0048 0287
              FDV TEMPO                            0287  34 9011 0140
              STU PCT F      EQU                   0140  21 0299 0337
     EQU      RAU VXPLS                            0337  60 0548 0387
              FMP O/F                              0387  39 0199 0049
              FAD VFPLS                            0049  32 0598 0437
              STU TEMPO                            0437  21 9011 0145
              RSU VXMIN                            0145  61 0549 0487
              FMP O/F                              0487  39 0199 0099
              FSB VFMIN                            0099  33 0599 0987
              FDV TEMPO                            0987  34 9011 0190
              STU EQRAT      ATM 1                 0190  21 0399 0038
  1
     PRCNT    RAU 10053                            0141  60 0048 0088
              FSB PCT F                            0088  33 0299 0138
              FDV PCT F                            0138  34 0299 0149
              STU O/F        EQU                   0149  21 0199 0337
  1
     EQUIV    RAU VXPLS                            0191  60 0548 0188
              FMP EQRAT                            0188  39 0399 0249
              FAD VXMIN                            0249  32 0549 0238
              STU TEMPO                            0238  21 9011 0195
              RSU VFPLS                            0195  61 0598 0288
              FMP EQRAT                            0288  39 0399 0349
              FSB VFMIN                            0349  33 0599 0338
              FDV TEMPO                            0338  34 9011 0241
              STU O/F                              0241  21 0199 0388
              FAD 10051                            0388  32 0090 0438
              STU TEMPO                            0438  21 9011 0245
              RAU 10053                            0245  60 0048 0488
              FDV TEMPO                            0488  34 9011 0291
              STU PCT F      ATM 1                 0291  21 0299 0038
  1
     ATM 1    RAU O/F                              0038  60 0199 0988
              FAD 10051                            0988  32 0090 0039
              STU 1 O/F                 1 PLUS O/F 0039  21 0094 0047
              RAB  0010                            0047  82 0010 0089
              RAA  0000      ATM 2                 0089  80 0000 0295
  1
     ATM 2    RAU  0537 A               CALCULATE  0295  60 2537 0341
              FMP O/F                   ATOMS PER  0341  39 0199 0449
              FAD  0587 A               GRAM OF    0449  32 2587 0139
              FDV 1 O/F                 PROPELLANT 0139  34 0094 0144
              STU G0005 A                          0144  21 2005 0189
              SXB  0001                            0189  53 0001 0345
```

```
104          NZB          ATM 3                   0345   42 0098 0999
105          AXA   0001   ATM 2                   0098   50 0001 0295
106 1
107   ATM 3  RAU   0547               CALCULATE   0999   60 0547 0239
108          FMP  O/F                 ENTHALPY    0239   39 0199 1349
109          FAD   0597               OVER R      1349   32 0597 0289
110          FDV  1 O/F               PER GRAM    0289   34 0094 0194
111          FDV  R                   OF          0194   34 1146 0046
112          STU  G0004   DIST2       PROPELLANT  0046   21 0004 0339
113 1
114 1             AN EIGHT IN POSITION TWO OF
115 1             CONSOLE CAUSES PUNCHING OF
116 1             A0  B0    ETC
117 1
118   DIST2  RAU   8000                           0339   60 8000 0097
119          BD2          IDEN                    0097   92 0389 0439
120          RAL  SPEC1                           0389   65 0242 0147
121          LDD          PUNCH                   0147   69 0489 1950
122          RAL  SPEC2                           0489   65 0292 0197
123          LDD  IDEN    PUNCH                   0197   69 0439 1950
124 1
125   IDEN   RAU  EQRAT               EQUIV RATO  0439   60 0399 0989
126          STD  M0006                           0989   24 9005 0395
127          UFA  55  I                           0395   02 0148 0240
128          SRT   0002                           0240   30 0002 0247
129          SLO   8002                           0247   16 8002 0290
130          SLT   0006                           0290   35 0006 0340
131          AUP  F0039                           0340   10 1148 0390
132          STU  M0011               IDNTFICATN  0390   21 9010 0297
133          SLT   0008                           0297   35 0008 0440
134          NZU          IDEN2                   0440   44 0093 0244
135          RAU  M0011                           0093   60 9010 0490
136          STU  F0039   IDEN3                   0490   21 1148 0990
137   IDEN2  RAU  F0000                           0244   60 1109 1340
138          SRT   0001                           1340   30 0001 0347
139          SLO   8002                           0347   16 8002 0391
140          STD  TEMPO                           0391   24 9011 0397
141          SRT   0008                           0397   30 0008 0441
142          SLO   8002                           0441   16 8002 0491
143          ALO  TEMPO                           0491   15 9011 0991
144          SLT   0001                           0991   35 0001 0447
145          AUP  M0011                           0447   10 9010 1341
146          STU  M0011                           1341   21 9010 0342
147          STD  F0039   IDEN3                   0342   24 1148 0990
148   IDEN3  RAU  F0000               CONVERT     0990   60 1109 0392
149          STD  M0009                           0392   24 9008 0198
150          FDV  CONS1               CHAM PRESS  0198   34 1140 0442
151          STU  F0000               TO ATMOSPH  0442   21 1109 0492
152          LDD  O/F                 OXID/FUEL   0492   69 0199 0992
153          STD  M0007               WT RATIO    0992   24 9006 0248
154          LDD  PCT F               PERCENT     0248   69 0299 1342
155          STD  M0008               FUEL BY WT  1342   24 9007 0193
158          RAU  G0004               ENTHALPY    0193   60 0004 0243
159          FMP  R                               0243   39 1146 0096
160          STU  M0010                           0096   21 9009 0293
161          RAL  SPEC3                           0293   65 0146 0343
162          STU  PROB                CLEAR PROB  0343   21 1904 0393
163          LDD          PUNCH                   0393   69 0196 1950
164          RAA   0050   IDEN1                   0196   80 0050 0443
165   IDEN1  SET   9005                           0443   27 9005 0348
166          LBB   0537 A                         0348   08 2537 0493
167          RAL  SPEC3                           0493   65 0146 0993
168          LDD          PUNCH                   0993   69 0246 1950
169          SET   9005                           0246   27 9005 1343
170          LBB   0542 A                         1343   08 2542 0445
171          RAL  SPEC3                           0445   65 0146 0294
172          LDD          PUNCH                   0294   69 0497 1950
173          SET   9005                           0497   27 9005 0344
174          LBB   0547 A                         0344   08 2547 0394
175          RAL  SPEC3                           0394   65 0146 0444
176          STU  M0009               CLEAR       0444   21 9008 0494
177          STD  M0010               CLEAR       0494   24 9009 0994
178          LDD          PUNCH                   0994   69 0997 1950
179          NZA          BEGIN                   0997   40 1344 0000
180          RAA   0000   IDEN1                   1344   80 0000 0443
181 1
182 1              CONSTANTS
183 1
184   10051   10  0000     0051                   0090   10 0000 0051
185   10053   10  0000     0053                   0048   10 0000 0053
186   55  I   00  0000     0055                   0148   00 0000 0055
187   R       19  8718     0051                   1146   19 8718 0051
188   CONS1   14  6960     0652                   1140   14 6960 0652
189   SPEC1   00 G0005     0010                   0242   00 0005 0010
190   SPEC2   00 G0004     0001                   0292   00 0004 0001
191   SPEC3   00 M0006     0006                   0146   00 9005 0006
192   SPEC4   00  9005     0006                   0495   00 9005 0006
193          PAT
```

```
 1           ROCKET PACKAGE EXCERPT FOR
 1           FOR GENERAL ROCKET PERFORMANCE
 1
 1
            SYN PROB      1904
            SYN EXP E     1850
            SYN SORT      1900
            SYN PUNCH     1950
            SYN LINK      1855
            SYN CARDN     1852
            SYN J000N     1961
            REG X1883     1899
            REG C9050     9050
            REG R1951     1960        READ BAND
            REG J1962     1967
            REG K1968     1973
            REG P1977     1986
            REG S1987     1995
            BLR  0000     1832
 1
 1
 1           EXPONENTIAL
 1
            REG X1883     1899        17 WORDS
 1
    EXP E   STD LINK                  EXPO     7   1850  24 1855 1858
            FMP EX1       EXB1        NENTIAL  7    858  39 1861 1911
    EX1      43  4294     4850        ENTRY    7    861  43 4294 4850
    EXB1    SET  9043                               911  27 9043 1866
            SET  9043                         72    866  27 9043 1871
            LDB X0001                         72   1871  09 1883 1836
            STU  9040                         72   1836  21 9040 1843
            FSB  9043                              1843  33 9043 1873
            BMI           EX92                     1873 .46 1876 1877
            FAD  9043                              1876  32 9043 1905
            NZU           EXB61                    1905  44 1859 1860
            FAD  9043                              1859  32 9043 1839
            BMI EXB3                               1839  46 1842 1943
            RAU  9040                 EXPONENT72   1943  60 9040 1851
            BMI           EXB4        MINUS   72    851  46 1854 1856
            LDD EX2       EXB5        YES     72    854  69 1857 1910
    X0001    40  0000     0052                72   1883  40 0000 0052
    EXB2    LDD  8666     EXB3        ALARM   73    877  69 8666 1842
    EXB3    RAU  8002     LINK        ZERO          842  60 8002 1855
    EXB61   RAU  9040                               860  60 9040 1867
            FDV EX1                                 867  34 1861 1862
            FAD  9058     LINK                      862  32 9058 1855
    EXB4    RSU  8003                 NO      73    856  61 8003 1863
            STU  9040                         73    863  21 9040 1921
            LDD EX3       EXB5                73   1921  69 1874 1910
    EXB5    STD  9041                 FIND    74   1910  24 9041 1916
            FAD HALF                               1916  32 1869 1845
            UFA EXP58     9049        LAMBDA  74   1C45  02 1848 9049
    X0007   STU  9042                         74   1689  21 9042 1847
            FAD  8002     9050                74   1847  32 8002 9050
    X0008   FAM  9040                         74   1890  37 9040 1919
            STU  9040                         74    919  21 9040 1927
            LDD  8005                 SAVE    74   1927  69 8005 1833
            STD  9043                 A       74   1833  24 9043 1939
            RSA  0007                         74    939  81 0007 1945
            RAU  8002     9059                74    945  60 8002 9059
    X0017   FMP  9040     9044                74    899  39 9040 9044
    X0002   FAD  9258     9045                74    884  32 9258 9045
    X0003   NZA  9046     9047                      885  40 9046 9047
    X0004   AXA  0001     9059                      886  50 0001 9059
    X0005   FMP  8003     9048                74    887  39 8003 9048
    X0006   STU  9040     EXB6                74    888  21 9040 1846
    EXB6    RAA  9043                         75    846  80 9043 1906
            RSU  9042                         75    906  61 9042 1913
            SRT  0002                         75    913  30 0002 1870
            RAU  8003                               870  60 8003 1878
            AUP  9040                         75    878  10 9040 1835
            STU  9040     9041                75   1835  21 9040 9041
    EX2     RAU  9058                         75    857  60 9058 1865
            FDV  9040     LINK                      865  34 9040 1855
    EX3     RAU  8001     LINK                      874  60 8001 1855
    HALF     50  0000     0050                      869  50 0000 0050
    X0009    93  2642     6747                76   1891  93 2642 6747
    X0010    25  5491     8048                76   1892  25 5491 8048
    X0011    17  4211     2049                76    893  17 4211 2049
    X0012    72  9517     3749                76    894  72 9517 3749
    X0013    25  4393     5750                76    895  25 4393 5750
    X0014    66  2730     8850                76    896  66 2730 8850
    X0015    11  5129     2851                76    897  11 5129 2851
    X0016    10  0000     0051                76    898  10 0000 0051
    EXP58    00  0000     0058                     1848  00 0000 0058
 1
 1
 1           SQUARE ROOT ROUTINE
 1
            REG C9050     9050
            REG S1987     1995        NINE WORDS
 1
    SQRT    STD LINK                               1900  24 1855 1908
            BMI STOP                               1908  46 1912 1864
            NZE           LINK                     1864  45 1868 1855
            STU C0000                              1868  21 9049 1875
            SET C0001                              1875  27 9050 1880
```

```
                LBR S0001                                 1880  08 1987 1840
                SRT  0002                 CUTOFF EXP      1840  30 0002 1947
                RAU  8002                                 1947  60 8002 1907
                MPY 00050                 HALF EXP        1907  19 1914 1834
                SUP  8002                 SAVE DEC        1834  11 8002 1844
                AUP 1ST E                                 1844  10 1997 1901
                ALO  8002    C0001                        1901  15 8002 9050
        S0001   STU C0010    C0002                        1987  21 9059 9051
        S0002   RAU C0000    C0003        GET N           1988  60 9049 9052
        S0003   FDV C0010    C0004        DIV BY R        1989  34 9059 9053
        S0004   FAD C0010    C0005        ADD R TO Q      1990  32 9059 9054
        S0005   FMP C0009    C0006        DIV BY 2        1991  39 9058 9055
        S0006   SUP C0010    C0007        TEST FOR        1992  11 9059 9056
        S0007   NZE C0008                  END            1993  45 9057 1948
                RAU C0010    LINK                         1948  60 9059 1855
        S0008   AUP C0010    C0001                        1994  10 9059 9050
        S0009    50  0000     0050        ONE HALF        1995  50 0000 0050
    1
           50    00  0000     0050                        1914  00 0000 0050
        1ST E    70  0000     0025                        1997  70 0000 0025
        STOP     99  9999     9999        SQRT NEG X      1912  99 9999 9999
    1
    1
    1              PUNCH BELL CARDS
    1
                REG C9050     9050
                SYN J000N     1961
                REG J1962     1967        SIX WORDS
                REG K1968     1973        SIX WORDS
                REG P1977     1986        PUNCH BAND
    1
        PUNCH   STD LINK                  START HERE      1950  24 1855 1909
                LDD  8003                                 1909  69 8003 1917
                SDA C0005                 1ST WORD        1917  22 9054 1924
                SLT  0004                                 1924  35 0004 1935
                SDA C0006                 NUMBER WDS      1935  22 9055 1942
                SRT  0002                                 1942  30 0002 1849
                RAU  8003                                 1849  60 8003 1915
                SRT  0002                                 1915  30 0002 1872
                SET C0007                                 1872  27 9056 1928
                LDD WDCT6                                 1928  69 1881 1934
                STD P0009                                 1934  24 1985 1838
                LDD PROB                                  1838  69 1904 1918
                STD P0008                                 1918  24 1984 1837
                LDD C0005    PCH3                         1837  69 9054 1944
        PCH3    STD P0007                                 1944  24 1983 1936
                ALO CARDN                                 1936  15 1852 1920
                ALO ONE D                                 1920  15 1923 1879
                SDA CARDN                                 1879  22 1852 1922
                STL P0010    NZERO                        1922  20 1986 1940
        NZERO   RAU C0006                 IS NO OF        1940  60 9055 1998
                SUP WDCT6                 WORDS LESS      1998  11 1881 1937
                BMI LESS6    PCH4                         1937  46 1841 1941
        PCH4    STU C0006                                 1941  21 9055 1949
                RAU P0009                                 1949  60 1985 1946
                SRT  0004                                 1946  30 0004 1974
              . AUP XMOVE                 SET TO MOV      1974  10 1929 1933
                ALO XLOC                   N WORDS        1933  15 1938 1996
                ALO C0005    MOVEW                        1996  15 9054 1853
        MOVEW   AUP 09999     8002                        1853  10 1925 8002
         8002   LDD LOC       8003                        8002  69 1999 8003
         8003   STD P0007    J000N                        8003  24 1983 1961
        J0000   RAU C0006    PCH2                         1961  60 9055 1975
        J0001   RAU C0006    PCH2                         1962  60 9055 1975
        J0002   ALO ONE D    MOVEW                        1963  15 1923 1853
        J0003   ALO ONE D    MOVEW                        1964  15 1923 1853
        J0004   ALO ONE D    MOVEW                        1965  15 1923 1853
        J0005   ALO ONE D    MOVEW                        1966  15 1923 1853
        J0006   ALO ONE D    MOVEW                        1967  15 1923 1853
        PCH2    PCH P0001                                 1975  71 1977 1930
                NZE          LINK                         1930  45 1902 1855
                RAU P0007                                 1902  60 1983 1903
                AUP P0009                                 1903  10 1985 1926
                STU C0005    PCH3                         1926  21 9054 1944
    1
        LESS6   RAL C0006                                 1841  65 9055 1976
                STD P0009                                 1976  24 1985 1931
                SRT  0004                 CLEAR ZERO      1931  30 0004 1882
                ALO XCLER     8002                        1882  15 1932 8002
         8002    00  0000    K0001                        8002  00 0000 1968
        K0001   STU P0001    K0002                        1968  21 1977 1969
        K0002   STU P0002    K0003                        1969  21 1978 1970
        K0003   STU P0003    K0004                        1970  21 1979 1971
        K0004   STU P0004    K0005                        1971  21 1980 1972
        K0005   STU P0005    K0006                        1972  21 1981 1973
        K0006   STU P0006    PCH4                         1973  21 1982 1941
    1
        XCLER    00  0000    K0001                        1932  00 0000 1968
        WDCT6    00  0006     0000                        1881  00 0006 0000
         9999    00  0000     9999                        1925  00 0000 9999
        XLOC    LDD  0000     8003                        1938  69 0000 8003
        XMOVE   STD P0000    J0001                        1929  24 1976 1962
        CARDN    00  0000     0000                        1852  00 0000 0000
        ONE D    00  0001     0000                        1923  00 0001 0000
                PLA  0000     1832
                PAT
```

E-417

APPENDIX G

FROZEN-COMPOSITION PROGRAM

```
1          GENERAL FROZEN COMPOSITION
1            PERFORMANCE PROGRAM
1
1
1
1          THIS PROGRAM ASSUMES THAT
1          LN OF COMBUSTION COMPOSITION
1          TEMPERATURE PRESSURE ENTHALPY
1          MOLECULAR WEIGHT FACTOR A AND
1          ALL NECESSARY THERMODYNAMIC
1          COEFFICIENTS ARE ALREADY IN
1          STORAGE
1
1
         SYN LNX       1700
         SYN EXP E     1850
         SYN SQRT      1900
         SYN PUNCH     1950
         SYN PCPCT     0017
         SYN COMEX     0061
         SYN START     0500
         SYN TEMP1     1048
         SYN TEMP2     1049
         SYN PC        1109
         SYN RDB       1193
         SYN LINK      1855
         SYN CARDN     1852
         SYN PROB      1904
         REG A1347     1349
         REG B1247     1249
         REG C9050     9050
         REG F1110     1149
         REG G0001     0015
         REG M9000     9000
         REG P1599     1659
         REG R1075     1099
         REG T0660     0959
         BLR  1832     1999
         EQU PCP      F0001
         EQU TEE      F0002
         EQU P        F0003
         EQU H        F0004
         EQU I        F0005
         EQU M        F0006
         EQU CF       F0007
         EQU EPSIL    F0008
         EQU MACH     F0009
         EQU I VAC    F0010
         EQU CP       F0011
         EQU GAMMA    F0012
         EQU S        F0015
         EQU CSTAR    F0020
         EQU AW       F0021
         EQU HSTR     F0023
         EQU AAY      F0024
         EQU HC       F0025
         EQU PLNP     F0026
         EQU SC       F0027
         EQU AWT      F0028
         EQU RA       F0029
         EQU RM       F0030
         EQU CONS1    F0031
         EQU CONS2    F0032
         EQU CONS3    F0033
         EQU CONS4    F0034
         EQU CONS5    F0035
         EQU R        F0037
         EQU GC       F0038
         EQU IDENT    F0039
         EQU ONE      F0040
         EQU LNT      G0002
         EQU PO       G0015
         EQU S CPR     1347
         EQU S HRT     1348
         EQU S  SR     1349
         EQU CODE      9000
         EQU T         9003
         EQU A         9021
         EQU B         9022
         EQU C         9023
         EQU D         9024
         EQU E         9025
         EQU F         9026
         EQU NI        9027
         EQU TWO       9028
         EQU THREE     9029
         EQU FOUR      9030
         EQU TEM 1     9049
         EQU BASIC     9050
         EQU TEMPO     9059
```

E-417

```
1
   START   RSM IDENT                                0500  68 1148 0053
           STL IDENT    X1          REVRS SIGN      0053  20 1148 0051
1
1            CONVERT LNNI TO NI
   X1      RAA  0000                                0051  80 0000 0057
           RAC  0000    X2                          0057  88 0000 0063
   X2      RAL P0001 A                              0063  65 3599 0103
           NZE          X5                          0103  45 0056 0107
           RAU P0002 A                              0056  60 3600 0055
           BMI X3       X4                          0055  46 0058 0059
   X4      RAU T0008 C                              0059  60 6667 0021
           LDD          EXP E                       0021  69 0024 1850
           STU T0008 C X3                           0024  21 6667 0058
   X3      AXA  0002                                0058  50 0002 0064
           AXC  0010    X2                          0064  58 0010 0063
1            CLEAR F REGION
   X5      SET M0004                                0107  27 9003 0062
           LDB F0004                                0062  09 1113 0016
           RSA  0026                                0016  81 0026 0022
           RAU  8003    X6                          0022  60 8003 0029
   X6      STL F0030 A                              0029  20 3139 0042
           NZA          X7                          0042  40 0045 0046
           AXA  0001    X6                          0045  50 0001 0029
1
1            SAVE TEE HC M AND AAY
1              OF COMBUSTION
   X7      LDD M0024                 AAY            0046  69 9023 0052
           STD F0024                                0052  24 1133 0036
           LDD M0025                 HC             0036  69 9024 0092
           STD F0025                                0092  24 1134 0037
           LDD TEE                                  0037  69 1111 0114
           STD T                                    0114  24 9003 0020
           LDD M0006                 M              0020  69 9005 0026
           STD F0006                                0026  24 1115 0018
1
1            COMPUTE R/AAY AND STORE IN RA
           RAU R                                    0018  60 1146 0101
           FDV AAY                                  0101  34 1133 0033
           STU RA                                   0033  21 1138 0041
1
1            COMPUTE R/M AND STORE IN RM
           RAU R                                    0041  60 1146 0151
           FDV M                                    0151  34 1115 0065
           STU RM                                   0065  21 1139 0142
           RAU  8003                                0142  60 8003 0049
           STL COMEX                                0049  20 0061 0164
1
1            FOR COMBUSTION OUT IS Z1
           LDD Z1                                   0164  69 0067 0070
           STD OUT      Y1                          0070  24 0023 0076
1
1            LOOP TO COMPUTE
1                 SUM NI CPR
1                 SUM NI HRT
1                 SUM NI  SR
1
1            LOOP IS COMPLETED WHEN ZERO
1              APPEARS IN P REGION
1              THEN GO TO OUT
1            OUT FOR COMB IS Z1
1            OUT FOR THROAT AND EXIT IS
1              FROZN
1
   Y1      RAU  8003                                0076  60 8003 0083
           STL S CPR                CLER S CPR      0083  20 1347 0000
           STL S HRT                CLER S HRT      0000  20 1348 0201
           STL S  SR                CLER S  SR      0201  20 1349 0102
           RAA  0000                                0102  80 0000 0108
           RAC  0000    Y2                          0108  88 0000 0214
   Y2      RAL P0001 A                              0214  65 3599 0153
           NZE          OUT                         0153  45 0106 0023
           STL CODE     THERM                       0106  20 9000 0264
   THERM   SET  9020                                0264  27 9020 0019
           LBB T0001 C                              0019  08 6660 0113
           RAU  9020                                0113  60 9020 0071
           SUP CODE                                 0071  11 9000 0079
           NZU          TH009                       0079  44 0133 0034
           HLT  0000     8866                       0133  01 0000 8866
```

```
       TH009   SET TWO                       0034  27 9028 0039
               LDB B0001                     0039  09 1247 0050
               RAU D                         0050  60 9024 0157
               FMP T                         0157  39 9003 0060
               FAD C                         0060  32 9023 0089
               FMP T                         0089  39 9003 0192
               FAD B                         0192  32 9022 0121
               FMP T                         0121  39 9003 0074
               FAD A                         0074  32 9021 0203
               FMP NI                        0203  39 9027 0156
               FAD S CPR                     0156  32 1347 0073
               STU S CPR                     0073  21 1347 0100
               RAU D                         0100  60 9024 0207
               FDV FOUR                      0207  34 9030 0110
               FMP T                         0110  39 9003 0163
               STU TEMPO                     0163  21 9059 0171
               RAU C                         0171  60 9023 0129
               FDV THREE                     0129  34 9029 0032
               FAD TEMPO                     0032  32 9059 0111
               FMP T                         0111  39 9003 0314
               STU TEMPO                     0314  21 9059 0221
               RAU B                         0221  60 9022 0179
               FDV TWO                       0179  34 9028 0082
               FAD TEMPO                     0082  32 9059 0161
               FMP T                         0161  39 9003 0364
               STU TEMPO                     0364  21 9059 0271
               RAU E                         0271  60 9025 0229
               FDV T                         0229  34 9003 0132
               FAD TEMPO                     0132  32 9059 0211
               FAD A                         0211  32 9021 0091
               FMP NI                        0091  39 9027 0044
               FAD S HRT                     0044  32 1348 0025
               STU S HRT                     0025  21 1348 0251
               RAU D                         0251  60 9024 0109
               FDV THREE                     0109  34 9029 0112
               FMP T                         0112  39 9003 0115
               STU TEMPO                     0115  21 9059 0123
               RAU C                         0123  60 9023 0031
               FDV TWO                       0031  34 9028 0084
               FAD TEMPO                     0084  32 9059 0213
               FMP T                         0213  39 9003 0066
               FAD B                         0066  32 9022 0095
               FMP T                         0095  39 9003 0048
               STU TEMPO                     0048  21 9059 0105
               RAU A                         0105  60 9021 0263
               FMP LNT                       0263  39 0002 0152
               FAD TEMPO                     0152  32 9059 0081
               FAD F                         0081  32 9026 0261
               FMP NI                        0261  39 9027 0414
               FAD S  SR                     0414  32 1349 0075
               STU S  SR                     0075  21 1349 0202
               AXA  0002                     0202  50 0002 0158
               AXC  0010      Y2             0158  58 0010 0214
    1
    1             TEST FOR CONVERGENCE
    1             IS DEL S ZERO
    1
    1             YES MEANS CONVERGENCE
    1               GO TO BTHER
    1
    1             NO MEANS NO CONVERGENCE
    1               CORRECT T AND THEN GO TC Y1
    1
       FROZN   RAU PLNP                      0150  60 1135 0139
               FAD S  SR                     0139  32 1349 0125
               STU TEM 1                     0125  21 9049 0183
               FDV SC                        0183  34 1136 0086
               FSB EINSS                     0086  33 0189 0165
               NZU            BTHER          0165  44 0069 0120
               RSU TEM 1                     0069  61 9049 0027
               FAD SC                        0027  32 1136 0313
               FDV S CPR                     0313  34 1347 0047
               FAD LNT                       0047  32 0002 0279
               STU LNT                       0279  21 0002 0155
               LDD            EXP E          0155  69 0208 1850
               STU T                         0208  21 9003 0215
               LDD FROZN                     0215  69 0150 0253
               STD OUT        Y1             0253  24 0023 0076
```

E-417

```
1
1           AFTER CONVERGENCE TEST IF
1           CORRECT TDATA IS IN STORAGE
1           YES GO TO FIX
1           NO GO TO TDATA
1
   BTHER   SET  9050                          0120  27 9050 0175
           LBB TEMP1                          0175  08 1048 0301
           RAU  9051                          0301  60 9051 0159
           FSB T                              0159  33 9003 0239
           BMI TDATA                          0239  46 0242 0043
           RAU T                              0043  60 9003 0351
           FSB  9050                          0351  33 9050 0131
           BMI TDATA    FIX                   0131  46 0242 0035
1
1           READ THERMAL DATA
1           WHEN CORRECT TDATA IS FOUND
1              GO TO Y1
   TDATA   RAA  0000                          0242  80 0000 0098
           RAC  0000    TD001                 0098  88 0000 0054
   TD001   RCD BASIC    BELL                  0054  70 9050 0104
   BASIC   RAL  9051    RDB                   9050  65 9051 1193
   RDB     SLT  0004                          1193  35 0004 0303
           STU  9051                          0303  21 9051 0311
           SUP P0001 A                        0311  11 3599 0353
           NZU TD005                          0353  44 0257 0258
           LDD T0008 C                        0258  69 6667 0170
           STD  9058                          0170  24 9058 0126
           SET  9051                          0126  27 9051 0181
           SBB T0001 C                        0181  28 6660 0363
           AXA  0002                          0363  50 0002 0119
           AXC  0010    TD001                 0119  58 0010 0054
   TD005   HLT  0000     7766                 0257  01 0000 7766
   BELL    RAU  9051                          0104  60 9051 0361
           FSB T                              0361  33 9003 0141
           BMI TDATA                          0141  46 0242 0145
           RAU T                              0145  60 9003 0403
           FSB  9050                          0403  33 9050 0233
           BMI TDATA                          0233  46 0242 0087
           SET  9050                          0087  27 9050 0292
           SBB TEMP1    Y1                    0292  28 1048 0076
1
   FIX     LDD T                              0035  69 9003 0191
           STD TEE                            0191  24 1111 0464
           LDD PO                             0464  69 0015 0068
           STD P        Z1                    0068  24 1112 0067
1
           EQU PCP      M0001
           EQU TEE      M0002
           EQU P        M0003
           EQU H        M0004
           EQU I        M0005
           EQU M        M0006
           EQU CF       M0007
           EQU EPSIL    M0008
           EQU MACH     M0009
           EQU I VAC    M0010
           EQU CP       M0011
           EQU GAMMA    M0012
           EQU S        M0015
           EQU CSTAR    M0020
           EQU AW       M0021
           EQU HSTR     M0023
           EQU AAY      M0024
           EQU HC       M0025
           EQU PLNP     M0026
           EQU SC       M0027
           EQU AWT      M0028
           EQU RA       M0029
           EQU RM       M0030
           EQU CONS1    M0031
           EQU CONS2    M0032
           EQU CONS3    M0033
           EQU CONS4    M0034
           EQU CONS5    M0035
           EQU R        M0037
           EQU GC       M0038
           EQU IDENT    M0039
           EQU ONE      M0040
1
```

E-417

CA-13

```
    1
    1            CALCULATE ROCKET PERFORMANCE
    1              PARAMETERS
    1
       Z1      SET M0001                              0067  27 9000 0072
               LDB F0001                              0072  09 1110 0413
    1
    1            COMPUTE CP
               RAU S CPR                              0413  60 1347 0401
               FMP RA                                 0401  39 9028 0154
               STU CP                                 0154  21 9010 0411
    1
    1            COMPUTE GAMMA
               FSB RM                                 0411  33 9029 0241
               STU TEM 1                              0241  21 9049 0099
               RAU CP                                 0099  60 9010 0307
               FDV TEM 1                              0307  34 9049 0160
               STU GAMMA                              0160  21 9011 0117
    1
    1            COMPUTE ENTHALPY
               RAU S HRT                              0117  60 1348 0453
               FMP TEE                                0453  39 9001 0206
               FMP RA                                 0206  39 9028 0209
               STU H                                  0209  21 9003 0167
    1
    1            TEST COMEX
    1              ZERO MEANS COMBUSTION
    1              NONZERO MEANS THROAT OR EXIT
    1
               RAU COMEX                              0167  60 0061 0265
               NZU TOREX                              0265  44 0169 0220
    1
    1            COMPUTE PSEUDO ENTROPY FOR
    1              COMBUSTION
               RAU S  SR                              0220  60 1349 0503
               STU SC                                 0503  21 9026 0461
               FMP RA                                 0461  39 9028 0514
               STU S                                  0514  21 9014 0321
               RSU UNITY             SET COMEX        0321  61 0124 0329
               STU COMEX    PNCH     FOR THROAT       0329  21 0061 0564
    1
    1            COMPUTE PSEUDO ENTROPY FOR
    1              THROAT AND EXIT
       TOREX   RAU S  SR                              0169  60 1349 0553
               FAD PLNP                               0553  32 9025 0283
               FMP RA                                 0283  39 9028 0136
               STU S                                  0136  21 9014 0093
               RAU COMEX                              0093  60 0061 0315
               BMI THROT    EXIT                      0315  46 0118 0219
               EQU TWO      B0001
    1
    1            CONVERGENCE TEST FOR THROAT
    1            IS HC EQUAL TO HSTR
    1            IF YES GO TO CSTR1
    1            IF NO THEN CORRECT P AND GO
    1            TO FROZN
    1
       THROT   RAU TEE                                0118  60 9001 0225
               FDV M                                  0225  34 9005 0028
               FMP R                                  0028  39 9036 0231
               FDV TWO                                0231  34 1247 0097
               STU RT/2M                              0097  21 0252 0205
               FMP GAMMA                              0205  39 9011 0308
               FAD H                                  0308  32 9003 0137
               STU HSTR                               0137  21 9022 0195
               FDV HC                                 0195  34 9024 0148
               FSB EINS                               0148  33 0451 0077
               NZU          CSTR1                     0077  44 0281 0182
               RAU GAMMA                              0281  60 9011 0289
               FAD ONE                                0289  32 9039 0269
               FMP RT/2M                              0269  39 0252 0302
               STU TEMPO                              0302  21 9059 0259
               RAU HC                                 0259  60 9024 0217
               FSB HSTR                               0217  33 9022 0147
               FDV TEMPO                              0147  34 9059 0200
               FAD ONE                                0200  32 9039 0379
               FMP P                                  0379  39 9002 0232
               STU PO                                 0232  21 0015 0168
               RAU PC                                 0168  60 1109 0463
               FDV PO                                 0463  34 0015 0365
               STU R0002                              0365  21 1076 0429
               STU F0001                              0429  21 1110 0513
               LDD          LNX                       0513  69 0116 1700
               FMP PC                                 0116  39 1109 0309
               STU F0026    FROZN                     0309  21 1135 0150
       CSTR1   LDD CSTR2    SEVRL                     0182  69 0085 0038
    1
```

E-417

```
 1              STORE A/W FOR THROAT
   CSTR2    RAU AW                                         0085  60 9020 0143
            STD AWT                                        0143  24 9027 0149
 1
 1              COMPUTE CSTAR
            FMP PC                                         0149  39 1109 0359
            FMP GC                                         0359  39 9037 0162
            FMP CONS1                                      0162  39 9030 0415
            STU CSTAR                                      0415  21 9019 0173
            LDD UNITY                        SET COMEX     0173  69 0124 0127
            STD COMEX    REMAN               FOR EXIT      0127  24 0061 0614
 1
   EXIT     LDD REMAN    SEVRL                             0219  69 0614 0038
 1
 1              COMPUTE THRUST COEFFICIENT CF
   REMAN    RAU I                                          0614  60 9004 0371
            FMP GC                                         0371  39 9037 0174
            FDV CSTAR                                      0174  34 9019 0177
            STU CF                                         0177  21 9006 0135
 1
 1              COMPUTE AREA RATIO
            RAU AW                                         0135  60 9020 0193
            FDV AWT                                        0193  34 9027 0096
            STU EPSIL                                      0096  21 9007 0603
 1
 1              COMPUTE SP IMP IN VACUUM IVAC
            RAU AW                                         0603  60 9020 0511
            FMP P                                          0511  39 9002 0964
            FMP CONS1                                      0964  39 9030 0267
            FAD I                                          0267  32 9004 0197
            STU I VAC                                      0197  21 9009 0255
 1
 1              COMPUTE MACH NUMBER
            RAU GAMMA                                      0255  60 9011 0563
            FMP TEE                                        0563  39 9001 0166
            FMP CONS2                                      0166  39 9031 0319
            FDV M                                          0319  34 9005 0122
            LDD MACH1    SQRT                              0122  69 0275 1900
   MACH1    STU TEMPO                                      0275  21 9059 0333
            RAU I                                          0333  60 9004 0291
            FDV TEMPO                                      0291  34 9059 0094
            STU MACH     PNCH                              0094  21 9008 0564
   SEVRL    STD LINK1                                      0038  24 0341 0144
 1
 1              COMPUTE SPECIFIC IMPULSE I
            RAU HC                                         0144  60 9024 0501
            FSB H                                          0501  33 9003 0331
            FDV CONS3                                      0331  34 9032 0134
            LDD IMPUL    SQRT                              0134  69 0187 1900
   IMPUL    FMP CONS4                                      0187  39 9033 0040
            STU I                                          0040  21 9004 0247
 1
 1              COMPUTE A/W
            RAU TEE                                        0247  60 9001 0305
            FDV P                                          0305  34 9002 0358
            FDV M                                          0358  34 9005 0561
            FDV I                                          0561  34 9004 1014
            FMP CONS2                                      1014  39 9031 0317
            FDV CONS1                                      0317  34 9030 0270
            STU AW       LINK1                             0270  21 9020 0341
 1
 1              PUNCH RESULTS THEN GO TO PCP 1
   PNCH     RAU  8003                                      0564  60 8003 0421
            STL CARDN                                      0421  20 1852 0355
            SET M0001                                      0355  27 9000 0210
            STB F0001                                      0210  29 1110 0613
            RSA  0005                                      0613  81 0005 0369
            RAB  0004                                      0369  82 0004 0325
            LDD IDENT                                      0325  69 9038 0381
            STD M0011    PNCH1                             0381  24 9010 0237
   PNCH1    NZB          PCP 1                             0237  42 0090 0391
            SXB  0001                                      0090  53 0001 0146
            AXA  0005                                      0146  50 0005 0352
            SET M0006                                      0352  27 9005 0357
            LBB F0001 A                                    0357  08 3110 0963
            NZA SPEC                                       0963  40 0216 0367
            RAL SPEC1    PNCH2                             0367  65 0320 0375
   PNCH2    LDD PNCH1    PUNCH                             0375  69 0237 1950
   SPEC     RAL SPEC2    PNCH2                             0216  65 0419 0375
   COMP1    LDD FROZN    PCP 1                             0250  69 0150 0391
 1
```

E-417

```
1
         EQU PCP        F0001
         EQU TEE        F0002
         EQU P          F0003
         EQU H          F0004
         EQU I          F0005
         EQU M          F0006
         EQU CF         F0007
         EQU EPSIL      F0008
         EQU MACH       F0009
         EQU I VAC      F0010
         EQU CP         F0011
         EQU GAMMA      F0012
         EQU S          F0015
         EQU CSTAR      F0020
         EQU AW         F0021
         EQU HSTR       F0023
         EQU AAY        F0024
         EQU HC         F0025
         EQU PLNP       F0026
         EQU SC         F0027
         EQU AWT        F0028
         EQU RA         F0029
         EQU RM         F0030
         EQU CONS1      F0031
         EQU CONS2      F0032
         EQU CONS3      F0033
         EQU CONS4      F0034
         EQU CONS5      F0035
         EQU R          F0037
         EQU GC         F0038
         EQU IDENT      F0039
         EQU ONE        F0040
1
1           ADVANCE PRESSURE RATIO PCP
1           COMPUTE PC LN PC/PE
1           AND STORE IN PLNP
1
  PCP 1  RAL PCPCT                                   0391  65 0017 0471
         ALO UNITY                                   0471  15 0124 0479
         STL PCPCT                                   0479  20 0017 0370
         RAA  8001                                   0370  80 8001 0176
         SLT  0004                                   0176  35 0004 0287
         STL PROB                                    0287  20 1904 0407
         RAU R0000 A                                 0407  60 3074 0529
         STU PCP                                     0529  21 1110 1013
         NZU              9999       FINISHED        1013  44 0417 9999
         LDD             LNX                         0417  69 0420 1700
         FMP PC                                      0420  39 1109 0409
         STU PLNP                                    0409  21 1135 0088
         RAU PC                                      0088  60 1109 1063
         FDV PCP                                     1063  34 1110 0260
         STU PO          FROZN                       0260  21 0015 0150
1
1           CONSTANTS FOR PROGRAM
  ONE     10  0000    0051                           1149  10 0000 0051
  B0001   20  0000    0051                           1247  20 0000 0051
  B0002   30  0000    0051                           1248  30 0000 0051
  B0003   40  0000    0051                           1249  40 0000 0051
  CONS1   14  6960    0652                           1140  14 6960 0652
  CONS2   86  4554    0052                           1141  86 4554 0052
  CONS3   10  0000    0054                           1142  10 0000 0054
  CONS4   29  4980    0053                           1143  29 4980 0053
  CONS5   57  0000    0050                           1144  57 0000 0050
  R       19  8718    0051                           1146  19 8718 0051
  GC      32  1740    0052                           1147  32 1740 0052
  EINS    00  1000    0053                           0451  00 1000 0053
  EINSS   01  0000    0052                           0189  01 0000 0052
  UNITY   00  0000    0001                           0124  00 0000 0001
  SPEC1   07 M0006    0006                           0320  07 9005 0006
  SPEC2   00 M0006    0006                           0419  00 9005 0006
1
```

E-417

```
1
1            LNX ROUTINE EXCERPT FROM
1            THE ROCKET PACKAGE
1
1
             REG C9050     9050
1
      LNX    STD LINK                                1700  24 1355 0408
             LDD OP1                                 0408  69 0611 1064
             STD C0005                               1064  24 9054 0470
             NZU           HLT                       0470  44 0223 0224
             BMI HLT                                 0223  46 0224 0227
             SRT  0002               EXPON IN        0227  30 0002 0383
             ALO EXP52               LO PUT IN       0383  15 0186 0441
             STL C0001               FLT NOTATN      0441  20 9050 0198
             SLO  8001               CLEAR LO        0198  16 8001 0405
             ALO 51EXP               NUM IN UPR      0405  15 0458 1163
             SLT  0002               ADD 51 EXP      1163  35 0002 0469
             STU C0002                               0469  21 9051 0277
             RAU C0001               SUB 51 FRM      0277  60 9050 0185
             FSB 51LNK               EXPONENT        0185  33 0138 0465
             FMP LN10                MUL LN 10       0465  39 0218 0268
             FAD LN3                 ADD LN  3       0268  32 0521 0297
             STU C0001                               0297  21 9050 0455
             RAU C0002                               0455  60 9051 1213
             FAD K                   X MINUS 3       1213  32 0266 0243
             STU C0003               OVER            0243  21 9052 0551
             RAU C0002               X PLUS  3       0551  60 9051 0459
             FSB K                                   0459  33 0266 0293
             FDV C0003               EQUALS Y        0293  34 9052 0196
             FAD  8003               FORM 2Y         0196  32 8003 0425
             ALO  8001               Y IN LOWER      0425  15 8001 0433
             STU C0003               2Y IN 9003      0433  21 9052 0491
             RSU  8002               MINUS Y IN      0491  61 8002 0199
             FMP  8001               Y SQUARED       0199  39 8001 0402
             STU C0002                               0402  21 9051 0509
             FMP K1                                  0509  39 0212 0262
             FAD K2                                  0262  32 0515 0541
             FMP C0002                               0541  39 9051 0194
             FAD K3                  FORM            0194  32 0347 0273
             FMP C0002               NUMERATOR       0273  39 9051 0226
             FAD K4                                  0226  32 0579 0505
             STU C0004                               0505  21 9053 1263
             RAU C0002                               1263  60 9051 0571
             FMP K5                                  0571  39 0274 0324
             FAD K6                                  0324  32 0327 0653
             FMP C0002                               0653  39 9051 0256
             FAD K7                  FORM            0256  32 0559 0235
             FMP C0002               DENOMNATOR      0235  39 9051 0188
             FAD K4                                  0188  32 0579 0555
             FDV C0004               QUOTIENT        0555  34 9053 0508
             FMP C0003               MULT BY 2Y      0508  39 9052 0961
             FAD C0001                               0961  32 9050 0591
             FMP C0005     LINK                      0591  39 9054 1855
      HLT    HLT  1111     1111                      0224  01 1111 1111
1
1             LN X ROUTINE CONSTANTS
      EXP52  00  0000      0052                      0186  00 0000 0052
      51EXP  51  0000      0000                      0458  51 0000 0000
      51LNK  51  0000      0052                      0138  51 0000 0052
      K      30  0000      0051                      0266  30 0000 0051
      LN10   23  0258      5151                      0218  23 0258 5151
      LN3    10  9861      2351                      0521  10 9861 2351
      OP1    10  0000      0051                      0611  10 0000 0051
      K1     81  5850      8249      DENOM 4         0212  81 5850 8249
      K2     73  4265      7350      DENOM 3         0515  73 4265 7350
      K3     16  1538      4651      DENOM 2         0347  16 1538 4651
      K4     99  9999      9950                      0579  99 9999 9950
      K5     17  0496      1749      NUM   4         0274  17 0496 1749
      K6     39  5804      2050      NUM   3         0327  39 5804 2050
      K7     12  8205      1351      NUM   2         0559  12 8205 1351
```

E-417

639		PAT										
		1111	0450	050	111000000	950	1000	1111111111	1450	1500	1100011000	1950
1	000	000	0451	0501	11000000	951	1001	1111111111	1451	1501	1100111000	1951
2	000	001	0452	0502	1111000000	952	1002	1111111111	1452	1502	1100111000	1952
3	000	000	0453	0503		953	1003	1111111111	1453	1503	1100111000	1953
4*	000	111111	0454	0504	1111000000	954	1004	0011111111	1454	1504	1100111000	1954
5	000	000	0455	0505	11000000	955	1005	1111111111	1455	1505	1100111000	1955
6	000	1111	0456	0506	1111000000	956	1006	1111111111	1456	1506	1100111000	1956
7	000	001	0457	0507	1111000000	957	1007	1111111111	1457	1507	1100111000	1957
8	000	000	0458	0508	111000000	958	1008	1111111111	1458	1508	1100111000	1958
9	000	000	0459	0509	11000000	959	1009	1101111111	1459	1509	1100111000	1959
1		1111	0460	051	1110000001	960	1010	1101111111	1460	1510	1101111000	1960
11	000	000	0461	0511		961	1011	1101111111	1461	1511	1101111000	1961
12	000	1111	0462	0512	1110000001	962	1012	1101111111	1462	1512	1101111000	1962
13	000	000	0463	0513		963	1013	0000001111	1463	1513	1101111000	1963
14	000	000	0464	0514		964	1014	0001111111	1464	1514	1101111000	1964
15	000	000	0465	0515	110000001	965	1015	1101111111	1465	1515	1101111000	1965
16	000	1111	0466	0516	1110000001	966	1016	1101111111	1466	1516	1101111000	1966
17	000	001	0467	0517	1110000001	967	1017	1101111111	1467	1517	1101111000	1967
18	000	1111	0468	0518	1110000001	968	1018	1101111111	1468	1518	1101111000	1968
19	000	000	0469	0519	1110000001	969	1019	1101111111	1469	1519	1101111000	1969
2		000	0470	052	1110000001	970	1020	1101111111	1470	1520	1101111000	1970
21	000	000	0471	0521	10000001	971	1021	1101111111	1471	1521	1101111000	1971
22*	0001111111		0472	0522	1110000001	972	1022	1101111111	1472	1522	1101111000	1972
23	000	1111	0473	0523	1110000001	973	1023	1101111111	1473	1523	1101111000	1973
24	000	111	0474	0524	1110000001	974	1024	1101111111	1474	1524	1101111000	1974
25	000	001	0475	0525	1110000001	975	1025	1001111111	1475	1525	1101111000	1975
26	000	11111	0476	0526	1110000001	976	1026	1001111111	1476	1526	1101111000	1976
27	000	111	0477	0527	1110000001	977	1027	1001111111	1477	1527	1101111000	1977
28*		111111111	0478	0528	1110000001	978	1028	1001111111	1478	1528	1101111000	1978
29	000	000	0479	0529	10000001	979	1029	1001111111	1479	1529	1101111000	1979
30*	1111111111		0480	053	1110000001	980	1030	1001111111	1480	1530	1101111000	1980
31	000	011	0481	0531	1110000001	981	1031	1001111111	1481	1531	1101111000	1981
32	000	'1111	0482	0532	1110000001	982	1032	1001111111	1482	1532	1101110000	1982
33	000	001	0483	0533	1110000001	983	1033	1001111111	1483	1533	1101110000	1983
34*	0001111111		0484	0534	1110000001	984	1034	1001111111	1484	1534	1101110000	1984
35	000	11111	0485	0535	1110000001	985	1035	1001111111	1485	1535	1101110000	1985
36*	000	111111	0486	0536	1110000001	986	1036	1001111111	1486	1536	1101110000	1986
37	000	1111	0487	0537	1110000001	987	1037	1001111111	1487	1537	1101110000	1987
38*	000	111111	0488	0538	1110000001	988	1038	1001111111	1488	1538	1101110000	1988
39	000	1111	0489	0539	1110000001	989	1039	1001111111	1489	1539	1101110000	1989
40*		11111111	0490	054	1110000001	990	1040	1001111111	1490	1540	1101110000	1990
41	000	000	0491	0541	10000001	991	1041	1001111111	1491	1541	1101110000	1991
42	000	1111	0492	0542	1110000001	992	1042	1001111111	1492	1542	1101110000	1992
43	000	1111	0493	0543	1110000001	993	1043	1000111111	1493	1543	1101110000	1993
44*	000	111111	0494	0544	1110000001	994	1044	1001111111	1494	1544	1101110000	1994
45*	000	111111	0495	0545	1110000001	995	1045	1001111111	1495	1545	1101110000	1995
46*	000	111111	0496	0546	1110000001	996	1046	1001111111	1496	1546	1101110000	1996
47	000	111	0497	0547	1110000001	997	1047	1001110111	1497	1547	1101110000	1997
48*	000	111111	0498	0548	1110000001	998	1048	0001110111	1498	1548	1101110000	1998
49*	000	111111	0499	0549	1110000001	999	1049	0001110111	1499	1549	1001110000	1999

APPENDIX H

VECTOR AND PROPELLANT PROGRAM

```
 1 1          PROGRAM FOR ASSEMBLING
 2 1          COMBUSTION PRODUCT PACKED
 3 1          VECTORS AND FUEL AND OXIDANT
 4 1          GRAM ATOM RATIOS ENTHALPIES
 5 1          AND OXIDATION NUMBERS
 6 1
 7            REG A0001     0011       ATOM TABLE
 8            REG F0100     0199       FUELS
 9            REG X0200     0299       OXIDANTS
10            REG L0300     0309       PCTS FUEL
11            REG D0310     0319       PCTS OXID
12            REG H0320     0329       FUEL ENTH
13            REG E0330     0339       OXID ENTH
14            REG W0340     0349       ATOMIC WTS
15            REG S0350     0359       OXID NUMBR
16            REG N0360     0379       MOLES
17            REG G0380     0399       GRAM ATOMS
18 1                                   PER GRAM
19            REG M0400     0510       ATOMIC WTS
20            REG V0600     0710       SYMBOL AND
21 1                                   OXID TABLE
22            REG U0800     0809
23            REG R1951     1960       READ BAND
24            REG P1977     1986       PUNCH BAND
25            REG C9000     9000
26            BLR  0000     0000
27            BLR  0090     0099       ZEROS
28            BLR  0360     0379       SPARE
29            BLR  0537     0549       OXIDANT
30            BLR  0587     0599       FUEL
31            BLR  0900     0909
32            BLR  1500     1999
33            SYN PUNCH     1930
34            SYN RMPCH     1940
35            EQU TEMPO    C0001       TEMPORARY
36            EQU TEMP1    C0002       TEMPORARY
37            EQU TEMP2    C0003       TEMPORARY
38            EQU R000X    R0001
39 1
40            EQU U01XX    U0101
41            EQU V00XX    V0001
42            EQU M00XX    M0001
43            EQU XXXXX     0000
44 1
45 1              TABLE OF ATOMIC WEIGHTS
46    M0001   39  9440    0052     ARGON        0400   39 9440 0052
47    M0002   22  7000    0053     ACTINIUM     0401   22 7000 0053
48    M0003   10  7880    0053     SILVER       0402   10 7880 0053
49    M0004   26  9800    0052     ALUMINUM     0403   26 9800 0052
50    M0005   24  3000    0053     AMERICIUM    0404   24 3000 0053
51    M0006   74  9100    0052     ARSENIC      0405   74 9100 0052
52    M0007   21  1000    0053     ASTATINE     0406   21 1000 0053
53    M0008   19  7000    0053     GOLD         0407   19 7000 0053
54    M0009   10  8200    0052     BORON        0408   10 8200 0052
56    M0011   90  1300    0051     BERYLLIUM    0410   90 1300 0051
57    M0012   20  9000    0053     BISMUTH      0411   20 9000 0053
58    M0013   24  5000    0053     BERKELIUM    0412   24 5000 0053
55    M0010   13  7360    0053     BARIUM       0409   13 7360 0053
59    M0014   79  9160    0052     BROMINE      0413   79 9160 0052
60    M0015   12  0110    0052     CARBON       0414   12 0110 0052
61    M0016   40  0800    0052     CALCIUM      0415   40 0800 0052
62    M0017   11  2410    0053     CADMIUM      0416   11 2410 0053
63    M0018   14  0130    0053     CERIUM       0417   14 0130 0053
64    M0019   24  8000    0053     CALIFORNUM   0418   24 8000 0053
65    M0020   35  4570    0052     CHLORINE     0419   35 4570 0052
66    M0021   24  5000    0053     CURIUM       0420   24 5000 0053
67    M0022   58  9400    0052     COBALT       0421   58 9400 0052
68    M0023   52  0100    0052     CHROMIUM     0422   52 0100 0052
69    M0024   13  2910    0053     CESIUM       0423   13 2910 0053
70    M0025   63  5400    0052     COPPER       0424   63 5400 0052
71    M0026   16  2510    0053     DYSPROSIUM   0425   16 2510 0053
72    M0027   25  5000    0053     EINSTEINUM   0426   25 5000 0053
73    M0028   16  7270    0053     ERBIUM       0427   16 7270 0053
74    M0029   15  2000    0053     EUROPIUM     0428   15 2000 0053
75    M0030   19  0000    0052     FLUORINE     0429   19 0000 0052
76    M0031   55  8500    0052     IRON         0430   55 8500 0052
77    M0032   25  2000    0053     FERMIUM      0431   25 2000 0053
78    M0033   22  3000    0053     FRANCIUM     0432   22 3000 0053
79    M0034   69  7200    0052     GALLIUM      0433   69 7200 0052
80    M0035   15  7260    0053     GADOLINIUM   0434   15 7260 0053
81    M0036   72  6000    0052     GERMANIUM    0435   72 6000 0052
82    M0037   10  0800    0051     HYDROGEN     0436   10 0800 0051
```

M0038	40	0300	0051	HELIUM	0437	40	0300	0051
M0039	17	8580	0053	HAFNIUM	0438	17	8580	0053
M0040	20	0610	0053	MERCURY	0439	20	0610	0053
M0041	16	4940	0053	HOLMIUM	0440	16	4940	0053
M0042	12	6910	0053	IODINE	0441	12	6910	0053
M0043	11	4820	0053	INDIUM	0442	11	4820	0053
M0044	19	2200	0053	IRIDIUM	0443	19	2200	0053
M0045	39	1000	0052	POTASSIUM	0444	39	1000	0052
M0046	83	8000	0052	KRYPTON	0445	83	8000	0052
M0047	13	8920	0053	LANTHANUM	0446	13	8920	0053
M0048	69	4000	0051	LITHIUM	0447	69	4000	0051
M0051	17	4990	0053	LUTETIUM	0450	17	4990	0053
M0052	24	3200	0052	MAGNESIUM	0451	24	3200	0052
M0053	54	9400	0052	MANGANESE	0452	54	9400	0052
M0054	95	9500	0052	MOLYBDENUM	0453	95	9500	0052
M0055	25	6000	0053	MENDELEVUM	0454	25	6000	0053
M0056	14	0080	0052	NITROGEN	0455	14	0080	0052
M0057	22	9910	0052	SODIUM	0456	22	9910	0052
M0058	92	9100	0052	NIOBIUM	0457	92	9100	0052
M0059	14	4270	0053	NEODYMIUM	0458	14	4270	0053
M0060	20	1830	0052	NEON	0459	20	1830	0052
M0061	58	7100	0052	NICKEL	0460	58	7100	0052
M0062	23	7000	0053	NEPTUNIUM	0461	23	7000	0053
M0063	16	0000	0052	OXYGEN	0462	16	0000	0052
M0064	19	0200	0053	OSMIUM	0463	19	0200	0053
M0065	30	9750	0052	PHOSPHORUS	0464	30	9750	0052
M0066	23	1000	0053	PROTACTINM	0465	23	1000	0053
M0067	20	7210	0053	LEAD	0466	20	7210	0053
M0068	10	6700	0053	PALLADIUM	0467	10	6700	0053
M0069	14	5000	0053	PROMETHIUM	0468	14	5000	0053
M0070	21	0000	0053	POLONIUM	0469	21	0000	0053
M0071	14	0920	0053	PRASEODYMM	0470	14	0920	0053
M0072	19	5090	0053	PLATINUM	0471	19	5090	0053
M0073	24	2000	0053	PLUTONIUM	0472	24	2000	0053
M0074	22	6050	0053	RADIUM	0473	22	6050	0053
M0075	85	4800	0052	RUBIDIUM	0474	85	4800	0052
M0076	18	6220	0053	RHENIUM	0475	18	6220	0053
M0077	10	2910	0053	RHODIUM	0476	10	2910	0053
M0078	22	2000	0053	RADON	0477	22	2000	0053
M0079	10	1100	0053	RUTHENIUM	0478	10	1100	0053
M0080	32	0660	0052	SULFUR	0479	32	0660	0052
M0081	12	1760	0053	ANTIMONY	0480	12	1760	0053
M0082	44	9600	0052	SCANDIUM	0481	44	9600	0052
M0083	78	9600	0052	SELENIUM	0482	78	9600	0052
M0084	28	0900	0052	SILICON	0483	28	0900	0052
M0085	15	0350	0053	SAMARIUM	0484	15	0350	0053
M0086	11	8700	0053	TIN	0485	11	8700	0053
M0087	87	6300	0052	STRONTIUM	0486	87	6300	0052
M0088	18	0950	0053	TANTALUM	0487	18	0950	0053
M0089	15	8930	0053	TERBIUM	0488	15	8930	0053
M0090	99	0000	0052	TECHNETIUM	0489	99	0000	0052
M0091	12	7610	0053	TELLURIUM	0490	12	7610	0053
M0092	23	2050	0053	THORIUM	0491	23	2050	0053
M0093	47	9000	0052	TITANIUM	0492	47	9000	0052
M0094	20	4390	0053	THALLIUM	0493	20	4390	0053
M0095	16	8940	0053	THULIUM	0494	16	8940	0053
M0096	23	8070	0053	URANIUM	0495	23	8070	0053
M0097	50	9500	0052	VANADIUM	0496	50	9500	0052
M0098	18	3860	0053	TUNGSTEN	0497	18	3860	0053
M0101	13	1300	0053	XENON	0500	13	1300	0053
M0102	88	9200	0052	YTTRIUM	0501	88	9200	0052
M0103	17	3040	0053	YTTERBIUM	0502	17	3040	0053
M0104	65	3800	0052	ZINC	0503	65	3800	0052
M0105	91	2200	0052	ZIRCONIUM	0504	91	2200	0052
1								
1			TABLE OF VALENCES					
V0001	61	0000	0000	ARGON	0500	61	0000	0000
V0002	61	6300	0000	ACTINIUM	0501	61	6300	0000
V0003	61	6700	0000	SILVER	0502	61	6700	0000
V0004	61	7300	0003	ALUMINUM	0503	61	7300	0003
V0005	61	7400	0000	AMERICIUM	0504	61	7400	0000
V0006	61	8200	0000	ARSENIC	0505	61	8200	0000
V0007	61	8300	0000	ASTATINE	0506	61	8300	0000
V0008	61	8400	0000	GOLD	0507	61	8400	0000
V0009	62	0000	0003	BORON	0508	62	0000	0003
V0010	62	6100	0000	BARIUM	0509	62	6100	0000
V0011	62	6500	0002	BERYLLIUM	0510	62	6500	0002
V0012	62	6900	0000	BISMUTH	0611	62	6900	0000
V0013	62	7200	0000	BERKELIUM	0612	62	7200	0000
V0014	62	7900	0001	BROMINE	0513	-62	7900	0001
V0015	63	0000	0004	CARBON	0514	63	0000	0004
V0016	63	6100	0002	CALCIUM	0515	63	6100	0002
V0017	63	6400	0000	CADMIUM	0616	63	6400	0000
V0018	63	6500	0000	CERIUM	0617	63	6500	0000

E-417

167	V0019		63	6600	0000	CALIFORNUM	0618	63	6600	0000
168	V0020	-	63	7300	0001	CHLORINE	0619	-63	7300	0001
169	V0021		63	7400	0000	CURIUM	0620	63	7400	0000
170	V0022		63	7600	0000	COBALT	0621	63	7600	0000
171	V0023		63	7900	0000	CHROMIUM	0622	63	7900	0000
172	V0024		63	8200	0000	CESIUM	0623	63	8200	0000
173	V0025		63	8400	0000	COPPER	0624	63	8400	0000
174	V0026		64	8800	0000	DYSPROSIUM	0625	64	8800	0000
175	V0027		65	0000	0000	EINSTEINUM	0626	65	0000	0000
176	V0028		65	7900	0000	ERBIUM	0627	65	7900	0000
177	V0029		65	8400	0000	EUROPIUM	0628	65	8400	0000
178	V0030	-	66	0000	0001	FLUORINE	0629	-66	0000	0001
179	V0031		66	6500	0000	IRON	0630	66	6500	0000
180	V0032		66	7400	0000	FERMIUM	0631	66	7400	0000
181	V0033		66	7900	0000	FRANCIUM	0632	66	7900	0000
182	V0034		67	6100	0000	GALLIUM	0633	67	6100	0000
183	V0035		67	6400	0000	GADOLINIUM	0634	67	6400	0000
184	V0036		67	6500	0000	GERMANIUM	0635	67	6500	0000
185	V0037		68	0000	0001	HYDROGEN	0636	68	0000	0001
186	V0038		68	6500	0000	HELIUM	0637	68	6500	0000
187	V0039		68	6600	0000	HAFNIUM	0638	68	6600	0000
188	V0040		68	6700	0000	MERCURY	0639	68	6700	0000
189	V0041		68	7600	0000	HOLMIUM	0640	68	7600	0000
190	V0042	-	69	0000	0001	IODINE	0641	-69	0000	0001
191	V0043		69	7500	0000	INDIUM	0642	69	7500	0000
192	V0044		69	7900	0000	IRIDIUM	0643	69	7900	0000
193	V0045		72	0000	0001	POTASSIUM	0644	72	0000	0001
194	V0046		72	7900	0000	KRYPTON	0645	72	7900	0000
195	V0047		73	6100	0000	LANTHANUM	0646	73	6100	0000
196	V0048		73	6900	0001	LITHIUM	0647	73	6900	0001
197	V0051		73	8400	0000	LUTETIUM	0650	73	8400	0000
198	V0052		74	6700	0002	MAGNESIUM	0651	74	6700	0002
199	V0053		74	7500	0000	MANGANESE	0652	74	7500	0000
200	V0054		74	7600	0000	MOLYBDENUM	0653	74	7600	0000
201	V0055		74	8500	0000	MENDELEVUM	0654	74	8500	0000
202	V0056		75	0000	0000	NITROGEN	0655	75	0000	0000
203	V0057		75	6100	0001	SODIUM	0656	75	6100	0001
204	V0058		75	6200	0000	NIOBIUM	0657	75	6200	0000
205	V0059		75	6400	0000	NEODYMIUM	0658	75	6400	0000
206	V0060		75	6500	0000	NEON	0659	75	6500	0000
207	V0061		75	6900	0000	NICKEL	0660	75	6900	0000
208	V0062		75	7700	0000	NEPTUNIUM	0661	75	7700	0000
209	V0063	-	76	0000	0002	OXYGEN	0662	-76	0000	0002
210	V0064		76	8200	0000	OSMIUM	0663	76	8200	0000
211	V0065		77	0000	0000	PHOSPHORUS	0664	77	0000	0000
212	V0066		77	6100	0000	PROTACTIUM	0665	77	6100	0000
213	V0067		77	6200	0000	LEAD	0666	77	6200	0000
214	V0068		77	6400	0000	PALLADIUM	0667	77	6400	0000
215	V0069		77	7400	0000	PROMETHIUM	0668	77	7400	0000
216	V0070		77	7600	0000	POLONIUM	0669	77	7600	0000
217	V0071		77	7900	0000	PRASEODYMM	0670	77	7900	0000
218	V0072		77	8300	0000	PLATINUM	0671	77	8300	0000
219	V0073		77	8400	0000	PLUTONIUM	0672	77	8400	0000
220	V0074		79	6100	0000	RADIUM	0673	79	6100	0000
221	V0075		79	6200	0000	RUBIDIUM	0674	79	6200	0000
222	V0076		79	6500	0000	RHENIUM	0675	79	6500	0000
223	V0077		79	6800	0000	RHODIUM	0676	79	6800	0000
224	V0078		79	7500	0000	RADON	0677	79	7500	0000
225	V0079		79	8400	0000	RUTHENIUM	0678	79	8400	0000
226	V0080		82	0000	0004	SULFUR	0679	82	0000	0004
227	V0081		82	6200	0000	ANTIMONY	0680	82	6200	0000
228	V0082		82	6300	0000	SCANDIUM	0681	82	6300	0000
229	V0083		82	6500	0000	SELENIUM	0682	82	6500	0000
230	V0084		82	6900	0004	SILICON	0683	82	6900	0004
231	V0085		82	7400	0000	SAMARIUM	0684	82	7400	0000
232	V0086		82	7500	0000	TIN	0685	82	7500	0000
233	V0087		82	7900	0000	STRONTIUM	0686	82	7900	0000
234	V0088		83	6100	0000	TANTALUM	0687	83	6100	0000
235	V0089		83	6200	0000	TERBIUM	0688	83	6200	0000
236	V0090		83	6300	0000	TECHNETIUM	0689	83	6300	0000
237	V0091		83	6500	0000	TELLURIUM	0690	83	6500	0000
238	V0092		83	6800	0000	THORIUM	0691	83	6800	0000
239	V0093		83	6900	0000	TITANIUM	0692	83	6900	0000
240	V0094		83	7300	0000	THALLIUM	0693	83	7300	0000
241	V0095		83	7400	0000	THULIUM	0694	83	7400	0000
242	V0096		84	0000	0000	URANIUM	0695	84	0000	0000
243	V0097		85	0000	0000	VANADIUM	0696	85	0000	0000
244	V0098		86	0000	0000	TUNGSTEN	0697	86	0000	0000
245	V0101		87	6500	0000	XENON	0700	87	6500	0000
246	V0102		88	0000	0000	YTTRIUM	0701	88	0000	0000
247	V0103		88	6100	0000	YTTERBIUM	0702	88	6100	0000
248	V0104		89	7500	0000	ZINC	0703	89	7500	0000
249	V0105		89	7900	0000	ZIRCONIUM	0704	89	7900	0000
250	1									

```
1          CLEAR ROUTINE
1
   CLEAR   RAA  0010                           0050  80 0010 0056
           RAM  8002    CLR 1                  0056  67 8002 0015
   CLR 1   STU  9049 A                         0015  21 9049 0023
           NZA          CLR 2                  0023  40 0026 0027
           SXA  0001    CLR 1                  0026  51 0001 0015
   CLR 2   SET  9049                           0027  27 9049 0032
           STB A0001                           0032  29 0001 0054
           RAA  0300    CLR 3                  0054  80 0300 0060
   CLR 3   SET  9050                           0060  27 9050 0065
           SBB  0090 A                         0065  28 2090 0043
           NZA          SET01                  0043  40 0046 0047
           SXA  0010    CLR 3                  0046  51 0010 0060
   SET01   RSU UNITY              SET ATOM     0047  61 0550 0055
           STU ATMCT              COUNTER      0055  21 0560 0013
           STD RELAY    READ      SET SWITCH   0013  24 0016 0019
1                                 TO ATOMS
1
1           READ ROUTINE
   READ    RCD R0001              READ CARD    0019  70 1951 0051
           LDD R0001              TRANSFER     0051  69 1951 0554
           STD P0001              IMPUT FROM   0554  24 1977 0030
           LDD R0002              READ BAND    0030  69 1952 0555
           STD P0002              TO PUNCH     0555  24 1978 0031
           LDD R0003              BAND         0031  69 1953 0556
           STD P0003                           0556  24 1979 0082
           LDD R0004                           0082  69 1954 0057
           STD P0004                           0057  24 1980 0033
           LDD R0005                           0033  69 1955 0058
           STD P0005                           0058  24 1981 0034
           LDD R0006                           0034  69 1956 0059
           STD P0006                           0059  24 1982 0035
           RAU R0010                           0035  60 1960 0515
           STL P0007              CLER P0007   0515  20 1983 0036
           STD P0009              CLER P0009   0036  24 1985 0038
           SRT  0002                           0038  30 0002 0045
           STU P0008                           0045  21 1984 0037
           NZU          PV007     SET P0010    0037  44 0041 0042
           ALO 823RD              TO PUNCH     0041  15 0044 0049
           STL P0010    PNCH      TYPE1 CARD   0049  20 1986 0039
   PV007   RAU R0004              REARRANGE    0042  60 1954 0559
           SRT  0004              VECTOR IN    0559  30 0004 0069
           SLO  8002              WORDS 2 3    0069  16 8002 0077
           STD R0004              4 5 AND 6    0077  24 1954 0557
           SLT  0004                           0557  35 0004 0017
           STU SYMBL              SAVE SYMBL   0017  21 0022 0025
           RAL R0004                           0025  65 1954 0759
           SLT  0002                           0759  35 0002 0565
           SLO  8002                           0565  16 8002 0073
           STD TEMP0                           0073  24 9000 0029
           ALO R0003                           0029  15 1953 0757
           SLT  0008                           0757  35 0008 0075
           STU R0003                           0075  21 1953 0756
           STL TEMP1                           0756  20 9001 0014
           RAU R0006                           0014  60 1956 0061
           SRT  0004                           0061  30 0004 0021
           STL R0006                           0021  20 1956 0859
           RAL  8003                           0859  65 8003 0067
           SLT  0004                           0067  35 0004 0527
           AUP R0005                           0527  10 1955 0959
           SRT  0004                           0959  30 0004 0519
           STL R0005                           0519  20 1955 0558
           AUP TEMP1                           0558  10 9001 0715
           STU R0004                           0715  21 1954 0857
           RAU TEMP0                           0857  60 9000 0765
           SRT  0002                           0765  30 0002 0071
           AUP R0004                           0071  10 1954 1009
           STU R0004    LOOK                   1009  21 1954 0957
1           CONSTANTS FOR READ ROUTINE
   823RD    00  0000     0880                  0044  00 0000 0880
1
1           TABLE LOOKUP ROUTINE TO FIND
1           CORRECT ROUTINE FOR SYMBOL
1           BEING PROCESSED
1
   LOOK    LDD SYMBL                           0957  69 0022 0525
           TLU U0001                           0525  84 0800 0755
           SUP  8003                           0755  11 8003 0063
           SRT  0004                           0063  30 0004 0523
           ALO 100 I     8002                  0523  15 0076 8002
     8002   00  0000    U01XX                  8002  00 0000 0900
1
```

E-417

E-417

CA-14 back

```
     U0101   RAU SYMBL             ATM PROGRM  0900  60 0022 0577
             SUP ATM                           0577  11 0080 0085
             NZU          PV009                0085  44 0089 0040
             HLT  9999     1111    WRONG SMBL  0089  01 9999 1111
 1
     U0102   RAU SYMBL             BOP PROGRM  0901  60 0022 0727
             SUP BOP                           0727  11 0530 0535
             NZU          CLEAR                0535  44 0739 0050
             HLT  9999     2222    WRONG SMBL  0739  01 9999 2222
 1
     U0103   RAU SYMBL             FUEL        0902  60 0022 0777
             SRT  0006             ENTHALPY    0777  30 0006 0741
             SLO  8002             PROGRAM     0741  16 8002 0749
             STD CODE                          0749  24 0052 0855
             SLT  0006                         0855  35 0006 0569
             SUP EF                            0569  11 0072 0827
             NZU          OK  3                0827  44 0081 0532
             HLT  9999     3333    WRONG SMBL  0081  01 9999 3333
     OK   3  RAA  0319    PAR 1                0532  80 0319 0088
 1
 1
 1               CONSOLE POSITION 2 IS SET TO 8
 1               IF IT IS DESIRED TO PUNCH OUT
 1               FUELS OXIDANTS PERCENTS AND
 1               ENTHALPIES
 1
 1
     U0104   RAU SYMBL             PROPELLANT  0903  60 0022 0877
             SUP END               READY TO    0877  11 0580 0585
             NZU          DIST2    PROCESS     0585  44 0789 0740
             HLT  9999     4444    WRONG SMBL  0789  01 9999 4444
     DIST2   LDD  8000                         0740  69 8000 0746
             BD2          END 1                0746  92 0799 0551
             RAL SPEC5                         0799  65 0552 1007
             LDD END 1    PUNCH                1007  69 0551 1930
     SPEC5    00  0100     0240                0552  00 0100 0240
 1
     U0105   RAU SYMBL             OXIDANT     0904  60 0022 0927
             SRT  0006             ENTHALPY    0927  30 0006 0791
             SLO  8002             PROGRAM     0791  16 8002 0849
             STD CODE                          0849  24 0052 0955
             SLT  0006                         0955  35 0006 0719
             SUP EX                            0719  11 0522 0977
             NZU          OK  5                0977  44 0531 0582
             HLT  9999     5555    WRONG SMBL  0531  01 9999 5555
     OK   5  RAA  0329    PAR 1                0582  80 0329 0088
 1
     U0106   RAU SYMBL             FUEL        0905  60 0022 1027
             SRT  0008             PROGRAM     1027  30 0008 0745
             SLO  8002                         0745  16 8002 0053
             STD CODE                          0053  24 0052 1005
             SLT  0008                         1005  35 0008 0573
             SUP F                             0573  11 0526 0581
             NZU          OK  6                0581  44 0735 0086
             HLT  9999     6666    WRONG SMBL  0735  01 9999 6666
     OK   6  RAA  0099                         0086  80 0099 0742
             STL R0007    PV180    CLER R0007  0742  20 1957 0760
 1
     U0107   RAU SYMBL             MOLECULE    0906  60 0022 1077
             SUP MOL               PROGRAM     1077  11 0730 0785
             NZU          PV015                0785  44 0839 0790
             HLT  9999     7777    WRONG SMBL  0839  01 9999 7777
 1
     U0108   RAU SYMBL             PERCENT     0907  60 0022 1127
             SRT  0006             FUEL        1127  30 0006 0841
             SLO  8002             PROGRAM     0841  16 8002 0899
             STD CODE                          0899  24 0052 1055
             SLT  0006                         1055  35 0006 0769
             SUP PF                            0769  11 0572 1177
             NZU          OK  8                1177  44 0731 0732
             HLT  9999     8888                0731  01 9999 8888
     OK   8  RAA  0299    PAR 1                0732  80 0299 0088
 1
     U0109   RAU SYMBL             PERCENT     0908  60 0022 1227
             SRT  0006             OXIDANT     1227  30 0006 0891
             SLO  8002             PROGRAM     0891  16 8002 0949
             STD CODE                          0949  24 0052 1105
             SLT  0006                         1105  35 0006 0819
             SUP PX                            0819  11 0722 1277
             NZU          OK  9                1277  44 0781 0782
             HLT  9999     9999                0781  01 9999 9999
     OK   9  RAA  0309    PAR 1                0782  80 0309 0088
 1
```

```
     U0110  RAU SYMBL                OXIDANT      0909  60 0022 1327
            SRT  0008                PROGRAM      1327  30 0008 0795
            SLO  8002                             0795  16 8002 0553
            STD CODE                              0553  24 0052 1155
            SLT  0008                             1155  35 0008 0723
            SUP X                                 0723  11 0576 0831
            NZU          OK 10                    0831  44 0835 0536
            HLT  9999    0000        WRONG SMBL   0835  01 9999 0000
     OK 10  RAA  0199                             0536  80 0199 0792
            STL R0007    PV180       CLER R0007   0792  20 1957 0760
 1
 1          CONSTANTS FOR TABLE LOOKUP
 1                       ROUTINE
     ATM    61  8374     0000                     0080  61 8374 0000
     BOP    62  7677     0000                     0530  62 7677 0000
     EF     65  6600     0000                     0072  65 6600 0000
     END    65  7564     0000                     0580  65 7564 0000
     EX     65  8700     0000                     0522  65 8700 0000
     F      66  0000     0000                     0526  66 0000 0000
     MOL    74  7673     0000                     0730  74 7673 0000
     PF     77  6600     0000                     0572  77 6600 0000
     PX     77  8700     0000                     0722  77 8700 0000
     X      87  0000     0000                     0576  87 0000 0000
     U0001  61  8374     0000        ATM          0800  61 8374 0000
     U0002  62  7677     0000        BOP          0801  62 7677 0000
     U0003  65  6699     0000        EF9          0802  65 6699 0000
     U0004  65  7564     0000        END          0803  65 7564 0000
     U0005  65  8799     0000        EX9          0804  65 8799 0000
     U0006  66  9900     0000        F9           0805  66 9900 0000
     U0007  74  7673     0000        MOL          0806  74 7673 0000
     U0008  77  6699     0000        PF9          0807  77 6699 0000
     U0009  77  8799     0000        PX9          0808  77 8799 0000
     U0010  87  9900     0000        X9           0809  87 9900 0000
     100 I  00  0000     0100                     0076  00 0000 0100
 1
 1          ROUTINE FOR PACKED VECTORS
 1          ATOMS START AT PV009 AND
 1          MOLECULES START AT PV015
 1
     PV009  LDD R0007                PLACE CODE   0040  69 1957 0810
            STD P0009                IN OUTPUT    0810  24 1985 0738
            RAU RELAY                ITS ATOM     0738  60 0016 0521
            NZU PV011                             0521  44 0575 0726
            HLT  2222    8888        SWITCH NOT   0726  01 2222 8888
 1                                   INITIALIZE
     PV011  RAL R0002                IS ATOM      0575  65 1952 1057
            SLT  0004                MORE THAN    1057  35 0004 0517
            SUP  8003                2 LETTERS    0517  11 8003 0725
            NZE          PV013                    0725  45 0028 0079
            HLT  3333    7777        YES STOP     0028  01 3333 7777
     PV013  RAL ATMCT                NO           0079  65 0560 0815
            ALO UNITY                ADVANCE      0815  15 0550 1205
            STL ATMCT                ATOM COUNT   1205  20 0560 0513
            ALO R0002                STORE ATOM   0513  15 1952 1107
            AUP ATMCT                COLUMN       1107  10 0560 0865
            SLO  8002                EQUIVALENT   0865  16 8002 0773
            SLT  0004                IN TABLE     0773  35 0004 0083
            ALO  8001                             0083  15 8001 0941
            AUP STORE    8003                     0941  10 0744 8003
     8003   STL A0001    PACKA                    8003  20 0001 0754
     PACKA  RAU ATMCT                FORM ATOM    0754  60 0560 0915
            SLT  0001                VECTOR       0915  35 0001 0571
            AUP UNITY                STORE IN     0571  10 0550 1255
            STU P0007    PV116       PUNCH BAND   1255  21 1983 0586
     PV015  LDD R0007                PLACE CODE   0790  69 1957 0860
            STD P0009                IN OUTPUT    0860  24 1985 0788
            RAU RELAY                IS THIS      0788  60 0016 0721
            NZU          PV019       FIRST MOL    0721  44 0775 0776
            STL RELAY                YES          0775  20 0016 0869
            RAU UNITY                DID WE       0869  60 0550 1305
            SLT  0001                PROCESS      1305  35 0001 0511
            SUP  8001                MORE THAN    0511  11 8001 0919
            SUP ATMCT                TEN ATOMS    0919  11 0560 0965
            BMI          PV017                    0965  46 0018 0969
            HLT  4444    6666        TOO MANY     0018  01 4444 6666
     PV017  STU COUNT    PV019       SET SOLIDS   0969  21 0024 0776
 1                                   COUNTER
     PV019  RAU R0010                NO IS THIS   0776  60 1960 1015
            SRT  0001                MOLECULE     1015  30 0001 0771
            RAL  8002                CONDENSED    0771  65 8002 0529
            NZE          PV023                    0529  45 0832 0533
            RAU COUNT                YES MAY WE   0832  60 0024 0579
            NZU PV024                PROCESS IT   0579  44 0583 0084
            HLT  5555    5555        NO           0084  01 5555 5555
```

E-417

E-417

```
501    PV024   SUP UNITY              YES         0583  11 0550 1355
502            STU COUNT   PV023                  1355  21 0024 0533
503    PV023   RAU R0005              IS MOLCULE  0533  60 1955 1059
504            NZU         PV025      MORE THAN   1059  44 0563 0064
505 1                                 15 PLACES
506            HLT  6666    4444      YES         0563  01 6666 4444
507    PV025   RAL R0002                          0064  65 1952 1157
508            NZE PV031                          1157  45 0910 0561
509            HLT  7777    3333      NO MOLCULE  0561  01 7777 3333
510    PV031   RAU CNTR1              CLEAR DATA  0910  60 0713 0567
511            STU CNTRX              ADDRESS     0567  21 0772 0825
512            STL TEMP1   PV032      SET ZERO    0825  20 9001 0882
513    PV032   RAL R0002              IS PRODUCT  0882  65 1952 1207
514            NZE         PV115      FINISHED    1207  45 0960 0711
515            SLT  0001              NO          0960  35 0001 0717
516            SUP NINE1                          0717  11 0020 0875
517            NZU LETTR   NUMBR                  0875  44 0729 0780
518    LETTR   LDD PV032   PV033                  0729  69 0882 0885
519    PV033   STD LINK                           0885  24 0838 0991
520            RAL R0002                          0991  65 1952 1257
521            AUP TEMP1                          1257  10 9001 1065
522            SLT  0002                          1065  35 0002 0821
523            STU TEMP1                          0821  21 9001 0779
524            STL R0002                          0779  20 1952 1405
525            RAU CNTRX                          1405  60 0772 1377
526            AUP TWO D                          1377  10 0830 0935
527            STU CNTRX   LINK                   0935  21 0772 0838
528 1
529    NUMBR   LDD PV034   PV033                  0780  69 0733 0885
530    PV034   RAU TEMP1                          0733  60 9001 1041
531            SRT  0002   PV087                  1041  30 0002 0747
532    PV087   SLO NINE               STORE       0747  16 0750 1455
533            SLO  8002              MAGNITUDE   1455  16 8002 0763
534            STD MAGNI              OF THE      0763  24 0066 1019
535            SCT  0000              COMPONENT   1019  36 0000 1091
536            STU COMPO   PV089                  1091  21 0796 0999
537    PV089   RAL A000X              SEARCH      0999  65 1550 0856
538            LDD PV091              SYMBOL      0856  69 1109 0012
539            SDA PV091    8001      TABLE FOR   0012  22 1109 8001
540 1                                 COMPONENT
541    PV091   RAL A0001   PV093                  1109  65 0001 0956
542    PV093   NZE         PV095                  0956  45 1010 0761
543            SRT  0001                          1010  30 0001 0767
544            SLT  0001                          0767  35 0001 0823
545            SLO COMPO                          0823  16 0796 0751
546            NZE         PV097                  0751  45 0354 1006
547            RAL PV091              ADVANCE     0854  65 1109 0813
548            ALO ONE D              ONE PLACE   0813  15 0516 0871
549            STL PV091    8001      ALONG       0871  20 1109 8001
550 1                                 TABLE
551    PV095   HLT  8888    2222      NOT IN      0761  01 8888 2222
552 1                                 TABLE
553    PV097   RAL PV091              GOT THE     1006  65 1109 0863
554            LDD PV099              RIGHT ONE   0863  69 0566 1069
555            SDA PV099    8001                  1069  22 0566 8001
556    PV099   RAU A0001   PV100      ADD IT TO   0566  60 0001 1056
557    PV100   SRT  0001              REST OF     1056  30 0001 0913
558            ALO MAGNI              PACKED      0913  15 0066 0921
559            SUP  8003              VECTOR IN   0921  11 8003 0829
560            AUP P0007              P0007       0829  10 1983 0087
561            SLT  0002                          0087  35 0002 0743
562            STU P0007                          0743  21 1983 0736
563            RAL R0003   CNTRX      SHIFT       0736  65 1953 0772
564    CNTRX   SLT XXXXX   PV101      WORD 3      0772  35 0000 0845
565 1
566    PV101   AUP R0002                          0845  10 1952 1307
567            STU R0002                          1307  21 1952 1106
568            STL R0003                          1106  20 1953 1156
569 1
570            RAL CNTRX              CNTRY DATA  1156  65 0772 1427
571            LDD CNTR2              ADRES SAME  1427  69 0880 0783
572            SDA CNTRY              AS CNTRX    0783  22 0737 0840
573 1
574            RAL R0004   CNTRY      SHIFT       0840  65 1954 0737
575    CNTRY   SLT XXXXX   PV102      WORD 4      0737  35 0000 1159
576    PV102   AUP R0003                          1159  10 1953 1357
577            STU R0003                          1357  21 1953 1206
578            STL R0004   PV031                  1206  20 1954 0910
579    PV115   RAU R0010                          0711  60 1960 1115
580            SRT  0001                          1115  30 0001 0971
581            RAU  8002                          0971  60 8002 0879
582            NZU         PV116      A SIGN FOR  0879  44 0833 0586
583            RSU P0007              THE PACKED  0833  61 1983 0787
584            STU P0007   PV116      VECTOR      0787  21 1983 0586
585    PV116   LDD 83RD                           0586  69 0389 0842
586            STD P0010   PNCH                   0842  24 1986 0039
587    PNCH    PCH P0001   READ       PUNCH CARD  0039  71 1977 0019
```

```
                     CONSTANTS FOR PACKED VECTOR
                             ROUTINE

      UNITY     00  0000      0001                     0550  00 0700 0001
      ONE D     00  0001      0000                     0516  00 0001 0000
      TWO D     00  0002      0000                     0830  00 0002 0000
      NINEI     00  0000      0009                     0020  00 0000 0009
      NINE      90  0000      0000                     0750  90 0000 0000
      STORE     STL A0001     PACKA                    0744  20 0001 0754
      A000X     00 A0001      0000                     1550  00 0001 0000
      CNTR1     SLT  0000     PV101                    0713  35 0000 0845
      CNTR2     SLT  0000     PV102                    0880  35 0000 1159
      83RD      00  0000      0800                     0889  00 0000 0800



                     ROUTINE FOR STORINGS FUELS AND
                          OXIDANTS

      PV180     RAU RELAY               IF NO          0760  60 0016 1021
                NZU           PV198     MOLECULES      1021  44 0925 0826
                                        IS THIS
                                        FIRST FUEL
                                        OR OXIDANT
                STL RELAY               YES            0925  20 0016 1119
                RAU NINEI               ARE THERE      1119  60 0020 0975
                SUP ATMCT               MORE THAN      0975  11 0560 1165
                BMI           PV198     TEN ATOMS      1165  46 0068 0826
                HLT  9988     9988      YES            0068  01 9988 9988
      PV198     RAU R0002                              0826  60 1952 1407
                NZU PV200               NO LETTERS     1407  44 0811 0062
                HLT  9876     9876      OR NUMBERS     0062  01 9876 9876
      PV200     STL TEMP1               CLER TEMP1     0811  20 9001 0518
                STD TEMP2               CLER TEMP2     0518  24 9002 0074
                STU RELA1               SET NONZRO     0074  21 0078 0881
                RAB  0000     PV201     B IS NUMBR     0881  82 0000 0837
                                        COUNTER
      PV201     RAL R0002               ANY FUEL       0837  65 1952 1457
                NZE           PV220     OR OX LEFT     1457  45 1060 0861
                SLT  0001               YES            1060  35 0001 0817
                SUP NINEI               IS SYMBOL      0817  11 0020 1025
                BMI LETR      NUMR      LET OR NUM     1025  46 0528 0929
      LETR      RAU RELA1               DO WE STOR     0528  60 0078 0883
                NZU           PV221     PREV COEFF     0883  44 0887 0888
                RAL R0002               NO             0887  65 1952 0758
                AUP TEMP1                              0758  10 9001 1215
                SLT  0002                              1215  35 0002 1071
                STU TEMP1     PV209                    1071  21 9001 0979

      PV209     STL R0002                              0979  20 1952 1256
                RSC  0003     PV210     SHIFT          1256  89 0003 0512
      PV210     RAL R0006 C             WORDS 2 3      0512  65 7956 0911
                SLT  0002               4 5 AND 6      0911  35 0002 0867
                AUP R0005 C                            0867  10 7955 1209
                STU R0005 C                            1209  21 7955 0858
                STL R0006 C                            0858  20 7956 1259
                NZC           PV201                    1259  48 0562 0837
                AXC  0001     PV210                    0562  58 0001 0512
      NUMR      STU RELA1               CLER RELA1     0929  21 0078 0931
                AXB  0001               ADD TO CNT     0931  52 0001 0937
                AUP TEMP2                              0937  10 9002 0895
                SLT  0001                              0895  35 0001 0851
                STU TEMP2     PV209                    0851  21 9002 0979
      PV220     LDD PAR 6     PV222                    0861  69 0514 0917
      PV221     LDD PV200     PV222     YES            0888  69 0811 0917
      PV222     STD LINK                               0917  24 0838 1141
                RSC  0009                              1141  89 0009 0797
                RAU TEMP1                              0797  60 9001 1306
                SCT  0000                              1306  36 0000 1029
                STU TEMP1     PV223                    1029  21 9001 0987
      PV223     RAL A0010 C             FIND           0987  65 6010 1265
                SRT  0001               SYMBOL   N     1265  30 0001 1121
                SLT  0001               TABLE          1121  35 0001 1477
                SLO TEMP1                              1477  16 9001 0985
                NZE           PV225                    0985  45 0938 0939
                NZC           PV224                    0938  48 1191 0892
                AXC  0001     PV223                    1191  58 0001 0987
      PV224     HLT  4321     4321      NOT IN         0892  01 4321 4321
                                        TABLE
      PV225     RAU CODE                GENERATE       0939  60 0052 0958
                SLT  0001               STORAGE        0958  35 0001 1315
                SRT  0008               LOCATION       1315  30 0008 0933
                NZU PV227     PV226                    0933  44 1037 0988
      PV226     RAU 100 I     PV227                    0988  60 0076 1037
```

E-417

```
     PV227  AUP  8005                             1037  10 8005 0945
            AUP  8007                             0945  10 8007 0753
            SLT  0004                             0753  35 0004 0963
            AUP MASK1                             0963  10 0716 1171
            STU PV233                             1171  21 0876 1079
            RAU TEN I              IS NUMBER      1079  60 0932 1087
            SUP  8006              OVER TEN       1087  11 8006 0995
            BMI          PV230     DIGITS         0995  46 0048 1049
            HLT  2233     4455     YES ERROR      0048  01 2233 4455
     PV230  NZU          PV231     IS IT TEN      1049  44 0853 0954
            SUP ONE I              NO             0853  11 1356 0961
            NZU PV232              IS IT NINE     0961  44 1365 0766
            HLT  5544     3322     YES ERROR      0766  01 5544 3322
     PV231  RAU TEMP2    PV233                    0954  60 9002 0876
     PV232  RAU TEMP2                             1365  60 9002 0873
            SCT  0000                             0873  36 0000 1045
            AUP  8006                             1045  10 8006 0953
            RAB  0050                             0953  82 0050 1309
            AUP  8006                             1309  10 8006 0967
            SLO  8002    PV233                    0967  16 8002 0876
     PV233  STU XXXXX    LINK                     0876  21 0000 0838
 1
 1
 1             CONSTANTS FOR FUELS AND
 1                  OXIDANTS ROUTINE
 1
     ONE I   00  0000     0001                    1356  00 0000 0001
     NINEI   00  0000     0009                    0020  00 0000 0009
     TEN I   00  0000     0010                    0932  00 0000 0010
     100 I   00  0000     0100                    0076  00 0000 0100
     MASK1  STU  0000    LINK                     0716  21 0000 0838
 1
 1
 1
 1             ROUTINE FOR STORING ENTHALPIES
 1             AND PERCENTS FOR FUELS AND
 1             OXIDANTS
 1
     PAR 1  RAU R0004                             0088  60 1954 1359
            STL TEMPO              CLER TEMPO     1359  20 9000 0816
            NZU ERR 1                             0816  44 1169 0070
     ERR 1  HLT  8888     1111     PARAMETER      1169  01 8888 1111
 1                                 MORE THAN
 1                                 10 FIGURES
            RSB  0001    COLAP                    0070  83 0001 0926
     COLAP  RAC  0005                             0926  88 0005 0982
            RAL R0003 B            COLLAPSE       0982  65 5953 1008
            SLO 90909    PAR 2     NUMBER BY      1008  16 1011 1415
     PAR 2  SLT  0001              REMOVING       1415  35 0001 1221
            AUP TEMPO              NINES          1221  10 9000 1129
            SLT  0001                             1129  35 0001 1035
            STU TEMPO                             1035  21 9000 0793
            SUP  8003                             0793  11 8003 0951
            SXC  0001                             0951  59 0001 1058
            NZC PAR 2                             1058  48 1415 0712
            NZB          PAR 3                    0712  42 1465 0866
            AXB  0001    COLAP                    1465  52 0001 0926
     PAR 3  RAU CODE               GENERATE       0866  60 0052 1108
            SLT  0001              STORAGE        1108  35 0001 0916
            SRT  0009              LOCATION       0916  30 0009 1137
            NZU PAR 5    PAR 4                    1137  44 1241 0942
     PAR 4  RAU TEN I    PAR 5                    0942  60 0932 1241
     PAR 5  AUP  8005                             1241  10 8005 1099
            SLT  0004                             1099  35 0004 1409
            AUP MASK5                             1409  10 0762 1017
            ALO TEMPO     8003                    1017  15 9000 8003
      8003  STL XXXXX    PAR 6                    8003  20 0000 0514
     PAR 6  PCH P0001    READ                     0514  71 1977 0019
 1
 1
 1             CONSTANTS FOR ENTHALPIES AND
 1                  PERCENTS ROUTINE
 1
     TEN I   00  0000     0010                    0932  00 0000 0010
     90909   90  9090     9090                    1011  90 9090 9090
     MASK5  STL  0000    PAR 6                    0762  20 0000 0514
 1
 1
```

```
1
1              ROUTINE TO CALCULATE THE GRAM
1              ATOMS AND ENTHALPIES AND THE
1              OXIDATION NUMBERS PER GRAM OF
1              COMBINED FUEL OR PER GRAM OF
1              COMBINED OXIDANT
1
   END 1   RAA  0010                             0551  80 0010 1158
           RAC  0010                             1158  88 0010 0564
           RAB  0001    END 2                    0564  82 0001 0520
   END 2   RAU  8003                             0520  60 8003 0578
           STL TEMPO    END 3     CLER TEMPO     0578  20 9000 0786
   END 3   RAU L0000 C            ADD ALL        0786  60 6299 1003
           FAD TEMPO              THE FUEL       1003  32 9000 0983
           STU TEMPO              OR OXIDANT     0983  21 9000 1291
           RAU L0000 C            PERCENTS       1291  60 6299 1053
           FDV 10053              AND CONVRT     1053  34 1406 1456
           STU C0010 C            TO FRACTNS     1456  21 9609 1013
           SXA  0001                             1013  51 0001 1219
           NZA          END 4                    1219  40 0822 0923
           SXC  0001    END 3                    0822  59 0001 0786
   END 4   RAU TEMPO              ARE PERCNT     0923  60 9000 0981
           FSB 11051              REALLY         0981  33 0534 1061
           BMI FRACT    PRCNT     FRACTIONS      1061  46 0714 0966
   FRACT   RAU TEMPO    END 5                    0714  60 9000 1271
   PRCNT   SET C0010 C                           0966  27 9609 1321
           SBB L0000 C                           1321  28 6299 0752
           RAU TEMPO                             0752  60 9000 1459
           FDV 10053    END 5                    1459  34 1406 1271
   END 5   FSB 10051                             1271  33 0524 1001
           RAM  8003                             1001  67 8003 1110
           AUP 47  I                             1110  10 1063 1067
           SUP  8002                             1067  11 8002 1075
           BMI          END 6                    1075  46 0728 1179
           HLT   1111    1111     PERCENTS       0728  01 1111 1111
1                                 OUT OF
1                                 LIMITS
   END 6   NZB          MW  1                    1179  42 1032 1033
           SXB  0001                             1032  53 0001 1038
           RAA  0010                             1038  80 0010 0794
           RAC  0020    END 2                    0794  88 0020 0520
1
1
1              LOCATE AND STORE THE REQUIRED
1              OXIDATION NUMBERS AND ATOMIC
1              WEIGHTS
1
1              CONSOLE POSITION 3 IS SET TO 8
1              IF IT IS DESIRED TO PUNCH OUT
1              ATOMIC WEIGHTS AND OXIDATION
1              NUMBERS
1
1
   MW  1   RAA  0000    MW  2     FIND ATOM      1033  80 0000 0989
   MW  2   RAU A0001 A            WEIGHT AND     0989  60 2001 1208
           NZU          DIST3     OXID NO        1208  44 1111 0812
           SRT  0001              OF COLUMN      1111  30 0001 1117
           SLO  8002              ONE            1117  16 8002 1125
           SLT  0001              ELEMENT        1125  35 0001 1031
           ALO MASK6                             1031  15 0584 1039
           LDD  8003                             1039  69 8003 0846
           TLU V0001    MW  3                    0846  84 0600 1258
   MW  3   STL TEMPO     8001                    1258  20 9000 8001
    8001   RAL V00XX    MW  4                    8001  65 0600 1308
   MW  4   SLT  0009                             1308  35 0009 1229
           SUP  8003                             1229  11 8003 1187
           BMI          MW  5                    1187  46 0890 1341
           SLO 51  I    MW  6                    0890  16 0843 0847
   MW  5   ALO 51  I    MW  6                    1341  15 0843 0847
   MW  6   STL S0001 A  MW  7     OXID NO        0847  20 2350 1103
   MW  7   RAL TEMPO                             1103  65 9000 1161
           SLO 200 D                             1161  16 0764 1269
           LDD MASK7                             1269  69 0872 1175
           SDA TEMPO     8001                    1175  22 9000 8001
    8001   LDD M00XX    MW  8                    8001  69 0400 1153
   MW  8   STD W0001 A            ATOMIC WT      1153  24 2340 0893
           AXA  0001    MW  2     NEXT ELMT      0893  50 0001 0989
1
   DIST3   LDD  8000                             0812  69 8000 0568
           BD3          AR  1                    0568  93 1371 0973
           RAL SPEC6                             1371  65 0574 1279
           LDD AR  1    PUNCH                    1279  69 0973 1930
   SPEC6    00 W0001     0020                    0574  00 0340 0020
1
```

```
     AR  1   RAA  0000                                    0973  80 0000 1329
             RAB  0190                                    1329  82 0190 1085
             RAC  0020     AR  2                          1085  88 0020 1391
     AR  2   SUP  8003                                    1391  11 8003 1149
             STU  TEMPO    AR  3   CLER TEMPO             1149  21 9000 1358
     AR  3   RAU  W0001 A          ATOMIC WT              1358  60 2340 1095
             NZU           AR  4                          1095  44 1199 0850
             FMP  F0001 B          ATOM COEFF             1199  39 4100 0950
             FAD  TEMPO            TEMPO HAS              0950  32 9000 1379
             STU  TEMPO            MOL WT                 1379  21 9000 1237
             AXA  0001                                    1237  50 0001 0943
             AXB  0001                                    0943  52 0001 1249
             SXA  0010                                    1249  51 0010 1408
             NZA           AR 29                          1408  40 1211 0862
             AXA  0010     AR  3                          1211  50 0010 1358
     AR 29   AXA  0010     AR  4                          0862  50 0010 0850
     AR  4   RAU  L0000 C          CALCULATE              0850  60 6299 1203
             NZU           AR 30   NUMBER OF              1203  44 1458 1160
             FDV  TEMPO    AR 30   MOLES OF               1458  34 9000 1160
     AR 30   STU  N0000 C          EACH FUEL              1160  21 6359 0912
             SXB  2010             OR OXIDANT             0912  53 2010 1319
             BMB  AR  5            WHICH GIVE             1319  43 0922 1023
             RAA  0000             1 GRAM OF              1023  80 0000 1429
             SXC  0001     AR  2   COMBINED               1429  59 0001 1391
 1                             FUEL AND 1 GRAM OF
 1                             COMBINED OXIDANT
     AR  5   RAU  10051                                   0922  60 0524 1479
             STU  RELAY                                   1479  21 0016 1369
             SET  9030                                    1369  27 9030 0724
             LBB  H0001            FUEL ENTH              0724  08 0320 1073
             SET  9050                                    1073  27 9050 0778
             LDB  N0001            FUEL MOLES             0778  09 0360 1113
             SET  9040             CLEAR 904              1113  27 9040 0718
             LBB  0090             BAND                   0718  08 0090 0993
             RSA  0009                                    0993  81 0009 1299
             RAB  0000                                    1299  82 0000 1210
             RAC  0000     AR  6                          1210  88 0000 1016
     AR  6   SUP  8003                                    1016  11 8003 1123
             STU  TEMPO    AR  7   CLER TEMPO             1123  21 9000 1081
     AR  7   RAU  9059 A           MOLES                  1081  60 9259 1089
             FMP  F0001 B          ATOM COEFF             1089  39 4100 1000
             FAD  TEMPO                                   1000  32 9000 0930
             STU  TEMPO                                   0930  21 9000 1287
             BMA           AR  8                          1287  41 0940 1441
             AXA  0001                                    0940  50 0001 0896
             AXB  0010     AR  7                          0896  52 0010 1081
     AR  8   STU  9040 C           9040 TO                1441  21 9640 1349
             RAU  A0002 C          9049                   1349  60 6002 1260
             NZU           AR  9   CONTAIN                1260  44 1163 0814
             RSA  0009             ATOMS PER              1163  81 0009 1419
             SXB  0089             GRAM OF                1419  53 0089 1225
             AXC  0001     AR  6   FUEL OR                1225  58 0001 1016
 1                                 OXIDANT
     AR  9   SUP  8003                                    0814  11 8003 1421
             STU  TEMPO            CLER TEMPO             1421  21 9000 0980
             STD  TEMP1            CLER TEMP1             0980  24 9001 0836
             STD  TEMP2            CLER TEMP2             0836  24 9002 0992
             RSA  0009     AR 10                          0992  81 0009 0748
     AR 10   RAU  S0010 A                                 0748  60 2359 1213
             FMP  9049 A           PLUS AND               1213  39 9249 1066
             BMI           AR 11   MINUS                  1066  46 1469 0570
             FAD  TEMP1            VALENCES               1469  32 9001 1399
             STU  TEMP1    AR 12   PER GRAM               1399  21 9001 1310
     AR 11   FAD  TEMPO            OF FUEL                0570  32 9000 1449
             STU  TEMPO    AR 12   OR OXIDANT             1449  21 9000 1310
     AR 12   BMA           AR 13                          1310  41 1263 0864
             AXA  0001     AR 10                          1263  50 0001 0748
     AR 13   RSA  0009     AR 14                          0864  81 0009 0720
     AR 14   RAU  9059 A           ENTHALPY               0720  60 9259 0828
             FMP  9039 A           PER GRAM               0828  39 9239 1131
             FAD  TEMP2            OF FUEL                1131  32 9002 1261
             STU  TEMP2            OR OXIDANT             1261  21 9002 0770
             BMA           AR 15                          0770  41 1173 0774
             AXA  0001     AR 14                          1173  50 0001 0720
     AR 15   RAU  RELAY                                   0774  60 0016 1471
             NZU           PCH O                          1471  44 1275 0976
             STL  RELAY    PCH F                          1275  20 0016 0820
     PCH F   SET  9040             PUNCH                  0820  27 9040 1325
             SBB  0587             ATOMS AND              1325  28 0587 0990
             RAL  SPEC1            ENTHALPY               0990  65 1043 0897
             LDD           RMPCH   AND VALENC             0897  69 1050 1940
             SET  9000             PER GRAM               1050  27 9000 1360
             STB  0598             OF FUEL                1360  29 0598 1051
             LDD  TEMP2                                   1051  69 9002 1410
             STD  0597                                    1410  24 0597 1100
             RAL  SPEC2                                   1100  65 1253 1460
             LDD           RMPCH                          1460  69 1313 1940
```

```
               SET  9030                OXIDANT      1313  27 9030 0768
               LBB  E0001               ENTHALPIES   0768  08 0330 1083
               SET  9050                OXIDANT      1083  27 9050 1088
               LDB  N0011               MOLES        1088  09 0370 1223
               SET  9040                CLEAR 904    1223  27 9040 0878
               LBB  0090                BAND         0878  08 0090 1093
               RSA  0009                             1093  81 0009 1499
               RAB  0100                             1499  82 0100 1311
               RAC  0000     AR  6                   1311  88 0000 1016
       PCH 0   SET  9040                PUNCH        0976  27 9040 1181
               SBB  0537                ATOMS AND    1181  28 0537 1040
               RAL  SPEC3               ENTHALPY     1040  65 1143 0947
               LDD           RMPCH      AND VALENC   0947  69 1150 1940
               SET  9000                PER GRAM     1150  27 9000 1361
               STB  0548                OF OXIDANT   1361  29 0548 1101
               LDD  TEMP2                            1101  69 9002 1411
               STD  0547                             1411  24 0547 1200
               RAL  SPEC4                            1200  65 1303 1461
               LDD  FINIS    RMPCH                   1461  69 0914 1940
 1                CONSTANTS FOR CALCULATING
 1                      ROUTINE
 1
       MASK6   RAL  0000     MW  4                   0584  65 0000 1308
       MASK7   LDD  0000     MW  8                   0872  69 0000 1153
       47  I   00   0000     0047                    1063  00 0000 0047
       51  I   00   0000     0051                    0843  00 0000 0051
       200 D   00   0200     0000                    0764  00 0200 0000
       10053   10   0000     0053                    1406  10 0000 0053
       11051   11   0000     0051                    0534  11 0000 0051
       10051   10   0000     0051                    0524  10 0000 0051
       FINIS   HLT  9999     9999       END PROGRM   0914  01 9999 9999
       SPEC1   00   0587     0010                    1043  00 0587 0010
       SPEC2   00   0597     0003                    1253  00 0597 0003
       SPEC3   00   0537     0010                    1143  00 0537 0010
       SPEC4   00   0547     0003                    1303  00 0547 0003
 1
 1                ROCKET PACKAGE EXCERPT FOR
 1                VECTOR AND PROPELLANTS PROGRAM
 1
               BLA  1500     1999
               BLR  0000     1499
 1
 1                OUTPUT ROUTINE
 1                PUNCH BELL CARDS
 1
               REG  C9050    9050
               REG  J1991    1996
               REG  K1965    1970
               REG  P1977    1986
               SYN  J000N    1990
               SYN  PROB     1864
               EQU  LOC      0000
 1
       PUNCH   STD  LINK                START HERE   1930  24 0838 1541
               LDD  8003                             1541  69 8003 1548
               SDA  C0005               1ST WORD     1548  22 9054 1504
               SLT  0004                             1504  35 0004 1515
               SDA  C0006               NUMBER WDS   1515  22 9055 1522
               SRT  0002                             1522  30 0002 1529
               RAU  8003                             1529  60 8003 1537
               SRT  0002                             1537  30 0002 1543
               SET  C0007                            1543  27 9056 1598
               LDD  WDCT6                            1598  69 1501 1554
               STD  P0009                            1554  24 1985 1538
               LDD  PROB                             1538  69 1864 1517
               STD  P0008                            1517  24 1984 1587
               LDD  C0005    PCH3                    1587  69 9054 1593
       PCH3    STD  P0007                            1593  24 1983 1536
               ALO  CARDN                            1536  15 1539 1643
               ALO  ONE D                            1643  15 0516 1521
               SDA  CARDN                            1521  22 1539 1542
               STL  P0010    NZERO                   1542  20 1986 1589
       NZERO   RAU  C0006               IS NO OF     1589  60 9055 1547
               SUP  WDCT6               WORDS LESS   1547  11 1501 1505
               BMI  LESS6    PCH4                    1505  46 1508 1509
       PCH4    STU  C0006                            1509  21 9055 1567
               RAU  P0009                            1567  60 1985 1639
               SRT  0004                             1639  30 0004 1549
               AUP  XMOVE               SET TO MOV   1549  10 1502 1507
               ALO  XLOC                 N WORDS     1507  15 1510 1565
               ALO  C0005    MOVEW                   1565  15 9054 1523
```

```
MOVEW   AUP 09999    8002                       1523  10 1526 8002
 8002   LDD LOC      8003                       8002  69 0000 8003
 8003   STD P0007    J000N                      8003  24 1983 1990
J0000   RAU C0006    PCH2                       1990  60 9055 1597
J0001   RAU C0006    PCH2                       1991  60 9055 1597
J0002   ALO ONE D    MOVEW                      1992  15 0516 1523
J0003   ALO ONE D    MOVEW                      1993  15 0516 1523
J0004   ALO ONE D    MOVEW                      1994  15 0516 1523
J0005   ALO ONE D    MOVEW                      1995  15 0516 1523
J0006   ALO ONE D    MOVEW                      1996  15 0516 1523
PCH2    PCH P0001                               1597  71 1977 1527
        NZE          LINK       IS IT DONE      1527  45 1530 0838
        RAU P0007                               1530  60 1983 1637
        AUP P0009                               1637  10 1985 1689
        STU C0005    PCH3                       1689  21 9054 1593

LESS6   RAL C0006                               1508  65 9055 1615
        STD P0009                               1615  24 1985 1588
        SRT  0004               CLEAR ZERO      1588  30 0004 1599
        ALO XCLER    8002                       1599  15 1552 8002
 8002    00  0000    K0001                      8002  00 0000 1965
K0001   STU P0001    K0002                      1965  21 1977 1966
K0002   STU P0002    K0003                      1966  21 1978 1967
K0003   STU P0003    K0004                      1967  21 1979 1968
K0004   STU P0004    K0005                      1968  21 1980 1969
K0005   STU P0005    K0006                      1969  21 1981 1970
K0006   STU P0006    PCH4                       1970  21 1982 1509

XCLER    00  0000    K0001                      1552  00 0000 1965
WDCT6    00  0006     0000                      1501  00 0006 0000
 9999    00  0000     9999                      1526  00 0000 9999
XLOC    LDD  0000     8003                      1510  69 0000 8003
XMOVE   STD P0000    J0001                      1502  24 1976 1991
CARDN    00  0000     0000                      1539  00 0000 0000
ONE D    00  0001     0000                      0516  00 0001 0000


           OUTPUT ROUTINE
           RANDOM LOCATION CARDS WITH
           ZERO VALUES OMITTED

        REG C9050    9050
        REG L1841    1844
        REG P1977    1986
        REG 01845    1845
        SYN LOC      0000

RMPCH   STD LINK                                1940  24 0838 1591
        LDD  8006               SAVE INDEX      1591  69 8006 1647
        STD C0003                ACC B AND      1647  24 9052 1503
        LDD  8007                C              1503  69 8007 1559
        STD C0004                               1559  24 9053 1665
        RAC  8002               NO OF WDS       1665  88 8002 1573

        LDD  8003                               1573  69 8003 1580
        SDA C0005               1ST WORD        1580  22 9054 1586
        SLT  0004                               1586  35 0004 1697
        SDA C0006               NUMBER WDS      1697  22 9055 1604
        SRT  0002                               1604  30 0002 1511
        RAU  8003                               1511  60 8003 1519
        SRT  0002                               1519  30 0002 1525
        SET C0007                               1525  27 9056 1630
        LBB L0001               C0004 IS        1630  08 1841 1544
        STL C0006                COL 80         1544  20 9055 1602
        RSB  0004                LOCATION       1602  83 0004 1558
        RAL C0005                               1558  65 9054 1715
        ALO PCHX     ENT1       C0003 IS        1715  15 1518 1623
ENT1    STL C0005                CURRENT        1623  20 9054 1680
                                 LOCATION
        ALO XRAU     8002                       1680  15 1533 8002
 8002   RAU LOC      00001                      8002  60 0000 1845
00001   NZU MOVER    C0007      C0007 HAS       1845  44 1649 9056
                                 L0001
L0001   SXC  0001                               1841  59 0001 1747
        NZC          FINS                       1747  48 1500 1551
        RAL C0005                               1500  65 9054 1557
        ALO ONE D    ENT1                       1557  15 0516 1623
```

```
1079   MOVER   STD P0005 B            MOVE WD      1649  24 5981 1534
1080           RAL C0005                           1534  65 9054 1641
1081           STD P0010 B                         1641  24 5986 1739
1082           NZB            PCH5    IS CARD      1739  42 1592 1693
1083           AXB  0001      C0007    FULL YET    1592  52 0001 9056
1084   PCH5    BMI            PLUS                 1693  46 1546 1797
1085           SLO C0006      BOTH    FIX COL 8    1546  16 9055 1553
1086   PLUS    ALO C0006      BOTH                 1797  15 9055 1553
1087   BOTH    STL P0010                           1553  20 1986 1789
1088           RAL RMCDN              NUMBER CDS   1789  65 1642 1847
1089           ALO ONE I                           1847  15 1356 1561
1090           STL RMCDN                           1561  20 1642 1545
1091           LDD P0009                           1545  69 1985 1638
1092           SIA P0009                           1638  23 1985 1688
1093           PCH P0001              PUNCH CARD   1688  71 1977 1577
1094           RSB  0004      C0008   C0008 HAS    1577  83 0004 9057
1095   L0002   STU C0006      C0007     L0002      1842  21 9055 9056
1096 1
1097   ONE D   00   0001       0000                0516  00 0001 0000
1098   ONE I   00   0000       0001   ONE INSTR    1356  00 0000 0001
1099   XRAU    59   9999      02001                1533  59 9999 3845
1100   PCHX    00   0000       8000                1518  00 0000 8000
1101   RMCDN   00   0000       0000   RANDOM CD    1642  00 0000 0000
1102 1                                 NUMBER
1103   FINS    SET C0007              CHANGE       1551  27 9056 1506
1104           LBB L0003               ORDERS      1506  08 1843 1596
1105           RSL PCHX                FOR FINS    1596  66 1518 1673
1106           STL C0005      C0007                1673  20 9054 9056
1107   L0003   LDD  8003      MOVER                1843  69 8003 1649
1108   L0004   RAB C0001              RESTOR       1844  82 9050 1652
1109           RAC C0002      LINK     INDX ACC    1652  88 9051 0838
1110           PAT
```

E-417

APPENDIX I

533 CONTROL PANEL ("ROCKET BOARD") WIRING INSTRUCTIONS

I. Read card C is used for reading Bell format cards. The word positions are numbered from the right (see 650 Manual of Operation, p. 10):

Read card C (card column)	Storage entry C	Word size entry C
11	Sign of word 1	
12-21	Word 1, positions 10 to 1	10
22	Sign of word 2	
23-32	Word 2, positions 10 to 1	10
33	Sign of word 3	
34-43	Word 3, positions 10 to 1	10
44	Sign of word 4	
45-54	Word 4, positions 10 to 1	10
55	Sign of word 5	
56-65	Word 5, positions 10 to 1	10
66	Sign of word 6	
67-76	Word 6, positions 10 to 1	10
6-9	Word 7, positions 8 to 5, emit sign +	8
5, 77-79	Word 8, positions 8 to 5, emit sign +	8
80, 1-4	Word 9, positions 9 to 5, emit sign +	9
10	Word 10, position 5, emit sign +; positions 4 to 1 of words 7, 8, 9, and 10 wired to emit zero	5

II. Read card B is used for reading Random location format cards:

Read card B (card column)	Storage entry B	Word size entry B
5-15	Word 1, positions 10 to 1, col. 15 is sign	10
20-30	Word 2, positions 10 to 1, col. 30 is sign	10
35-45	Word 3, positions 10 to 1, col. 45 is sign	10
50-60	Word 4, positions 10 to 1, col. 60 is sign	10
65-75	Word 5, positions 10 to 1, col. 75 is sign	10
1-4	Word 6, positions 8 to 5, emit sign +	8
16-19	Word 7, positions 8 to 5, emit sign +	8
31-34	Word 8, positions 8 to 5, emit sign +	8
46-49	Word 9, positions 8 to 5, emit sign +	8
61-64	Co-selector 1 transferred points (U, 1 to 4)(make col. 61 a split wire, p. 119)	
76-80	Not wired Words 6 to 9 emit zero into positions 4 to 1	

E-417

Selector wiring for determining and entering the word count in word 10 and ensuring that word 10 is a legitimate word is as follows:

Co-selector 1 common (W, 1 to 4) to word 10, positions 8 to 5 storage entry B
Word size of word 10. entry B is 8
Co-selector 1 normal (V, 1 to 4), to (V, 32). (This guarantees a nonzero value on word 10 to preserve the negative sign for a branch on minus test.)
Emit zeros to word 10, positions 4 to 2, storage entry B
Emit sign of word 10 minus (V, 28)
Pilot selector 1 common (K, 23) to word 10, position 1, storage entry B
Pilot selector 1 normal (J, 23) to emit zero
Pilot selector 1 transferred (H, 23) to pilot selector 2 common (K, 24)

Pilot selector 2 transferred (H, 24) to pilot selector 3 common (K, 25)
Pilot selector 3 normal (J, 25) to emit 2 (W, 21)
Pilot selector 3 transferred (H, 25) to pilot selector 4 common (K, 26)
Pilot selector 4 normal (J, 26) to emit 3 (X, 21)
Pilot selector 4 transferred (H, 26) to pilot selector 5 common (K, 27)
Pilot selector 5 normal (J, 27) to emit 4 (Y, 21)
Pilot selector 5 transferred (H, 27) to emit 5 (Z, 21)
Pilot selector 2 normal (J, 24) to emit 1 (V, 21)
First reading col. 1 (A, 23) to load (B, 21)
First reading col. 1 (A, 23) to common of col. split (Z, 34) } split wire
Col. split 0-9 (Y, 34) to D pick pilot selector 1 (F, 23)

Co-selector 3 pick (R, 25) to col. split 12-X (X, 34)
Co-selector 3 common (W, 11) to emit 9 (W, 34)
Co-selector 3 transfer (U, 11) to entry B (D, 21)

First reading col. 16 (A, 38) to D pick pilot selector 2 (F, 24)
First reading col. 31 (C, 33) to D pick pilot selector 3 (F, 25)
First reading col. 46 (C, 28) to D pick pilot selector 4 (F, 26) (Split wire, p. 120)
First reading col. 61 (D, 23) to D pick pilot selector 5 (F, 27)
Couple pilot selector 5 (G, 27) to co-selector pickup 1 (S, 23)

Digit impulse (Q, 21) to digit selector common (R, 21)
First reading col. 15 (A, 37) to col. split 12-X (X, 33)
Col. split common (Z, 33) to entry B (D, 22)

Hold for pilot selectors 1 to 5 (P, 23 to 27) and co-selectors 1 and 3 (U, 23 and 25) are wired to read hold (T, 39).

III. Read card A is used to read input cards (SOAP II format) for Vector and Propellant Program (requires the alphabetic attachment and pilot selectors 11, 12, 13):

First reading col. 3 (A, 25) to col. split common (Z, 35)
Col. split 12-X (X, 35) to entry A (C, 22)
Entry A (C, 23) to pilot selector 12-X pick (E, 34)
Pilot selector 12 couple exit (G, 34) to alphabetic control WI (AL, 12) and also to W2 to W6.

Storage entry A, word 10, position 3 (J, 19) to pilot selector 13 common (K, 35)
Pilot selector 13 normal (J, 35) to zero read impulse (AN, 20)
Pilot selector 13 transfer (H, 35) to read card A, col. 41 (C, 1)
Pilot selector 13 D pick (F, 35) to first reading col. 41 (C, 23)
Storage entry A, word 10, position 2 (J, 20) to pilot selector 13 common (N, 35)
Pilot selector 13 normal (M, 35) to zero read impulse (AP, 20)
Pilot selector 13 transfer (L, 35) to read impulse 9 (V, 34)
Storage entry A, word 10, position 1 (J, 21) to pilot selector 11 common (N, 33)
Pilot selector 11 normal (M, 33) to zero read impulse (AP, 21)
Pilot selector 11 transfer (L, 33) to read impulse 8 (V, 33)
Pilot selector 11 D pick (F, 33) to first reading, col. 42 (C, 24)
Read card A, col. 43 (C, 3) to storage entry A, word 1, position 5 (E, 6)
Read card A, col. 44 to 47 (C, 4 to 7) split wire to word 1, positions 4 to 1 (E, 7 to 10) and to word 7, positions 4 to 1 (H, 7 to 10)
Read card A, col. 48 to 50 (C, 8 to 10) to word 4, positions 5 to 3 (F, 17 to 19)
Read card A, col. 51 (C, 11) to word 2, position 5 (E, 17)
Read card A, col. 52 to 55 (C, 12 to 15) split wire to word 2, positions 4 to 1 (E, 18 to 21) and to word 8, positions 4 to 1 (H, 18 to 21)
Read card A, col. 56 (C, 16) to word 4, position 2 (F, 20)
Read card A, col. 57 (C, 17) to word 3, position 5 (F, 6)
Read card A, col. 58 to 61 (C, 18 to D, 1) split wire to word 3, positions 4 to 1 (F, 7 to 10) and to word 9, positions 4 to 1 (J, 7 to 10)
Read card A, col. 62 (D, 2) to word 4, position 1 (F, 21)
Read card A, col. 63 to 67 (D, 3 to 7) to word 5, positions 5 to 1 (G, 6 to 10)
Read card A, col. 68 to 72 (D, 8 to 12) to word 6, positions 5 to 1 (G, 17 to 21)
First reading, col. 43 to 47 (C, 25 to 29) to alphabetic first read, word 1, positions 5 to 1 (AK, 13 to 17)
Col. 48 to 50 (C, 30 to 32) to alphabetic first read, word 4, positions 5 to 3 (AL, 18 to 20)
Col. 51 to 55 (C, 33 to 37) to alphabetic first read, word 2, positions 5 to 1 (AK, 18 to 22)
Col. 56 (C, 38) to alphabetic first read, word 4, position 2 (AL, 21)
Col. 57 to 61 (C, 39 to D, 23) to alphabetic first read, word 3, positions 5 to 1 (AL, 13 to 17)
Col. 62 (D, 24) to alphabetic first read, word 4, position 1 (AL, 22)
Col. 63 to 67 (D, 25 to 29) to alphabetic first read, word 5, positions 5 to 1 (AM, 13 to 17)
Col. 68 to 72 (D, 30 to 34) to alphabetic first read, word 6, positions 5 to 1 (AM, 18 to 22)

E-41

Read validity check wire off (AR, 43) to (AR, 44)
Chain wire pilot selector hold of pilot selectors 11, 12, and 13 (P, 33 to 35) to read hold (T, 39)
Word size entry A, words 7 to 9 (AL, 7 to 9) to word size emitter 4 (AK, 5)
Word size entry A, word 10 (AL, 10) to word size emitter 3 (AK, 4)

IV. Punch card C is used to punch Bell format cards and Trace format cards:

Punch card C (card column)	Storage exit C
11	Sign of word 1
12-21	Word 1, positions 10 to 1
22	Sign of word 2
23-32	Word 2, positions 10 to 1
33	Sign of word 3
34-43	Word 3, positions 10 to 1
44	Sign of word 4
45-54	Word 4, positions 10 to 1
55	Sign of word 5
56-65	Word 5, positions 10 to 1
66	Co-selector 7 common (W, 59) Co-selector 7 normal (V, 59) to word 6 sign (AG, 64)(Split wire, see Trace cards)
67	Word 6, position 10
68-72	Co-selectors 6 and 7 common (W, 54 to 58) Co-selectors 6 and 7 normal (W, 54 to 58) to word 6, positions 9 to 5
73-76	Word 6, positions 4 to 1
6-9	Co-selector 6 common (W, 50 to 53) Co-selector 6 normal (V, 50 to 53) to word 7, positions 8 to 5
5, 77-79	Word 8, positions 8 to 5
10	Word 9, position 5
80, 1-4	Word 10, positions 9 to 5

For Trace cards:
Co-selector 6 transfer (U, 50 to 53) to word 7, positions 4 to 1
Co-selectors 6 and 7 transfer (U, 54 to 57) to word 8, positions 4 to 1
Co-selector 7 transfer (U, 58) to word 6, sign position
Co-selector 7 transfer (U, 59) to word 8, sign position

An 8 in position 9 of word 10 causes Trace cards to be punched by means of control information:

Control information (AM, 56) to co-selectors 6 and 7 pick (R, 28, 29)
Co-selectors 6 and 7 hold (T, 28, 29) to punch hold (R, 39)
Jack plug "P+" (V, 42) to (W, 42)

E-417

CA-16 back

V. Punch card B is used to punch Random location cards:

Punch card B (card column)	Storage exit B
5-15	Word 1, positions 10 to 1, col. 15 is sign
20-30	Word 2, positions 10 to 1, col. 30 is sign
35-45	Word 3, positions 10 to 1, col. 45 is sign
50-60	Word 4, positions 10 to 1, col. 60 is sign
65-75	Word 5, positions 10 to 1, col. 75 is sign
1	Pilot selector 6 common (K, 28) Pilot selector 6 normal (J, 28) to word 6, position 8
2-4	Word 6, positions 7 to 5
16	Pilot selector 7 common (K, 29) Pilot selector 7 normal (J, 29) to word 7, position 8
17-19	Word 7, positions 7 to 5
31	Pilot selector 8 common (K, 30) Pilot selector 8 normal (J, 30) to word 8, position 8
32-34	Word 8, positions 7 to 5
46	Pilot selector 9 common (K, 31) Pilot selector 9 normal (J, 31) to word 9, position 8
47-49	Word 9, positions 7 to 5
61	Pilot selector 10 common (K, 32) Pilot selector 10 normal (J, 32) to word 10, position 8
62-64	Word 10, positions 7 to 5
76-79	Word 9, positions 4 to 1
80	Word 10, position 9

Pilot selector 6 I pick (G, 28) to sign word 6
Pilot selector 7 I pick (G, 29) to sign word 7
Pilot selector 8 I pick (G, 30) to sign word 8
Pilot selector 9 I pick (G, 31) to sign word 9
Pilot selector 10 I pick (G, 32) to sign word 10
Co-selector 2 pick (R, 24) to punch X impulse (A, 43)
Co-selector 2 common (W, 6) to punch hold (R, 39)
Co-selector 2 transferred (U, 6) split wire to transfer of pilot selectors 6 to 10 inclusive (L, 28 to 32)
Pilot selectors 6 to 10 common (N, 28 to 32) to pilot selector hold 6 to 10 (Q, 28 to 32)
Co-selector 2 hold (T, 24) to punch hold (S, 39)
Control information 4 (AK, 61) to punch B (D, 43)

E-417

VI. Punch card A is used to punch SOAP II format cards:

E-417

Punch card A (card column)	Storage exit A
1	Col. split common (AM, 52) Col. split 0-9 (AL, 52) to emit 6 (AA, 43) Col. split 12-X (AK, 52) to emit 12 (S, 43); Wire DI (Q, 43) to common (R, 43)
2-6	Emit 9,1,9,5,4, respectively, from punch emitter
7-10	Co-selector 5 common positions 4 to 1 (W, 46 to 49) Co-selector 5 normal positions 4 to 2 (V, 46 to 48) to emit 1,9,5, respectively, from punch emitter Co-selector 5 normal position 1 (V, 49) to col. split common (AM, 45) Col. split 0-9 (AL, 45) to emit 3 Col. split 12-X (AK, 45) to emit 12 (S, 43) Co-selector 5 transfer positions 4 to 2 (U, 46 to 48) to emit 8,0,0, respectively Co-selector 5 transfer position 1 (U, 49) to col. split common (AM, 46) Col. split 0-9 (AL, 46) to emit 3 Col. split 12-X (AK, 46) to emit 12 (S, 43)
11-20	Word 9, positions 10 to 1, wire sign of word 9 to col. 20 with col. split (AM, 47)
21	Emit 2
22	Emit 4
23-26	Word 8, positions 8 to 5
27-29	Emit 8,0,0, respectively
30	Col. split common (AM, 48) Col. split 0-9 (AM, 48) to emit 0 Col. split 12-X (AM, 48) to emit 12
31-40	Word 7, positions 10 to 1, wire sign through col. split to col. 40 and 42
41	Word 8, position 1
42	Sign of word 7
43-47	Word 1, positions 5 to 1
48-50	Word 4, positions 5 to 3
51-55	Word 2, positions 5 to 1
56	Word 4, position 2
57-61	Word 3, positions 5 to 1
62	Word 4, position 1
63-67	Word 5, positions 5 to 1
68-72	Word 6, positions 5 to 1

Control information 2 (AK, 63) to co-selector 5 pick (R, 27)
Control information 3 (AK, 62) to Alpha cut W1 and also chain wire to W2, W3, W4, W5, and W6
3 (AL, 62) to Punch A (C, 43)
Co-selector 5 hold (T, 27) to punch hold (R, 40)

E-417

REFERENCES

1. Traustel, S.: Berechnung von Vergasungsgleichgewichten durch Losung von Zwei Gleichungen mit Zwei Unbekannten. Z.V.D.I., Bd. 88, Dec. 1944, pp. 688-690.

2. Brinkley, Stuart R., Jr.: Note on the Conditions of Equilibrium for Systems of Many Constituents. Jour. Chem. Phys., vol. 14, no. 9, Sept. 1946, pp. 563-564.

3. Brinkley, Stuart R., Jr.: Calculation of the Equilibrium Composition of Systems of Many Constituents. Jour. Chem. Phys., vol. 15, no. 2, Feb. 1947, pp. 107-110.

4. Krieger, F. J., and White, W. B.: A Simplified Method for Computing the Equilibrium Composition of Gaseous Systems. Jour. Chem. Phys., vol. 16, no. 4, Apr. 1948, pp. 358-360.

5. Wenner, Ralph R.: Prediction of Reaction Equilibria. Chem. Eng. Prog., vol. 45, no. 3, Mar. 1949, pp. 194-207.

6. Sachsel, G. F., Mantis, M. E., and Bell, J. C.: A Note on the Calculation of Multicomponent Propellant Gas Compositions. Third Symposium on Combustion and Flame and Explosion Phenomena, The Williams & Wilkins Co. (Baltimore), 1949, pp. 620-623.

7. Winternitz, Paul F.: A Method for Calculating Simultaneous, Homogeneous Gas Equilibria and Flame Temperatures. Third Symposium on Combustion and Flame and Explosion Phenomena, The Williams & Wilkins Co. (Baltimore), 1949, pp. 623-633.

8. Kandiner, Harold J., and Brinkley, Stuart R., Jr.: Calculation of Complex Equilibrium Relations. Ind. and Eng. Chem., vol. 42, no. 5, May 1950, pp. 850-855.

9. Huff, Vearl N., Gordon, Sanford, and Morrell, Virginia E.: General Method and Thermodynamic Tables for Computation of Equilibrium Composition and Temperature of Chemical Reactions. NACA Rep. 1037, 1951. (Supersedes NACA TN's 2113 and 2161.)

10. Martin, Frederick J., and Yachter, Morris: Calculation of Equilibrium Gas Compositions. Ind. and Eng. Chem., vol. 43, no. 11, Nov. 1951, pp. 2446-2449.

11. Kobe, Kenneth A., and Leland, Thomas W.: Calculation of Chemical Equilibrium in Complex Systems. Bur. Eng. Res. Spec. Pub. no. 26, Univ. of Texas, 1954.

12. Martinez, J. S., and Elverum, G. W., Jr.: A Method of Calculating the Performance of Liquid-Propellant Systems Containing the Species C, H, O, N, F, and One Other Halogen - with Tables of Required Thermochemical Properties to 6000° K. Memo. No. 20-121, Jet Prop. Lab, C.I.T., Dec. 6, 1955. (Contract DA-04-495-ORD-18.)

13. Donegan, A. J., and Farber, M.: Solution of Thermochemical Propellant Calculations on a High-Speed Computer. Jet Prop., vol. 26, no. 3, Mar. 1956, pp. 164-171.

14. Brinkley, Stuart R., Jr.: Computational Methods in Combustion Calculations. Vol. II of Combustion Processes - High Speed Aerodynamics and Jet Propulsion, B. Lewis, R. N. Pease, and H. S. Taylor, eds., Princeton Univ. Press, 1956, pp. 64-98.

15. Weinberg, F. J.: Explicit Equations for the Calculation, by Successive Approximations, of Equilibrium Gas Compositions at High Temperatures: the Hydrogen + Carbon + Oxygen and the Hydrogen + Carbon + Oxygen + Nitrogen Systems Without Solid Carbon Formation. Proc. Roy. Soc. (London), ser. A, vol. 241, no. 1224, July 23, 1957, pp. 132-140.

16. McIntire, R. L.: Computers and Thermodynamics. Automatic Control, vol. 8, no. 2, Feb. 1958, pp. 51-55.

17. Chu, S. T.: An Iterative Method of Determining Equilibrium Compositions of Reacting Gases. Jet Prop., vol. 28, no. 4, Apr. 1958, pp. 252-254.

18. White, W. B., Johnson, S. M., and Dantzig, G. B.: Chemical Equilibrium in Complex Mixtures. Jour. Chem. Phys., vol. 28, no. 5, May 1958, pp. 751-755.

19. Hilsenrath, J., Klein, M., and Sumida, D. Y.: Mechanized Computation of Thermodynamic Tables at the National Bureau of Standards: The Calculation of the Equilibrium Composition and Thermodynamic Properties of Dissociated and Ionized Gaseous Systems. Thermodynamic and Transport Properties of Gases, Liquids, and Solids - Symposium on Thermal Properties, ASME and McGraw-Hill Book Co., Inc., 1959, pp. 416-437.

20. Wilkins, Roger L., and Payne, William H.: High Speed Machine Calculation of the Performance of Rocket Propellants Containing N-Elements. Res. Rep. 59-15, Rocketdyne, North Am. Aviation, Inc., Feb. 24, 1959.

21. Fiegenbutz, L. V.: Combustion Charts for High Energy Fuels. II - A Description of General Methods for Calculating Equilibrium Concentrations of Combustion Products. Rep. No. ZR-658-031, Convair, Mar. 2, 1959.

22. Villars, D. S.: A Method of Successive Approximations for Computing Combustion Equilibria on a High Speed Digital Computer. Jour. Phys. Chem., vol. 63, no. 4, Apr. 1959, pp. 521-525.

23. Scarborough, James B.: Numerical Mathematical Analysis. Johns Hopkins Press (Baltimore), 1930, pp. 187-190.

24. Bridgman, P. W.: Condensed Collection of Thermodynamic Formulas. Harvard Univ. Press, Cambridge (Mass.), 1926.

25. Gordon, Sanford, and Huff, Vearl N.: Theoretical Performance of Liquid Hydrazine and Liquid Fluorine as a Rocket Propellant. NACA RM E53E12, 1953.

26. Huff, Vearl N., Turner, Don N., and Reese, Oliver W.: General-Purpose Subroutines for the IBM 650 Magnetic Drum Data-Processing Machine with Attachments. NASA TN D-68, 1959.

E-417

E-417

CA-17

TABLE I. - COEFFICIENTS FOR OBTAINING THERMODYNAMIC DATA FOR SEVERAL SUBSTANCES

[Coefficients for use in equations (105) to (107).]

Substance (a)	Temperature interval, °K	Coefficients					
		A	B	C	D	E	F
C	150 - 300	+2527 8238 51	+1867 6400 47	-2011 9997 45	+3832 8460 42	+1318 3612 56	+4598 3693 51
	300 - 500	+2511 0512 51	+2341 2431 46	-2064 1813 44	+2504 6361 41	+1318 3951 56	+4694 0319 51
	500 - 700	+2505 9144 51	+1127 9624 46	-6304 0443 43	+5333 3424 40	+1318 4070 56	+4722 3131 51
	700 - 1000	+2503 4230 51	+5325 3290 45	-2160 0382 43	+1354 8725 40	+1318 4156 56	+4737 1984 51
	1000 - 1300	+2503 2775 51	+5521 0150 45	-1695 7438 43	+8855 6245 39	+1318 4123 56	+4737 2493 51
	1300 - 1700	+2504 6546 51	+9314 6910 45	-2465 5314 43	+1190 5488 40	+1318 3969 56	+4726 7149 51
	1700 - 2100	+2501 5285 51	+5907 5500 45	-1820 8474 43	+9928 4700 39	+1318 4349 56	+4749 6818 51
	2100 - 2600	+2488 4570 51	-1345 7700 46	+8780 3410 42	+2879 3181 39	+1318 6460 56	+4852 5918 51
	2600 - 3200	+2472 3653 51	-4335 7912 46	+3975 0497 43	-3693 6212 39	+1319 0115 56	+4990 6948 51
	3200 - 3800	+2476 2539 51	-6493 0882 46	+5315 2588 43	-5893 7109 39	+1319 1045 56	+4983 7555 51
	3800 - 4400	+2504 1340 51	-7041 0160 46	+5063 4142 43	-5359 6037 39	+1318 6229 56	+4783 1816 51
	4400 - 5000	+2546 5888 51	-6519 6370 46	+4155 2568 43	-4063 3061 39	+1317 6142 56	+4455 1751 51
	5000 - 6000	+2610 4540 51	-4741 7690 46	+2664 8172 43	-2304 4960 39	+1315 6607 56	+3935 3511 51
Graphite	300 - 500	+5673 0710 50	-2106 2241 48	+1744 0045 46	-1691 9439 43	+4619 0744 55	-2545 1750 51
	500 - 700	+1058 3269 51	-2064 1842 48	+1091 7536 46	-7970 7376 42	+4607 1927 55	-5175 2399 51
	700 - 1000	+1628 3807 51	-1307 2653 48	+5023 1415 45	-2756 8704 42	+4584 8409 55	-8591 5430 51
	1000 - 1300	+2289 3860 51	-3947 4982 47	+9829 2657 44	-2901 7625 41	+4546 1211 55	-1287 2246 52
	1300 - 1700	+2407 1476 51	-4784 1780 47	+1008 1106 45	-3136 4202 41	+4537 7132 55	-1361 1939 52
	1700 - 2100	+2709 5422 51	-2313 1973 47	+3670 0610 44	-8357 2671 40	+4507 5530 55	-1573 1714 52
	2100 - 2600	+2841 4329 51	-1619 7368 47	+2059 3854 44	-3684 0068 40	+4491 5653 55	-1667 5373 52
	2600 - 3200	+2958 2033 51	-1146 5505 47	+1154 2930 44	-1567 2361 40	+4474 0549 55	-1753 4691 52
	3200 - 3800	+3040 3247 51	-9509 5628 46	+7614 5316 43	-7812 3581 39	+4460 0657 55	-1814 4793 52
	3800 - 4400	+3097 3807 51	-9187 9709 46	+6184 4345 43	-5311 4558 39	+4449 1831 55	-1856 9802 52
	4400 - 5000	+3152 7766 51	-8885 2831 46	+5138 2079 43	-3740 3250 39	+4436 8642 55	-1899 1194 52
CCl	150 - 300	+3820 3364 51	+4255 4820 47	-7410 0490 45	+2285 0707 43	+1092 3347 56	+5349 2058 51
	300 - 500	+3693 1871 51	-9241 6910 47	+7775 5823 45	-8061 9700 42	+1092 5828 56	+6074 2136 51
	500 - 700	+3912 5706 51	-7820 0920 47	+4222 7425 45	-3279 9984 42	+1092 0413 56	+4884 6073 51
	700 - 1000	+4115 6696 51	-4342 0958 47	+1693 0522 45	-9680 7557 41	+1091 2721 56	+3666 0743 51
	1000 - 1300	+4271 6614 51	-2203 0847 47	+6118 7076 44	-2567 8708 41	+1090 4684 56	+2678 1140 51
	1300 - 1700	+4378 2291 51	-9382 1810 46	+1978 6630 44	-6167 2272 40	+1089 6529 56	+1956 5236 51
	1700 - 2100	+4428 6744 51	-5606 4340 46	+9129 2970 43	-2231 4653 40	+1089 1732 56	+1606 6487 51
	2100 - 2600	+4461 6643 51	-3393 9946 46	+4422 3777 43	-8479 8548 39	+1088 7729 56	+1368 9058 51
	2600 - 3200	+4484 6128 51	-2289 1842 46	+2381 7346 43	-3571 2362 39	+1088 4376 56	+1199 9462 51
	3200 - 3800	+4500 7379 51	-1781 1588 46	+1497 8228 43	-1797 2303 39	+1088 1620 56	+1079 4739 51
	3800 - 4400	+4513 7299 51	-1439 6338 46	+1005 6037 43	-9752 0000 38	+1087 8935 56	+9798 5788 50
	4400 - 5000	+4522 5949 51	-1319 2912 46	+7941 9120 42	-6609 4577 38	+1087 6927 56	+9117 3280 50
	5000 - 6000	+4532 7490 51	-1122 4142 46	+5808 8556 42	-3943 1880 38	+1087 4110 56	+8309 5849 50
CCl_4	150 - 300	+6883 4230 51	-2183 6856 49	+2209 0207 47	-3765 2673 44	+4132 9670 55	-2005 0830 51
	300 - 500	+8534 3172 51	-7160 8000 48	+6201 5460 46	-7111 6167 43	+4098 5503 55	-1142 3036 52
	500 - 700	+1008 7133 52	-4760 2740 48	+2629 9117 46	-2170 8108 43	+4062 5210 55	-1986 7563 52
	700 - 1000	+1120 9988 52	-2287 4085 48	+9077 1820 45	-5425 6390 42	+4022 5045 55	-2659 6737 52
	1000 - 1300	+1195 6348 52	-1043 2162 48	+2943 6828 45	-1282 6918 42	+3986 5351 55	-3131 0836 52
	1300 - 1700	+1248 4721 52	-3391 1184 47	+7258 7051 44	-2338 0965 41	+3945 8748 55	-3490 8748 52
	1700 - 2100	+1268 0666 52	-1729 2303 47	+2873 9710 44	-7327 1794 40	+3926 8367 55	-3627 8096 52
	2100 - 2600	+1279 3339 52	-8857 1920 46	+1192 5272 44	-2449 6562 40	+3912 7677 55	-3709 6952 52
	2600 - 3200	+1286 1578 52	-4880 6790 46	+5345 6302 43	-8955 1435 39	+3902 3779 55	-3760 5577 52
	3200 - 3800	+1290 2043 52	-3013 4232 46	+2724 8863 43	-3823 6766 39	+3895 0427 55	-3791 3780 52
	3800 - 4400	+1292 8751 52	-1886 0004 46	+1451 7234 43	-1740 7449 39	+3889 1827 55	-3812 2942 52
	4400 - 5000	+1294 5807 52	-1253 5153 46	+8422 0090 42	-8823 9152 38	+3884 8198 55	-3825 9243 52
	5000 - 6000	+1296 2205 52	-6498 6420 45	+3820 8266 42	-3347 9564 38	+3879 6914 55	-3839 4390 52
CF	150 - 300	+3640 0200 51	+8085 8640 47	-1026 9011 46	+2438 4900 43	+1950 6783 56	+4867 6076 51
	300 - 500	+3498 5413 51	-4528 6370 47	+3399 6376 45	-1921 1982 42	+1950 9729 56	+5674 6721 51
	500 - 700	+3597 7497 51	-8040 8130 47	+4156 7731 45	-2824 2658 42	+1950 7415 56	+5176 7255 51
	700 - 1000	+3810 1072 51	-6268 2490 47	+2385 5288 45	-1274 7825 42	+1949 9158 56	+3918 2736 51
	1000 - 1300	+4048 2657 51	-3885 1238 47	+1061 8631 45	-4275 8782 41	+1948 6368 56	+2414 2551 51
	1300 - 1700	+4225 0270 51	-2089 1357 47	+4374 3033 44	-1339 8215 41	+1947 2978 56	+1226 0050 51
	1700 - 2100	+4334 2200 51	-1335 8403 47	+2161 7485 44	-5212 2758 40	+1946 2672 56	+4713 8170 50
	2100 - 2600	+4411 7942 51	-8377 6910 46	+1084 5361 44	-2048 7978 40	+1945 3278 56	-8671 8950 49
	2600 - 3200	+4467 8185 51	-5822 8670 46	+6020 0162 43	-8903 5200 39	+1944 5100 56	-4985 2010 50
	3200 - 3800	+4508 2460 51	-4630 6640 46	+3870 6023 43	-4584 6109 39	+1943 8215 56	-8000 8070 50
	3800 - 4400	+4541 0295 51	-3813 2379 46	+2644 8087 43	-2522 3761 39	+1943 1526 56	-1050 5867 51
	4400 - 5000	+4569 6116 51	-3184 7846 46	+1851 2604 43	-1379 0052 39	+1942 4685 56	-1273 6745 51
	5000 - 6000	+4608 1204 51	-2076 7807 46	+9178 6561 42	-2634 8774 38	+1941 3042 56	-1586 8660 51
CF_2	150 - 300	+4048 5275 51	-2616 5412 48	+2155 8933 46	-2058 6114 43	+6584 7865 55	+5829 4252 51
	300 - 500	+4074 4857 51	-2499 6320 48	+2064 8571 46	-1981 1983 43	+6584 1442 55	+5680 2914 51
	500 - 700	+4691 9175 51	-2394 9638 48	+1263 9499 46	-9151 9648 42	+6568 6792 55	+2347 8274 51
	700 - 1000	+5409 6786 51	-1408 4350 48	+5348 7413 45	-2842 5180 42	+6539 7513 55	-1979 9985 51
	1000 - 1300	+6025 9535 51	-7504 6540 47	+2030 6869 45	-7987 0809 41	+6504 7319 55	-5917 2859 51
	1300 - 1700	+6398 7799 51	-3929 7130 47	+8155 2021 44	-2451 9736 41	+6475 5249 55	-8433 7760 51
	1700 - 2100	+6642 6054 51	-2224 2198 47	+3543 7494 44	-8257 7665 40	+6450 9950 55	-1013 7338 52
	2100 - 2600	+6788 3007 51	-1372 2122 47	+1756 5186 44	-3252 3470 40	+6432 4476 55	-1119 1218 52
	2600 - 3200	+6891 2452 51	-9243 3170 46	+9493 4160 43	-1396 0756 40	+6416 6267 55	-1195 3073 52
	3200 - 3800	+6967 1014 51	-6796 6480 46	+5630 0065 43	-6591 8731 39	+6402 7074 55	-1252 6276 52
	3800 - 4400	+7021 0652 51	-5466 6732 46	+3777 3931 43	-3621 0579 39	+6390 9978 55	-1294 2206 52
	4400 - 5000	+7058 0449 51	-4920 3790 46	+2933 2725 43	-2418 8941 39	+6382 1426 55	-1322 8904 52
	5000 - 6000	+7097 4438 51	-4178 3006 46	+2148 5733 43	-1461 5182 39	+6370 9039 55	-1354 3379 52
CF_3	150 - 300	+4415 9046 51	-1079 2001 49	+1028 9803 47	-1547 4411 44	+3294 5442 55	+6322 6310 51
	300 - 500	+6995 4769 51	+6890 2840 48	-6064 6113 46	+9838 4060 43	+3233 5181 55	-8614 0409 51
	500 - 700	-1340 4500 50	-2596 2896 49	+1511 2585 47	-1367 1095 44	+3485 6118 55	+3544 3864 52
	700 - 1000	+6412 2822 51	-5167 3100 48	+2151 1245 46	-1307 2694 43	+3257 6653 55	-4378 9560 51
	1000 - 1300	+7725 6912 51	-2967 7290 48	+8838 4890 45	-3912 9278 42	+3209 7765 55	-1236 8123 52
	1300 - 1700	+9068 6613 51	-1109 7817 48	+2576 9457 45	-8070 0746 41	+3114 9770 55	-2139 6277 52
	1700 - 2100	+9682 7034 51	-6851 8810 47	+1229 5950 45	-2863 4956 41	+3061 1725 55	-2559 1310 52
	2100 - 2600	+1013 8660 52	-4418 4184 47	+6387 7821 44	-1094 2288 41	+3008 1267 55	-2883 3689 52
	2600 - 3200	+1047 7649 52	-3606 9383 47	+4132 9340 44	-5398 9138 40	+2961 3360 55	-3127 2861 52
	3200 - 3800	+1076 8882 52	-3381 4409 47	+3076 1815 44	-3205 5453 40	+2914 5240 55	-3339 4045 52
	3800 - 4400	+1102 5318 52	-3277 2624 47	+2461 8412 44	-2128 3409 40	+2865 7705 55	-3530 0856 52
	4400 - 5000	+1125 0822 52	-3285 3329 47	+2101 1199 44	-1569 0770 40	+2817 3513 55	-3699 8762 52
	5000 - 6000	+1150 6199 52	-3117 8637 47	+1722 3104 44	-1082 7473 40	+2750 5776 55	-3898 6721 52
CF_4	150 - 300	+4643 8961 51	-1683 7831 49	+1601 9450 47	-2396 9562 44	-1014 9484 54	+5178 0680 51
	300 - 500	+5623 0578 51	-8719 8704 48	+7316 1903 46	-7605 1763 43	-1222 0906 54	-3985 7300 50
	500 - 700	+7960 4636 51	-6242 2794 48	+3262 8202 46	-2359 3972 43	-1831 2412 54	-1328 2457 52
	700 - 1000	+9906 5230 51	-3434 1001 48	+1267 5804 46	-6495 1661 42	-2626 6184 54	-2506 3601 52
	1000 - 1300	+1147 9388 52	-1815 3256 48	+4641 2069 45	-1652 2082 42	-3541 4110 54	-3514 4361 52
	1300 - 1700	+1233 7867 52	-1186 3523 48	+2313 9431 45	-6249 2947 41	-4218 0861 54	-4090 3195 52
	1700 - 2100	+1298 6542 52	-8631 0470 47	+1280 2308 45	-2607 4621 41	-4855 4757 54	-4538 0510 52
	2100 - 2600	+1342 9488 52	-7049 5815 47	+8401 4548 44	-1348 7181 41	-5387 8368 54	-4851 9210 52
	2600 - 3200	+1383 6480 52	-6127 0088 47	+5871 1932 44	-7435 7727 40	-5966 7885 54	-5145 8668 52
	3200 - 3800	+1421 5792 52	-5686 3751 47	+4435 9055 44	-4538 3719 40	-6598 0089 54	-5424 2675 52
	3800 - 4400	+1455 3027 52	-5438 3782 47	+3578 3524 44	-3067 9795 40	-7256 5240 54	-5676 6439 52
	4400 - 5000	+1485 3135 52	-5353 0332 47	+3054 5903 44	-2273 9993 40	-7916 3830 54	-5904 0139 52
	5000 - 6000	+1520 3418 52	-5012 9280 47	+2490 5609 44	-1562 2083 40	-8854 9760 54	-6178 5165 52

[a]All substances in gaseous phase except graphite.

TABLE I. - Continued. COEFFICIENTS FOR OBTAINING THERMODYNAMIC DATA FOR SEVERAL SUBSTANCES

[Coefficients for use in equations (105) to (107)]

Substance (a)	Temperature interval, °K	Coefficients					
		A	B	C	D	E	F
CH	150 - 300	+3512 7827 51	+4636 0810 46	-5378 9030 44	+1146 7347 42	+1344 6458 56	+1985 4362 51
	300 - 500	+3518 9332 51	+8459 4710 46	-9090 7610 44	+1731 4444 42	+1344 6317 56	+1950 3265 51
	500 - 700	+3488 5177 51	-4341 9700 46	-1474 4120 44	+9635 7572 41	+1344 7464 56	+2140 1459 51
	700 - 1000	+3400 5554 51	-5633 2938 47	+1934 0930 45	-6925 5361 41	+1345 2502 56	+2759 7067 51
	1000 - 1300	+3525 5707 51	-8199 6840 47	+2173 4717 45	-8003 0957 41	+1344 7547 56	+2069 0007 51
	1300 - 1700	+3837 6747 51	-6520 0620 47	+1371 1096 45	-4245 5202 41	+1342 4710 56	+1564 3000 49
	1700 - 2100	+4192 6268 51	-4067 2700 47	+6710 9154 44	-1698 9591 41	+1339 0392 56	-2447 1172 51
	2100 - 2600	+4465 9529 51	-2009 4469 47	+2655 2706 44	-5294 6286 40	+1335 5954 56	-4436 8745 51
	2600 - 3200	+4632 7107 51	-9757 7450 46	+9834 5740 43	-1342 4602 40	+1333 0453 56	-5683 3608 51
	3200 - 3800	+4698 1775 51	-7731 9680 46	+5967 1047 43	-5314 9447 39	+1332 0116 56	-6167 1269 51
	3800 - 4400	+4702 1190 51	-1030 5653 47	+7078 9557 43	-6530 3692 39	+1332 3200 56	-6159 8616 51
	4400 - 5000	+4683 7437 51	-1461 5449 47	+9345 2350 43	-9239 1545 39	+1333 4036 56	-5958 5943 51
	5000 - 6000	+4705 6474 51	-1610 6331 47	+9697 4750 43	-9522 5104 39	+1333 1471 56	-6102 7716 51
CH_4	150 - 300	+4041 7634 51	+2256 4400 47	-8630 3440 45	+3562 5920 43	+1060 6422 56	-6347 7250 50
	300 - 500	+3771 6119 51	-1914 0720 48	+1386 0780 46	-5564 2687 42	+1061 2254 56	+9066 3870 50
	500 - 700	+4137 3746 51	-3824 2483 48	+1900 8319 46	-1114 4742 43	+1060 5115 56	-8222 6700 50
	700 - 1000	+4960 9077 51	-3993 5554 48	+1469 0695 46	-7032 1539 42	+1057 6295 56	-5511 1720 51
	1000 - 1300	+6265 1238 51	-3554 3046 48	+9493 8230 45	-3578 7489 42	+1051 0805 56	-1351 2328 52
	1300 - 1700	+7669 4643 51	-2559 0212 48	+5320 7298 45	-1596 8105 42	+1040 8233 56	-2280 0662 52
	1700 - 2100	+8940 9968 51	-1821 1267 48	+2963 0253 45	-7240 6212 41	+1028 9329 56	-3153 5615 52
	2100 - 2600	+9999 5267 51	-1151 4294 48	+1522 5193 45	-3042 6540 41	+1015 9947 56	-3915 9002 52
	2600 - 3200	+1082 7726 52	-7167 4950 47	+7704 7857 44	-1264 4178 41	+1003 5136 56	-4530 1437 52
	3200 - 3800	+1139 5575 52	-4744 1100 47	+4200 8572 44	-5795 9231 40	+9932 4942 55	-4961 4187 52
	3800 - 4400	+1178 8522 52	-3183 3398 47	+2393 0379 44	-2833 4861 40	+9846 8258 55	-5268 2486 52
	4400 - 5000	+1205 5418 52	-2229 3658 47	+1456 2454 44	-1510 4845 40	+9779 0774 55	-5481 0163 52
	5000 - 6000	+1232 4498 52	-1249 1856 47	+7039 3966 43	-6132 3844 39	+9695 2767 55	-5702 5529 52
CO	150 - 300	+3501 4842 51	+1087 8922 46	-2132 6547 44	+7176 7187 41	+3308 4242 55	+3809 0776 51
	300 - 500	+3504 8282 51	+5717 3880 46	-7717 9140 44	+1948 0969 42	+3308 3690 55	+3790 2032 51
	500 - 700	+3457 2625 51	-2833 6849 47	+1252 0307 45	-3568 5188 41	+3310 1729 55	+4099 1393 51
	700 - 1000	+3478 1473 51	-5369 0403 47	+1958 1791 45	-9091 0461 41	+3310 1638 55	+4029 9306 51
	1000 - 1300	+3651 5834 51	-5144 8902 47	+1380 4870 45	-5272 6366 41	+3301 4098 55	+2971 0270 51
	1300 - 1700	+3860 8374 51	-3546 9532 47	+7404 9426 44	-2247 5935 41	+3285 9734 55	+1582 1786 51
	1700 - 2100	+4040 9776 51	-2413 3244 47	+3930 0638 44	-9624 6665 40	+3269 0418 55	+3411 6830 50
	2100 - 2600	+4182 5494 51	-1491 5448 47	+1963 8756 44	-3880 7574 40	+3251 7557 55	-6791 5710 50
	2600 - 3200	+4288 4419 51	-9428 1210 46	+1001 4612 44	-1595 3818 40	+3235 9292 55	-1463 2026 51
	3200 - 3800	+4364 4008 31	-6326 1270 46	+5453 3767 43	-7027 3322 39	+3222 2132 55	-2039 2716 51
	3800 - 4400	+4419 2221 51	-4399 2938 46	+3153 4215 43	-3308 2674 39	+3210 1502 55	-2466 3384 51
	4400 - 5000	+4455 6250 51	-3418 0326 46	+2087 5301 43	-1819 9816 39	+3200 9544 55	-2753 9920 51
	5000 - 6000	+4489 0699 51	-2554 6512 46	+1323 6630 43	-9051 5936 38	+3190 9734 55	-3024 6520 51
CO_2	150 - 300	+3563 7140 51	-4925 8570 48	+4540 0397 46	-6280 3430 43	+5747 4400 51	+5400 7202 51
	300 - 500	+3816 8846 51	-2963 9146 48	+2490 7914 46	-2567 1204 43	-4925 1570 52	+3956 0791 51
	500 - 700	+4442 4313 51	-2696 4402 48	+1430 5622 46	-1054 0891 43	-1901 0823 53	+6296 7070 50
	700 - 1000	+5077 4390 51	-1862 6330 48	+7097 4891 45	-3796 5406 42	-4195 9603 53	-3119 0925 51
	1000 - 1300	+5616 2514 51	-1446 4518 48	+3992 8769 45	-1646 9220 42	-6690 3300 53	-6421 4910 51
	1300 - 1700	+6233 4300 51	-7697 8330 47	+1624 9078 45	-5067 2175 41	-1129 1388 54	-1056 0477 52
	1700 - 2100	+6653 7149 51	-4526 7290 47	+7359 4847 44	-1790 7679 41	-1524 1600 54	-1347 7832 52
	2100 - 2600	+6946 1749 51	-2588 8848 47	+3382 8632 44	-6523 5648 40	-1891 5354 54	-1559 6591 52
	2600 - 3200	+7139 6491 51	-1643 2337 47	+1725 5138 44	-2650 3605 40	-2185 9376 54	-1703 0668 52
	3200 - 3800	+7296 9835 51	-1012 4495 47	+8494 4890 43	-1007 5545 40	-2485 6878 54	-1823 3039 52
	3800 - 4400	+7355 3715 51	-9492 3200 46	+6828 6345 43	-7193 5879 39	-2598 7416 54	-1867 0777 52
	4400 - 5000	+7412 7505 51	-8253 2950 46	+5117 7600 43	-4618 8168 39	-2726 6119 54	-1911 4164 52
	5000 - 6000	+7871 5782 51	+9909 4290 46	-6572 2870 43	+7825 5668 39	-4364 6730 54	-2298 7484 52
COF_2	150 - 300	+4131 1379 51	-8226 1920 48	+7478 2778 46	-9970 6473 43	+2401 0874 54	+7645 3612 51
	300 - 500	+4500 8690 51	-5432 1224 48	+4581 6857 46	-4789 2357 43	+2320 2046 54	+5535 4142 51
	500 - 700	+5678 2507 51	-4772 8328 48	+2562 2417 46	-1955 9689 43	+2047 8396 54	-7674 1900 50
	700 - 1000	+6831 6009 51	-2985 8582 48	+1156 0805 46	-6481 0941 42	+1625 3541 54	-7624 2150 51
	1000 - 1300	+7879 7798 51	-1693 2846 48	+4684 2722 45	-1945 3137 42	+1089 1210 54	-1423 1012 52
	1300 - 1700	+8678 4190 51	-7904 5080 47	+1673 8397 45	-5273 3114 41	+4801 6047 53	-1962 5655 52
	1700 - 2100	+9108 8118 51	-4627 0080 47	+7630 8454 44	-1926 0389 41	+6748 8280 52	-2261 6387 52
	2100 - 2600	+9396 9763 51	-2546 8965 47	+3401 2225 44	-6947 7252 40	-2892 8132 53	-2470 5039 52
	2600 - 3200	+9587 4023 51	-1454 6465 47	+1576 5317 44	-2628 8817 40	-5779 4560 53	-2612 2675 52
	3200 - 3800	+9704 5646 51	-9199 5550 46	+8210 7660 43	-1147 7945 40	-7897 2630 53	-2701 4363 52
	3800 - 4400	+9781 4824 51	-5987 9330 46	+4538 2056 43	-5439 1950 39	-9569 4820 53	-2761 5713 52
	4400 - 5000	+9832 8204 51	-4061 2490 46	+2673 6624 43	-2799 4552 39	-1087 2569 54	-2802 5647 52
	5000 - 6000	+9883 3737 51	-2174 6468 46	+1235 8455 43	-1082 8889 39	-1244 9725 54	-2844 2347 52
Cl	150 - 300	+2499 7173 51	-5624 1480 47	+4632 7803 45	-441[illegible] 2433 42	+1633 2049 55	+5612 5486 51
	300 - 500	+2506 4788 51	-5929 6416 47	+5200 7614 45	-622[illegible] 5033 42	+1632 9938 55	+5573 8263 51
	500 - 700	+2656 4730 51	-2859 9690 47	+1686 3535 45	-162[illegible] 5100 42	+1629 1113 55	+4735 7792 51
	700 - 1000	+2743 3927 51	+6972 4500 45	+3294 7080 43	-111[illegible] 0739 41	+1625 6851 55	+4193 6441 51
	1000 - 1300	+2741 6558 51	+9775 6604 46	-2503 7621 44	+824[illegible] 8597 40	+1625 9067 55	+4191 7610 51
	1300 - 1700	+2710 4271 51	+9894 5320 46	-2052 2334 44	+612[illegible] 6450 40	+1628 0747 55	+4391 5167 51
	1700 - 2100	+2662 2371 31	+7245 6250 46	-1178 8354 44	+288[illegible] 4541 40	+1632 5570 55	+4721 8621 51
	2100 - 2600	+2620 4236 51	+4588 0250 46	-6064 0807 43	+121[illegible] 7404 40	+1637 6549 55	+5022 9170 51
	2600 - 3200	+2587 6175 51	+2858 2904 46	-3068 8116 43	+503[illegible] 4423 39	+1642 5883 55	+5266 1807 51
	3200 - 3800	+2565 1467 51	+1900 4820 46	-1679 7858 43	+231[illegible] 8500 39	+1646 6403 55	+5436 7772 51
	3800 - 4400	+2549 4787 51	+1280 0393 46	-9597 3450 42	+113[illegible] 1857 39	+1650 0529 55	+5559 0897 51
	4400 - 5000	+2539 0046 51	+9115 8820 45	-5941 3944 42	+615[illegible] 6189 38	+1652 6975 55	+5642 4806 51
	5000 - 6000	+2528 1946 51	+5179 8450 45	-2909 6748 42	+253[illegible] 4032 38	+1656 0533 55	+5731 4370 51
Cl_2	150 - 300	+3448 0294 51	-1658 5658 48	+2692 6483 46	-478[illegible] 5249 43	+3934 6532 54	+6890 4000 51
	300 - 500	+3835 3499 51	-1188 8256 48	+1031 7245 46	-119[illegible] 1520 43	+3873 9265 54	+4963 9378 51
	500 - 700	+4091 1205 51	-7711 9500 47	+4259 4980 45	-351[illegible] 7128 42	+3815 0122 54	+3572 8781 51
	700 - 1000	+4269 0209 51	-3765 4088 47	+1485 0640 45	-873[illegible] 1259 41	+3752 5719 54	+2509 1450 51
	1000 - 1300	+4388 1534 51	-1876 4198 47	+5195 4893 44	-215[illegible] 2894 41	+3696 4574 54	+1760 9050 51
	1300 - 1700	+4478 1904 51	-7895 4060 46	+1610 3315 44	-453[illegible] 1719 40	+3628 3890 54	+1152 1280 51
	1700 - 2100	+4529 1124 51	-4114 9154 46	+5753 0589 43	-790[illegible] 8876 39	+3578 5248 54	+7973 3350 50
	2100 - 2600	+4610 0199 51	+3446 6630 46	-7130 3870 43	+275[illegible] 3050 40	+3467 1576 54	+1942 1692 50
	2600 - 3200	+4760 6830 51	+1734 0760 47	-2492 1302 44	+668[illegible] 4165 40	+3199 1333 54	-9806 5385 50
	3200 - 3800	+4874 2401 51	+2677 9490 47	-3503 0664 44	+857[illegible] 2934 40	+2961 0183 54	-1888 1367 51
	3800 - 4400	+4707 9090 51	+1249 2260 47	-2466 4155 44	+714[illegible] 8116 40	+3476 8067 54	-4600 9460 50
	4400 - 5000	+3900 2910 51	-4688 6050 47	+1508 8757 44	+212[illegible] 2074 40	+6193 9315 54	+6505 1700 51
	5000 - 6000	+1847 5100 51	-1749 7481 48	+9091 4226 44	-627[illegible] 1116 40	+1399 8920 55	+2441 5074 52
ClF	150 - 300	+3451 8575 51	-6195 0380 47	+8977 4934 45	-7666 4753 42	+1049 7334 55	+6384 2088 51
	300 - 500	+3579 0533 51	-1315 6216 48	+1125 5565 46	-1238 9078 43	+1047 9573 55	+5807 3032 51
	500 - 700	+3875 6488 51	-9742 9350 47	+5316 9799 45	-4249 9844 42	+1040 8878 55	+4196 6080 51
	700 - 1000	+4115 2891 51	-5105 3400 47	+1999 4981 45	-1155 8321 42	+1032 1081 55	+2761 0926 51
	1000 - 1300	+4288 6764 51	-2591 5310 47	+7178 9728 44	-2989 9947 41	+1023 4995 55	+1667 1854 51
	1300 - 1700	+4412 8578 51	-1117 8049 47	+2318 1580 44	-6881 6527 40	+1014 0647 55	+8273 7321 50
	1700 - 2100	+4477 2114 51	-6520 2695 46	+1001 7884 44	-2019 8553 40	+1007 8838 55	+3807 5405 50
	2100 - 2600	+4547 1461 51	-7415 5100 45	-5651 6910 42	+9141 7438 39	+9986 6554 54	-1340 3011 50
	2600 - 3200	+4645 6835 51	+7474 1360 46	-1161 9276 44	+3389 7793 40	+9817 5674 54	-8938 7220 50
	3200 - 3800	+4702 7409 51	+1144 8060 47	-1631 2277 44	+4294 1388 40	+9707 0473 54	-1340 0407 51
	3800 - 4400	+4616 7451 51	+2967 7500 46	-1034 3624 44	+3467 4400 40	+9985 3475 54	-58[illegible] 7590 50
	4400 - 5000	+4293 3670 51	-2350 0980 47	+6853 7890 43	+1305 7477 40	+1111 2799 55	+2237 9870 51
	5000 - 6000	+3523 3574 51	-7547 9324 47	+3686 1299 44	-2000 6130 40	+1412 3199 55	+9021 9350 51

[a]All substances in gaseous phase except graphite.

E-417

TABLE I. - Continued. COEFFICIENTS FOR OBTAINING THERMODYNAMIC DATA FOR SEVERAL SUBSTANCES

[Coefficients for use in equations (105) to (107).]

Substance (a)	Temperature interval, °K	Coefficients					
		A	B	C	D	E	F
ClF_3	150 - 300	+5127 0429 51	-1749 4520 49	+1761 6464 47	-2976 1208 44	+2856 0159 55	+4659 5420 51
	300 - 500	+6457 5624 51	-5893 7083 48	+5115 6181 46	-5909 3643 43	+2828 1043 55	-2930 9810 51
	500 - 700	+7730 3861 51	-3819 8758 48	+2115 3958 46	-1756 7111 43	+2798 6643 55	-9857 9920 51
	700 - 1000	+8622 9749 51	-1802 3217 48	+7167 0960 45	-4305 6373 42	+2767 0675 55	-1520 7148 52
	1000 - 1300	+9203 6441 51	-8107 5540 47	+2291 6450 45	-1002 4218 42	+2739 3569 55	-1887 3181 52
	1300 - 1700	+9616 4642 51	-2539 0922 47	+5440 6701 44	-1755 2752 41	+2707 5754 55	-2168 5910 52
	1700 - 2100	+9764 0535 51	-1278 0686 47	+2126 0319 44	-5422 3408 40	+2693 2176 55	-2271 7800 52
	2100 - 2600	+9847 6403 51	-6517 8960 46	+8787 1110 43	-1805 4192 40	+2682 7742 55	-2332 5352 52
	2600 - 3200	+9897 9694 51	-3586 5496 46	+3936 3035 43	-6597 0677 39	+2675 1109 55	-2370 0484 52
	3200 - 3800	+9927 8564 51	-2207 8365 46	+2001 7247 43	-2809 9884 39	+2669 6912 55	-2392 8132 52
	3800 - 4400	+9946 9377 51	-1412 0292 46	+1092 2948 43	-1315 6062 39	+2665 5387 55	-2407 7328 52
	4400 - 5000	+9959 2224 51	-9559 0740 45	+6462 9910 42	-6817 9250 38	+2662 4430 55	-2417 5282 52
	5000 - 6000	+9971 6836 51	-4900 9530 45	+2907 6060 42	-2567 3024 38	+2658 5622 55	-2427 7976 52
F	300 - 500	+2774 1677 51	+1569 7918 47	-1219 8418 45	+8817 6073 41	+2448 1175 55	+3274 3817 51
	500 - 700	+2741 1306 51	+2447 1894 47	-1290 5400 45	+9364 9496 41	+2448 8816 55	+3442 3810 51
	700 - 1000	+2668 2300 51	+1435 7079 47	-5466 0762 44	+2926 9741 41	+2451 8215 55	+3882 1075 51
	1000 - 1300	+2606 1647 51	+7594 5950 46	-2066 6151 44	+8244 1470 40	+2455 3341 55	+4278 5777 51
	1300 - 1700	+2568 8565 51	+3901 3852 46	-8171 2274 43	+2516 1409 40	+2458 2444 55	+4530 4593 51
	1700 - 2100	+2543 7180 51	+1989 4083 46	-3203 1108 43	+7669 7618 39	+2460 7969 55	+4706 8085 51
	2100 - 2600	+2530 2137 51	+1158 2342 46	-1516 1332 43	+2979 4828 39	+2462 5383 55	+4804 8492 51
	2600 - 3200	+2520 8123 51	+6763 1070 45	-7187 4217 42	+1160 3995 39	+2464 0181 55	+4875 0108 51
	3200 - 3800	+2514 3282 51	+3904 6228 45	-3373 8858 42	+4456 9788 38	+2465 2647 55	+4924 7717 51
	3800 - 4400	+2510 0138 51	+2262 4946 45	-1637 1748 42	+1810 1580 38	+2466 2929 55	+4958 8764 51
	4400 - 5000	+2507 8249 51	+1625 4622 45	-1023 3196 42	+1001 0333 38	+2466 8878 55	+4976 3975 51
F_2	150 - 300	+3474 8807 51	-2479 3670 47	+2808 0384 45	+4516 8609 42	+3067 9524 55	+4488 2780 51
	300 - 500	+3499 3010 51	-1230 4361 48	+1038 9229 46	-1091 0390 43	+3067 9438 55	+4441 2399 51
	500 - 700	+3781 3514 51	-1031 1322 48	+5565 7851 45	-4317 1200 42	+3061 1457 55	+2916 9669 51
	700 - 1000	+4041 7357 51	-5868 2000 47	+2277 7137 45	-1285 7726 42	+3051 4311 55	+1359 1435 51
	1000 - 1300	+4247 3596 51	-3180 6992 47	+8736 8100 44	-3561 1383 41	+3040 9909 55	+6212 3900 49
	1300 - 1700	+4395 0680 51	-1548 4066 47	+3194 9833 44	-9363 6692 40	+3029 8390 55	-9330 9680 50
	1700 - 2100	+4473 0713 51	-1083 0146 47	+1705 8185 44	-3801 9221 40	+3022 6281 55	-1468 3319 51
	2100 - 2600	+4530 1221 51	-8004 6210 46	+1001 6324 44	-1705 3955 40	+3015 9621 55	-1873 5356 51
	2600 - 3200	+4577 2369 51	-6669 1418 46	+6657 4614 43	-8791 4462 39	+3009 4373 55	-2213 6134 51
	3200 - 3800	+4617 9447 51	-6168 3545 46	+4992 5151 43	-5319 2178 39	+3002 9324 55	-2510 8582 51
	3800 - 4400	+4654 6023 51	-5845 5975 46	+3970 3472 43	-3521 4000 39	+2995 9930 55	-2784 3785 51
	4400 - 5000	+4686 8046 51	-5734 8144 46	+3364 9472 43	-2580 7455 39	+2989 1276 55	-3027 5170 51
	5000 - 6000	+4726 7301 51	-5239 8070 46	+2658 8548 43	-1685 9673 39	+2978 4168 55	-3341 3410 51
H	150 - 300	+2500 3116 51	+4852 8250 45	-6211 4920 43	+1415 8863 41	+4294 5264 55	-4609 6828 50
	300 - 500	+2499 6710 51	-2385 2015 45	+2047 2396 43	-2955 4273 40	+4294 5386 55	-4573 1922 50
	500 - 700	+2499 0717 51	-3432 3430 45	+1896 0083 43	-1754 6524 40	+4294 5692 55	-4533 8129 50
	700 - 1000	+2499 5465 51	-1261 8040 45	+4772 2317 42	-3092 1566 39	+4294 5582 55	-4561 8786 50
	1000 - 1300	+2498 9933 51	-2095 0920 45	+6015 1654 42	-2948 5802 39	+4294 6101 55	-4522 0179 50
	1300 - 1700	+2499 9803 51	-1102 0773 44	+6488 9065 40	+4834 1707 36	+4294 5389 55	-4589 9392 50
	1700 - 2100	+2499 2764 51	-1021 2900 45	+1742 6965 42	-5235 9488 38	+4294 6258 55	-4537 6904 50
	2100 - 2600	+2499 9862 51	-4814 9770 43	+2852 3330 39	+7596 2533 36	+4294 5410 55	-4590 4575 50
	2600 - 3200	+2500 3308 51	+1682 7689 44	-2310 5728 41	+4594 2012 37	+4294 4715 55	-4617 5197 50
	3200 - 3800	+2500 2231 51	+6871 4240 43	-8940 1590 40	+1468 3878 37	+4294 4842 55	-4609 4814 50
	3800 - 4400	+2499 6156 51	-2770 3100 44	+2094 2038 41	-2893 9034 37	+4294 6455 55	-4559 8696 50
	4400 - 5000	+2498 9665 51	-5593 0080 44	+3785 6331 41	-4517 9884 37	+4294 8763 55	-4504 7409 50
H_2	150 - 300	+2989 2484 51	-4103 4770 48	+4407 7218 46	-8356 1287 43	+3401 1138 55	-1324 4021 51
	300 - 500	+3383 2407 51	-4324 5294 47	+3912 7728 45	-5061 2747 42	+3393 0261 55	-3572 0562 51
	500 - 700	+3459 0074 51	-1656 0656 47	+9153 4690 44	-7399 4236 41	+3391 6394 55	-3981 7170 51
	700 - 1000	+3480 7949 51	-8057 9160 46	+2316 5682 44	-2880 5124 38	+3391 4081 55	-4101 0320 51
	1000 - 1300	+3471 9964 51	-1811 4833 47	+4046 6752 44	-6393 1054 40	+3393 1405 55	-4004 9763 51
	1300 - 1700	+3478 9902 51	-3159 4629 47	+6167 8657 44	-1505 2076 41	+3394 2702 55	-3995 7133 51
	1700 - 2100	+3584 4555 51	-3452 5690 47	+5352 7626 44	-1138 9801 41	+3386 2783 55	-4672 5704 51
	2100 - 2600	+3759 4391 51	-2880 8338 47	+3648 3990 44	-6459 7043 40	+3365 5684 55	-5907 5858 51
	2600 - 3200	+3950 4861 51	-2214 0298 47	+2252 3788 44	-3163 7688 40	+3337 4923 55	-7304 4520 51
	3200 - 3800	+4015 1762 51	-2473 1652 47	+2122 3369 44	-2701 7443 40	+3332 1516 55	-7727 5210 51
	3800 - 4400	+4253 9189 51	-1542 7069 47	+1065 7981 44	-1000 8309 40	+3278 8324 55	-9597 2790 51
	4400 - 5000	+4316 8247 51	-1611 9098 47	+9809 8240 43	-8461 6973 39	+3267 4437 55	-1005 6383 52
	5000 - 6000	+4613 8660 51	-6368 8580 46	+2766 2305 43	-6509 3656 38	+3168 4849 55	-1251 8853 52
HCl	300 - 500	+3507 7834 51	+3434 8560 46	-3783 9075 44	+7488 3407 41	+7840 0952 54	+2478 6303 51
	500 - 700	+3496 6325 51	-8772 1500 45	-1483 8166 44	+5505 0572 41	+7844 5758 54	+2549 0010 51
	700 - 1000	+3455 5431 51	-2524 1094 47	+8256 9265 44	-2240 1276 41	+7868 1516 54	+2838 6335 51
	1000 - 1300	+3497 7739 51	-4336 2524 47	+1120 6186 45	-3799 5512 41	+7857 2051 54	+2632 6456 51
	1300 - 1700	+3637 7472 51	-4092 2196 47	+8387 1455 44	-2412 5676 41	+7762 0326 54	+1733 9321 51
	1700 - 2100	+3828 5869 51	-3262 2034 47	+5240 1857 44	-1237 0559 41	+7587 5851 54	+4355 1680 50
	2100 - 2600	+4008 0692 51	-2269 0376 47	+2958 7010 44	-5696 4676 40	+7371 4782 54	-8489 9400 50
	2600 - 3200	+4163 1444 51	-1552 5681 47	+1637 9704 44	-2558 9129 40	+7141 4411 54	-1992 0853 51
	3200 - 3800	+4279 2700 51	-1136 3225 47	+9795 8780 43	-1262 3444 40	+6935 9632 54	-2867 0492 51
	3800 - 4400	+4365 4707 51	-8607 3540 46	+6238 6255 43	-6741 6929 39	+6753 4656 54	-3533 0504 51
	4400 - 5000	+4428 6165 51	-6932 3370 46	+4323 4380 43	-3995 4750 39	+6599 9666 54	-4029 0913 51
	5000 - 6000	+4496 5332 51	-4983 7368 46	+2652 7672 43	-1976 9074 39	+6397 5200 54	-4580 2542 51
HF	150 - 300	+3502 9862 51	-5341 4090 45	+3907 3861 43	-1722 7617 40	-1026 8292 52	+9285 0538 50
	300 - 500	+3503 7414 51	-7163 1600 44	-5447 6980 42	+5181 9187 40	-1044 2091 52	+9241 9270 50
	500 - 700	+3510 6273 51	+3178 3340 46	-2370 2806 44	+3298 9392 41	-1264 3243 52	+8825 1182 50
	700 - 1000	+3497 5136 51	-1383 0680 46	-5305 0300 43	+1983 9089 41	-5429 5120 51	+9703 1135 50
	1000 - 1300	+3459 5106 51	-2005 0034 47	+4630 1579 44	-9300 2525 40	+2673 4630 52	+1258 5941 51
	1300 - 1700	+3477 7106 51	-3196 6027 47	+6293 8357 44	-1587 5290 41	+2887 5590 52	+1190 5757 51
	1700 - 2100	+3595 2253 51	-3334 3110 47	+5229 6762 44	-1153 0942 41	-6743 7760 52	+4224 9140 50
	2100 - 2600	+3754 7551 51	-2772 2634 47	+3563 5125 44	-6593 9114 40	-2520 7695 53	-7009 1120 50
	2600 - 3200	+3932 3426 51	-2104 1015 47	+2197 0853 44	-3337 2252 40	-5111 5610 53	-1999 9964 51
	3200 - 3800	+4086 7884 51	-1614 8342 47	+1377 0946 44	-1723 8858 40	-7831 6590 53	-3159 4638 51
	3800 - 4400	+4209 3672 51	-1252 4527 47	+8941 3920 43	-9272 9771 39	-1042 4966 54	-4104 5633 51
	4400 - 5000	+4301 3524 51	-1027 8717 47	+6265 6581 43	-5431 6307 39	-1264 8039 54	-4825 1389 51
	5000 - 6000	+4402 9214 51	-7489 6732 46	+3816 7579 43	-2461 9992 39	-1564 9097 54	-5647 2957 51
H_2O	150 - 300	+4012 7997 51	+4448 8300 46	-1184 6208 45	+4440 3590 42	+5696 5839 54	-1658 1832 50
	300 - 500	+3984 3281 51	-1560 3100 47	+8521 9880 44	+9334 5693 41	+5702 9188 54	-3361 4200 48
	500 - 700	+3995 7858 51	-5866 2548 47	+2772 9813 45	-1277 3920 42	+5705 5261 54	-7248 4000 48
	700 - 1000	+4103 2581 51	-7272 2748 47	+2513 6379 45	-9392 8919 41	+5673 7398 54	-5886 8940 50
	1000 - 1300	+4273 7895 51	-9457 9644 47	+2418 4150 45	-7900 2882 41	+5608 4188 54	-1548 2509 51
	1300 - 1700	+4561 3587 51	-9361 2130 47	+1893 3359 45	-5227 3842 41	+5420 0843 54	-3374 7881 51
	1700 - 2100	+4985 3551 51	-8042 8280 47	+1277 9848 45	-2926 8695 41	+5036 1704 54	-6240 3270 51
	2100 - 2600	+5419 7867 51	-5975 1330 47	+7745 7137 44	-1467 6260 41	+4512 4857 54	-9338 2540 51
	2600 - 3200	+5838 4391 51	-4173 6144 47	+4396 9203 44	-6843 2077 40	+3882 1430 54	-1242 5644 52
	3200 - 3800	+6196 8101 51	-2837 1462 47	+2441 1367 44	-3130 1900 40	+3213 9760 54	-1514 9891 52
	3800 - 4400	+6449 0690 51	-2024 8380 47	+1471 0187 44	-1599 5108 40	+2645 3976 54	-1711 7423 52
	4400 - 5000	+6624 7105 51	-1547 9092 47	+9747 8790 43	-9242 5186 39	+2187 2059 54	-1851 2177 52

[a]All substances in gaseous phase except graphite.

TABLE I. - Concluded. COEFFICIENTS FOR OBTAINING THERMODYNAMIC DATA FOR SEVERAL SUBSTANCES

[Coefficients for use in equations (105) to (107).]

Substance (a)	Temperature interval, °K	Coefficients					
		A	B	C	D	E	F
N	300 - 500	+2499 6710 51	-2385 2015 45	+2047 2396 43	-2955 4273 40	+5707 9313 55	+4183 1808 51
	500 - 700	+2499 1148 51	-3267 4440 45	+1798 0743 43	-1659 2209 40	+5707 9603 55	+4186 8511 51
	700 - 1000	+2499 6036 51	-1131 0429 45	+4232 2090 42	-2736 5544 39	+5707 9478 55	+4183 9375 51
	1000 - 1300	+2499 0940 51	-1901 1726 45	+5442 2129 42	-2666 8173 39	+5707 9952 55	+4187 5999 51
	1300 - 1700	+2500 2204 51	+3456 2550 44	-9655 6710 41	+4200 6645 38	+5707 9078 55	+4179 7565 51
	1700 - 2100	+2501 6390 51	+2522 5800 45	-4789 7317 42	+1627 5565 39	+5707 7262 55	+4169 0522 51
	2100 - 2600	+2508 6192 51	+1107 6049 46	-1756 3079 43	+5016 8252 39	+5706 6696 55	+4115 3955 51
	2600 - 3200	+2517 3414 51	+2174 0230 46	-3034 2712 43	+7858 2646 39	+5705 0383 55	+4045 6309 51
	3200 - 3800	+2512 6964 51	+1967 0040 46	-2871 8071 43	+7694 4866 39	+5706 2395 55	+4083 2154 51
	3800 - 4400	+2482 1655 51	-6399 2200 45	-8908 3900 42	+4843 1658 39	+5715 2935 55	+4343 0639 51
	4400 - 5000	+2434 6193 51	-5054 2730 46	+1913 3373 43	+1308 3373 39	+5732 4433 55	+4765 1025 51
	5000 - 6000	+2351 2887 51	-1171 7309 47	+5608 4591 43	-2764 8502 39	+5766 8718 55	+5513 9770 51
N_2	150 - 300	+3501 6234 51	+1419 9930 46	-2221 4814 44	+6337 0257 41	+8539 5697 53	+3078 0353 51
	300 - 500	+3507 3207 51	+6478 8790 46	-7700 5600 44	+1686 9531 42	+8527 6963 53	+3045 5391 51
	500 - 700	+3468 1570 51	-1742 8035 47	+6732 6921 44	+6988 8312 40	+8673 6314 53	+3295 4226 51
	700 - 1000	+3462 1286 51	-4539 6402 47	+1622 1534 45	-6973 0151 41	+8776 6703 53	+3385 9335 51
	1000 - 1300	+3600 4480 51	-4968 5174 47	+1321 7619 45	-4923 4174 41	+8096 8196 53	+2555 2204 51
	1300 - 1700	+3793 9348 51	-3715 9604 47	+7731 5595 44	-2325 2167 41	+6685 5239 53	+1278 3599 51
	1700 - 2100	+3979 4426 51	-2618 0633 47	+4257 4284 44	-1039 0909 41	+4949 4356 53	+3226 6000 48
	2100 - 2600	+4131 6527 51	-1645 9670 47	+2167 0242 44	-4284 4626 40	+3093 6592 53	-1092 8453 51
	2600 - 3200	+4249 0997 51	-1039 9359 47	+1106 6286 44	-1770 7380 40	+1332 3679 53	-1962 7879 51
	3200 - 3800	+4327 0196 51	-7332 7190 46	+6383 0855 43	-8445 0756 39	-4394 6700 51	-2551 1939 51
	3800 - 4400	+4383 7162 51	-5322 6420 46	+3896 3172 43	-4326 2187 39	-1248 3259 53	-2990 7052 51
	4400 - 5000	+4426 8870 51	-3934 9468 46	+2455 1316 43	-2274 3750 39	-2321 5622 53	-3332 6930 51
	5000 - 6000	+4822 3937 51	+1235 5686 47	-7763 4410 43	+8482 4648 39	-1669 0365 54	-6686 7119 51
NH	150 - 300	+3501 4877 51	-1135 4880 46	+3492 4950 43	+1605 9661 41	+5707 5674 55	+1837 3594 51
	300 - 500	+3506 9044 51	+1658 8050 46	-1893 7787 44	+3971 7660 41	+5707 4332 55	+1806 0451 51
	500 - 700	+3507 6770 51	+2796 6700 46	-3019 6472 44	+5706 5528 41	+5707 4505 55	+1802 3997 51
	700 - 1000	+3467 4923 51	-1587 8517 47	+4682 2623 44	-3133 4757 40	+5709 6465 55	+2076 5108 51
	1000 - 1300	+3476 0496 51	-3595 9897 47	+8992 4746 44	-2700 9943 41	+5710 4331 55	+2082 2903 51
	1300 - 1700	+3578 3151 51	-3917 3724 47	+7834 3879 44	-2085 4695 41	+5703 9404 55	+1443 5951 51
	1700 - 2100	+3753 2238 51	-3437 2875 47	+5329 0472 44	-1133 8710 41	+5688 4282 55	+2671 2430 50
	2100 - 2600	+3924 7696 51	-2774 1647 47	+3440 1817 44	-5700 1390 40	+5668 6761 55	-9419 7230 50
	2600 - 3200	+4082 2543 51	-2416 9060 47	+2402 2699 44	-3132 6809 40	+5647 1309 55	-2072 8080 51
	3200 - 3800	+4226 3537 51	-2291 3941 47	+1856 8495 44	-1990 5685 40	+5624 2276 55	-3121 4787 51
	3800 - 4400	-9768 5140 52	-6242 7160 49	+5044 9155 46	-7082 5339 42	+3413 8680 56	+8395 4054 53
	4400 - 5000	-1813 5084 53	-8906 1750 49	+6213 1583 46	-7379 7014 42	+6634 6534 56	+1553 9865 54
	5000 - 6000	-2323 8668 52	-1115 6880 49	+6734 9310 45	-6814 6304 41	+1606 8773 56	+2311 5519 53
NH_3	150 - 300	+4016 0739 51	-5921 7280 47	+2172 9700 45	+8870 2067 42	+4660 2050 55	+2676 3530 50
	300 - 500	+3929 2082 51	-1358 1227 48	+1045 1508 46	-6997 1157 42	+4662 0202 55	+7631 5510 50
	500 - 700	+4204 7432 51	-2082 9945 48	+1039 4443 46	-6167 7796 42	+4656 2775 55	-6133 4010 50
	700 - 1000	+4643 7799 51	-2103 0382 48	+7635 1643 45	-3485 0380 42	+4641 3606 55	-3108 4650 51
	1000 - 1300	+5267 2607 51	-2084 8879 48	+5491 9755 45	-1983 4803 42	+4612 0057 55	-6862 3930 51
	1300 - 1700	+6020 3398 51	-1698 3392 48	+3497 6990 45	-1020 9245 42	+4558 7608 55	-1178 4321 52
	1700 - 2100	+6822 7393 51	-1316 2876 48	+2126 3664 45	-5097 7779 41	+4484 9963 55	-1725 7876 52
	2100 - 2600	+7558 4148 51	-8904 3840 47	+1171 7555 45	-2312 0365 41	+4395 8496 55	-2253 4893 52
	2600 - 3200	+8185 0643 51	-5794 8770 47	+6206 9477 44	-1009 0955 41	+4301 8144 55	-2717 1642 52
	3200 - 3800	+8640 1560 51	-3931 9340 47	+3470 3306 44	-4747 1369 40	+4219 6290 55	-3062 3326 52
	3800 - 4400	+8962 9398 51	-2692 3282 47	+2017 9453 44	-2371 7716 40	+4149 2986 55	-3314 0852 52
	4400 - 5000	+9187 2759 51	-1912 4119 47	+1245 5081 44	-1282 4365 40	+4092 3525 55	-3492 7645 52
	5000 - 6000	+9414 7085 51	-1099 4602 47	+6180 2898 43	-5346 0492 39	+4021 6182 55	-3679 8456 52
NO	300 - 500	+3629 9914 51	+2657 5880 47	-2717 2093 45	+4701 8630 42	+1177 3583 55	+4650 8256 51
	500 - 700	+3526 2159 51	-3327 2407 47	+1496 6665 45	-5017 5332 41	+1180 6009 55	+5285 0742 51
	700 - 1000	+3571 2043 51	-5722 3794 47	+2111 9083 45	-1023 0275 42	+1179 4145 55	+5066 8759 51
	1000 - 1300	+3769 9172 51	-4896 8460 47	+1322 3357 45	-5147 2119 41	+1169 0270 55	+3837 0127 51
	1300 - 1700	+3976 2131 51	-3140 6382 47	+6572 2561 44	-2009 1463 41	+1153 6702 55	+2461 7464 51
	1700 - 2100	+4137 1746 51	-2076 7231 47	+3380 3593 44	-8273 2029 40	+1138 5290 55	+1351 2723 51
	2100 - 2600	+4259 7731 51	-1265 1294 47	+1656 3960 44	-3228 0166 40	+1123 5766 55	+4673 8600 50
	2600 - 3200	+4349 0587 51	-8120 9610 46	+8518 4400 43	-1311 7501 40	+1110 2937 55	-1928 0800 50
	3200 - 3800	+4413 5660 51	-5677 9250 46	+4786 5005 43	-5809 5741 39	+1098 7485 55	-6803 6460 50
	3800 - 4400	+4459 4771 51	-4305 6534 46	+2995 3452 43	-2883 0271 39	+1088 9003 55	-1035 1524 51
	4400 - 5000	+4489 7869 51	-3762 9949 46	+2235 0024 43	-1791 0895 39	+1081 6691 55	-1270 7127 51
	5000 - 5500	+4509 2548 51	-3739 5470 46	+1972 1171 43	-1430 4410 39	+1076 9605 55	-1419 8637 51
	5500 - 6000	+4525 5565 51	-3723 0352 46	+1802 9307 43	-1226 2702 39	+1072 4569 55	-1546 9048 51
O	150 - 300	+2832 8173 51	+1431 7687 48	-1468 4834 46	+2566 9894 43	+3017 4976 55	+3217 0845 51
	300 - 500	+2714 6413 51	+3870 4329 47	-3379 2646 45	+3969 6103 42	+3019 9635 55	+3891 1039 51
	500 - 700	+2629 9259 51	+2286 8597 47	-1271 4552 45	+1065 1442 42	+3021 9345 55	+4354 2996 51
	700 - 1000	+2576 2890 51	+1028 8519 47	-4106 0040 44	+2484 6390 41	+3023 8309 55	+4676 2053 51
	1000 - 1300	+2547 0979 51	+5221 5330 46	-1496 6858 44	+6739 3053 40	+3025 1125 55	+4858 4101 51
	1300 - 1700	+2519 3465 51	+1151 2610 46	-2514 3283 43	+8031 2904 39	+3027 2774 55	+5048 5417 51
	1700 - 2100	+2514 1793 51	+9680 0900 45	-1678 4195 43	+4800 0132 39	+3027 7264 55	+5083 3051 51
	2100 - 2600	+2508 6997 51	+6151 5400 45	-9959 5160 42	+2941 9744 39	+3028 4518 55	+5123 3201 51
	2600 - 3200	+2506 8516 51	+6191 4220 45	-1014 7413 43	+3113 4905 39	+3028 8330 55	+5137 3787 51
	3200 - 3800	+2496 0645 51	-4318 7660 45	-1785 1200 41	+1353 7926 39	+3031 3904 55	+5226 2595 51
	3800 - 4400	+2484 1660 51	-1828 7300 46	+9952 7176 42	-1281 2973 38	+3035 1914 55	+5331 3688 51
	4400 - 5000	+2461 6602 51	-3966 3519 46	+2327 9192 43	-1788 5282 39	+3043 5044 55	+5532 3795 51
O_2	150 - 300	+3507 8622 51	+7336 8300 46	-1566 0917 45	+5367 9823 42	+1022 7365 54	+4678 3884 51
	300 - 500	+3468 1122 51	-2094 4310 47	+1311 3020 45	+4112 4133 41	+1031 5694 54	+4905 2651 51
	500 - 700	+3491 8904 51	-6759 0190 47	+3398 6627 45	-2087 8706 42	+1030 0629 54	+4833 9311 51
	700 - 1000	+3655 2327 51	-6543 3148 47	+2462 0346 45	-1270 0679 42	+9684 3794 53	+3884 7354 51
	1000 - 1300	+3904 0901 51	-4442 4078 47	+1199 2093 45	-4661 9082 41	+8345 0760 53	+2319 0523 51
	1300 - 1700	+4104 9900 51	-2517 0318 47	+5093 9020 44	-1409 3115 41	+6835 7755 53	+9729 7660 50
	1700 - 2100	+4222 7020 51	-1953 0831 47	+2975 1070 44	-5976 9259 40	+5794 9642 53	+1747 6760 50
	2100 - 2600	+4302 7917 51	-1791 1603 47	+2194 9064 44	-3493 6626 40	+4957 1490 53	-3765 2230 50
	2600 - 3200	+4378 2138 51	-1859 5901 47	+1888 4516 44	-2642 8824 40	+4050 9189 53	-8980 5550 50
	3200 - 3800	+4481 6232 51	-1804 0341 47	+1533 7064 44	-1904 1376 40	+2395 5642 53	-1649 5016 51
	3800 - 4400	+4595 4599 51	-1604 0929 47	+1175 2869 44	-1306 8504 40	+6835 3000 51	-2514 2771 51
	4400 - 5000	+4700 9554 51	-1392 3351 47	+9033 6640 43	-9220 7268 39	-2507 6420 53	-3338 5270 51
OH	150 - 300	+3764 1804 51	+1330 9369 48	-1397 7859 46	+2549 9846 43	+2208 6061 55	+6394 1790 50
	300 - 500	+3650 7552 51	+2767 0068 47	-2437 5563 45	+2946 8393 42	+2210 9337 55	+1286 3048 51
	500 - 700	+3583 7943 51	+1516 8258 47	-9296 3300 44	+9667 5264 41	+2212 6553 55	+1658 9638 51
	700 - 1000	+3516 1720 51	-4302 4030 46	+4112 6890 43	+1744 5983 41	+2215 8159 55	+2091 0067 51
	1000 - 1300	+3471 4812 51	-2792 0696 47	+6819 0371 44	-1854 4121 41	+2219 7325 55	+2435 4839 51
	1300 - 1700	+3526 0017 51	-3607 9397 47	+7223 5714 44	-1930 9877 41	+2217 1231 55	+2122 0534 51
	1700 - 2100	+3690 5516 51	-3191 5272 47	+5009 9631 44	-1107 8802 41	+2202 1973 55	+1012 3454 51
	2100 - 2600	+3838 8762 51	-2495 8340 47	+3335 8184 44	-6301 3695 40	+2184 1527 55	-4676 3000 49
	2600 - 3200	+4037 2441 51	-1797 8853 47	+1877 3664 44	-2853 0364 40	+2155 0371 55	-1497 1187 51
	3200 - 3800	+4187 6806 51	-1285 8703 47	+1095 7568 44	-1369 6166 40	+2127 1678 55	-2636 9671 51
	3800 - 4400	+4298 3386 51	-9543 3180 46	+6837 4562 43	-7166 3961 39	+2102 5017 55	-3497 0396 51
	4400 - 5000	+4379 1568 51	-7525 5620 46	+4643 9276 43	-4172 0827 39	+2081 6369 55	-4136 5232 51

[a]All substances in gaseous phase except graphite.

E-417

TABLE II. - INPUT TO VECTOR

AND PROPELLANT DECK*

Product code		
Card column		
44-47	48-50	51-60
	B$\overline{\mathrm{O}}$P	
0037	ATM	H
0054	ATM	N
0061	ATM	$\overline{\mathrm{O}}$
0450	M$\overline{\mathrm{O}}$L	H2
0451	M$\overline{\mathrm{O}}$L	H2$\overline{\mathrm{O}}$1
0650	M$\overline{\mathrm{O}}$L	N2
0651	M$\overline{\mathrm{O}}$L	N1$\overline{\mathrm{O}}$1
0750	M$\overline{\mathrm{O}}$L	$\overline{\mathrm{O}}$2
0751	M$\overline{\mathrm{O}}$L	$\overline{\mathrm{O}}$1H1
	F1	N2H4
	EF1	1547029756
	PF1	1000000053
	X1	H2$\overline{\mathrm{O}}$2
	EX1	2868162655
	PX1	1000000053

*The symbol $\overline{\mathrm{O}}$ is used to indicate the alphabetic letter; the symbol 0 is used for zero.

TABLE III. - OUTPUT OF VECTOR AND PROPELLANT DECK

Type of card	Product code	Packed vector	Product code		
	Card column				
	17-20	31-40	44-47	48-50	51-60
Packed vectors	0037 0054 0061 0450 0451 0650 0651 0750 0751	0000000001 0000000011 0000000021 0000000002 0000000221 0000000012 0000001121 0000000022 0000002101	0037 0054 0061 0450 0451 0650 0651 0750 0751	ATM ATM ATM MŌL MŌL MŌL MŌL MŌL MŌL	H N Ō H2 H2Ō1 N2 N1Ō1 Ō2 Ō1H1
Cards for listing only to check input				F1 EF1 PF1 X1 EX1 PX1	N2H4 1547029756 1000000053 H2Ō2 2868162655 1000000053

Type of card	Drum location	Contents	Drum location	Contents	Drum location	Contents
	Card column					
	1-4	5-15	16-19	20-30	31-34	35-45
a_f (hydrogen) b_f (nitrogen)	0587	1248127850+	0588	6240639049+		
Fuel enthalpy, h_f Fuel valence, V_f^+	0597	4827226954+	0598	1248127850+		
a_x (hydrogen) c_x (oxygen)	0537	5879586049+	0539	5879586049+		
Oxidant enthalpy, h_x Oxidant valence, V_x^+ Oxidant valence, V_x^-	0547	8431804353+	0548	5879586049+	0549	1175917250-

TABLE IV. - INPUT TO MAIN OPERATING DECK

Card format (see appendix B)	Information on card	Where discussed in text								
Random	Case number	Appendix C	1148 000002 0800+							
	O/F, %P, r	Eqs. (99) and (104)	0199 000000 0000+	0299 000000 0000+	0399 857142 8650+					
	P_c, lb/sq in. abs	Appendix C	1109 600000 0053+							
	P_c/P schedule	Appendix C	1075 100000 0051+	1076 175438 5051+	1077 204137 1052+	1078 408274 2052+	1079 680456 9952+			
	a_f, b_f	Eq. (95)	0587 124812 7850+	0588 624063 9049+						
	h_f, V_f^+	Eqs. (97), (100), (105)	0597 482722 6954+	0598 124812 7850+						
	a_x, c_x	Eq. (95)	0537 587958 6049+	0539 587958 6049+						
	h_x, V_x^+, V_x^-	Eqs. (97), (100), (105)	0547 843180 4353+	0548 587958 6049+	0549 117591 7250-					
Basic load bin	Transfer to vector loading routine	Packed vector loading routine	000000 1999+							
SOAP II output	Packed vectors	Packed chemical vector	691954 1953+	000000 0037+	240000 8000+	000000 0001+	0+ 0 037ATM	H		
			691954 1953+	000000 0054+	240000 8000+	000000 0011+	0+ 0 054ATM	N		
			691954 1953+	000000 0061+	240000 8000+	000000 0021+	0+ 0 061ATM	O		
			691954 1953+	000000 0450+	240000 8000+	000000 0002+	0+ 0 450MOL	H2		
			691954 1953+	000000 0451+	240000 8000+	000000 0221+	0+ 0 451MOL	H2O1		
			691954 1953+	000000 0650+	240000 8000+	000000 0012+	0+ 0 650MOL	N2		
			691954 1953+	000000 0651+	240000 8000+	000000 1121+	0+ 0 651MOL	N1O1		
			691954 1953+	000000 0750+	240000 8000+	000000 0022+	0+ 0 750MOL	O2		
			691954 1953+	000000 0751+	240000 8000+	000000 2101+	0+ 0 751MOL	O1H1		
Basic load bin	Transfer out of vector loading	Packed vector loading routine	000000 0000+							
Basic load bin	Thermodynamic coefficients	Sections on thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003744 0500+	249896 6551+	559300 8044-	3785 633141+	451798 8437-	429487 6955+	450474 0950-
			659051 1193+	005444 0500+	243461 9551+	505427 3046-	1913 337345+	130833 7339+	573244 5955+	476510 2551+
			659051 1193+	006144 0500+	246166 0251+	396635 1946-	2327 919243+	178852 8739-	304350 4455+	553237 0551+
			659051 1193+	045044 0500+	431409 5651+	162596 2147-	9909 293043+	858305 4339-	326831 8755+	100334 8052-
			659051 1193+	045144 0500+	662471 0551+	154790 9247-	9747 879043+	924251 8639-	218720 5954+	185121 7752-
			659051 1193+	065044 0500+	442627 5851+	396671 7046-	2477 670243+	230199 3239-	230202 7153-	332756 6551-
			659051 1193+	065144 0500+	448978 6951+	376299 4946-	2235 002443+	179108 9539-	108166 9155+	127071 2751-
			659051 1193+	075044 0500+	470095 5451+	139233 5147-	9033 664043+	922072 6839-	250764 7055-	393852 7051-
			659051 1193+	075144 0500+	497915 6851+	752556 2046-	4649 927643+	417208 2739-	208163 6955+	413652 3251-
Bell	Temperature interval	Load thermal data routine	0012 00000	0 +440000 0054	+500000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003738 0440+	249961 5651+	277031 0044-	2094 203841+	289390 3437-	429464 5555+	455986 9650-
			659051 1193+	005438 0440+	248216 5551+	639922 0045-	8908 390042-	484316 5839+	571529 3555+	434306 3951+
			659051 1193+	006138 0440+	248416 6051+	182873 0046-	9952 717642+	128129 7338-	303519 1455+	533136 8851+
			659051 1193+	045038 0440+	425388 4251+	154292 8147-	1065 966844+	100106 0140-	327884 2655+	959698 6051-
			659051 1193+	045138 0440+	644906 9051+	202483 8047-	1471 018744+	159951 0840-	264539 7654+	171174 2352-
			659051 1193+	065038 0440+	438382 0951+	531661 8046-	3891 393243+	431934 6339-	125122 1753-	299156 6851-
			659051 1193+	065138 0440+	445947 7151+	430565 3446-	2995 345243+	288302 7139-	108890 0355+	103515 2451-
			659051 1193+	075038 0440+	459545 9951+	160409 2947-	1175 286944+	190685 0440-	683530 0051+	251427 7151-
			659051 1193+	075138 0440+	429833 8651+	954331 8046-	6837 456243+	716639 6119-	210250 1755+	349703 9651-
Bell	Temperature interval	Load thermal data routine	0011 00000	0 +380000 0054	+440000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003732 0380+	250022 3151+	687142 4043+	8940 159040-	146838 7837+	429448 4255+	460948 1450-
			659051 1193+	005432 0380+	251269 6451+	196700 4046+	2871 807143-	769448 6639+	570623 9555+	408321 5451+
			659051 1193+	006132 0380+	249606 4551+	431876 6045-	1785 120041-	135379 2639+	303139 0455+	522629 3551+
			659051 1193+	045032 0380+	401515 6451+	247333 6247-	2172 483444+	270197 6840-	333215 6855+	772739 2051-
			659051 1193+	045132 0380+	619661 0151+	283714 6747-	2441 136744+	313019 0040-	371397 6056+	151498 9152-
			659051 1193+	065032 0380+	432700 1151+	733381 5046-	6384 162643+	844681 9139-	435062 0051-	255104 6051-
			659051 1193+	065132 0380+	441356 6051+	567792 5046-	4786 500543+	580957 4139-	109874 6555+	680364 6050-
			659051 1193+	075032 0380+	448162 3251+	180403 4147-	1533 706444+	190413 7640-	239556 4253+	164950 1651-
			659051 1193+	075132 0380+	418768 0651+	128587 0347-	1095 756844+	136961 6640-	212716 7855+	263696 7151-
Bell	Temperature interval	Load thermal data routine	0010 00000	0 +320000 0054	+380000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003726 0320+	250033 0851+	168276 8944+	2310 572841-	459420 1237+	429447 1555+	461751 9750-
			659051 1193+	005426 0320+	251734 1451+	217402 3046+	3034 271243-	785826 4639+	570503 8355+	404563 0951+
			659051 1193+	006126 0320+	250685 1651+	619142 2045+	1014 741343-	311349 0539+	302883 3055+	513797 8751+
			659051 1193+	045026 0320+	395046 0951+	221425 2447-	2252 616044+	316421 7240-	333749 7655+	730424 6051-
			659051 1193+	045126 0320+	583843 9151+	417361 4447-	4396 920344+	684320 7740-	388214 3054+	124256 4452-
			659051 1193+	065026 0320+	424907 0351+	104015 2347-	1106 878944+	177122 0840-	133295 4053+	196255 6551-
			659051 1193+	065126 0320+	434905 8751+	812096 1046-	8518 440043+	131175 0140-	111029 3755+	192808 0050-
			659051 1193+	075026 0320+	437821 3851+	185959 0147-	1888 451644+	264288 2440-	405091 8953+	898055 5050-
			659051 1193+	075126 0320+	403724 4151+	179788 5347-	1877 366444+	285303 6440-	215503 7155+	149711 8751-
Bell	Temperature interval	Load thermal data routine	0009 00000	0 +260000 0054	+320000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003721 0260+	249998 6251+	481497 7043-	2852 333039+	759625 3356+	429454 1055+	459045 7550-
			659051 1193+	005421 0260+	250861 9251+	110760 4946+	1756 307943-	501682 5239+	570666 9655+	411539 5551+
			659051 1193+	006121 0260+	250869 9751+	615156 0045+	9959 516042-	294197 4439+	302845 1855+	512332 0151+
			659051 1193+	045021 0260+	375937 0651+	288149 0747-	3649 314144+	646187 1040-	336557 9655+	590705 4851-
			659051 1193+	045121 0260+	541976 6751+	597513 3047-	7745 715744+	146762 6041-	451248 5754+	933825 4051-
			659051 1193+	065021 0260+	415153 9051+	164695 7647-	2168 431944+	428777 2840-	309550 2553+	109197 5751-
			659051 1193+	065121 0260+	425977 3151+	126512 9447-	1656 396044+	322801 6640-	112357 6655+	467386 0050+
			659051 1193+	075021 0260+	430279 1751+	179116 0347-	2194 906444+	349366 2640-	495714 9053+	376522 3050-
			659051 1193+	075121 0260+	383887 6251+	249583 4047-	3335 818444+	630136 9540-	218415 2755+	467630 0049-
Bell	Temperature interval	Load thermal data routine	0008 00000	0 +210000 0054	+260000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003717 0210+	249927 6451+	102129 0045-	1742 696542+	523594 8838-	429462 5855+	453769 0450-
			659051 1193+	005417 0210+	250163 9051+	252258 0045+	4789 731742-	162755 6539+	570772 6255+	416905 2251+
			659051 1193+	006117 0210+	251417 9351+	968009 0045+	1678 419543-	480001 3239+	302772 6455+	508330 5151+
			659051 1193+	045017 0210+	358432 3551+	345405 2547-	5355 345144+	113973 4941-	338629 5755+	467158 2451-
			659051 1193+	045117 0210+	498535 5151+	804282 8047-	1277 984845+	292686 9541-	503617 0454+	624032 7051-
			659051 1193+	065017 0210+	397927 0051+	262006 1247-	4260 967644+	104014 4941-	495167 1353+	451240 0048+
			659051 1193+	065117 0210+	413717 4651+	207672 3147-	3380 359344+	827120 2940-	113852 9055+	135127 2351+
			659051 1193+	075017 0210+	422270 2051+	195308 3147-	2975 107044+	597692 5940-	579496 4253+	174767 6050+
			659051 1193+	075117 0210+	369055 1651+	319152 7247-	5009 963144+	110788 0241-	220219 7355+	101234 6451+
Bell	Temperature interval	Load thermal data routine	0007 00000	0 +170000 0054	+210000 0054					
Basic load bin	Thermodynamic coefficients	Sections of thermodynamic data and load thermal data routine, eqs. (105) to (107)	659051 1193+	003713 0170+	249998 0351+	110207 7344-	4488 906540+	483417 0736+	429453 8955+	458993 9250-
			659051 1193+	005413 0170+	250022 0451+	345625 5044+	9655 671041-	420066 4538+	570790 7855+	417975 6551+
			659051 1193+	006113 0170+	251934 6551+	115126 1046+	2514 328343-	803129 0439+	302727 7455+	504854 1751+
			659051 1193+	045013 0170+	347894 6751+	316028 8047-	6169 765444+	150596 8741-	339427 4455-	399539 6951-
			659051 1193+	045113 0170+	456135 8751+	936121 3047-	1893 335945+	522738 4241-	542006 4354+	337478 8151-
			659051 1193+	065013 0170+	379386 8051+	371701 3247-	7734 001444+	232616 7741-	668617 4853+	127883 9851+
			659051 1193+	065113 0170+	397621 3151+	314063 8247-	6572 256144+	200914 6341-	115367 0755+	246176 6451+
			659051 1193+	075013 0170+	410499 0051+	251703 1847-	5093 902044+	140933 1541-	683517 4555+	972976 6050+
			659051 1193+	075113 0170+	352600 1751+	360793 9747-	7223 571444+	193098 7741-	221712 3155+	212205 3451+
Bell	Temperature interval	Load thermal data routine	0006 00000	0 +130000 0054	+170000 0054					

TABLE V. - OUTPUT OF MAIN OPERATING DECK

		EQUIV RATO R	O/F	PRCNT FUEL	PC PSIA	ENTH CAL/ GM	IDENT FICA TN	
9005	6	+8571 4286 50	+1592 1118 51	+3857 8583 52	+6000 0000 53	+2380 1691 54	+0857 0208 63	1
		A SUB F	B SUB F	C SUB F	D SUB F	E SUB F		
9005	6	+1248 1278 50	+6240 6390 49				+0857 0208 63	2
		F SUB F	G SUB F	H SUB F	I SUB F	J SUB F		
9005	6						+0857 0208 63	3
		FUEL ENTH HF	FUEL +VAL VF+	FUEL -VAL VF-				
9005	6	+4827 2269 54	+1248 1278 50				+0857 0208 63	4
		A SUB X	B SUB X	C SUB X	D SUB X	E SUB X		
9005	6	+5879 5860 49		+5879 5860 49			+0857 0208 63	5
		F SUB X	G SUB X	H SUB X	I SUB X	J SUB X		
9005	6						+0857 0208 63	6
		OXID ENTH HX	OXID +VAL VX+	OXID -VAL VX-				
9005	6	+8431 8043 53	+5879 5860 49	-1175 9172 50			+0857 0208 63	7

						IDENT FICA TN		CARD NO.
PRESS RATO	TEMP K	PRESS ATM	ENTH CAL/ GM	SPEC IMP	RRRR			1
MOLEC WT	THRST COEF CF	AREA RATO	MACH NO.	I VAC		CASE		2
CP CAL/ GM	GAMMA	DLNM/ DLNP T	DLNM/ DLNT P	ENTRO PY			PC	3
PI SUB I	PI SUB T	PI SUB EP	PISUB CSTR	C STAR			PE	4
CODE 0 37	H	CODE 0 54	N					5
CODE 0 61	O	CODE 4 50	H2					6
CODE 4 51	H2O	CODE 6 50	N2					7
CODE 6 51	NO	CODE 7 50	O2					8
CODE 7 51	OH							9

9005	6	+1000 0000 51	+2820 0975 54	+4082 7418 52	+2380 1693 54		+0857 0208 63	1	7 0001
9005	6	+1832 4978 52					+0857 0208 63	1	0 0002
9005	6	+8600 2537 50	+1170 6861 51	+3918 7000 48	-8967 4585 49	+3202 5166 51	+0857 0208 63	1	0 0003
9005	6		+1130 7117 49				+0857 0208 63	1	0 0004
9005	6	+0000 0000 37	+1884 9336 50	+0000 0000 54	+1198 2934 46		+0857 0208 63	1	0 0005
9005	6	+0000 0000 61	+7941 1497 48	+0000 0004 50	+4652 5476 51		+0857 0208 63	1	0 0006
9005	6	+0000 0004 51	+2661 5805 52	+0000 0006 50	+8986 4247 51		+0857 0208 63	1	0 0007
9005	6	+0000 0006 51	+3950 4512 49	+0000 0007 50	+1860 7803 49		+0857 0208 63	1	0 0008
9005	6	+0000 0007 51	+3180 8095 50				+0857 0208 63	1	0 0009
9005	6	+1763 0118 51	+2599 0325 54	+2315 7770 52	+2213 8880 54	+1202 8578 53	+0857 0208 63	2	7 0001
9005	6	+1839 4694 52	+6718 3421 50	+1000 0000 51	+9999 9900 50	+2218 3977 53	+0857 0208 63	2	0 0002
9005	6	+7500 1172 50	+1184 4539 51	+1866 4000 48	-4600 4567 49	+3202 5172 51	+0857 0208 63	2	0 0003
9005	6	+3211 9738 48	+6078 4200 48		+1279 7000 48	+5760 4609 54	+0857 0208 63	2	0 0004
9005	6	+0000 0000 37	+6129 6978 49	+0000 0000 54	+1574 5346 45		+0857 0208 63	2	0 0005
9005	6	+0000 0000 61	+1289 9700 48	+0000 0004 50	+2592 6825 51		+0857 0208 63	2	0 0006
9005	6	+0000 0004 51	+1528 1160 52	+0000 0006 50	+5123 4150 51		+0857 0208 63	2	0 0007
9005	6	+0000 0006 51	+8852 1215 48	+0000 0007 50	+3154 4989 48		+0857 0208 63	2	0 0008
9005	6	+0000 0007 51	+8591 8027 49				+0857 0208 63	2	0 0009
9005	6	+2041 3710 52	+1703 3560 54	+2000 0000 51	+1650 2977 54	+2520 0886 53	+0857 0208 63	3	7 0001
9005	6	+1846 0004 52	+1407 5494 51	+3609 2728 51	+2542 3479 51	+2836 6442 53	+0857 0208 63	3	0 0002
9005	6	+5727 2366 50	+1231 6744 51	+1190 0000 46	-4021 9322 47	+3202 5170 51	+0857 0208 63	3	0 0003
9005	6	+9255 6857 47	-1309 3700 48	-3527 1000 48		+5760 4609 54	+0857 0208 63	3	0 0004
9005	6	+0000 0000 37	+7135 4999 46	+0000 0000 54	+3884 2841 39		+0857 0208 63	3	0 0005
9005	6	+0000 0000 61	+5726 6914 42	+0000 0004 50	+2221 9334 50		+0857 0208 63	3	0 0006
9005	6	+0000 0004 51	+1333 2781 51	+0000 0006 50	+4444 3360 50		+0857 0208 63	3	0 0007
9005	6	+0000 0006 51	+6396 0183 44	+0000 0007 50	+1556 5795 43		+0857 0208 63	3	0 0008
9005	6	+0000 0007 51	+2297 8421 46				+0857 0208 63	3	0 0009
9005	6	+4082 7420 52	+1491 5306 54	+1000 0000 51	+1531 2268 54	+2717 8889 53	+0857 0208 63	4	7 0001
9005	6	+1846 0388 52	+1518 0271 51	+5861 1205 51	+2917 3868 51	+2974 9172 53	+0857 0208 63	4	0 0002
9005	6	+5517 8364 50	+1242 4039 51	+1500 0000 45	-6049 8219 5	+3202 5166 51	+0857 0208 63	4	0 0003
9005	6	+6988 0686 47	-1429 7700 48	-3409 9000 48		+5760 4609 54	+0857 0208 63	4	0 0004
9005	6	+0000 0000 37	+5278 4766 45	+0000 0000 54	+2759 3682 37		+0857 0208 63	4	0 0005
9005	6	+0000 0000 61	+3627 2626 40	+0000 0004 50	+1111 0859 50		+0857 0208 63	4	0 0006
9005	6	+0000 0004 51	+6666 6369 50	+0000 0006 50	+2222 2154 50		+0857 0208 63	4	0 0007
9005	6	+0000 0006 51	+1479 0822 43	+0000 0007 50	+1023 7844 41		+0857 0208 63	4	0 0008
9005	6	+0000 0007 51	+9075 8745 44				+0857 0208 63	4	0 0009
9005	6	+6804 5699 52	+1348 1969 54	+6000 0001 50	+1453 1962 54	+2840 0511 53	+0857 0208 63	5	7 0001
9005	6	+1846 0433 52	+1586 2586 51	+8449 4012 51	+3195 2580 51	+3062 3705 53	+0857 0208 63	5	0 0002
9005	6	+5361 3060 50	+1251 2292 51	+3000 0000 44	-1082 3995 46	+3202 5168 51	+0857 0208 63	5	0 0003
9005	6	+5786 3339 47	-1481 9800 48	-3340 6000 48		+5760 4609 54	+0857 0208 63	5	0 0004
9005	6	+0000 0000 37	+5962 6786 44	+0000 0000 54	+2889 5353 35		+0857 0208 63	5	0 0005
9005	6	+0000 0000 61	+4808 4378 35	+0000 0004 50	+6666 6369 49		+0857 0208 63	5	0 0006
9005	6	+0000 0004 51	+3599 9971 50	+0000 0006 50	+1333 3327 50		+0857 0208 63	5	0 0007
9005	6	+0000 0006 51	+6167 0896 41	+0000 0007 50	+1403 8250 39		+0857 0208 63	5	0 0008
9005	6	+0000 0007 51	+5969 0563 43				+0857 0208 63	5	0 0009

E-417

Type of equation	Equation number in text	Gaseous molecules				Gaseous atoms				Condensed phases					
		$\Delta \ln n_1$	$\Delta \ln n_2$	$\Delta \ln n_3$	---	$\Delta \ln n_Z$	$\Delta \ln n_Y$	$\Delta \ln n_X$	---	---	$\Delta \ln n_M$	$\Delta \ln n_N$	$-\Delta \ln A$	$\Delta \ln T$	Constant
Gaseous equilibria	(29)	1	0	0	0	$-a_1$	$-b_1$	$-c_1$	---	0	0	0	0	$-q_1$	$-\delta_1$
		0	1	0	0	$-a_2$	$-b_2$	$-c_2$	---	0	0	0	0	$-q_2$	$-\delta_2$
		0	0	1	0	$-a_3$	$-b_3$	$-c_3$	---	0	0	0	0	$-q_3$	$-\delta_3$
		0	0	0	---	---	---	---	---	0	0	0	0	---	---
Mass balance	(28)	a_1n_1	a_2n_2	a_3n_3	---	n_Z	0	0	0	---	a_Mn_M	a_Nn_N	$\sum a_in_i$	0	$A\Delta a$
		b_1n_1	b_2n_2	b_3n_3	---	0	n_Y	0	0	---	b_Mn_M	b_Nn_N	$\sum b_in_i$	0	$A\Delta b$
		c_1n_1	c_2n_2	c_3n_3	---	0	0	n_X	0	---	c_Mn_M	c_Nn_N	$\sum c_in_i$	0	$A\Delta c$
		----	----	----	---	0	0	0	---	---	----	----	----	0	---
Condensed-phase equilibria	(30)	0	0	0	0	---	---	---	---	0	0	0	0	---	---
		0	0	0	0	a_M	b_M	c_M	---	0	0	0	0	q_M	δ_M
		0	0	0	0	a_N	b_N	c_N	---	0	0	0	0	q_N	δ_N
Pressure	(31)	p_1	p_2	p_3	---	p_Z	p_Y	p_X	---	0	0	0	0	0	ΔP
Enthalpy*	(32)	$(H_T^o)_1n_1$	$(H_T^o)_2n_2$	$(H_T^o)_3n_3$	---	$(H_T^o)_Zn_Z$	$(H_T^o)_Yn_Y$	$(H_T^o)_Xn_X$	---	---	$(H_T^o)_Mn_M$	$(H_T^o)_Nn_N$	$\sum(H_T^o)_in_i$	$T\sum(C_P^o)_in_i$	$A\Delta H$

*Row vector to be substituted in place of enthalpy row for isentropic expansion to assigned pressure:

Entropy	(33)	$(S_T)'_1n_1$	$(S_T)'_2n_2$	$(S_T)'_3n_3$	---	$(S_T)'_Zn_Z$	$(S_T)'_Yn_Y$	$(S_T)'_Xn_X$	---	---	$(S_T)'_Mn_M$	$(S_T)'_Nn_N$	$\sum(S_T)_in_i$	$\sum(C_P^o)_in_i$	$A\Delta S$

Figure 1. - General matrix of correction equations for adiabatic combustion at assigned pressure.

Type of equation	Gaseous atoms				Condensed phases					
	$\Delta \ln p_Z$	$\Delta \ln p_Y$	$\Delta \ln p_X$	---	---	Δn_M	Δn_N	$-\Delta \ln A$	$\Delta \ln T$	Constant
Mass balance	$\sum a_i^2 p_i$	$\sum a_i b_i p_i$	$\sum a_i c_i p_i$	---	---	a_M	a_N	$\sum a_i n_i$	$\sum a_i q_i p_i$	$A\Delta a + \sum a_i \delta_i p_i$
	$\sum a_i b_i p_i$	$\sum b_i^2 p_i$	$\sum b_i c_i p_i$	---	---	b_M	b_N	$\sum b_i n_i$	$\sum b_i q_i p_i$	$A\Delta b + \sum b_i \delta_i p_i$
	$\sum a_i c_i p_i$	$\sum b_i c_i p_i$	$\sum c_i^2 p_i$	---	---	c_M	c_N	$\sum c_i n_i$	$\sum c_i q_i p_i$	$A\Delta c + \sum c_i \delta_i p_i$
	------	------	------	---	---	--	--	----	------	------
Condensed-phase equilibria	------	------	------	---	0	0	0	0	------	------
	a_M	b_M	c_M	---	0	0	0	0	q_M	δ_M
	a_N	b_N	c_N	---	0	0	0	0	q_N	δ_N
Pressure	$\sum a_i p_i$	$\sum b_i p_i$	$\sum c_i p_i$	---	0	0	0	0	$\sum q_i p_i$	$\Delta P + \sum \delta_i p_i$
Enthalpy*	$\sum (H_T^o)_i a_i p_i$	$\sum (H_T^o)_i b_i p_i$	$\sum (H_T^o)_i c_i p_i$	---	---	$(H_T^o)_M$	$(H_T^o)_N$	$\sum (H_T^o)_i n_i$	$T \sum (C_P^o)_i n_i + \sum (H_T^o) q_i p_i$	$A\Delta H + \sum (H_T^o)_i \delta_i p_i$

*Row vector to be substituted in place of enthalpy row for isentropic expansion to assigned pressure:

Entropy	$\sum (S_T)_i' a_i p_i$	$\sum (S_T)_i' b_i p_i$	$\sum (S_T)_i' c_i p_i$	---	---	$(S_T)_M'$	$(S_T)_N'$	$\sum (S_T)_i n_i$	$\sum (C_P^o)_i n_i + \sum (S_T)_i' q_i p_i$	$A\Delta S + \sum (S_T)' \delta_i p_i$

Figure 2. - General reduced augmented matrix for adiabatic combustion at assigned pressure. (Summations in terms of p_i for gaseous products only. Summations in terms of n_i for all products.)

Type of equation	Gaseous atoms				Condensed phases				
	$\left(\frac{\partial \ln p_Z}{\partial \ln T}\right)_P$	$\left(\frac{\partial \ln p_Y}{\partial \ln T}\right)_P$	$\left(\frac{\partial \ln p_X}{\partial \ln T}\right)_P$			$\left(\frac{\partial n_M}{\partial \ln T}\right)_P$	$\left(\frac{\partial n_N}{\partial \ln T}\right)_P$	$-\left(\frac{\partial \ln A}{\partial \ln T}\right)_P$	Constant
Mass balance	$\sum a_i^2 p_i$	$\sum a_i b_i p_i$	$\sum a_i c_i p_i$	---	---	a_M	a_N	$\sum a_i n_i$	$\sum a_i q_i p_i$
	$\sum a_i b_i p_i$	$\sum b_i^2 p_i$	$\sum b_i c_i p_i$	---	---	b_M	b_N	$\sum b_i n_i$	$\sum b_i q_i p_i$
	$\sum a_i c_i p_i$	$\sum b_i c_i p_i$	$\sum c_i^2 p_i$			c_M	c_N	$\sum c_i n_i$	$\sum c_i q_i p_i$
	------	------	------	---	---	--	--	----	------
Condensed-phase equilibria	------	------	------	---	0	0	0	0	------
	a_M	b_M	c_M	---	0	0	0	0	q_M
	a_N	b_N	c_N	---	0	0	0	0	q_N
Pressure	$\sum a_i p_i$	$\sum b_i p_i$	$\sum c_i p_i$	---	0	0	0	0	$\sum q_i p_i$

Figure 3. - General reduced augmented matrix for partial derivatives at constant pressure. (Summations in terms of p_i for gaseous products only. Summations in terms of n_i for all products.)

Type of equation	Gaseous atoms				Condensed phases			
	$\left(\frac{\partial \ln p_Z}{\partial \ln A}\right)_T$	$\left(\frac{\partial \ln p_Y}{\partial \ln A}\right)_T$	$\left(\frac{\partial \ln p_X}{\partial \ln A}\right)_T$			$\left(\frac{\partial n_M}{\partial \ln A}\right)_T$	$\left(\frac{\partial n_N}{\partial \ln A}\right)_T$	Constant
Mass balance	$\sum a_i^2 p_i$	$\sum a_i b_i p_i$	$\sum a_i c_i p_i$	---	---	a_M	a_N	$\sum a_i n_i$
	$\sum a_i b_i p_i$	$\sum b_i^2 p_i$	$\sum b_i c_i p_i$	---	---	b_M	b_N	$\sum b_i n_i$
	$\sum a_i c_i p_i$	$\sum b_i c_i p_i$	$\sum c_i^2 p_i$	---	---	c_M	c_N	$\sum c_i n_i$
	------	------	------	---	---	--	--	----
Condensed-phase equilibria	--	--	--	---	---	0	0	0
	a_M	b_M	c_M	---	---	0	0	0
	a_N	b_N	c_N	---	---	0	0	0

Figure 4. - General reduced augmented matrix for partial derivatives at constant temperature. (Summations in terms of p_i for gaseous products only. Summations in terms of n_i for all products.)

E-417



Figure 5. - Flow chart for Main Calculating Program.

E-417



Figure 6. - Flow chart for packed vector loading.

E-411



Figure 7. - Flow chart for input data routine.



Figure 8. - Flow chart for load thermal data.

E-417

CA-19



Figure 9. - Flow chart for unpacking routine.

E-417



T Region
10-word block

T0001 + k	Code
T0002 + k	A
T0003 + k	B
T0004 + k	C
T0005 + k	D
T0006 + k	E
T0007 + k	F
T0008 + k	ln n_i
T0009 + k	q_i
T0010 + k	$-\delta_i$
k = 0, 10, 20...	290

Figure 10. - Flow chart for thermal routine.



Figure 11. - Flow chart for vector multiplication routine.



Figure 12. - Flow chart for matrix completion routine.



Figure 13. - Flow chart for matrix solution routine.



Figure 14. - Flow chart for correction routine.



Figure 15. - Flow chart for performance-parameter routine.



Figure 16. - Rate of convergence for several propellants.



Figure 17. - Convergence for reaction $N_2H_4 + \frac{3}{2} H_2O_2$.

E-417



Figure 18. - Solution vector control and convergence; 4 elements, 17 gaseous products, 2 condensed products.

E-417

CA-20 back



Figure 19. - Flow chart for frozen-composition routine.



Figure 20. - Flow chart for Vector and Propellant Program.

E-417

E-417



Figure 21. - Flow chart for ATM (pseudo-operation).



Figure 22. - Flow chart for MOL (pseudo-operation).

E-417



Figure 23. - Flow chart for F and X (pseudo-operations).



Figure 24. - Flow chart for percent fuel or oxidant and enthalpy of fuel or oxidant (pseudo-operations).

E-417

CA-21



Figure 25. - Flow chart for percent propellants routine.

NASA TN D-132
National Aeronautics and Space Administration.
A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF EQUILIBRIUM COMPOSITIONS AND THEORETICAL ROCKET PERFORMANCE OF PROPELLANTS. Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff. October 1959. 161p. diagrs., tabs. OTS price, $3.00.
(NASA TECHNICAL NOTE D-132)

A general computer program for chemical equilibrium and rocket performance calculations was written for the IBM 650 computer with 2000 words of drum storage 60 words of high-speed core storage, indexing registers, and floating point attachments. The program can carry out combustion and isentropic-expansion calculations on a chemical system that may include as many as 10 different chemical elements, 30 reaction products, and 25 pressure ratios. It calculates composition, temperature, pressure, specific impulse, specific impulse in vacuum, characteristic velocity, thrust coefficient, area ratio, molecular weight, Mach (over)

Copies obtainable from NASA, Washington

1. Engines, Rocket (3.1.8)
2. Fuels - Rockets (Includes Fuel and Oxidant) (3.4.3.3)
3. Combustion - Rocket Engines (3.5.2.5)

I. Gordon, Sanford
II. Zeleznik, Frank J.
III. Huff, Vearl N.
IV. NASA TN D-132

NASA

NASA TN D-132
National Aeronautics and Space Administration.
A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF EQUILIBRIUM COMPOSITIONS AND THEORETICAL ROCKET PERFORMANCE OF PROPELLANTS. Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff. October 1959. 161p. diagrs., tabs. OTS price, $3.00.
(NASA TECHNICAL NOTE D-132)

A general computer program for chemical equilibrium and rocket performance calculations was written for the IBM 650 computer with 2000 words of drum storage 60 words of high-speed core storage, indexing registers, and floating point attachments. The program can carry out combustion and isentropic-expansion calculations on a chemical system that may include as many as 10 different chemical elements, 30 reaction products, and 25 pressure ratios. It calculates composition, temperature, pressure, specific impulse, specific impulse in vacuum, characteristic velocity, thrust coefficient, area ratio, molecular weight, Mach (over)

Copies obtainable from NASA, Washington

1. Engines, Rocket (3.1.8)
2. Fuels - Rockets (Includes Fuel and Oxidant) (3.4.3.3)
3. Combustion - Rocket Engines (3.5.2.5)

I. Gordon, Sanford
II. Zeleznik, Frank J.
III. Huff, Vearl N.
IV. NASA TN D-132

NASA

NASA TN D-132
National Aeronautics and Space Administration.
A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF EQUILIBRIUM COMPOSITIONS AND THEORETICAL ROCKET PERFORMANCE OF PROPELLANTS. Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff. October 1959. 161p. diagrs., tabs. OTS price, $3.00.
(NASA TECHNICAL NOTE D-132)

A general computer program for chemical equilibrium and rocket performance calculations was written for the IBM 650 computer with 2000 words of drum storage 60 words of high-speed core storage, indexing registers, and floating point attachments. The program can carry out combustion and isentropic-expansion calculations on a chemical system that may include as many as 10 different chemical elements, 30 reaction products, and 25 pressure ratios. It calculates composition, temperature, pressure, specific impulse, specific impulse in vacuum, characteristic velocity, thrust coefficient, area ratio, molecular weight, Mach (over)

Copies obtainable from NASA, Washington

1. Engines, Rocket (3.1.8)
2. Fuels - Rockets (Includes Fuel and Oxidant) (3.4.3.3)
3. Combustion - Rocket Engines (3.5.2.5)

I. Gordon, Sanford
II. Zeleznik, Frank J.
III. Huff, Vearl N.
IV. NASA TN D-132

NASA

NASA TN D-132
National Aeronautics and Space Administration.
A GENERAL METHOD FOR AUTOMATIC COMPUTATION OF EQUILIBRIUM COMPOSITIONS AND THEORETICAL ROCKET PERFORMANCE OF PROPELLANTS. Sanford Gordon, Frank J. Zeleznik, and Vearl N. Huff. October 1959. 161p. diagrs., tabs. OTS price, $3.00.
(NASA TECHNICAL NOTE D-132)

A general computer program for chemical equilibrium and rocket performance calculations was written for the IBM 650 computer with 2000 words of drum storage 60 words of high-speed core storage, indexing registers, and floating point attachments. The program can carry out combustion and isentropic-expansion calculations on a chemical system that may include as many as 10 different chemical elements, 30 reaction products, and 25 pressure ratios. It calculates composition, temperature, pressure, specific impulse, specific impulse in vacuum, characteristic velocity, thrust coefficient, area ratio, molecular weight, Mach (over)

Copies obtainable from NASA, Washington

1. Engines, Rocket (3.1.8)
2. Fuels - Rockets (Includes Fuel and Oxidant) (3.4.3.3)
3. Combustion - Rocket Engines (3.5.2.5)

I. Gordon, Sanford
II. Zeleznik, Frank J.
III. Huff, Vearl N.
IV. NASA TN D-132

NASA

NASA TN D-132

number, specific heat, isentropic exponent, enthalpy, entropy, and several thermodynamic first derivatives.

Copies obtainable from NASA, Washington

NASA

NASA TN D-132

number, specific heat, isentropic exponent, enthalpy, entropy, and several thermodynamic first derivatives.

Copies obtainable from NASA, Washington

NASA

NASA TN D-132

number, specific heat, isentropic exponent, enthalpy, entropy, and several thermodynamic first derivatives.

Copies obtainable from NASA, Washington

NASA

NASA TN D-132

number, specific heat, isentropic exponent, enthalpy, entropy, and several thermodynamic first derivatives.

Copies obtainable from NASA, Washington

NASA